EV Battery Course — Module 16: Next-Generation Battery Research

Oct 9, 2026 · @Ashishpreet

Next-generation batteries attack three limits of today's Li-ion: the graphite anode (silicon, lithium metal), the flammable liquid electrolyte (solid-state), and expensive or scarce cathode metals (sodium-ion, sulfur, cobalt-free). In parallel, manufacturing (dry electrodes, bipolar designs) and data science (AI, machine learning, digital twins) are changing how batteries are developed and built. This module evaluates each on energy, safety, cost, life, manufacturability, materials, scalability and readiness, keeping laboratory results separate from products.

1. Learning objectives

- Explain the principle and main obstacle of each next-generation technology.
- Compare sulfide, oxide and polymer solid electrolytes.
- Calculate theoretical capacities that make lithium metal, silicon and sulfur attractive.
- Rate each technology's commercial readiness honestly.
- Explain how AI, machine learning and digital twins are used in battery R&D and manufacturing.

2. Fundamentals: the readiness scale

Use technology readiness levels (TRL) to keep claims honest:

TRL	Meaning	Battery example
1–3	Concept, lab proof	Coin-cell results in a paper
4–5	Lab validation in relevant format	Small pouch cells, hundreds of cycles
6–7	Prototype in relevant environment	Automotive-format A/B samples, pilot line
8	Qualified, early production	C-samples, SOP preparation, limited fleets
9	Proven in mass production	Cells in vehicles sold at volume

3. Technology-by-technology

Solid-state electrolytes

Replace the liquid electrolyte (and often the separator) with a solid ion conductor. Benefits: non-flammable, possibly enables lithium-metal anodes, potentially higher energy. Challenges: solid-solid interfaces lose contact as electrodes expand; dendrites can still grow along grain boundaries; manufacturing needs high stack pressure or new processes.

Type	Example materials	Ionic conductivity (room temp.)	Strengths	Weaknesses
Sulfide	Argyrodites (Li_6PS_5Cl), LGPS	High (~1–25 mS/cm, comparable to liquids)	Soft, good contact, high conductivity	Reacts with moisture to form toxic H_2S; narrow stability window
Oxide	LLZO (garnet), LATP	Moderate (~0.1–1 mS/cm)	Stable, safe	Brittle, high-temperature sintering, poor contact
Polymer	PEO-based	Low at room temp; usable at ~60–80 °C	Easy processing, flexible	Needs heating; limited voltage
Halide	Li_3InCl_6 etc.	Moderate-high	High-voltage stable	Cost of some elements; newer

Status: semi-solid cells are in limited commercial use in China; Toyota, Samsung SDI, QuantumScape, Factorial, SES and others run pilot lines with production targets in the late 2020s. Treat any date as a target.

Lithium-metal anodes

The ultimate anode: 3,860 mAh/g and the lowest possible potential. "Anode-free" designs plate lithium from the cathode onto bare copper during the first charge. Obstacles: dendrites, low coulombic efficiency, volume change and safety. Usually paired with solid or advanced liquid electrolytes. *Status:* pilot (TRL 5–7).

Lithium-sulfur (Li-S)

Sulfur cathode: about 1,672 mAh/g and very cheap. Average voltage about 2.1 V. Obstacles: polysulfides dissolve and shuttle to the anode (capacity loss), sulfur's large volume change, poor conductivity, lithium-metal anode issues. Strong gravimetric but weaker volumetric energy. *Status:* pilot; first markets are drones and aviation where mass matters most.

Sodium-ion

Covered in Modules 3–4. Sodium replaces lithium; hard-carbon anode; layered oxide, Prussian blue or polyanion cathodes. Strengths: abundant materials, cold performance, safety, transport at 0 V. Weakness: lower energy. *Status:* early commercial (TRL 8–9 in China for storage and small vehicles).

Silicon-rich anodes

Silicon stores about 3,600 mAh/g (as $Li_{15}Si_4$) but swells up to ~300%. Solutions: nano-silicon, silicon-carbon composites, silicon oxide, porous structures, new binders, pre-lithiation. *Status:* blends of a few % are commercial; silicon-dominant anodes from companies such as Sila, Group14 and Amprius are early commercial or pilot, mostly in consumer and premium applications.

High-voltage cathodes

LNMO (~4.7 V), lithium-rich manganese (LMR), and NMC charged to higher voltage. Challenge: the electrolyte oxidises above about 4.3–4.5 V; needs new electrolytes and coatings. *Status:* LMR announced by several OEMs for the late 2020s; LNMO pilot.

Cobalt-reduced and cobalt-free chemistries

NMC 811 and beyond, NMx (nickel-manganese), LMFP, LFP and LMR reduce or remove cobalt to cut cost and supply risk. *Status:* LFP and LMFP commercial; ultra-high-nickel cobalt-free layered cathodes at pilot to early commercial.

Dry-electrode manufacturing

Mix active material, carbon and a fibrillating binder (PTFE) as dry powder and press it into a film laminated onto foil; no solvent, no drying ovens, no NMP recovery. Potential savings in factory footprint and energy. Challenges: uniformity at high speed, binder stability at the anode, throughput. *Status:* Tesla and others have reported partial use (notably for anodes) with cathode scaling more difficult; many players at pilot.

Bipolar designs

Each electrode plate carries cathode on one side and anode on the other; cells stack in series inside one package, cutting interconnects and resistance. Toyota already uses a bipolar NiMH battery in the Aqua hybrid (2021) and has announced bipolar LFP plans. Requires solid or well-sealed electrolytes to prevent ionic short circuits between cells.

Structural batteries

Two meanings: (1) packs that are part of the vehicle structure (CTB/CTC, Module 5, commercial); (2) multifunctional materials where electrodes themselves carry load, e.g. carbon-fibre electrodes researched at Chalmers University (laboratory, low energy density so far).

Recycling innovations

Direct cathode regeneration, upcycling old cathodes to newer compositions, automated disassembly, electrolyte and graphite recovery, and lower-chemical hydrometallurgy. *Status:* mostly pilot.

4. Evaluation matrix (as of October 2026)

Technology	Energy potential	Safety	Cost potential	Cycle life today	Fits existing lines?	Material availability	Readiness
Sulfide solid-state + Li metal	Very high	High (non-flammable)	High initially	Moderate (improving)	Low	Li, sulfur OK; germanium avoided	Pilot (TRL 6–7)
Oxide/polymer solid-state	High	High	Medium-high	Moderate	Low-medium	Good	Pilot / niche
Semi-solid-state	Medium-high	Medium-high	Medium	Good	Medium-high	Good	Early commercial (China)
Lithium-sulfur	Very high (gravimetric)	Medium	Low (materials)	Low	Medium	Excellent	Pilot
Sodium-ion	Low-medium	High	Low	Good	High	Excellent	Early commercial
Silicon-rich anode	High	Medium	Medium	Moderate	High	Excellent	Commercial (blends) / early commercial (rich)
High-voltage / LMR cathodes	High	Medium	Low-medium	Moderate	High	Good (Mn)	Pilot / pre-commercial
Dry electrode	Process	n/a	Lower cost	n/a	Requires new equipment	n/a	Pilot / partial commercial

Technology	Energy potential	Safety	Cost potential	Cycle life today	Fits existing lines?	Material availability	Readiness
Bipolar	Higher pack density	Depends on chemistry	Medium	Depends	Low-medium	n/a	Commercial NiMH; LFP pilot

5. Diagram: where each technology attacks today's cell

```
flowchart LR
  A["Anode: graphite"] -->|"silicon, lithium metal, anode-free"| A2["More capacity"]
  E["Liquid electrolyte + separator"] -->|"sulfide, oxide, polymer solids"| E2["Safety, Li-metal enabling"]
  C["Cathode: NMC / LFP"] -->|"LMR, LNMO, LMFP, sulfur, sodium"| C2["Cost, energy, minerals"]
  P["Process: wet coating"] -->|"dry electrode, bipolar"| P2["Cost, footprint"]
```

6. Step-by-step: why lithium-metal is hard

1. On charge, lithium plates onto the anode, not into a host lattice.
2. Plating is uneven; tips grow faster (dendrites) because current concentrates there.
3. Each cycle exposes fresh lithium; SEI reforms and consumes lithium and electrolyte (low coulombic efficiency).
4. Isolated "dead lithium" builds up; the anode swells.
5. Dendrites can pierce the separator, causing shorts.
6. Solutions: solid electrolytes, high stack pressure, electrolyte additives, 3D hosts, careful charging limits.

7. Engineering equations

$$Q_{th} = \frac{n F}{3.6 M}\ (\text{mAh/g}) \qquad e = Q \times V_{avg}$$

Ionic conductivity and resistance of an electrolyte layer:

$$R_{ion} = \frac{t}{\sigma A}$$

t = thickness (cm), σ = ionic conductivity (S/cm), A = area (cm²).

8. Worked examples

Example 1: theoretical capacities.

- Sulfur to Li_2S (n = 2 per S, M = 32.06): 2 × 96,485 ÷ (3.6 × 32.06) = **1,672 mAh/g** → × 2.1 V ≈ **3.5 Wh/g** of sulfur (material level).
- Lithium metal (M = 6.94): 96,485 ÷ (3.6 × 6.94) = **3,862 mAh/g**.

Example 2: anode mass for 100 Ah.

Anode	Practical capacity	Mass for 100 Ah
Graphite	350 mAh/g	286 g
Silicon-carbon (example)	1,500 mAh/g	67 g
Lithium metal (no excess)	3,860 mAh/g	26 g

Real lithium-metal cells add excess lithium, so savings are smaller, but the anode mass falls dramatically.

Example 3: solid electrolyte resistance. Separator layer 30 µm (0.003 cm), area 1 cm².

- Sulfide, σ = 10 mS/cm: R = 0.003 ÷ (0.01 × 1) = **0.3 Ω·cm²**.
- Oxide, σ = 0.5 mS/cm: R = 0.003 ÷ 0.0005 = **6 Ω·cm²**: 20× higher, which is why oxides need very thin layers or higher temperatures.

9. AI, machine learning and digital twins

Application	What it does	Status / example
AI for materials discovery	Screens millions of candidate compounds by predicted stability and conductivity; guides experiments	Microsoft and PNNL (2024) screened ~32 million candidates computationally and synthesised a new solid electrolyte using less lithium; still laboratory
ML for life prediction	Predicts cycle life from early-cycle data	Severson et al. (*Nature Energy* 2019) predicted cycle life from the first 100 cycles with ~9% error; used to shorten testing

Application	What it does	Status / example
ML for SOC/SOH	Neural networks or hybrid physics-ML estimators in BMS or cloud	Cloud-based SOH analytics in fleets; on-board use limited by validation and safety requirements
Digital twins (design)	Physics-based cell and pack models (electrochemical, thermal, mechanical) for virtual testing	Standard in cell design (e.g. pseudo-2D models)
Digital twins (manufacturing)	Model of the production line to optimise coating, drying, formation and flow	Used in ramp-up and process optimisation
Digital twins (in use)	Cloud model of each pack updated with field data	Predictive maintenance, warranty analytics, second-life grading

10. Real-world examples

- **CATL Naxtra and BYD sodium-ion cells:** early commercial sodium-ion for vehicles and storage.
- **NIO 150 kWh semi-solid pack (WeLion):** limited deliveries from 2024.
- **Toyota and Idemitsu:** sulfide solid-state partnership targeting the late 2020s.
- **QuantumScape:** oxide-separator anode-free cells at B-sample stage with VW's PowerCo.
- **Amprius and Sila:** silicon-rich anodes in drones, wearables and some premium vehicles.

All dates and specifications should be checked against the latest company disclosures.

11. Manufacturing applications

- Sodium-ion and silicon blends reuse existing lines: fastest adoption.
- Sulfide solid-state needs dry/inert processing (H_2S risk), new stacking and high-pressure formation: new plant layouts.
- Dry electrodes remove the drying ovens and NMP recovery (a large share of energy and floor space; Module 12).
- For costing, evaluate not just cell cost per kWh but capex per GWh, yield learning curves and equipment availability.

12. Common mistakes and misconceptions

- **"Solid-state is solid-state."** There are several electrolyte families with very different properties.
- **"Highest Wh/kg wins."** Cost, life, safety and manufacturability decide adoption.
- **"AI will discover the perfect battery soon."** AI narrows the search; synthesis, testing and scale-up still take years.
- **"Lab cycle numbers transfer to cars."** Lab cells often use excess electrolyte, thin electrodes and high pressure.

13. Practical case study: evaluating a solid-state supplier pitch

Pitch. A start-up claims 450 Wh/kg, 1,000 cycles, 15-minute charging, available for 2028 vehicles.

Questions. Cell format and size? Stack pressure required and how it is applied in a pack? Temperature range? Data from independent labs? Coulombic efficiency per cycle? Abuse test results? Pilot-line capacity and yield? Cost roadmap per kWh? Supply of electrolyte materials?

Outcome. The start-up's cells need 1 MPa stack pressure and 45 °C operation for the claimed life; pack-level energy falls to about 300 Wh/kg with fixtures and heating. Recommendation: joint evaluation programme, no production commitment until B-samples meet targets.

Lesson. Translate cell claims into pack-level, real-condition numbers before believing them.

14. Revision notes

- Anode upgrades: silicon (commercial blends), lithium metal (pilot).
- Electrolyte upgrade: solid-state (sulfide, oxide, polymer, halide), mostly pilot; semi-solid in limited use.
- Cathode/material alternatives: sodium-ion (early commercial), LMR and LNMO (pilot), Li-S (pilot).
- Process upgrades: dry electrodes, bipolar stacking.
- AI/ML/digital twins accelerate discovery, testing and manufacturing.

15. Glossary

Term	Meaning
TRL	Technology readiness level
Anode-free	Cell with no initial anode material; lithium plates from the cathode
LGPS / LLZO	Sulfide / garnet oxide solid electrolytes
Polysulfide shuttle	Li-S degradation mechanism
LMR	Lithium-manganese-rich cathode
Dry electrode	Solvent-free electrode process
Bipolar	Electrodes with anode and cathode on opposite faces of one current collector
P2D model	Pseudo-two-dimensional electrochemical model

16. Knowledge check

Conceptual

1. Why do sulfide solid electrolytes need special handling?
2. Why does lithium metal have poor coulombic efficiency?
3. Why is Li-S attractive for aircraft but less so for cars?
4. How does dry-electrode processing reduce cost?
5. What role does ML play in shortening battery testing?

Numerical

1. Theoretical capacity of silicon as $Li_{15}Si_4$ (3.75 Li per Si, M = 28.09)?
2. An oxide electrolyte layer is 20 μm with σ = 1 mS/cm. Area-specific resistance?
3. A cell needs 50 Ah; anode options graphite (350) vs silicon-carbon (1,200 mAh/g). Mass difference?

Application

1. Rank sodium-ion, solid-state and silicon-rich anodes for an Indian 2030 budget car and justify.
2. Design a 2-year technology-watch plan for an OEM's battery team.

17. Answer key

Conceptual

1. They react with moisture to release toxic H_2S and degrade, so processing needs dry or inert atmospheres.
2. Each cycle creates fresh lithium surface where electrolyte reacts, forming new SEI and isolated dead lithium.
3. Very high gravimetric energy suits aircraft; cars care about volumetric energy and cycle life, where Li-S is weaker.
4. It removes solvent, drying ovens and NMP recovery: less energy, capex and floor space.
5. It predicts end-of-life from early data, so not every cell must be cycled to failure before decisions.

Numerical

1. 3.75 × 96,485 ÷ (3.6 × 28.09) = 361,819 ÷ 101.12 = **3,578 mAh/g**.
2. t = 0.002 cm; R = 0.002 ÷ 0.001 = **2 Ω·cm²**.
3. Graphite 50 ÷ 0.35 = 142.9 g; Si-C 50 ÷ 1.2 = 41.7 g; difference **101 g**.

Application

1. Sodium-ion first (cost, safety, minerals, cold/heat tolerance, existing lines) if energy suffices for city range; silicon-rich anodes second (incremental, works with LFP/LMFP for range); solid-state last for budget cars (cost and maturity).
2. Quarterly literature and patent scan; supplier sample programme (Na-ion, LMFP, Si-anode) with defined test protocol; annual roadmap review with TRL ratings; cost models per technology; partnerships with IIT/ARAI/CSIR labs; trigger points for design decisions.

18. Further learning

- Janek & Zeier, "A solid future for battery development," *Nature Energy* 2016, and the 2023 follow-up.
- Manthiram et al., "Lithium–sulfur batteries: progress and prospects," *Advanced Materials* 2015.
- Severson et al., *Nature Energy* 2019 (ML cycle-life prediction).
- Faraday Institution reports (UK) on solid-state, sodium-ion and recycling (free).
- IEA *Batteries and Secure Energy Transitions* (2024).

Next: Module 17, advanced engineering calculations and simulation.