

Parameter Number	Description	Bit Lenght	MODBUS Function Code	Range	Range in notation	Block Transfer Allowed	Memory Region	Access Mode	Factory Setting in notation
External Power reduction									
P1025	Power reduction mode	16bit	06	0...2	0 ... 2	No	Data Set 0	Write	1
P1020	Power reduction reference value	16bit	06	0...100 %	0...100	No	Data Set 5	Write	100
P1026	Power reduction timeout	16bit	06	0...10000 min	0...10000	No	Data Set 0	Write	0
P1027	S. power reduction systembus	16bit	06	9...2554	9...2554	No	Data Set 0	Write	66
Reduction at upper Frequency									
P1030	Power reduction at upper frequency	16bit	06	0...1	0...1	No	Data Set 0	Write	0
P1034	Frequency start power reduction	16bit	06	35.00...70.00 Hz	3500...7000	No	Data Set 0	Write	5050
P1035	Frequency stop power reduction	16bit	06	35.00...70.00 Hz	3500...7000	No	Data Set 0	Write	5005
P1036	Gradient for power reduction	16bit	06	5.00...50.00	500...5000	No	Data Set 0	Write	2000
P1037	Freeze Min Value	16bit	06	0...1	0...1	No	Data Set 0	Write	1
Active power ramps									
P1188	Ramp reduction	16bit	06	1.00...100.00 %/s	100...10000	No	Data Set 0	Write	8000
P1189	Ramp increase	16bit	06	1.00...100.00 %/s	100...10000	No	Data Set 0	Write	8000
P1022	Power ramp after zero voltage	16bit	06	1.00...200.00 %/min	100...20000	No	Data Set 0	Write	1000
Reactive power control									
P520 *selected by P1153	Reference value for cos_phi / Q	16bit	06	-300.00...300.00%	35536...7530, -30000...30000	No	Data Set 5	Write	0
P1150	Operation mode	16bit	06	0...3	0...3	No	Data Set 5	Write	0
P1151	Minimum cos_phi	16bit	06	0.90...0.99	90...99	No	Data Set 0	Write	95
P1152	Maximum reactive power	16bit	06	26.0...79.8 kVA	260...798	No	Data Set 0	Write	571
P1153	Source for reference value of cos_phi / Q	16bit	06	9...2554	9...2554	No	Data Set 0	Write	133
P1160	Reference value cos_phi	16bit	03	-0.9000...1.0000, 0.9000...1.0000	56536...55536, 9000...10000	No	Data Set 0	Read	
P1161	Reference value reactive power	16bit	03	-79.8...-26.0, 26.0...79.8 kVA	64738...65276, 260...798	No	Data Set 0	Read	
Reactive power control / Cos_phi-P characteristic									
P1154	Relative P over-excited	16bit	06	0.00...100.00 %	0...10000	No	Data Set 0	Write	1000
P1155	Relative P under-excited	16bit	06	0.00...100.00 %	0...10000	No	Data Set 0	Write	9000
P1255	Option characteristic line	16bit	06	0...2	0...2	No	Data Set 0	Write	0
Reactive power control / Cos_phi-P characteristic(CEI 0-21)									
P1473	Point A, Power	16bit	06	0.00...100.00 %	0...10000	No	Data Set 0	Write	2000
P1474	Point A, cos_phi	16bit	06	-100.00 ... 100.00 %	55536...65536 0... 10000	No	Data Set 0	Write	0
P1475	Point B, Power	16bit	06	0.00...100.00 %	0...10000	No	Data Set 0	Write	5000
P1476	Point B, cos_phi	16bit	06	-100.00 ... 100.00 %	55536...65536 0... 10000	No	Data Set 0	Write	0
P1477	Point C, Power	16bit	06	0.00...100.00 %	0...10000	No	Data Set 0	Write	10000
P1478	Point C, cos_phi	16bit	06	-100.00 ... 100.00 %	55536...65536 0... 10000	No	Data Set 0	Write	10000
P1479	Point D, Power	16bit	06	0.00...100.00 %	0...10000	No	Data Set 0	Write	500
P1480	Point D, cos_phi	16bit	06	-100.00 ... 100.00 %	55536...65536 0... 10000	No	Data Set 0	Write	10000
P1481	Lock-in-voltage	16bit	06	100.00 ... 110.00 %	10000 ...11000	No	Data Set 0	Write	10500
P1482	Lock-out voltage	16bit	06	90.00...100.00 %	9000...10000	No	Data Set 0	Write	9800
P1483	Lock-out-Power, Characteristic a)	16bit	06	0.00...100.00 %	0...10000	No	Data Set 0	Write	5000
P1484	Lock-out-Power, Characteristic b)	16bit	06	0.00...100.00 %	0...10000	No	Data Set 0	Write	500
Reactive power control / Q-U characteristic									
P1012	Type of Characteristic	16bit	06	0 ... 2	0 ... 2	No	Data Set 0	Write	0
P500	reference value voltage Q(U)-Characteristic	16bit	06	80.00 ... 120.00 %	8000 ... 12000	No	Data Set 0	Write	10000
P1156	Absolute Ugrid over-excited 2	16bit	06	0.00...200.00 %	0...20000	No	Data Set 0	Write	9000
P1013	Absolute Ugrid over-excited 1 (CEI 0-21)	16bit	06	0.00...200.00 %	0...20000	No	Data Set 0	Write	9200
P1014	Absolute Ugrid under-excited 1 (CEI 0-21)	16bit	06	0.00...200.00 %	0...20000	No	Data Set 0	Write	10800
P1157	Absolute Ugrid under-excited 2	16bit	06	0.00...200.00 %	0...20000	No	Data Set 0	Write	11000
P1015	Lock-in-Power (CEI 0-21)	16bit	06	10.00 ... 100.00 %	1000 ... 10000	No	Data Set 0	Write	2000
P1158	Response time Q-U-Characteristic	16bit	06	1...120 s	1...120	No	Data Set 0	Write	60
P1158	Response time Q available	16bit	06	1...600 s	0 ... 600	No	Data Set 0	Write	90
FRT									
P1165	Operating mode FRT	16bit	06	0...1	0...1	No	Data Set 0	Write	0
P1169	Operating mode reactive current at FRT	16bit	06	0...1	0...1	No	Data Set 0	Write	1
P1181	Operating mode temporary grid disconnection	16bit	06	0...1	0...1	No	Data Set 0	Write	0
P1197	Active current at LVRT	16bit	06	0.00...100.00 %	0...10000	No	Data Set 0	Write	100
P1414	Reference current LVRT	16bit	06	0...1	0...1	No	Data Set 0	Write	0
FRT / reactive current characteristic									
P1170	Minimum undervoltage	16bit	06	0.00...100.00 %	0...10000	No	Data Set 0	Write	9000
P1171	Maximum undervoltage	16bit	06	0.00...100.00 %	0...10000	No	Data Set 0	Write	5000
P1172	Minimum overvoltage	16bit	06	100.00...200.00 %	10000...20000	No	Data Set 0	Write	11000
P1173	Minimum overvoltage	16bit	06	100.00...200.00 %	10000...20000	No	Data Set 0	Write	15000
P1174	Capacitive reactive current at min. undervoltage	16bit	06	0.0...374.0 A	0...3740	No	Data Set 0	Write	680
P1175	Capacitive reactive current at max. undervoltage	16bit	06	0.0...374.0 A	0...3740	No	Data Set 0	Write	3400
P1176	Inductive reactive current at min. overvoltage	16bit	06	0.0...374.0 A	0...3740	No	Data Set 0	Write	680
P1177	Inductive reactive current at max. overvoltage	16bit	06	0.0...374.0 A	0...3740	No	Data Set 0	Write	3400

P1222	Operating mode additional reactive current at FRT	16bit	06	0...1	0...1	No	Data Set 0	Write	1
FRT / temporary grid disconnection(2 of 6 limits)									
P1182	TDG undervoltage 1	16bit	06	10.00...100.00 %	1000...10000	No	Data Set 0	Write	8000
P1183	Response time TDG undervoltage 1	32bit	06	0...500000000 ms	0...500000000	No	Data Set 0	Write	1500
P1184	TDG overvoltage 1	16bit	06	100.00...150.00 %	10000...15000	No	Data Set 0	Write	11000
P1185	Response time TDG overvoltage 1	32bit	06	0...500000000 ms	0...500000000	No	Data Set 0	Write	50
P1200	TDG undervoltage 2	16bit	06	10.00...100.00 %	1000...10000	No	Data Set 0	Write	4500
P1201	Response time TDG undervoltage 2	32bit	06	0...500000000 ms	0...500000000	No	Data Set 0	Write	200
P1202	TDG overvoltage 2	16bit	06	100.00...150.00 %	10000...15000	No	Data Set 0	Write	11000
P1203	Response time TDG overvoltage 2	32bit	06	0...500000000 ms	0...500000000	No	Data Set 0	Write	50
P1204	TDG underfrequency limit 1	32bit	06	0.0000...70.0000 Hz	0...700000	No	Data Set 0	Write	475000
P1205	Response time TDG overfrequency limit 1	32bit	06	0...500000000 ms	0...500000000	No	Data Set 0	Write	10
P1206	TDG overfrequency limit 1	32bit	06	0.0000...70.0000 Hz	0...700000	No	Data Set 0	Write	515000
P1207	Response time TDG overfrequency limit 1	32bit	06	0...500000000 ms	0...500000000	No	Data Set 0	Write	10
P1208	TDG underfrequency limit 2	32bit	06	0.0000...70.0000 Hz	0...700000	No	Data Set 0	Write	465000
P1209	Response time TDG overfrequency limit 2	32bit	06	0...500000000 ms	0...500000000	No	Data Set 0	Write	10
P1210	TDG overfrequency limit 2	32bit	06	0.0000...70.0000 Hz	0...700000	No	Data Set 0	Write	525000
P1211	Response time TDG overfrequency limit 2	32bit	06	0...500000000 ms	0...500000000	No	Data Set 0	Write	10
P1186	TDG break-off time	16bit	06	0.1...3000.0 s	1...30000	No	Data Set 0	Write	50
P686	plausibility test voltage TDG	16bit	06	0...1000.0 V	0...10000	No	Data Set 0	Write	250
P687	plausibility test frequency TDG	32bit	06	0.0000 ... 70.0000 Hz	0...700000	No	Data Set 0	Write	2000
FRT / temporary grid disconnection(all 6 limits)									
P421	KTE_Erweiterung_Index (write)	16bit	06	0 ... 13	0 ... 13	No	Data Set 0	Write	1
P422	KTE_Erweiterung_Index (read)	16bit	06	0 ... 13	0 ... 13	No	Data Set 0	Write	1
P423	TDG undervoltage	16bit	06	0.00...100.00 %	0...10000	No	Data Set 0	Write	0
P424	TDG time undervoltage	32bit	06	0...500000000 ms	0...500000000	No	Data Set 0	Write	0
P425	TDG overvoltage	16bit	06	100.00...150.00 %	1000 ... 15000	No	Data Set 0	Write	0
P426	TDG time overvoltage	32bit	06	0...500000000 ms	0...500000000	No	Data Set 0	Write	0
P670	TDG underfrequency	32bit	06	0.0000 ... 70.0000 Hz	0...700000	No	Data Set 0	Write	0
P671	TDG time underfrequency	32bit	06	0...500000000 ms	0...500000000	No	Data Set 0	Write	0
P672	TDG overfrequency	32bit	06	0.0000 ... 70.0000 Hz	0...700000	No	Data Set 0	Write	0
P673	TDG time overfrequency	32bit	06	0...500000000 ms	0...500000000	No	Data Set 0	Write	0
Remark: Adjustment of power management characteristics normally does not have to be changed in operation, therefore the values can be written in data set 0 (DS0), values that will be written periodically have to be written in data set 5 (DS5).									