



MODBUS PROTOCOL DETAILS - ACTIVE & REACTIVE POWER CONTROL

Address (DEC)	Description	Unit
ACTIVE POWER CONTROL - PROTOCOL DETAILS		
798	Power Management Mode	Default: 0, 0: Disable 1: Rated 2: Actual
799	Power Management Percentage	Default: 100, (0~100), Reset timer: 0xFFFF
REACTIVE POWER CONTROL - PROTOCOL DETAILS		
Address (HEX)	Description	Unit
8350	ReactivePower_Mode	0 : Disable (Default) 1 : Fixed cos(ϕ) 2 : Variable cos(ϕ) of P 3 : Fixed Kvar 4 : Variable Kvar of U 5 : Q(U) CEI021 B
8351	Fixed_CosPhi	Unit: 1 Range: cap 80~100, eq -80~-100 ind 80~100, eq 80~100 Default: 100
8352	CosPhiOfPower_Mode	0: Rated (Default) 1: Actual
8353	CosPhiOfPower_CosPhi_Upper	Unit: 1 Range: cap 80~100, eq -80~-100 ind 80~100, eq 80~100 Default: -90
8354	CosPhiOfPower_CosPhi_Lower	Unit: 1 Range: cap 80~100, eq -80~-100 ind 80~100, eq 80~100 Default: 90
8355	CosPhiOfPower_PowerPercent_Lower P1 (Single-phase and three-phase defined backwards)	Unit: 1% Range: 0~100% Default: 0%
8356	CosPhiOfPower_PowerPercent_Upper P2 (Single-phase and three-phase defined backwards)	Unit: 1% Range: 0~100% Default: 100%
8357	Fixed_Kvar_Percent_Mode	0: Rated (Default) 1: Actual
8358	Fixed_Kvar_Percent	Unit: 1% Range: -63~63% Default: 0%
8359	KvarOfUac_Percent_Mode	0: Rated (Default) 1: Actual

Address (HEX)	Description	Unit
835A	<i>KvarOfUac_KvarPercent_Upper</i>	Unit: 1% Range: -63~63% Default: -44%
835B	<i>KvarOfUac_KvarPercent_Lower</i>	Unit: 1% Range: -63~63% Default: 44%
835C	<i>KvarOfUac_Vmin</i>	Unit: 0.1 V Range: 184~230 V Default: 184 V
835D	<i>KvarOfUac_Vmax</i>	Unit: 0.1 V Range: 230~264.5 V Default: 253 V
835E	<i>KvarOfUac_V_Lower</i>	Unit: 0.1 V Range: 184~230 V Default: 184 V
835F	<i>KvarOfUac_V_Upper</i>	Unit: 0.1 V Range: 230~264.5 V Default: 253 V
8360	<i>KvarOfUac_Hysteresis</i>	Unit: 0.1 V Range: 0~TBD V Default: 0 V
8361	<i>ReactivePower_ResponseDelay</i>	Unit: 0.01 sec Range: 0~120 sec Default: 10 sec
8362	<i>CosPhiOfPower_Lockin_V</i>	Unit: 0.1 V Range: 230.0~253.0 V Default: 241.5 V
8363	<i>CosPhiOfPower_Lockout_V</i>	Unit: 0.1 V Range: 207.0~230.0 V Default: 230.0 V
8364	<i>KvarOfUac_Lockin_PowerPercent</i>	Unit: 1 % Range: 10%~100% Default: 20 %
8365	<i>KvarOfUac_Lockout_PowerPercent</i>	Unit: 1 % Range: 5%~10% Default: 5 %
8366	<i>KvarOfUac_Delay_Time</i>	Unit: 0.01 sec Range: 0~120 sec Default: 0 sec
8367	xxx	
8368	xxx	
8369	xxx	
836A	xxx	
836B	xxx	
836C	xxx	
836D	xxx	
836E	xxx	
836F	xxx	