A/V Receiver Control Commands List

About Automatic Feedback

When the customer changes the status using key on the front panel or the remote controller of AV receiver,
AV receiver send new status automatically.
Also respond well when initially displayed.
(For ex.)   The user changes function on the front panel.
            Response from AV receiver : FN**<CR+LF>

Automatic feedback to all that response command written in commands_list is available.
However the following Command output is limited.

AV Receiver status	Response	Reason for limiting
POWER	PWR*<CR+LF>	When EXTENSION or RF Remote setting is ON, "PWR1" Command is guaranteed. The model not have EXTENSION Setup menu, "PWR1" Command is not guaranteed.
Response iPod meta data	GBI*<CR+LF> GCI*<CR+LF> GDI*<CR+LF> GEI*<CR+LF>	Except when the "time" information update
Response NETWORK meta data	GBH*<CR+LF> GCH*<CR+LF> GDH*<CR+LF> GEH*<CR+LF> GHH*<CR+LF>	
TUNER PRESET name	TQ*<CR+LF>	Only tuner presets that have changed name.

The following commands without the user event, automatically feedback if the state changes.

Function	Response
PLAYING LISTENING MODE	LM****<CR+LF>
Response iPod meta data	GBI*<CR+LF> GCI*<CR+LF> GDI*<CR+LF> GEI*<CR+LF>
Response NETWORK meta data	GBH*<CR+LF> GCH*<CR+LF> GDH*<CR+LF> GEH*<CR+LF>
FL display information	FL*<CR+LF>

The following commands written in commands_list5 are also given by automatic feedback.

Function	Response
Remote Play ZONE	RPZ*<CR+LF>