Tech Ops: Work order management — Trouble calls (TCs) standard policy

POL2166 | MODIFIED 04/01/2026

Summary

This document describes how trouble calls must be handled and defines cases where a TC may be canceled and replaced by a change of service (CoS).

Quick Links

- What's changed in this article
- At a glance
- Truck roll completion
  - Table 3-1: Truck roll completion codes
- Exceptions
  - Sanctioned "scrubbing" efforts
  - Failed Getting Started Kit (tech recovery)
  - Install-related
- Not home/no access
- System outage
- Converting TC to CoS
- Line of business error
- Cases when TC cannot be canceled

- Table 6-1: Cases where TC cancellation is not acceptable

What's changed in this article

Date	Summary of change
January 4, 2024	Replaced archived related article.
September 13, 2023	Clarified language around requesting CommOps support.

At a glance

A TC is a job created in response to a customer-reported service issue, real or perceived. TCs may be new, repeat, chronic or install-related. TCs are created with the presumption the customer's services have been installed and working properly and need repair. All TCs must be rolled upon and completed as scheduled.

Truck roll completion

For all completed TCs, technicians must enter the fix code that best describes the primary action taken to resolve the issue. Technicians must avoid using any secondary fix code in the primary/first code position. Secondary codes may be added in positions #2 through #6.

Table 3-1: Truck roll completion codes

Code	Short description	Detailed description	When to use
AM1*	AMPLEGCY-ID'fd	Legacy Unity Gain Amp Identified (already installed)	When on an install, CoS or service call technician verifies a legacy house amp exist at the premise. (This code should not be selected as the primary resolution code.)
AM2*	AMPMOCAID'fd	MoCA Unity Gain Amp Identified (already installed)	When on an install, CoS or service call technician verifies a MoCA Unity Gain Amp exist at the premise. (This code should not be selected as the primary resolution code.)
AM3*	AMPMOCA - INS/RPL	MoCA Unity Gain Amp Installed/Replace	When on an install, CoS or service call technician installs or replaces a MoCA house amp at the premise. (This code should not be selected as the primary resolution code.)

Code	Short description	Detailed description	When to use
AM4*	PASMOCAINS/RPL	MoCA Passive Installed/Replaced	When on an install, CoS or service call technician installs or replaces a MoCA/DOCSIS passive at the premise. (This code should not be selected as the primary resolution code.)
AM5*	PAS-MOCAID'fd	MoCA Passive Identified (already installed)	When on an install, CoS or service call technician verifies a MoCA/DOCSIS passive exist at the premise. (This code should not be selected as the primary resolution code.)
AM9*	AMP-REMOVED-AMP	Amp Removed Permanently from Premise	When on an install, CoS or service call technician removes amp from the premise (This code should not be selected as the primary resolution code.)

Code	Short description	Detailed description	When to use
B20	BIZ-ADV CPE	Advanced Services CPE replace and provision (BVE, METRO E, PRI, SDWAN)	Used when replacing or provisioning any Advanced Business Service customer premise equipment. This includes Metro E, BVE, PRI, Q2Q, SDWAN, EoHFC, Wi-Fi Pro, Connection Pro, MDTA or Mini MDTA, and any other Advanced services not listed. The associated product line will be tied to the job type of the TC for mapping purposes, e.g., BVE job type would indicate BVE equipment being swapped.
E03	CUST ED	CUSTOMER EDUCATION	When educating a customer at any point for any product. We would tie the customer education to the specific job type of the call, i.e., X1 TC would tie to customer education on X1. (This is a chargeable code for the customer.)
H22	INT-GW MTA RPRV	INTERNET - GATEWAY/EMTA REPROVISIONED	When provisioning a Gateway/eMTA/Business Modem that lost provisioning. Would also include if/when Static IP needed to be loaded.

Code	Short description	Detailed description	When to use
ME1	ME-OPTIC RPL	ME OPTIAL REPLACE	When swapping or replacing an optical device during a Metro E job.
O01	DRP-CONN REPL	DROP RELATED - CONNECTOR(S) REPLACED	When replacing a connector (coax or fiber) at a premise.
S32	XH-Sensor RPL	Security - SENSOR(S) REPLACED	When replacing any security (Xfinity Home or SmartOffice) sensor or lifestyle device (excluding cameras). This would include door/window, light modules, motion sensors, keypads, etc.
S33	XH-TS RPL/PRV	XH - TOUCHSCREEN DEVICE REPLACED OR PROVISIONED	When replacing or provisioning a touchscreen for Xfinity Home or SmartOffice.
S35	XH-CAM RPL	SEC- CAMERA REPLACED / RESET	When replacing or repairing a camera within Xfinity Home/SmartOffice.
S43	XH-Other	SEC - Other (panel swap, fire code etc.)	To capture any other security related activity e.g., swap panel, fire alarm confirmation, SmartOffice switch replacement.
T01	DRP-OH DRP RPL	DROP RELATED - OVERHEAD DROP / AERIAL REPLACED	Replacing an Aerial drop on an install, change or trouble call.

Code	Short description	Detailed description	When to use
T03	DRP-UG DRP RPL	DROP RELATED - UNDERGROUND DROP REPLACED	Replacing an Underground drop on an install, change or TC.
T04	DRP-RAN TEMP UG	DROP RELATED - INSTALLED TEMP LINE / REFER FOR UG	Laid an Underground drop above ground to restore customer service and referred the job to be bury service drop.
T05	DRP-CUT DRP RPR	DROP RELATED - REPAIRED CUT DROP	Used when splicing/fixing a service drop that was cut/damaged.
T12	DRP-GND BLK RPL	DROP RELATED - GROUND BLOCK REPLACED	Used when technicians replace a groundblock and/or brings the home to code.
T13	DRP-SPLTTR RPLC	DROP RELATED - SPLITTER(S) REPLACED	Used when technicians replace a splitter on the premise.
T15	DRP-TRAP IN/RPL	DROP RELATED - TRAP INSTALLED OR REPLACED	Used when technicians install or replace a trap/filter (noise/ingress, MoCA filter) at a premise.
T22	WRONG RATE CODE	ACCOUNT RELATED - WRONG SERVICE CODE CAUSED SERVICE ISSUE	Used when a modification to the account (rate code specific adjustment) or updated service hit (INIT, UDB refresh etc.) is used to correct the premise.

Code	Short description	Detailed description	When to use
T24	REPLACE CPE	REPLACED CPE (Video, Data, Voice)	Used to replace any CPE at a premise (this should not be used for advanced services B20). The CPE would attribute to the type work order that is created, e.g., DVR job type, CPE swap would tie to video swap, Xfinity Internet TC would tie to modem/gateway swap.
T25	NON CPE SWAP	NON CPE SWAP	When swapping a device or peripherals not considered CPE.
T34	CUST EQP	CUSTOMER EQUIPMENT PROBLEM	Used when verifying that any customer owned equipment/software is causing the concern at the premise. This is to be used for both residential and business services. Technicians should make a note on the account within Tech360 to specify any additional details. (This is a chargeable code for the customer.)

Code	Short description	Detailed description	When to use
T53	IW-CABLE RPL	INSIDE WIRING - CABLE REPLACED (Video/Data/Fiber)	Used when replacing any cabling inside a premise. This includes coax, Ethernet, HDMI, or Fiber Jumpers. This is a chargeable code for a customer.
T74	INT-HN CONFIG	INTERNET - CORRECTED HOME NETWORK CONFIGURATION	Used when configuring wireless or network related functions for a customer in a residential or business location. This is a chargeable code for the customer.
T92	DV-TELE WIRING	VOICE - PHONE WIRING REPLACED/REPAIRED	Used when repairing or replacing any phone related wiring in a premise (residential or business). This is inclusive of scotch locks, jumpers, phone jacks or punchdown blocks. This is a chargeable code to the customer.
U31	REF TO MAINT	REFER TO MAINTENANCE	Used when referring a job to the maintenance department. Technicians should ensure an RTM form is filled out and they have a confirmed JB number validating the submission.

Code	Short description	Detailed description	When to use
U32	REF TO CONST	REFER TO CONSTRUCTION	Used when referring a job that needs construction related activity. Not to be used for Underground service drop referrals. This could include a custom wall outlet or MDU rewire.
U36	REF TO SUPER	REFER TO SUPERVISOR	Used when referring a job to the technician's immediate supervisor to escalate to bring other departments in for resolution. Technicians should submit a note on the reason for the referral.
U44	REF TO UNDGRND	REFER TO UNDERGROUND	Used when referring a job to the Underground service drop teams within the region. Technicians should leverage the One Drop App submission process to ensure the drop is set for replacement. Additionally, this should be done while onsite so accurate capture of job detail can be done.

***Note:** AM1, AM2, AM3, AM4, AM5, and AM9 are to be used only as secondary codes (positions #2 through #6). On any TC, a technician must first select the primary resolution code before placing a secondary code.

Exceptions

All TCs must be rolled upon and completed as scheduled with exceptions for the following scenarios **only**:

- Sanctioned "scrubbing" efforts
- Failed Getting Started Kit (tech recovery)
- Install-related

All other service issues, real or perceived, must be completed with the appropriate TC fix code. This includes cases where the TC is resolved by customer education or technician's determination of customer premise/equipment problems.

Note: For all other questions regarding cancellations and rescheduling, refer to the **CEI policy**.

Sanctioned "scrubbing" efforts

- **Specialized teams may contact customers with pending TCs** to resolve service issues faster than the scheduled TC.
- These groups will confirm restoration of services and proceed with cancellation of TC if appropriate.
- Prior call ahead activities should take place only within authorized centers.
- Technicians or dispatch agents should not make calls ahead in attempt to clear TC unless directed by their senior leadership team.

Failed Getting Started Kit (tech recovery)

- If a technician arrives to a TC and finds that a Getting Started Kit Activation has taken place within 30 days of TC creation, the TC job should be canceled and replaced by a Failed Getting Started Kit (Tech Recovery job type) job for the same date and time.
- There must be no jobs between Getting Started Kit Activation and the TC.
- The TC is only eligible for cancellation if it's the first TC scheduled after Getting Started Kit Activation.
- Any TC that was scheduled 30 days after the Getting Started Kit cannot be canceled.
- For more details on troubleshooting failed Getting Started Kit, refer to **Troubleshooting Failed Getting Started Kit Bulletin**.

Scenario	Customer-generated TC use case
Failed Getting Started Kit <30 days after purchase	Customer reports their TV, Xfinity Internet, or Xfinity Voice service are not working and, upon arrival, the technician learns that the customer had a Getting Started Kit in the last 30 days. Failed Getting Started Kit includes issues with in home wiring, issues with outside wiring, provisioning of the device in question and sometimes the inability of the customer to properly perform the installation. For more details on troubleshooting failed Getting Started Kit, refer to **Troubleshooting Failed Getting Started Kit Bulletin**. Any TC that was scheduled 30 days after the Getting Started Kit cannot be canceled.

Install-related

- If a technician arrives to a scheduled TC and finds that there are no service issues present, but instead customer is requesting additional services such as device or outlet changes, the technician may contact CommOps to have the TC canceled.
- In these cases, the CommOps partner should create the appropriate CoS job type to represent customer needs on-site and determine if technician is able to complete same day.
- **Notes:**
  - The CoS is chargeable and customer consent should be captured.
  - If the job is a drop bury, low hanging drop or any other non-service impacting appointment, perform the same work as if the job were an “Ok on Arrival”/No Access scenario and close job appropriately.
  - A new SRO job should be created to ensure follow-up work.

Not home/no access

TCs must **not** be rescheduled in cases where the customer is not home, or technician has no access to necessary areas/equipment. This job must be completed with the proper resolution

code from Table 2-1.

Table 2-1: Not Home/ No Access and System Outage Completion

Accepted not home/no access truck completion codes		Use case
U10	Not Home - Checked outside only	Used when a customer is not home, and the technician was able to check outside connections at the premise.
U11	Customer Home - No Access	Used when technicians contact the customer, however, could not access a location/room on the premise, preventing the technician from resolving the work order.
U12	Not Home and No Outside Check	Used when the customer is not home, and the technician was unable to check/verify the outside connections.
U14	Customer Refused Entry	Used when the customer cancels upon technician arrival and does not allow any work to be completed.
U21	Okay on Arrival	Used after all troubleshooting has been completed. Technician determines customer is not having any service issues and has a passing PHT score.

Note: In any case where the customer does not answer the automated pre-call reminder or confirms through the text message, the TC cannot be canceled. Technician must arrive at TC as scheduled and complete with the appropriate fix code to indicate not home or no access.

System outage

If a TC was scheduled during an active outage or system issue (billing system) and the outage might impact the job, the TC should be rescheduled with a system outage reschedule reason. The customer must be notified prior to the TC being rescheduled.

Note: Make every effort to reschedule the appointment during the same day unless requested by the customer.

Converting TC to CoS

TCs are created with the presumption that the customer's services have been installed and need repair. After arriving on a scheduled TC, and the technician determines services need to be added or installed, the trouble call can be canceled by the TSC and the correct CoS order keyed.

A CoS order is an install order that is generated to add/remove product or services with the appropriate installation fees and monthly recurring charges to the customer's account.

Line of business error

If TC scheduled is for the wrong line of business, and the technician does not have the proper Commercial, SmartOffice or Pro Protection skill set, they may request CommOps to have a same day tech assist in addition to performing service checks for services within their skill set and/or licensing. If there is no availability for a same day tech assist, the TC should still be completed to the best of the technician's capability and a new Special Request Order (SRO) job type will be created for additional work needed.

Cases when TC cannot be canceled

Note: Work orders should not be canceled after 9:00 p.m. unless it was a customer request
.

Table 6-1: Cases where TC cancellation is not acceptable

Scenario	Action	Fix Codes*
Technician rolls to customer's home, but the customer refuses technician entrance into the home stating no further service issues.	Once a Trouble Call has been rolled to the customer's home, the work order must be completed and counted as a Trouble Call. Technician should complete the job with a Customer Home – No Access code.	• U14 Cust Refused Entry • Please note that in certain regions, technicians must call into the TLC to verify and close out this scenario.
There is no one home over the age of 18, the technician cannot access the premises.	Once a Trouble Call has been rolled to the customer's home, it must be completed and counted as a Trouble Call. Note: Please follow local policy and process. Technician should either check outside or immediately complete the work order with a No Adult No Access code or No Adult Checked Outside.	• U10: NH-Checked Outside • U12: NH No Outside CHECK

Scenario	Action	Fix Codes*
Technician rolls to customer's home, but the customer is not home.	Once a Trouble Call has been rolled to the customer's home, the work order must be completed and counted as a Trouble Call. Technician should reach out to supervisor and dispatcher to confirm not home. Job should be completed with proper Not Home codes.	• U10: NH-Checked Outside • U12: NH No Outside CHECK

↑ Back To Top

Related Articles

- Trouble call (TC) scheduling and charging policy
- Xfinity Communities trouble call (TC) policy