DEJ SOFTWARE™

PHAROS DATA ARK

Complete appliance

A complete Data Ark includes its host and prepared system storage, with either an external library drive or a system-drive library. Installed content needs no internet connection.

Your one-time setup code



Use the private code supplied with this card or appliance.

(Prevents nearby setup-time hijacking.)

What you need

- The supplied host, system storage, power supply and any supplied library drive.
- A browser device on the hotspot or the same local network.

First start

1. Connect the supplied library drive, if any, before applying power.
2. For a hotspot appliance, join its supplied Wi-Fi network and open http://192.168.4.1/setup.html.
3. For a LAN appliance, connect it and your browser to the same local network; use the device address supplied with it.
4. If first-owner setup is pending, enter the supplied private code and choose the two passwords. If the owner already set credentials locally, no additional code step is needed.

> **Caretaker password:** authorizes web changes when prompted.
>
> **Linux admin password:** protects SSH and terminal access as `admin`. Use a different, particularly strong password. Both passwords require at least 12 characters; root login stays disabled.
>
> Five wrong codes trigger a one-minute pause. Successful setup retires the code. Complete initial HTTP setup privately before inviting others.

Browsing installed content needs no password. No online activation, registration or DEJ Software account is required.

PHAROS DATA ARK

Hardware & operating notes

- Keep the supplied storage attached while the appliance is running.
- Use System / System / Power to restart or shut down safely. A shutdown requires someone to power the device back on.

Further help

The complete handbook is included with the Ark. Online: dejsoftware.com/data-ark/docs/.

On an installed appliance, use System / System / Power before disconnecting power or removing storage. Containers use their host controls.