DEJ SOFTWARE™

PHAROS DATA ARK

Prepared microSD card

A prepared card turns a compatible Raspberry Pi into a local library. It can serve its installed content without internet access. The supplied card determines the installed selection and capacity.

Your one-time setup code

_ _ _ _

Use the private code supplied with this card or appliance.

(Prevents nearby setup-time hijacking.)



What you need

- A compatible Raspberry Pi, power supply and cooling. The tested reference is a Pi 4 Model B with 2 GB RAM.
- A phone, tablet or computer with a browser. The built-in Wi-Fi is sufficient; an external USB radio is optional.

First start

1. With the Pi powered off, insert the supplied microSD card and connect power.
2. Join the DataArk hotspot. If your device reports no internet, choose to stay connected.
3. Open http://192.168.4.1/setup.html and enter the private setup code supplied with this card.
4. Choose separate caretaker and Linux admin passwords. Allow the first startup a few minutes.

> **Caretaker password:** authorizes web changes when prompted.
>
> **Linux admin password:** protects SSH and terminal access as `admin`. Use a different, particularly strong password. Both passwords require at least 12 characters; root login stays disabled.
>
> Five wrong codes trigger a one-minute pause. Successful setup retires the code. Complete initial HTTP setup privately before inviting others.

Browsing installed content needs no password. No online activation, registration or DEJ Software account is required.

PHAROS DATA ARK

Hardware & operating notes

- Tested reference: Raspberry Pi 4 Model B, 2 GB RAM; CanaKit 3.5 A USB-C power supply; ventilated MazerPi case with fan and heatsinks.
- A Pi 4 with 4 GB or 8 GB RAM provides more headroom. Use a reliable supply and cooling.
- Optional range: a Linux-supported USB Wi-Fi adapter with external antenna and access-point support. Assign it to the hotspot under Wi-Fi or Hotspot / Wi-Fi adapter assignment; plugging it in alone does not change roles.
- Optional storage: add an external USB content drive using System / Library / Use an external library drive. Existing content can be copied and verified before switching. Use adequate peripheral power.

Further help

The complete handbook is included with the Ark. Online: dejsoftware.com/data-ark/docs/.

On an installed appliance, use System / System / Power before disconnecting power or removing storage. Containers use their host controls.