☰   💬   ?

New Driver   modified   « Drivers code (/driver/list)   Import   Tabs   ⌄ 4 ⌄ No wr

```
 1    Instructions
 2    /*
 3    a.   Remove current instance for HubiThings Replica
 4    b.   Turn your TV ON and make sure you are in digital
 5         tV Mode (i.e., not on an HDMI channel).
 6    c.   Install the new driver code.
 7    d.   Reinstall the TV through HubiThings Replica
 8    e.   Open the device's edit page.
 9    f.   Enter your TV's IP Address and SAVE PREFERENCES.
10    g.   Wait 10 or so seconds.
11    i.   Connect to the TV for local functions
12         1.   Press Menu
13         2.   On the TV Screen, respond to the pop-up with
14              "allow:
15         3.   wait 30 secs then press Home - note home
16              display on set.
17         You should now be set for local control.
18
19    Testing Local functions.
20         1.   Turn the TV OFF. And wait 2 minutes
21              (The TV STATUS reporting can get confused (even
22               for SmartThings) with quick power-off / power
23               on cycles.  TV still works - just power state is
24               incorrect.)
25              a. attribute Switch becomes "off" very quickly.
26              b. About 30 seconds later, wsStatus is "closed-failure"
27         2.   Turn the TV On
28              a.   TV Turns on and switch becomes "on"
29         3.   Press HOME
30              a.   wsStatus "open"
31              b.   Home screen displays.
32              c.   Press home again to eliminate home screen.
33
34    Verifying SmartThings Status interface.
35         1.   Open Samsung TV Plus to any channel
36              (HOME key then arrow keys for navigation.  ENTER
37               when at the TV Plus icon.)
38              a.   Note attributes tvChannel and tvChannelName
39                   are populated.  This takes 5 seconds to populate
40                   due to timing issues.
41         2.   Press channelUp and not changes in tvChannel data.
42         3.   Go to key Set Tv Channel and enter a valid channel
43              number.  Same result in TV Data
```

Documentation   Community   Videos   FAQ