

TUSCAN 2K MONITOR

TCL Z80 ASSEMBLER PAGE 0017

ADDR	CODE	STMT	SOURCE STATEMENT
		0930 ;	- CY = 1 IF NO PARAMETER READ
		0931 ;	- BUFPTR UPDATED AS CHARACTERS READ
		0932 ;	DESTROYS- BC,DE,FLAGS
		0933 ;	
FBF4	CDA6FB	0934	PARAM: CALL GETUCT ;GET CHARACTER
FBF7	210000	0935	LD HL,0 ;DEFAULT PARAMETER
FBFA	D8	0936	RET C ;TERMINATOR
FBFB	FE27	0937	CP ;ASCII LITERAL FLAG?
FBFD	200F	0938	JR NZ,NOTLIT ;NO,TRY DECIMAL
FBFF	CD9BFB	0939	CALL GEICH ;GET LITERAL
FC02	FE0D	0940	CP CR ;CHECK FOR ABSENT CHAR
FC04	28D8	0941	JR Z,PARER ;ERROR
FC06	6F	0942	LD L,A ;SAVE ASCII
FC07	CDA6FB	0943	CALL GETUCT ;GET TERMINATOR
FC0A	30D2	0944	JR NC,PARER ;NOT THERE
FC0C	3F	0945	CCF ;CY=0
FC0D	C9	0946	RET
FC0E	FE23	0947	NOTLIT: CP DECMRK ;DECIMAL FLAG?
FC10	2011	0948	JR NZ,HEX ;NO,TRY HEX
FC12	CDBAFB	0949	DECPAR: CALL GEIDEC ;GET DECIMAL DIGIT
FC15	3F	0950	CCF ;CY=0
FC16	D0	0951	RET NC ;GOT TERMINATOR
FC17	E5	0952	PUSH HL
FC18	D1	0953	POP DE ;COPY OF HL
FC19	29	0954	ADD HL,HL ;HL=HL*10
FC1A	29	0955	ADD HL,HL
FC1B	19	0956	ADD HL,DE
FC1C	29	0957	ADD HL,HL
FC1D	0600	0958	LD B,0 ;BC=NEW DIGIT
FC1F	4F	0959	LD C,A
FC20	09	0960	ADD HL,BC
FC21	18EF	0961	JR DECPAR ;GET NEXT CHAR
FC23	CDCCFB	0962	HEX: CALL HEXCHK ;ENSURE A IS HEX
FC26	29	0963	HEXPAR: ADD HL,HL ;HL=HL*16
FC27	29	0964	ADD HL,HL
FC28	29	0965	ADD HL,HL
FC29	29	0966	ADD HL,HL
FC2A	85	0967	ADD A,L ;ADD NEW DIGIT
FC2B	6F	0968	LD L,A ;NO CARRY POSSIBLE
FC2C	CDC8FB	0969	CALL GETHEX ;TRY FOR ANOTHER DIGIT
FC2F	30F5	0970	JR NC,HEXPAR ;GOT ONE
FC31	3F	0971	CCF
FC32	C9	0972	RET ;CY=0
		0973 ;	
		0974 ;	GET2PAR- SR TO READ UPTO 2 PARAMETERS FROM THE INPUT
		0975 ;	BUFFER AND STORE THEM IN PAR1 & PAR2. THE NUMBER
		0976 ;	OF PARAMETERS READ (0,1 OR 2) IS SAVED IN NPARS.
		0977 ;	INPUTS - NONE
		0978 ;	OUTPUTS- NPARS = # OF PARAMETERS READ
		0979 ;	PAR1 = 1ST PARAMETER (IF ANY)
		0980 ;	PAR2 = 2ND PARAMETER (IF ANY)
		0981 ;	A=LAST TERMINATOR FOUND (COMMA OR <CR>)
		0982 ;	DESTROYS-AF',A,FLAGS,HL,DE,BC (ABORTS VIA PARER IF ERROR)
		0983 ;	
FC33	AF	0984	GET2PAR: XOR A ;NO PARAMETERS READ YET
FC34	08	0985	EX AF,AF' ;SAVE CTR
FC35	CDF4FB	0986	CALL PARAM ;READ 1ST PARAMETER
FC38	3813	0987	JR C,ALLREAD ;NOT THERE