

TUSCAN 2K MONITOR
ADDR CODE

SMT SOURCE STATEMENT

TCL Z80 ASSEMBLER PAGE 0025

```

FE42 CDADFA 1394 CALL BUFFCR
FE45 CD64FE 1395 CALL FLAGDIS ;DISPLAY FLAGS
FE48 116800 1396 LD DE,ISAV+1 ;GET I
FE4B 1A 1397 LD A,(DE)
FE4C 13 1398 INC DE
FE4D 13 1399 INC DE
FE4E CD91FC 1400 CALL PRTASP ;DISPLAY IT
FE51 1A 1401 LD A,(DE) ;GET A
FE52 13 1402 INC DE
FE53 CD91FC 1403 CALL PRTASP ;AND DISPLAY IT
FE56 0607 1404 LD B,7 ;7 DOUBLE REGISTERS
FE58 1A 1405 PRITDBL: LD A,(DE) ;GET REGISTER CONTENTS
FE59 6F 1406 LD L,A
FE5A 13 1407 INC DE
FE5B 1A 1408 LD A,(DE)
FE5C 67 1409 LD H,A
FE5D 13 1410 INC DE
FE5E CD8CFC 1411 CALL PRTHLSP ;PRINT VALUE
FE61 10F5 1412 DJNZ PRITDBL ;PRINT OTHERS
FE63 C9 1413 RET
1414 ;
FE64 2191FF 1415 FLAGDIS: LD HL,FLGTAB ;PTR TO MASKS
FE67 0606 1416 LD B,6 ;6 FLAGS
FE69 3A6900 1417 PRITFLG: LD A,(AFSAV) ;GET FLAGS
FE6C A6 1418 AND (HL) ;TEST ONE
FE6D 23 1419 INC HL ;PTR TO NAME
FE6E 7E 1420 LD A,(HL) ;GET IT
FE6F 2002 1421 JR NZ,FLAGSET ;SET,SO PRINT NAME
FE71 3E2D 1422 LD A,'_' ;ELSE PRINT '_'
FE73 CDD4F8 1423 FLAGSET: CALL CONOUT
FE76 23 1424 INC HL
FE77 10F0 1425 DJNZ PRITFLG
FE79 C394FC 1426 JP SPACE ;FOLLOW WITH SPACE
1427 ;
1428 ;XAMIN - FUNCTION TO ALLOW THE PSEUDO REGISTERS TO BE
1429 ; DISPLAYED AND MODIFIED. THE COMMAND FORMATS ARE :
1430 ; X DISPLAY ALL REGISTERS
1431 ; XA DISPLAY & MODIFY A
1432 ; XI DISPLAY & MODIFY I
1433 ; XF DISPLAY & MODIFY FLAGS
1434 ; XB DISPLAY & MODIFY BC
1435 ; XD DISPLAY & MODIFY DE
1436 ; XH DISPLAY & MODIFY HL
1437 ; XX DISPLAY & MODIFY IX
1438 ; XY DISPLAY & MODIFY IY
1439 ; XS DISPLAY & MODIFY SP
1440 ; XP DISPLAY & MODIFY PC
1441 ;
FE7C CDA6FB 1442 XAMIN: CALL GETUCT ;GET REGISTER LETTER
FE7F 38BE 1443 JR C,RDIS ;NONE,SO PRINT ALL
FE81 FE46 1444 CP 'F' ;FLAGS?
FE83 283B 1445 JR Z,FLGMFY
FE85 FE41 1446 CP 'A' ;A?
FE87 2825 1447 JR Z,ACCMFY
FE89 FE49 1448 CP 'I' ;I?
FE8B 2826 1449 JR Z,INTMFY
FE8D 219DFF 1450 LD HL,REGTAB ;TEST FOR OTHER POSSIBILITIES
FE90 010800 1451 LD BC,8 ;BY A TABLE SEARCH

```