



Uref 0...2.5V (0.11 Ohm sense resistor)  
>=2.50V 100% - 1.77A RMS  
1.25V 50% - 0.88A RMS  
0.50V 20% - 0.35A RMS

EN (with pull-up)  
GND driver enabled  
VCC driver disabled

PDN/UART (with pull-down)  
GND automatic standstill current reduction  
VCC automatic standstill power down disable  
optional UART interface

MS1	MS2	Steps	Interpolation
GND	GND	8	Yes to 256
UIO	GND	2	Yes to 256
GND	UIO	4	Yes to 256
UIO	UIO	16	Yes to 256
SPREAD (with pull-down)			
GND	GND	stealthChop	
UIO	UIO	spreadCycle	

To access all other modes you have to use the UART interface.

# Component Side View (Bottom)

