


Standalone Operation (SPI_MODE=GND)

CFG6/En → Driver enabled
GND → Driver disabled
Vio → Driver disabled
Open → Driver enabled with ramp down from 100% to 34% after about 3 s



CFG2	CFG1	Steps	Interpolation	Chopper	Mode
GND	GND	1	No		spreadCycle
GND	Vio	2	No		spreadCycle
GND	Open	2	Yes	to 256	spreadCycle
Vio	GND	4	No		spreadCycle
Vio	Vio	16	No		spreadCycle
Vio	Open	4	Yes	to 256	spreadCycle
Open	GND	16	Yes	to 256	spreadCycle
Open	Vio	4	Yes	to 256	spreadChop
Open	Open	16	Yes	to 256	stealthChop

Component Side View (Bottom)

