



HP LaserJet Managed Flow MFP M830 –
Service Cost Data
(HP Internal and Channel Partner only)

© Copyright 2017 HP Development Company,
L.P.

Reproduction, adaptation, or translation without
prior written permission is prohibited, except as
allowed under the copyright laws.

The information contained herein is subject to
change without notice.

The only warranties for HP products and
services are set forth in the express warranty
statements accompanying such products and
services. Nothing herein should be construed as
constituting an additional warranty. HP shall not
be liable for technical or editorial errors or
omissions contained herein.

Edition 2, 9/2017

M c05766651
S c05838413

Table of contents

1 Introduction	1
2 Estimates for print usage and failure : AMPV and MIBF	2
Average Monthly Print Volume (AMPV) and Mean Images Between Failures (MIBF)	3
Estimated Recommended Print Volumes and Maximum Usage	4
3 Mean Time to Repair (MTTR)	5
4 Product and Consumable Life	6
Product Engine and Scanner Life	7
Consumable Life	8
Maintenance Schedule	9
5 Part Stocking	10
Consumables and Maintenance Kits	11
Service Parts	12
Field Stock	14
6 Installation, Training and Escalation process	15
Installation Process	15
Training	15
Escalation Process	15
Appendix A Appendix A: Site Requirements	16
Product dimensions and weight	17
Box dimensions and weight	18
Serviceability Space Requirements	18
Acoustic Specifications	18
Environmental specifications	18
Guidelines	19
Recommended specifications	19

Power Requirements 19

1 Introduction

The intent of this document is to provide initial product information to resellers and managed print service providers. It is not intended for end-user or customer use. The data contained within this document reflect estimates made without actual field data, and are intended as guidelines. Confidentiality and nondisclosure agreements apply to the use of the information contained herein.

Actual product performance is dependent on several factors, including, but not limited to type of usage or workflows, environmental conditions, media types, and proper preventative maintenance.



NOTE: All part numbers listed in the document might change.

2 Estimates for print usage and failure : AMPV and MIBF

This section provides information on the following topics:

- [Average Monthly Print Volume \(AMPV\) and Mean Images Between Failures \(MIBF\)](#)
- [Estimated Recommended Print Volumes and Maximum Usage](#)

Average Monthly Print Volume (AMPV) and Mean Images Between Failures (MIBF)

Average Monthly Print Volume (AMPV): The average number of images printed or copied per month.

 **NOTE:** An image is defined as a single-sided letter/A4 page.

Mean Images Between Failures (MIBF): Value is calculated based on AMPV and estimated annualized service event rate.

Mean Images Between Visits (MIBV): For all maintenance items replaced by the customer, MIBV is the same as MIBF.

Table 2-1 AMPV and MIBF

AMPV	MIBF
Up to 30,000	1,152,000 images
30,000 – 60,000	1,152,000 images
60,000 – 90,000	1,152,000 images
90,000 – 120,000	1,152,000 images

Estimated Recommended Print Volumes and Maximum Usage

Recommended Monthly Print Volume (RMPV): The estimated number of images printed per month by the average target customer for the product.

It considers the device usage expectations, device robustness, and approximate monthly intervention rates. The RMPV value assists customers to choose an appropriate product to fit their expected average usage needs.

Maximum Monthly Usage (Duty Cycle): A term used broadly in the printer industry to communicate the robustness of the device. It is the estimated maximum capability of the device.

Mean Time Between Failures (MTBF): Value is calculated based on recommended AMPV and estimated annualized service event rate.

MTBF estimates for an HP LaserJet Managed Flow MFP M830 is 2.8 years.

Table 2-2 Product estimates for monthly usage

HP LaserJet Managed Flow MFP M830	Estimated usage
Recommended Monthly Print Volume (RMPV)	15,000 – 100,000 images
Maximum Monthly Usage (Duty Cycle)	up to 450,000 images total print and scan
Estimated Average Monthly Scanner Usage	26,750 – 44,500 images

3 Mean Time to Repair (MTTR)

The **Mean Time to Repair (MTTR)** is the average time required to replace an individual part in the product.

Service MTTR is the average time required to replace an individual part, assuming that a customer replaces all maintenance items.

Maintenance MTTR is the average time required to replace an individual consumable. This includes the hardware system maintenance checklist.

Overall MTTR is the average time required to replace an individual component (part or consumable), assuming the service technician replaces all maintenance items.

Table 3-1 MTTR

MTTR	Time
Service MTTR	45 minutes
Maintenance MTTR	20 minutes
Overall MTTR	35 minutes

4 Product and Consumable Life

- [Product Engine and Scanner Life](#)
- [Consumable Life](#)
- [Maintenance Schedule](#)

Product Engine and Scanner Life

This is the number of pages the product was designed to perform at a given failure rate. The product will continue to work past this number of pages; however, the MIBF will decrease as the product is used.

Actual engine life is dependent on several factors such as usage, environmental conditions, and proper preventative maintenance.

Table 4-1 Life of components

Component	Life
Print Engine	4,000,000 images
Flatbed Scanner	300,000 images
ADF Scanner	1,500,000 images
3500 Sheet HCI	4,000,000 images
Stapler/Stacker	4,000,000 images
Stapler/Stacker hole puncher	4,000,000 images
Booklet Maker	4,000,000 images

When the product has exceeded its rated life or has a regular extremely high usage (High RMPV at more than 112,000 images per month over more than two years), additional failures might occur. Potential failures include squeaking gears and more frequent paper jams.

Some of the parts that might have an increased failure rate are listed in the following table:

Table 4-2 Parts that have an increased failure rate

HP Part Number ¹	Part Description
C3F79-67901	High capacity input (HCI) tray assembly
RM1-9788-000CN	Fusing drive assembly
RM1-9742-000CN	Registration roller assembly
RM1-9732-000CN	Face down paper delivery tray assembly
CF367-67920	ADF whole unit assembly
CF367-67919	Image scanner A3 paper size whole unit assembly

¹ All part numbers are subject to change.

Consumable Life

A customer or end user installs consumable items for a product. The rated life for each of the consumable components are listed in the following table:

Table 4-3 Consumable Life

Item name	Product Number	Part Number	Kit Components	Life
Fuser maintenance assembly kit – 110 VAC	C2H67A	C2H67-67901	(1) Fuser (1) Pressure roller (8) Feed rollers (2) Pick-up rollers	240,000 images ²³
Fuser maintenance assembly kit– 220 VAC	C2H57A	C2H57-67901	(1) Fuser (1) Pressure roller (8) Feed rollers (2) Pick-up rollers	240,000 images ²³
Black toner cartridge	CF325XC	CF325-67901	(1) Toner cartridge	42,600 ¹
2000-Staple cartridge kit (Booklet Maker)	CC383A	CF367-67914	Staple cartridge	2,000
Stapler cartridge refill kit (Stapler/ Stacker)	C8091A	C8085-60541	Staple cartridge	5,000 staples
ADF roller maintenance kit	C1P70A	C1P70-67901	ADF Pickup roller ADF Separation pad	100,000 pages

¹ Print cartridge life is approximate, based on average A4/Letter-size page count with ISO coverage. Declared cartridge yield value in accordance with ISO/IEC 19798. Actual yields vary considerably based on images printed and other factors. For more information, visit www.hp.com/go/learnaboutsupplies

² Adjust alert levels to extend fuser life.

³ Maintenance life will vary based on the average job length. For more information of the fuser life, refer the HP LaserJet Managed Flow MFP M830 Service Manual. The page count is only based on the ISO yields.

Maintenance Schedule

The maintenance kits for this product are categorized as Long Life Consumables and are captured in printing cost per page. For maintenance components and their replacement intervals, see [Consumable Life on page 8](#). All maintenance parts can be installed by the end user. No additional maintenance is required. The following table provides an example of a schedule:

Table 4-4 Example of a maintenance schedule

Pages	Server Maintenance Kit ¹	ADF Roller Kit ^{1,2}
100,000		
200,000		
240,000		
300,000		
400,000		
480,000		
500,000		
600,000		
700,000		
720,000		
800,000		
900,000		
960,000		

¹ MFP's control panel will prompt when replacement is necessary.

² Replacement interval is based on the total number of pages through the ADF, not total page count.

5 Part Stocking

The parts strategy is Field Replaceable Units (FRU) only.



NOTE: Parts are not available to be repaired at a lower level than stated here or in the product Service Manual.

Trunk Stock: This term refers to the following parts for a technician servicing up to 20 printers (HP LaserJet Managed Flow MFP M830).



NOTE: All part numbers are subject to change for the parts listed in this section.

- [Consumables and Maintenance Kits](#)
- [Service Parts](#)
- [Field Stock](#)

Consumables and Maintenance Kits

For consumables and maintenance components replacement intervals, see [Consumable Life on page 8](#)

Table 5-1 Consumables and Maintenance Kits

Part Number	Part Description	Quantity
5851-5857	A3 paper size ADF mylar kit	1
C2H67-67901	Fuser maintenance assembly kit – 110 VAC	1
CF325-67901	Black toner cartridge	2
C2H57-67901	Fuser maintenance assembly kit – 220 VAC	1
CF367-67914	2000-Staple cartridge kit (Booklet Maker)	1
C8085-60541	Stapler cartridge refill kit (Stapler/Stacker)	1
C1P70-67901	ADF Roller Maintenance kit	1

Service Parts

The Service Parts list includes an estimated failure rate per 100,000 pages and includes the parts to resolve approximately 80% of service calls.

Table 5-2 Service Parts

Part Number	Part Description	Quantity	Fails/100k Pages
CF367-67915	Formatter PC board assembly	2	0.039
CF367-67903	Tray 2 roller kit	2	0.004
5851-6632	Control panel assembly	1	0.016
RM2-0540-000CN	DC controller PC board assembly	1	0.007
CF367-67904	Tray 1 pick-up roller	1	0.001
CF367-67928	Fusing assembly – 110 VAC	1	0.013
CF367-67929	Fusing assembly – 220 VAC	1	0.013
CF367-67907	Transfer roller kit	1	0.002
C3F79-67901	High capacity input (HCI) tray assembly	1	0.001
CZ244-67903	High capacity input (HCI) right tray assembly	1	0.001
CZ244-67904	High capacity input (HCI) left tray assembly	1	0.001
CZ244-00028	Duplexing assembly	1	0.001
J8029-61001	Jetdirect 2800w NFC wireless D assembly	1	0.001
CF367-67911	Fax PC board assembly	1	0.001
L41606-011 or 933853-011	Self-Encrypting Drive, SED (HDD)	1	0.001
CF367-67917	1GB DIMM memory module	1	0.002
CF367-67920	ADF whole unit assembly	1	0.008
CF367-60002	Scanner control board assembly	1	0.003
5851-5864	Reflector foam A/3 paper size assembly	1	0.001
CF367-67919	Image scanner A3 paper size whole unit assembly	1	0.003
RM1-9742-000CN	Registration roller assembly	1	0.001
RM1-9767-000CN	High-voltage power supply	1	0.002
RM1-9788-000CN	Fusing drive assembly	1	0.001
RM1-9726-000CN	Cassette paper tray assembly (Tray 2, 3)	1	0.003
RM1-9765-000CN	Inter connect PC board assembly	1	0.004
RM1-9745-000CN	Paper pick-up assembly	1	0.001

Table 5-2 Service Parts (continued)

Part Number	Part Description	Quantity	Fails/100k Pages
RM2-5207-000CN	Laser scanner assembly	1	0.001
RM2-0558-000CN	Driver PC board assembly	1	0.001
RM2-0548-000CN	Low-voltage power supply assembly 110 VAC	1	0.002
RM2-0549-000CN	Low-voltage power supply assembly – 220 VAC	1	0.002

Field Stock

The suggested parts inventory for the HP LaserJet Managed Flow MFP M830 to stock at the field stocking locations are listed in the following table:

Table 5-3 Field Stock

Part Number	Part Description	Quantity
5851-5861	Background selector (for backside scan)	1
5851-5380	Keyboard assembly (US English)	1
5851-5008	Keyboard assembly (UK English)	1
J8026-61001	USB wireless print server kit	1
RM1-9784-000CN	Drum drive assembly	1
RM1-9707-000CN	Loop sensor (PS9) unit	1
RM2-0567-000CN	Controller PC board assembly	1
RM1-8879-000CN	Lifter drive assembly	1

6 Installation, Training and Escalation process

- [Installation Process](#)
- [Training](#)
- [Escalation Process](#)

Installation Process

This product is designed as customer installable. It requires two individuals to roll the printer off of the pallet. Additional installation requirements may vary by region or country.

Tools Required: None

Hardware installation time: Approximately 1 hour, depending on the configuration.

Training

Service Authorization for the HP LaserJet Managed Flow MFP M830 is obtained through media services, library, and WBT.

Training processes and availability vary by region/country. For details, refer the regional documentation.

Escalation Process

Escalation processes vary by region/country. For details, refer the regional documentation.

A Appendix A: Site Requirements

- [Product dimensions and weight](#)
- [Box dimensions and weight](#)
- [Serviceability Space Requirements](#)
- [Acoustic Specifications](#)
- [Environmental specifications](#)
- [Power Requirements](#)

Product dimensions and weight

The following table provides the maximum values for a product. Actual values will vary depending on the product configuration.

Table A-1 Product dimensions and weight

Height	Depth	Width	Weight ¹
1203 mm	761 mm	1103 mm	136 kg
(47.4 inches)	(30 inches)	(43.4 inches)	(300 lb)

¹ Without print cartridges.

Box dimensions and weight

The following table provides the values for each model and the appropriate input or output accessories.

Table A-2 Box dimensions and weight

Height	Depth	Width	Weight ¹
1561 mm	838 mm	856 mm	136 kg
(61.45 inches)	(32.99 inches)	(33.70 inches)	(300 lb)

Serviceability Space Requirements

Ensure the printer is installed in an area with enough space around it for proper service access and ventilation. Actual values will vary depending on the product configuration.

Table A-3 Serviceability space requirements

Height	Depth	Width
1593 mm	1196 mm	1363 mm
(62.7 inches)	(47.1 inches)	(53.7 inches)

Acoustic Specifications

Ensure the printer is installed in an area where the printer sound level will not disturb workers.

Table A-4 Sound power level

Acoustics: Sound power level	Declared per ISO 9296
Printing ¹	^L wAD=7.5 Bels (A) [75 dB (A)]
Copying ²	^L wAD=7.6 Bels (A) [76 dB (A)]
Ready	^L wAD=5.3 Bels (A) [53 dB (A)]

¹ Configuration tested for base model, simplex printing with A4 paper size

² Configuration tested for base model, simplex copying from ADF with A4 paper size.

Table A-5 Sound pressure level

Acoustics: Sound pressure level	Declared per ISO 9296
Printing	^L pAm=58 dB (A)
Copying	^L pAm=59 dB (A)
Ready	^L pAm=37 dB (A)

Environmental specifications

The environmental specifications must be maintained to ensure the proper operation of the device.

- [Guidelines](#)
- [Recommended specifications](#)

Guidelines

Consider the following points before installing the printer:

- Install the product in a well-ventilated, dust-free area.
- Install the product on a level, flat surface that can support its size and weight.

 **NOTE:** Do not install on carpet or other soft surfaces.

Make sure that all four device feet are level. Ensure Input stabilizers are in the down position.

- Install the product where temperature and humidity are stable, with no abrupt changes (away from water sources, humidifiers, air conditioners, refrigerators, or other major appliances.)
- Install the product away from direct sunlight, areas that experience vibration, open flames, ammonia fumes, ultrasonic heaters, and devices that emit a magnetic field.

If the printer is placed near a window, make sure that the window has a curtain or blind to block direct sunlight. Ensure the window is closed, so the temperature and humidity levels inside the room do not get affected by the outdoor environment.

Recommended specifications

The following table lists the recommended environment conditions:

Table A-6 Environmental specifications

Environmental Condition	Recommended	Allowed	Storage/standby
Temperature (MFP and print cartridge)	17° to 25° C (62.6° to 77° F)	15° to 30° C (59° to 77° F)	0° to 40° C (32° to 104° F)
Relative Humidity	30% to 70%	10% to 80%	10% to 90%
Altitude	Not applicable	0 to 3048 meters (0 to 10,000 feet)	Not applicable

Power Requirements

Power requirements are based on the country/region where the device is sold.

 **NOTE:** Do not convert operating voltages. This can damage the device and void the product warranty.

Table A-7 Power requirements

Specification	110–Volt models	220–Volt models
Power Requirements	110 to 127 volts ($\pm 10\%$)	220 to 240 volts ($\pm 10\%$)
	50/60 Hz (± 2 Hz)	50/60 Hz (± 2 Hz)
Rated current	11.0 Amps	5.5 Amps