

Register [DaveW DitroniX]	Register ID	Description	Area	Function	E32 Manf Defaults	IPEM SIX E32 Hex	HA/ESPHome Platform Phase
0x00	MeterEn	Metering Enable	Status Registers				
0x01	ChannelMapI	Current Channel Mapping Configuration	Status Registers		0x0210	0x0210	
0x02	ChannelMapU	Voltage Channel Mapping Configuration	Status Registers		0x0654	0x0654	
0x05	SagPeakDetCfg	Sag and Peak Detector Period Configuration	Status Registers		0x143F	0x143F	
0x06	OVth	Over Voltage Threshold	Status Registers		0xC000	0xC000	
0x07	ZXConfig	Zero-Crossing Config	Status Registers		0x0001	0xD654	
0x08	SagTh	Voltage Sag Th	Status Registers	vSagTh	0x1000	0x347B	
0x09	PhaseLossTh	Voltage Phase Losing Th	Status Registers		0x0400	0x0400	
0x0A	INWarnTh0	N Current Line Th	Status Registers		0xFFFF	0xFFFF	
0x0B	OIth	Over Current Threshold	Status Registers		0xC000	0xC000	
0x0C	FreqLoTh	Low Threshold for Frequency Detection	Status Registers		0x1324	0x1324	
0x0D	FreqHiTh	High Threshold for Frequency Detection	Status Registers	FreqHiThresh	0x13EC	0x13EC	
0x0E	PMPwrCtrl	Partial Measurement Mode Power Control	Status Registers		0x010F	0x010F	
0x0F	IRQ0MergeCfg	IRQ0 Merge Configuration	Status Registers		0x0000	0x0000	
0x10	DetectCtrl	Current Detect Controller	Low Power Registers		x	x	
0x11	DetectTh1	Channel CT1 Currrent Threshold in Detection Mode	Low Power Registers		x	x	phase_a
0x12	DetectTh2	Channel CT2 Currrent Threshold in Detection Mode	Low Power Registers		x	x	phase_b
0x13	DetectTh3	Channel CT3 Currrent Threshold in Detection Mode	Low Power Registers		x	x	phase_c
0x14	PMOffsetCT1	Ioffset for Phase A in Partial Measurment Mode	Low Power Registers		x	x	phase_a
0x15	PMOffsetCT2	Ioffset for Phase B in Partial Measurment Mode	Low Power Registers		x	x	phase_b
0x16	PMOffsetCT3	Ioffset for Phase C in Partial Measurment Mode	Low Power Registers		x	x	phase_c
0x17	PMPGA	OGAgain Configuration in in Partial Measurment Mode	Low Power Registers		x	x	
0x18	PMIRMSCT1	irms for Phase A in Partial Measurment Mode	Low Power Registers		x	x	phase_a
0x19	PMIRMSCT2	irms fDetectTh3r Phase B in Partial Measurment Mode	Low Power Registers		x	x	phase_b
0x1A	PMIRMSCT3	irms for Phase C in Partial Measurment Mode	Low Power Registers		x	x	phase_c
0x1B	PMConfig	Measure Configuraiton in Partial Measurment Mode	Low Power Registers		x	x	
0x1C	PMAvgSamples	Number of 8K samples to be averages in RMS/mean computation	Low Power Registers		x	x	
0x1D	PMIRMSLSB	LSB bits of PMRRrms (A/B/C)	Low Power Registers		x	x	
0x20	LOGIrms0	Current (Log Irms0) Configuration for Segment Compensation	Configuration Registers		0x0000	x	
0x21	LOGIrms1	Current (Log Irms1) Configuration for Segment Compensation	Configuration Registers		0x0000	x	
0x22	F0	Nominal Frequency	Configuration Registers		0x5000	x	
0x23	T0	Nominal Temperature	Configuration Registers		0x0025	x	
0x24	PhiAIrms01	Phase A Phase Compensation for Current Segment 0 and 1	Configuration Registers		0x0000	x	
0x25	PhiAIrms2	Phase A Phase Compensation for Current Segment 2	Configuration Registers		0x0000	x	
0x26	GainAIrms01	Phase A Gain Compensation for Current Segment 0 and 1	Configuration Registers		0x0000	x	
0x27	GainAIrms2	Phase A Gain Compensation for Current Segment 2	Configuration Registers		0x0000	x	
0x28	PhiBIrms01	Phase B Phase Compensation for Current Segment 0 and 1	Configuration Registers		0x0000	x	
0x29	PhiBIrms2	Phase B Phase Compensation for Current Segment 2	Configuration Registers		0x0000	x	
0x2A	GainBIrms01	Phase B Gain Compensation for Current Segment 0 and 1	Configuration Registers		0x0000	x	
0x2B	GainBIrms2	Phase B Gain Compensation for Current Segment 2	Configuration Registers		0x0000	x	
0x2C	PhiCIrms01	Phase C Phase Compensation for Current Segment 0 and 1	Configuration Registers		0x0000	x	
0x2D	PhiCIrms2	Phase C Phase Compensation for Current Segment 2	Configuration Registers		0x0000	x	
0x2E	GainCIrms01	Phase C Gain Compensation for Current Segment 0 and 1	Configuration Registers		0x0000	x	
0x2F	GainCIrms2	Phase C Gain Compensation for Current Segment 2	Configuration Registers		0x0000	x	
0x31	PLconstH	High Word of PL_Constant	Configuration Registers		0x0861	0x0861	
0x32	PLconstL	Low Word of PL_Constant	Configuration Registers		0xC468	0xC468	
0x33	MMode0	Metering Mode Config. Mains Frequency	Configuration Registers	_lineFreq	0x0087	0x0185	line_frequency
0x34	MMode1	Metering Mode Config. PGA Gain Configuration for Current Channels	Configuration Registers	_pgagain	0x0000	0x157F	gain_pga
0x35	PStartTh	Startup Power Th (P)	Configuration Registers		0x0000	0x1D4C	
0x36	QStartTh	Startup Power Th (Q)	Configuration Registers		0x0000	0x1D4C	
0x37	SStartTh	Startup Power Th (S)	Configuration Registers		0x0000	0x1D4C	
0x38	PPhaseTh	Startup Power Accum Th (P)	Configuration Registers		0x0000	0x02EE	
0x39	QPhaseTh	Startup Power Accum Th (Q)	Configuration Registers		0x0000	0x02EE	

0x3A	SPhaseTh	Startup Power Accum Th (S)	Configuration Registers		0x0000	0x02EE	
0x41	PoffsetCT1	CT1 Line Power Offset (P)	Calibration Registers		0x0000		phase_a
0x42	QoffsetCT1	CT1 Line Power Offset (Q)	Calibration Registers		0x0000		phase_a
0x43	PoffsetCT2	CT2 Line Power Offset (P)	Calibration Registers		0x0000		phase_b
0x44	QoffsetCT2	CT2 Line Power Offset (Q)	Calibration Registers		0x0000		phase_b
0x45	PoffsetCT3	CT3 Line Power Offset (P)	Calibration Registers		0x0000		phase_c
0x46	QoffsetCT3	CT3 Line Power Offset (Q)	Calibration Registers		0x0000		phase_c
0x47	PQGainCT1	CT1 Line Calibration Gain	Calibration Registers		0x0000		phase_a
0x48	PhiCT1	CT1 Line Calibration Angle	Calibration Registers		0x0000		phase_a
0x49	PQGainCT2	CT2 Line Calibration Gain	Calibration Registers		0x0000		phase_b
0x4A	PhiCT2	CT2 Line Calibration Angle	Calibration Registers		0x0000		phase_b
0x4B	PQGainCT3	CT3 Line Calibration Gain	Calibration Registers		0x0000		phase_c
0x4C	PhiCT3	CT3 Line Calibration Angle	Calibration Registers		0x0000		phase_c
0x51	PoffsetCT1F	CT1 Fund Power Offset (P)	Fundamental Harmonic Energy Calibration Registers		0x0000		phase_a
0x52	PoffsetCT2F	CT2 Fund Power Offset (P)	Fundamental Harmonic Energy Calibration Registers		0x0000		phase_b
0x53	PoffsetCT3F	CT3 Fund Power Offset (P)	Fundamental Harmonic Energy Calibration Registers		0x0000		phase_c
0x54	PGainCT1F	CT1 Fund Power Gain (P)	Fundamental Harmonic Energy Calibration Registers		0x0000		phase_a
0x55	PGainCT2F	CT2 Fund Power Gain (P)	Fundamental Harmonic Energy Calibration Registers		0x0000		phase_b
0x56	PGainCT3F	CT3 Fund Power Gain (P)	Fundamental Harmonic Energy Calibration Registers		0x0000		phase_c
0x61	UGainCT1	CT1 Voltage RMS Gain	Measurement Calibration Registers	_uGainCT1	0x8000	0x959C	phase_a
0x62	IGainCT1	CT1 Current RMS Gain	Measurement Calibration Registers	_iGainCT1	0x8000	0x9664	phase_a
0x63	UoffsetCT1	CT1 Voltage Offset	Measurement Calibration Registers		0x0000		phase_a
0x64	IoffsetCT1	CT1 Current Offset	Measurement Calibration Registers		0x0000		phase_a
0x65	UGainCT2	CT2 Voltage RMS Gain	Measurement Calibration Registers	_uGainCT2	0x8000		phase_b
0x66	IGainCT2	CT2 Current RMS Gain	Measurement Calibration Registers	_iGainCT2	0x8000		phase_b
0x67	UoffsetCT2	CT2 Voltage Offset	Measurement Calibration Registers		0x0000		phase_b
0x68	IoffsetCT2	CT2 Current Offset	Measurement Calibration Registers		0x0000		phase_b
0x69	UGainCT3	CT3 Voltage RMS Gain	Measurement Calibration Registers	_uGainCT3	0x8000		phase_c
0x6A	IGainCT3	CT3 Current RMS Gain	Measurement Calibration Registers	_iGainCT3	0x8000		phase_c
0x6B	UoffsetCT3	CT3 Voltage Offset	Measurement Calibration Registers		0x0000		phase_c
0x6C	IoffsetCT3	CT3 Current Offset	Measurement Calibration Registers		0x0000		phase_c
0x70	SoftReset	Software Reset	EMM Status Registers				
0x71	EMMState0	EMM State 0	EMM Status Registers	GetMeterStatus0	0x0000	0x0370	
0x72	EMMState1	EMM State 1	EMM Status Registers	GetMeterStatus1	0x0000	0x7F00	
0x73	EMMIntState0	EMM Interrupt Status 0	EMM Status Registers	GetSysStatus0	0x0000	0x0370	
0x74	EMMIntState1	EMM Interrupt Status 1	EMM Status Registers	GetSysStatus1	0x0000	0x7F00	
0x75	EMMIntEn0	EMM Interrupt Enable 0	EMM Status Registers		0x0000	0xB76F	
0x76	EMMIntEn1	EMM Interrupt Enable 1	EMM Status Registers		0x0000	0xDDFD	
0x78	LastSPIData	Last Read/Write SPI Value	EMM Status Registers		0x0000	0x7E44	
0x79	CRCErrStatus	CRC Error Status	EMM Status Registers		0x0000		
0x7A	CRCDigest	CRC Digest	EMM Status Registers		0x0000	0x1A7D	
0x7F	CfgRegAccEn	Configure Register Access Enable	EMM Status Registers		0x0000		
0x80	APenergyT	Total Forward Active	Energy Registers	GetImportEnergy	x	x	
0x81	APenergyCT1	CT1 Forward Active	Energy Registers		x	x	phase_a
0x82	APenergyCT2	CT2 Forward Active	Energy Registers		x	x	phase_b
0x83	APenergyCT3	CT3 Forward Active	Energy Registers		x	x	phase_c
0x84	ANenergyT	Total Reverse Active	Energy Registers	GetExportEnergy	x	x	
0x85	ANenergyCT1	CT1 Reverse Active	Energy Registers	GetExportEnergy	x	x	phase_a
0x86	ANenergyCT2	CT2 Reverse Active	Energy Registers	GetExportEnergy	x	x	phase_b
0x87	ANenergyCT3	CT3 Reverse Active	Energy Registers	GetExportEnergy	x	x	phase_c
0x88	RPenergyT	Total Forward Reactive	Energy Registers	GetImportReactiveEnergy	x	x	
0x89	RPenergyCT1	CT1 Forward Reactive	Energy Registers	GetImportReactiveEnergy	x	x	phase_a
0x8A	RPenergyCT2	CT2 Forward Reactive	Energy Registers	GetImportReactiveEnergy	x	x	phase_b
0x8B	RPenergyCT3	CT3 Forward Reactive	Energy Registers	GetImportReactiveEnergy	x	x	phase_c
0x8C	RNenergyT	Total Reverse Reactive	Energy Registers	GetExportReactiveEnergy	x	x	
0x8D	RNenergyCT1	CT1 Reverse Reactive	Energy Registers	GetExportReactiveEnergy	x	x	phase_a
0x8E	RNenergyCT2	CT2 Reverse Reactive	Energy Registers	GetExportReactiveEnergy	x	x	phase_b
0x8F	RNenergyCT3	CT3 Reverse Reactive	Energy Registers	GetExportReactiveEnergy	x	x	phase_c

0x90	SAenergyT	Total Apparent Energy	Energy Registers	GetImportApparentEnergy	x	x	
0x91	SenergyCT1	CT1 Apparent Energy	Energy Registers	GetImportApparentEnergy	x	x	phase_a
0x92	SenergyCT2	CT2 Apparent Energy	Energy Registers	GetImportApparentEnergy	x	x	phase_b
0x93	SenergyCT3	CT3 Apparent Energy	Energy Registers	GetImportApparentEnergy	x	x	phase_c
0xA0	APenergyTF	Total Forward Fund. Energy	Fundamental Harmonic Energy Calibration Registers		x	x	
0xA1	APenergyCT1F	CT1 Forward Fund. Energy	Fundamental Harmonic Energy Calibration Registers		x	x	phase_a
0xA2	APenergyCT2F	CT2 Forward Fund. Energy	Fundamental Harmonic Energy Calibration Registers		x	x	phase_b
0xA3	APenergyCT3F	CT3 Forward Fund. Energy	Fundamental Harmonic Energy Calibration Registers		x	x	phase_c
0xA4	ANenergyTF	Total Reverse Fund Energy	Fundamental Harmonic Energy Calibration Registers		x	x	
0xA5	ANenergyCT1F	CT1 Reverse Fund. Energy	Fundamental Harmonic Energy Calibration Registers		x	x	phase_a
0xA6	ANenergyCT2F	CT2 Reverse Fund. Energy	Fundamental Harmonic Energy Calibration Registers		x	x	phase_b
0xA7	ANenergyCT3F	CT3 Reverse Fund. Energy	Fundamental Harmonic Energy Calibration Registers		x	x	phase_c
0xA8	APenergyTH	Total Forward Harm. Energy	Fundamental Harmonic Energy Calibration Registers		x	x	
0xA9	APenergyCT1H	CT1 Forward Harm. Energy	Fundamental Harmonic Energy Calibration Registers		x	x	phase_a
0xAA	APenergyCT2H	CT2 Forward Harm. Energy	Fundamental Harmonic Energy Calibration Registers		x	x	phase_b
0xAB	APenergyCT3H	CT3 Forward Harm. Energy	Fundamental Harmonic Energy Calibration Registers		x	x	phase_c
0xAC	ANenergyTH	Total Reverse Harm. Energy	Fundamental Harmonic Energy Calibration Registers		x	x	
0xAD	ANenergyCT1H	CT1 Reverse Harm. Energy	Fundamental Harmonic Energy Calibration Registers		x	x	phase_a
0xAE	ANenergyCT2H	CT2 Reverse Harm. Energy	Fundamental Harmonic Energy Calibration Registers		x	x	phase_b
0xAF	ANenergyCT3H	CT3 Reverse Harm. Energy	Fundamental Harmonic Energy Calibration Registers		x	x	phase_c
0xB0	PmeanT	Total Mean Power (P)	Power & Power Factor Registers		x	x	
0xB1	PmeanCT1	CT1 Mean Power (P)	Power & Power Factor Registers		x	x	phase_a
0xB2	PmeanCT2	CT2 Mean Power (P)	Power & Power Factor Registers		x	x	phase_b
0xB3	PmeanCT3	CT3 Mean Power (P)	Power & Power Factor Registers		x	x	phase_c
0xB4	QmeanT	Total Mean Power (Q)	Power & Power Factor Registers		x	x	
0xB5	QmeanCT1	CT1 Mean Power (Q)	Power & Power Factor Registers	GetReactivePowerCT	x	x	phase_a
0xB6	QmeanCT2	CT2 Mean Power (Q)	Power & Power Factor Registers	GetReactivePowerCT	x	x	phase_b
0xB7	QmeanCT3	CT3 Mean Power (Q)	Power & Power Factor Registers	GetReactivePowerCT	x	x	phase_c
0xB8	SmeanT	Total Mean Power (S)	Power & Power Factor Registers		x	x	
0xB9	SmeanCT1	CT1 Mean Power (S)	Power & Power Factor Registers	GetApparentPowerCT	x	x	phase_a
0xBA	SmeanCT2	CT2 Mean Power (S)	Power & Power Factor Registers	GetApparentPowerCT	x	x	phase_b
0xBB	SmeanCT3	CT3 Mean Power (S)	Power & Power Factor Registers	GetApparentPowerCT	x	x	phase_c
0xBC	PFmeanT	Mean Power Factor	Power & Power Factor Registers		x	x	
0xBD	PFmeanCT1	CT1 Power Factor	Power & Power Factor Registers	GetPowerFactorCT	x	x	phase_a
0xBE	PFmeanCT2	CT2 Power Factor	Power & Power Factor Registers	GetPowerFactorCT	x	x	phase_b
0xBF	PFmeanCT3	CT3 Power Factor	Power & Power Factor Registers	GetPowerFactorCT	x	x	phase_c
0xC0	PmeanTLSB	Lower Word (Tot. Act. Power)	Power & Power Factor Registers		x	x	
0xC1	PmeanCT1LSB	Lower Word (CT1 Act. Power)	Power & Power Factor Registers		x	x	phase_a
0xC2	PmeanCT2LSB	Lower Word (CT2 Act. Power)	Power & Power Factor Registers		x	x	phase_b
0xC3	PmeanCT3LSB	Lower Word (CT3 Act. Power)	Power & Power Factor Registers		x	x	phase_c
0xC4	QmeanTLSB	Lower Word (Tot. React. Power)	Power & Power Factor Registers		x	x	
0xC5	QmeanCT1LSB	Lower Word (CT1 React. Power)	Power & Power Factor Registers		x	x	phase_a
0xC6	QmeanCT2LSB	Lower Word (CT2 React. Power)	Power & Power Factor Registers		x	x	phase_b
0xC7	QmeanCT3LSB	Lower Word (CT3 React. Power)	Power & Power Factor Registers		x	x	phase_c
0xC8	SmeanTLSB	Lower Word (Tot. App. Power)	Power & Power Factor Registers		x	x	
0xC9	SmeanCT1LSB	Lower Word (CT1 App. Power)	Power & Power Factor Registers		x	x	phase_a
0xCA	SmeanCT2LSB	Lower Word (CT2 App. Power)	Power & Power Factor Registers		x	x	phase_b
0xCB	SmeanCT3LSB	Lower Word (CT3 App. Power)	Power & Power Factor Registers		x	x	phase_c
0xD0	PmeanTF	Total Active Fund. Power	Funamental & Harmonic Power & V/I RMS Registers		x	x	
0xD1	PmeanCT1F	CT1 Active Fund. Power	Funamental & Harmonic Power & V/I RMS Registers		x	x	phase_a
0xD2	PmeanCT2F	CT2 Active Fund. Power	Funamental & Harmonic Power & V/I RMS Registers		x	x	phase_b
0xD3	PmeanCT3F	CT3 Active Fund. Power	Funamental & Harmonic Power & V/I RMS Registers		x	x	phase_c
0xD4	PmeanTH	Total Active Harm. Power	Funamental & Harmonic Power & V/I RMS Registers		x	x	
0xD5	PmeanCT1H	CT1 Active Harm. Power	Funamental & Harmonic Power & V/I RMS Registers		x	x	phase_a
0xD6	PmeanCT2H	CT2 Active Harm. Power	Funamental & Harmonic Power & V/I RMS Registers		x	x	phase_b
0xD7	PmeanCT3H	CT3 Active Harm. Power	Funamental & Harmonic Power & V/I RMS Registers		x	x	phase_c
0xD9	URMSCT1	CT1 RMS Voltage	Funamental & Harmonic Power & V/I RMS Registers		x	x	phase_a
0xDA	URMSCT2	CT2 RMS Voltage	Funamental & Harmonic Power & V/I RMS Registers		x	x	phase_b

0xDB	URMSCT3	CT3 RMS Voltage	Funamental & Harmonic Power & V/I RMS Registers		x	x	phase_c
0xDC	IRMSN	Calculated N RMS Current	Funamental & Harmonic Power & V/I RMS Registers		x	x	
0xDD	IRMSCT1	CT1 RMS Current	Funamental & Harmonic Power & V/I RMS Registers		x	x	phase_a
0xDE	IRMSCT2	CT2 RMS Current	Funamental & Harmonic Power & V/I RMS Registers		x	x	phase_b
0xDF	IRMSCT3	CT3 RMS Current	Funamental & Harmonic Power & V/I RMS Registers		x	x	phase_c
0xE0	PmeanTFLSB	Lower Word (Tot. Act. Fund. Power)	Funamental & Harmonic Power & V/I RMS Registers		x	x	
0xE1	PmeanCT1FLSB	Lower Word (CT1 Act. Fund. Power)	Funamental & Harmonic Power & V/I RMS Registers		x	x	phase_a
0xE2	PmeanCT2FLSB	Lower Word (CT2 Act. Fund. Power)	Funamental & Harmonic Power & V/I RMS Registers		x	x	phase_b
0xE3	PmeanCT3FLSB	Lower Word (CT3 Act. Fund. Power)	Funamental & Harmonic Power & V/I RMS Registers		x	x	phase_c
0xE4	PmeanTHLSB	Lower Word (Tot. Act. Harm. Power)	Funamental & Harmonic Power & V/I RMS Registers		x	x	
0xE5	PmeanCT1HLSB	Lower Word (CT1 Act. Harm. Power)	Funamental & Harmonic Power & V/I RMS Registers		x	x	phase_a
0xE6	PmeanCT2HLSB	Lower Word (CT2 Act. Harm. Power)	Funamental & Harmonic Power & V/I RMS Registers		x	x	phase_b
0xE7	PmeanCT3HLSB	Lower Word (CT3 Act. Harm. Power)	Funamental & Harmonic Power & V/I RMS Registers		x	x	phase_c
0xE9	URMSCT1LSB	Lower Word (CT1 RMS Voltage)	Funamental & Harmonic Power & V/I RMS Registers		x	x	phase_a
0xEA	URMSCT2LSB	Lower Word (CT2 RMS Voltage)	Funamental & Harmonic Power & V/I RMS Registers		x	x	phase_b
0xEB	URMSCT3LSB	Lower Word (CT3 RMS Voltage)	Funamental & Harmonic Power & V/I RMS Registers		x	x	phase_c
0xED	IRMSCT1LSB	Lower Word (CT1 RMS Current)	Funamental & Harmonic Power & V/I RMS Registers		x	x	phase_a
0xEE	IRMSCT2LSB	Lower Word (CT2 RMS Current)	Funamental & Harmonic Power & V/I RMS Registers		x	x	phase_b
0xEF	IRMSCT3LSB	Lower Word (CT3 RMS Current)	Funamental & Harmonic Power & V/I RMS Registers		x	x	phase_c
0xF1	UPeakA	CT1 Voltage Peak	Peak Frequency Angle and Temperature Registers		x	x	phase_a
0xF2	UPeakB	CT2 Voltage Peak	Peak Frequency Angle and Temperature Registers		x	x	phase_b
0xF3	UPeakC	CT3 Voltage Peak	Peak Frequency Angle and Temperature Registers		x	x	phase_c
0xF4	Reserved	Reserved Register					
0xF5	IPeakCT1	CT1 Current Peak	Peak Frequency Angle and Temperature Registers		x	x	phase_a
0xF6	IPeakCT2	CT2 Current Peak	Peak Frequency Angle and Temperature Registers		x	x	phase_b
0xF7	IPeakCT3	CT3 Current Peak	Peak Frequency Angle and Temperature Registers		x	x	phase_c
0xF8	Freq	Frequency	Peak Frequency Angle and Temperature Registers		x	x	frequency
0xF9	PAngleCT1	CT1 Mean Phase Angle	Peak Frequency Angle and Temperature Registers	GetPhaseCT	x	x	phase_a
0xFA	PAngleCT2	CT2 Mean Phase Angle	Peak Frequency Angle and Temperature Registers	GetPhaseCT	x	x	phase_b
0xFB	PAngleCT3	CT3 Mean Phase Angle	Peak Frequency Angle and Temperature Registers	GetPhaseCT	x	x	phase_c
0xFC	Temp	Measured Temperature	Peak Frequency Angle and Temperature Registers	GetTemperature	x	x	chip_temperature
0xFD	UangleCT1	CT1 Voltage Phase Angle	Peak Frequency Angle and Temperature Registers		x	x	phase_a
0xFE	UangleCT2	CT2 Voltage Phase Angle	Peak Frequency Angle and Temperature Registers		x	x	phase_b
0xFF	UangleCT3	CT3 Voltage Phase Angle	Peak Frequency Angle and Temperature Registers		x	x	phase_c