


JP1 open (as made): the screen keeps BL pulled high, backlight always on.
Bridge JP1 to switch the backlight from D1 (high = on).







Pin map (XIAO pin = ESP32-S3 GPIO / ESP32-C6 GPIO):
SCLK = D8 = GPIO7 / GPIO19
SDIN = D10 = GPIO9 / GPIO18
DC = D3 = GPIO4 / GPIO21
RES = D4 = GPIO5 / GPIO22
CS = D5 = GPIO6 / GPIO23
BL = D1 = GPIO2 / GPIO1, only when JP1 is bridged
Unused on purpose: D0, D2 (S3 strapping GPIO3), D6/D7 (UART0), D9, 5V

Screen breakout: two rows of four pins, 2.54 mm pitch.
Row spacing 15.24 mm and outline about 12.9 x 20.8 mm are photo estimates: TO MEASURE.
Fit the screen face up, flex cable at the end away from the XIAO.

Screen row spacing and outline are photo estimates: TO MEASURE
XIAO ESP32-S3 or ESP32-C6 + Questwise 0.42in 96x54 TFT, no wires

Sheet: /
File: tiny-tft-carrier.kicad_sch

Title: Tiny TFT carrier

Size: A4	Date:	**Rev: A**
KiCad E.D.A. 10.0.7		Id: 1/1