

fh6parse kiosk hardware archive

Shop URLs die. This file is the buy list that still works without them: **name, SKU / EAN, size, what it is, how to substitute**. Wiring and pin map stay in [LINUX-KIOSK.md](#) and [LINUX-KIOSK-WIRING.pdf](#).

Archived **2026-09-20**. Manufacturer PDFs in [hardware-archive/](#). Wayback:

https://web.archive.org/web/*/THE_URL.

Do **not** fit the Raspberry Pi M.2 HAT+ from the SSD kit. OS disk is the **Pimoroni Duo + official 512 GB 2230 SSD**. GPIO is the **Kamami screw terminal**, on a **40-pin riser** if the cooler is in the way. Assemble must-dos: **\$ Must do** below and [LINUX-KIOSK.md](#) **\$2.13**.

How to replace a dead listing

1. Match **SKU / EAN / manufacturer part** first.
2. If those are gone, match the **physical facts** in the “Substitute” column (hole size, pin count, voltage).
3. Prefer the **manufacturer** page over a marketplace clone.

Board and storage

Use	Buy as	IDs that survive	Shop (may die)	Manufacturer / brief	Substitute
Computer	Raspberry Pi 5 , 64-bit OS	BCM2712, 40-pin GPIO identical to Pi 4	any Pi 5	raspberrypi.com/products/raspberry-pi-5	Pi 5 only (RP1 GPIO). Not Pi 4 for this cooler / PCIe / J2.
PSU	Official Raspberry Pi 27 W USB-C (5.1 V / 5 A)	27 W, USB-C, 5 A	any official PSU	raspberrypi.com/products/27w-usb-c-power-supply	Must be 5 A. Phone chargers and Pi 3 2.5 A supplies are not enough.
Cooler	Raspberry Pi Active Cooler	Botland RPI-23925 , EAN 5056561803357 . 4-pin FAN, 8000 rpm PWM, spring clips, Pi 5 only	Botland.store	raspberrypi.com/products/active-cooler · brief RP-008188	Clip-on aluminium + 4-pin blower on the Pi 5 FAN header. Not a Pi 4 fan.
NVMe board	Pimoroni NVMe Base Duo	PIM704 , EAN 769894025024 , Botland PIM-24851 . 87.5 × 56 mm, 2× M.2 M-key 2230–2280, PCIe Gen 2 FPC	Botland.pl	shop.pimoroni.com/products/nvme-base-duo-for-raspberry-pi-5 · getting started	Dual M-key NVMe under the Pi 5 on the PCIe FPC . Not a 40-pin HAT. Not the official M.2 HAT+.
OS disk	Raspberry Pi SSD 512 GB , M.2	From kit Botland RPI-25484 , EAN 5056561805023 . 22	SSD Kit 512 GB — take the disk only	raspberrypi.com/products/ssd · brief RP-008357	Official Pi 512 GB 2230 NVMe. Duo

Use	Buy as	IDs that survive	Shop (may die)	Manufacturer / brief	Substitute
	2230 , NVMe M-key	× 30 × 2.3 mm, 3.3 V, max 2.8 W, TLC, PCIe Gen3			slot A , 2230 standoff hole. Kit HAT+ stays in the drawer.
Spare PCIe flex (drawer)	Pimoroni PCle Pipe 35 mm or 50 mm	PIM703 (35 mm) / PIM702 (50 mm)	Botland / Pimoroni (sold next to the Duo)	Same Duo getting-started	The OS cable. Clips break; keep one spare.
Case	3D-printed enclosure	PETG (not PLA). Vents above the cooler and below the Duo	—	—	PLA softens ~60 °C. Cooler brief wants airflow.

GPIO and panel

Use	Buy as	IDs that survive	Shop (may die)	Manufacturer / brief	Substitute
GPIO screws	40-pin screw-terminal breakout	Kamami 588019 , EAN 5906623475650 . Board ~58 × 22 mm, 40-pin female, screw terminals, M2.5 standoffs, screwdriver	Kamami	Same 40-pin screw block as the old 52Pi / AliExpress listing	40-pin GPIO screw terminal, silk BCM (I017 = GPIO 17). Pin 1 at USB-C.
If terminal will not fit	40-pin GPIO riser	Extra-tall 2×20 female-to-male stacking header	any electronics shop	—	Same pin 1. Do not rotate. Terminal sits on the riser.
File + mill knobs	DFRobot Fermion EC11	SEN0235 . 20 pulses/turn, VCC / GND / A / B / C. 3.3–5 V	DFRobot / clones labelled SEN0235	wiki.dfrobot.com SEN0235	Two modules. Power from 3.3 V only. Leave shaft C open.
LOAD / SET / RUN	Three 16 mm 5-pin vandal, momentary, 5 V ring LED	LAS16-style. Tabs: LED+ LED– NO C NC. 2.8 mm Faston	Allegro / industrial 16 mm 5 V ring	Meter the tabs — silk varies	Green LOAD, yellow SET, red RUN. NC unused. LED on 5 V, not GPIO.
Sleep (optional)	Fourth same vandal, or any momentary NO	Same as LOAD	—	—	NO → BCM 25, C → GND. Unwired is fine.
Panel power (optional)	Momentary NO on Pi 5 J2	Two pads next to RTC, GPIO pin-40 corner. Not a 40-pin GPIO	—	Pi 5 reduced schematic, PWR_BTN	Short the two J2 pads. Not BCM 25 / 20.
Pendrive socket	Metal USB 3.0 Type-A panel mount	27 mm round cutout, Type-A female on the front, USB 3 pigtail	Allegro 17741983408	Any metal USB 3.0 A 27 mm bulkhead	Pigtail to Pi USB 3 (blue). P047 stays on USB 2 . Not GPIO.
Printer	MUNBYN P047 / ITPP047	80 mm ESC/POS, USB, auto-cutter, own mains PSU	MUNBYN / ITPP047	/dev/usb/lp0, DLE EOT status	80 mm thermal with cutter. Do not power from Pi USB.

Use	Buy as	IDs that survive	Shop (may die)	Manufacturer / brief	Substitute
Display	800×600 LCD, portrait	After rotation framebuffer 600×800 . micro-HDMI on HDMI0	—	—	Pi 5 HDMI0 = port next to USB-C.
Keypad (future)	SparkFun Qwiic 12-key	COM-15290 , I ² C 0x4B	SparkFun	Official Qwiic 4-pin on GPIO 2/3	Leave header 3 / 5 empty until fitted.

Consumables (no SKU)

Use	Spec
GPIO sense (encoder A/B, button NO)	24 AWG stranded (0.25 mm ²), under ~40 cm
3.3 V, 5 V LED+, GND	22 AWG stranded (0.34 mm ²)
J2 flying leads	26–28 AWG, under 20 cm
Vandal tabs	Insulated 2.8 mm Faston , crimped
Screw ends	Bootlace ferrule, strip ~5 mm
Colours	Black GND · orange 3.3 V · red 5 V LED+ only · brown RUN (not red) · green LOAD · yellow SET · violet SLEEP · blue file A/B · white/grey mill A/B
USB-C / HDMI strain	Clamp both to the case. No USB-C extension on the 27 W PSU
Panel USB hole	Thick boss, metal nut + washer. Pigtail clamped to the case, not the Pi

Must do (assemble)

These keep the kiosk alive in a mill shop. Same list in [LINUX-KIOSK.md](#) §2.13.

#	Do	If you skip it
1	Never 5 V on a BCM pin. LED rings on pin 2 only. RUN is brown , not red.	Dead Pi
2	Seat the PCIe flex power-off, both clips locked, no crease. The four Duo standoffs carry the sandwich, not the cable.	Black screen, OS gone, SD slot often blocked
3	Clamp USB-C and micro-HDMI0 to the case. Official 27 W cable only — no USB-C extension (PD 5 A dies).	Undervoltage / blank HDMI after vibration
4	Screw-terminal silk is BCM : I017 = GPIO 17, not header pin 17. Pin 1 at USB-C. Do not rotate a riser.	3.3 V on a GPIO or one-pin-over short
5	PETG case, vents above the Active Cooler and below the Duo. Do not pack foam on the blower.	Thermal throttle / PLA warp
6	Strain-relieve the GPIO bundle and the USB 3 pigtail to the case , not the Pi header.	Walked screws / cracked USB hole

Suggestions (shop, first month)

Do	Why
Spare PCIe flex (PIM702 / PIM703) in the drawer	Clips are fragile; this is the OS cable

Do	Why
Thick boss + nut/washer on the 27 mm USB; dummy plug when idle	Operator yank cracks 3D print; metal dust in the socket
Keep the USB 3 pigtail off the encoder loom	USB 3 is noisy; knobs skip
Solder or glue the EC11 Dupont end	Pin rows walk; Pi end is already screws
Cable-tie a GPIO riser so it cannot lift	Extra connector walks
Dab of threadlocker on the 2230 M2; check after a week	Tiny screw, vibration
Coarse foam on the cooler intake	CNC dust in the blower
Official 27 W brick close to the Pi	Long/cheap USB-C leads drop 5 A

Leave unless it bites: J2 halt, UPS, slot B clone, PCIe Gen 3, RAID.

Shop URLs (copy for Wayback)

If a shop 404s: open https://web.archive.org/web/*/URL with the URL below.

<https://kamami.pl/prototypowanie-raspberry-pi/588019-modul-hat-ze-zlaczami-srubowymi-dla-raspberry-pi-590>
<https://botland.com.pl/rozszerzenia-gpio-i-nakladki-hat-do-raspberry-pi-5/24851-plytka-rozszerzen-nvme-b>
<https://botland.com.pl/raspberry-pi-hat-nakladki-pci-express/25484-raspberry-pi-ssd-kit-512gb-zestaw-z-d>
<https://botland.store/raspberry-pi-5-mounting-elements/23925-raspberry-pi-active-cooler-heatsink-fan-for>
<https://allegro.pl/oferta/gniazdo-usb-3-0-typu-a-metalowe-do-zabudowy-na-pendrive-panelowe-27-mm-1774198>
<https://shop.pimoroni.com/products/nvme-base-duo-for-raspberry-pi-5>
<https://learn.pimoroni.com/article/getting-started-with-nvme-base-duo>
<https://www.raspberrypi.com/products/active-cooler/>
<https://www.raspberrypi.com/products/ssd/>
https://wiki.dfrobot.com/Fermion_EC11_Rotary_Encoder_Module_SKU_SEN0235

Not in the box (do not buy for this kiosk)

Part	Why
Raspberry Pi M.2 HAT+ (in the SSD kit)	Occupies the 40-pin header. GPIO terminal + cooler lose. Disk moves to the Duo.
52Pi EP-0129 LED GPIO HAT	Too tall vs the Active Cooler. Kamami 588019 is the slim screw block.
Analog keypad (e.g. DFR0792)	Pi 5 has no ADC. Future keypad is Qwiic I ² C.
Pi 3 / 4 PSU, Pi 4 cooler	Wrong current / wrong FAN header.
USB-C extension on the 27 W PSU	PD 5 A fails; undervoltage. Clamp the official cable.