

Pin Information Table of Xiaomeige ACG525 Domestic Gowin FPGA Development Board

	Function Signal	Pin FPGA
CLOCK	CLOCK	
	CLK_G(50M)	T9
LED	LED	
	LED0	D14
	LED1	C14
	LED2	B9
	LED3	A9
KEY	KEY	
	KEY0	B16
	KEY1	A15
	KEY2	C15
UART	UART	
	uart_tx	V8
	uart_rx	U8
7 Seg Led	7 Seg Led	
	SEG7_DIO(DS)	F4
	SEG7_RCLK(ST_CP)	F3
	SEG7_SCLK(SH_CP)	H4
Buzzer	Buzzer	
	BEEP	A16
HDMI TX	HDMI	
	tmds_data_p[2]	R5
	tmds_data_p[1]	T6
	tmds_data_p[0]	R7
	tmds_data_n[2]	T5
	tmds_data_n[1]	V6
	tmds_data_n[0]	T7
	tmds_clk_p	M10
	tmds_clk_n	N9
Gigabit Ethernet	Gigabit Ethernet	
	eth_mdc	D3
	eth_mdio	E4
	eth_rst_n	G6
	rgmii_rx_clk_i	L5
	rgmii_rxd[0]	G3
	rgmii_rxd[1]	G1
	rgmii_rxd[2]	F6
	rgmii_rxd[3]	F5
	rgmii_rxdv	E1

	rgmii_tx_clk	C1	
	rgmii_txd[0]	D2	
	rgmii_txd[1]	D1	
	rgmii_txd[2]	F2	
	rgmii_txd[3]	F1	
	rgmii_txen	C2	
I2C	I2C (OLED、RTC、EEPROM)		
	i2c_sclk	R3	
	i2c_sdat	T3	
USB2.0	USB2.0		
	usb_dxp_io	U5	
	usb_dxn_io	V5	
	usb_rxdn_i	T12	
	usb_rxdp_i	N5	
	usb_term_dn_io	V7	
	usb_term_dp_io	U7	
	USB_PULLUP_EN	M11	
MIPI-CSI	MIPI-CSI		
	MIPI_PWDN	N11	
	MIPI_SDAT	P11	
	MIPI_SCLK	N10	
	MIPI_RX_D0_N	T1	MIPI
	MIPI_RX_D0_P	T2	MIPI
	MIPI_RX_D1_N	U1	MIPI
	MIPI_RX_D1_P	U2	MIPI
	MIPI_RX_D2_N	N3	MIPI
	MIPI_RX_D2_P	N4	MIPI
	MIPI_RX_D3_N	P3	MIPI
	MIPI_RX_D3_P	P4	MIPI
	MIPI_RX_CLK_N	M5	MIPI
	MIPI_RX_CLK_P	L6	MIPI
MIPI-DSI	MIPI-DSI		
	M_GPIO_0	R8	
	M_GPIO_1	T8	
	SCL	N6	
	SDA	P7	
	LT_2P5_0_P	P2	
	LT_2P5_0_N	P1	
	LT_2P5_1_P	L4	
	LT_2P5_1_N	L3	
	LT_2P5_2_P	L2	
	LT_2P5_2_N	L1	
	LT_2P5_3_P	N2	
	LT_2P5_3_N	N1	
	LT_2P5_CLK_N	K3	
	LT_2P5_CLK_P	K4	

40-PIN GPIO

40-PIN GPIO

GPIO0	C17
GPIO1	C18
GPIO2	F14
GPIO3	G14
GPIO4	D17
GPIO5	D18
GPIO6	G16
GPIO7	G18
GPIO8	F17
GPIO9	F18
GPIO10	H13
GPIO11	H14
GPIO12	K15
GPIO13	K16
GPIO14	J13
GPIO15	K14
GPIO16	K12
GPIO17	K13
GPIO18	L12
GPIO19	L13
GPIO20	H17
GPIO21	H18
GPIO22	K17
GPIO23	K18
GPIO24	L17
GPIO25	L18
GPIO26	N17
GPIO27	N18
GPIO28	P17
GPIO29	P18
GPIO30	P15
GPIO31	P16
GPIO32	U13
GPIO33	V13
GPIO34	U11
GPIO35	V11

ACM7606

GPIO0 ACM7606	
ad7606_os_o[1]	C17
ad7606_os_o[0]	C18
ad7606_convst_o	F14
ad7606_os_o[2]	G14
ad7606_rd_n_o	D17
ad7606_reset_o	D18
ad7606_busy_i	G16
ad7606_cs_n_o	G18
FIRSTDATA	F18

ad7606_db_i[0]	H13
ad7606_db_i[1]	H14
ad7606_db_i[2]	K15
ad7606_db_i[3]	K16
ad7606_db_i[4]	J13
ad7606_db_i[5]	K14
ad7606_db_i[6]	K12
ad7606_db_i[7]	K13
ad7606_db_i[8]	L12
ad7606_db_i[9]	L13
ad7606_db_i[10]	H17
ad7606_db_i[11]	H18
ad7606_db_i[12]	K17
ad7606_db_i[13]	K18
ad7606_db_i[14]	L17
ad7606_db_i[15]	L18

ACM1030

GPIO0 ACM1030	
AD1_D1	C17
AD1_D0	C18
AD1_D3	F14
AD1_D2	G14
AD1_D5	D17
AD1_D4	D18
AD1_D7	G16
AD1_D6	G18
AD1_D9	F17
AD1_D8	F18
AD1_OVR	H13
AD1_CLK	H14
AD2_D0	K15
AD2_D1	K16
AD2_D2	J13
AD2_D3	K14
AD2_D4	K12
AD2_D5	K13
AD2_D6	L12
AD2_D7	L13
AD2_D8	H17
AD2_D9	H18
AD2_OVR	K17
AD2_CLK	K18

ACM9238

GPIO0 ACM9238	
CH2_D0	C17
CH2_CLK	C18
CH2_D2	F14
CH2_D1	G14

CH2_D4	D17
CH2_D3	D18
CH2_D6	G16
CH2_D5	G18
CH2_D8	F17
CH2_D7	F18
CH2_D10	H13
CH2_D9	H14
CH2_OTR	K15
CH2_D11	K16
CH1_D1	J13
CH1_D0	K14
CH1_D3	K12
CH1_D2	K13
CH1_D5	L12
CH1_D4	L13
CH1_D7	H17
CH1_D6	H18
CH1_D9	K17
CH1_D8	K18
CH1_D11	L17
CH1_D10	L18
CH1_OTR	N17
CH1_CLK	N18

ACM9767

GPIO0 ACM9767	
DA1_12	C17
DA1_13	C18
DA1_10	F14
DA1_11	G14
DA1_8	D17
DA1_9	D18
DA1_6	G16
DA1_7	G18
DA1_4	F17
DA1_5	F18
DA1_2	H13
DA1_3	H14
DA1_0	K15
DA1_1	K16
clk1	J13
wrt1	K14
clk2	K12
wrt2	K13
DA2_13	L12
DA2_12	L13
DA2_11	H17
DA2_10	H18
DA2_9	K17
DA2_8	K18

DA2_7	L17
DA2_6	L18
DA2_5	N17
DA2_4	N18
DA2_3	P17
DA2_2	P18
DA2_1	P15
DA2_0	P16

GPIO0	
keyboard_col_x4_o[3]	H14
keyboard_col_x4_o[2]	K16
keyboard_col_x4_o[1]	K14
keyboard_col_x4_o[0]	K13
keyboard_row_x4_i[3]	L13
keyboard_row_x4_i[2]	H18
keyboard_row_x4_i[1]	K18
keyboard_row_x4_i[0]	L18

OV5640

GPIO0 OV5640	
CMOS1_PWDN	C17
CMOS1_RST	C18
CMOS1_D0	F14
CMOS1_D1	G14
CMOS1_D2	D17
CMOS1_D3	D18
CMOS1_D4	G16
CMOS1_D5	G18
CMOS1_D6	F17
CMOS1_D7	F18
CMOS1_XCLK	H13
CMOS1_PCLK	H14
CMOS1_HREF	K15
CMOS1_VSYNC	K16
CMOS1_SDA	J13
CMOS1_SCLK	K14
CMOS2_PWDN	K12
CMOS2_RST	K13
CMOS2_D0	L12
CMOS2_D1	L13
CMOS2_D2	H17
CMOS2_D3	H18
CMOS2_D4	K17
CMOS2_D5	K18
CMOS2_D6	L17
CMOS2_D7	L18
CMOS2_XCLK	N17
CMOS2_PCLK	N18
CMOS2_HREF	P17
CMOS2_VSYNC	P18

	CMOS2_SDA	P15
	CMOS2_SCLK	P16
GPIO2 36-pin	GPIO2 36-pin	
	LCD_GPIO0	T11
	LCD_GPIO1	R11
	LCD_GPIO2	V15
	LCD_GPIO3	U15
	LCD_GPIO4	V16
	LCD_GPIO5	U16
	LCD_GPIO6	U18
	LCD_GPIO7	U17
	LCD_GPIO8	T18
	LCD_GPIO9	T17
	LCD_GPIO10	N14
	LCD_GPIO11	M14
	LCD_GPIO12	N16
	LCD_GPIO13	N15
	LCD_GPIO14	M18
	LCD_GPIO15	M16
	LCD_GPIO16	L16
	LCD_GPIO17	L15
	LCD_GPIO18	M13
	LCD_GPIO19	L14
	LCD_GPIO20	J16
	LCD_GPIO21	H15
	LCD_GPIO22	G13
	LCD_GPIO23	H12
	LCD_GPIO24	F16
	LCD_GPIO25	F15
	LCD_GPIO26	E18
	LCD_GPIO27	E16
GM7123	GPIO2 GM7123	
	VGA_HS	T11
	VGA_VS	R11
	VGA_R1	V15
	VGA_R0	U15
	VGA_R3	V16
	VGA_R2	U16
	VGA_R5	U18
	VGA_R4	U17
	VGA_R7	T18
	VGA_R6	T17
	VGA_G1	N14
	VGA_G0	M14
	VGA_G3	N16
	VGA_G2	N15
	VGA_G5	M18
	VGA_G4	M16

	VGA_G7	L16
	VGA_G6	L15
	VGA_B1	M13
	VGA_BLK	L14
	VGA_B2	J16
	VGA_B3	H15
	VGA_B4	G13
	VGA_B5	H12
	VGA_B0	F16
	VGA_B6	F15
	VGA_B7	E18
	VGA_CLOCK	E16
TFT	GPIO2 TFT	
	TFT_de	U18
	TFT_pwm	U17
	TFT_hs	T18
	TFT_vs	T17
	TFT_rgb[4]	N14
	TFT_clk	M14
	TFT_rgb[2]	N16
	TFT_rgb[3]	N15
	TFT_rgb[0]	M18
	TFT_rgb[1]	M16
	TFT_rgb[9]	L16
	TFT_rgb[10]	L15
	TFT_rgb[7]	M13
	TFT_rgb[8]	L14
	TFT_rgb[6]	J16
	TFT_rgb[5]	H15
	TFT_rgb[14]	G13
	TFT_rgb[15]	H12
	TFT_rgb[12]	F16
	TFT_rgb[13]	F15
	TFT_rgb[11]	E18
DDR	DDR	
	IO_ddr_dq[0]	A12
	IO_ddr_dq[1]	B11
	IO_ddr_dq[2]	G9
	IO_ddr_dq[3]	G11
	IO_ddr_dq[4]	A11
	IO_ddr_dq[5]	C10
	IO_ddr_dq[6]	F10
	IO_ddr_dq[7]	A10
	IO_ddr_dq[8]	C13
	IO_ddr_dq[9]	A13
	IO_ddr_dq[10]	E11
	IO_ddr_dq[11]	F11
	IO_ddr_dq[12]	C12

IO_dds_dq[13]	D12
IO_dds_dq[14]	B14
IO_dds_dq[15]	A14
IO_dds_dqs[0]	D11
IO_dds_dqs_n[0]	C11
IO_dds_dqs[1]	F12
IO_dds_dqs_n[1]	E12
O_dds_addr[0]	A3
O_dds_addr[1]	A6
O_dds_addr[2]	B3
O_dds_addr[3]	C7
O_dds_addr[4]	B4
O_dds_addr[5]	C8
O_dds_addr[6]	C4
O_dds_addr[7]	C6
O_dds_addr[8]	D4
O_dds_addr[9]	A2
O_dds_addr[10]	E6
O_dds_addr[11]	B6
O_dds_addr[12]	A5
O_dds_addr[13]	B2
O_dds_ba[0]	D6
O_dds_ba[1]	A4
O_dds_ba[2]	D8
O_dds_cas_n	F8
O_dds_cke	C5
O_dds_clk	D9
O_dds_clk_n	C9
O_dds_cs_n	E7
O_dds_dqm[0]	F9
O_dds_dqm[1]	F13
O_dds_odt	F7
O_dds_ras_n	G8
O_dds_reset_n	A7
O_dds_we_n	E8