

CAN Protocol NO.	998
CAN Baud Rate	250K
Charger Receiving CAN ID	0x1806E7F4
Charger Transmitting CAN ID	0x18FF50E7

Communication Specification:

Message1:

OUT	IN	CAN ID	Cycle (ms)
BMS	Charger	0x1806E7F4	1000
Data			
Position	Data Name		
BYTE1	Max Allowable Charging Terminal Voltage High Byte		0.1V/bit Offset: 0 e.g.: Vset =3201, its corresponding 320.1V
BYTE2	Max Allowable Charging Terminal Voltage Low Byte		
BYTE3	Max Allowable Charging Current High Byte		0.1A/bit Offset: 0 e.g.: Iset =582, its corresponding 58.2A
BYTE4	Max Allowable Charging Current Low Byte		
BYTE5	Control		0: Charger is starting up to charge.1: Battery protection, charger close output.
BYTE6	Reserved		
BYTE7	Reserved		
BYTE8	Reserved		

Message 2

Message 2

OUT	IN	CAN ID	Cycle(ms)
CCS	BCA	0x18FF50E7	1000
Data			
Position	Data Name		
BYTE1	Output Voltage High Byte		0.1V/bit Offset:0 e.g.:Vout =3201, its corresponding 320.1v
BYTE2	Output Voltage Low Byte		
BYTE3	Output Current High Byte		0.1A/bit Offset:0 e.g.: Iout=582, its corresponding 58.2A. Highest Byte mark: 0: Charging, 1: Discharging
BYTE4	Output Current Low Byte		
BYTE5	STATUS Flags		
BYTE6	Temp		
BYTE7	Reserved		
BYTE8	Reserved		

CAN Protocol NO.	997
CAN Baud Rate	250K
Charger Receiving CAN ID	0x1806E8F4
Charger Transmitting CAN ID	0x18FF50E8

Communication Specification:

Message1:

OUT	IN	CAN ID	Cycle (ms)
BMS	Charger	0x1806E8F4	1000
Data			
Position	Data Name		
BYTE1	Max Allowable Charging Terminal Voltage High Byte		0.1V/bit Offset: 0 e.g.: Vset =3201, its corresponding 320.1V
BYTE2	Max Allowable Charging Terminal Voltage Low Byte		
BYTE3	Max Allowable Charging Current High Byte		0.1A/bit Offset: 0 e.g.: Iset =582, its corresponding 58.2A
BYTE4	Max Allowable Charging Current Low Byte		
BYTE5	Control		0: Charger is starting up to charge.1: Battery protection, charger close output.
BYTE6	Reserved		
BYTE7	Reserved		
BYTE8	Reserved		

Message 2

Message 2

OUT	IN	CAN ID	Cycle(ms)
CCS	BCA	0x18FF50E8	1000
Data			
Position	Data Name		
BYTE1	Output Voltage High Byte		0.1V/bit Offset:0 e.g.:Vout =3201, its corresponding 320.1v
BYTE2	Output Voltage Low Byte		
BYTE3	Output Current High Byte		0.1A/bit Offset:0 e.g.: Iout=582, its corresponding 58.2A. Highest Byte mark: 0: Charging, 1: Discharging
BYTE4	Output Current Low Byte		
BYTE5	STATUS Flags		
BYTE6	Temp		
BYTE7	Reserved		
BYTE8	Reserved		

CAN Protocol NO.	1200
CAN Baud Rate	500K
Charger Receiving CAN ID	0x1806E5F4
Charger Transmitting CAN ID	0x18FF50E5

Communication Specification:

Message1:

OUT	IN	CAN ID	Cycle (ms)
BMS	Charger	0x1806E5F4	1000
Data			
Position	Data Name		
BYTE1	Max Allowable Charging Terminal Voltage High Byte		0.1V/bit Offset: 0 e.g.: Vset =3201, its corresponding 320.1V
BYTE2	Max Allowable Charging Terminal Voltage Low Byte		
BYTE3	Max Allowable Charging Current High Byte		0.1A/bit Offset: 0 e.g.: Iset =582, its corresponding 58.2A
BYTE4	Max Allowable Charging Current Low Byte		
BYTE5	Control		0: Charger is starting up to charge.1: Battery protection, charger close output.
BYTE6	Reserved		
BYTE7	Reserved		
BYTE8	Reserved		

Message 2

Message 2

OUT	IN	CAN ID	Cycle(ms)
CCS	BCA	0x18FF50E5	1000
Data			
Position	Data Name		
BYTE1	Output Voltage High Byte		0.1V/bit Offset:0 e.g.:Vout =3201, its corresponding 320.1v
BYTE2	Output Voltage Low Byte		
BYTE3	Output Current High Byte		0.1A/bit Offset:0 e.g.: Iout=582, its corresponding 58.2A. Highest Byte mark: 0: Charging, 1: Discharging
BYTE4	Output Current Low Byte		
BYTE5	STATUS Flags		
BYTE6	Temp		
BYTE7	Reserved		
BYTE8	Reserved		

CAN Protocol NO.	1198
CAN Baud Rate	500K
Charger Receiving CAN ID	0x1806E7F4
Charger Transmitting CAN ID	0x18FF50E7

Communication Specification:

Message1:

OUT	IN	CAN ID	Cycle (ms)
BMS	Charger	0x1806E7F4	1000
Data			
Position	Data Name		
BYTE1	Max Allowable Charging Terminal Voltage High Byte		0.1V/bit Offset: 0 e.g.: Vset =3201, its corresponding 320.1V
BYTE2	Max Allowable Charging Terminal Voltage Low Byte		
BYTE3	Max Allowable Charging Current High Byte		0.1A/bit Offset: 0 e.g.: Iset =582, its corresponding 58.2A
BYTE4	Max Allowable Charging Current Low Byte		
BYTE5	Control		0: Charger is starting up to charge.1: Battery protection, charger close output.
BYTE6	Reserved		
BYTE7	Reserved		
BYTE8	Reserved		

Message 2

Message 2

OUT	IN	CAN ID	Cycle(ms)
CCS	BCA	0x18FF50E7	1000
Data			
Position	Data Name		
BYTE1	Output Voltage High Byte		0.1V/bit Offset:0 e.g.:Vout =3201, its corresponding 320.1v
BYTE2	Output Voltage Low Byte		
BYTE3	Output Current High Byte		0.1A/bit Offset:0 e.g.: Iout=582, its corresponding 58.2A. Highest Byte mark: 0: Charging, 1: Discharging
BYTE4	Output Current Low Byte		
BYTE5	STATUS Flags		
BYTE6	Temp		
BYTE7	Reserved		
BYTE8	Reserved		

CAN Protocol NO.	1430
CAN Baud Rate	250K
Charger Receiving CAN ID	0x1806E5F4
Charger Transmitting CAN ID	0x18FF50E5

Communication Specification:

Message1:

OUT	IN	CAN ID	Cycle (ms)
BMS	Charger	0x1806E5F4	1000
Data			
Position	Data Name		
BYTE1	Max Allowable Charging Terminal Voltage High Byte		0.1V/bit Offset: 0 e.g.: Vset =3201, its corresponding 320.1V
BYTE2	Max Allowable Charging Terminal Voltage Low Byte		
BYTE3	Max Allowable Charging Current High Byte		0.1A/bit Offset: 0 e.g.: Iset =582, its corresponding 58.2A
BYTE4	Max Allowable Charging Current Low Byte		
BYTE5	Control		0: Charger is starting up to charge.1: Battery protection, charger close output.
BYTE6	Reserved		0: Charging Mode; 1:Heating Mode;
BYTE7	Reserved		
BYTE8	Reserved		

Message 2

OUT	IN	CAN ID	Cycle(ms)
CCS	BCA	0x18FF50E5	1000
Data			
Position	Data Name		
BYTE1	Output Voltage High Byte		0.1V/bit Offset:0 e.g.:Vout =3201, its corresponding320.1v
BYTE2	Output Voltage Low Byte		
BYTE3	Output Current High Byte		0.1A/bit Offset:0 e.g.:Iout=582, its corresponding 58.2A. Highest Byte mark: 0: Charging, 1: Discharging
BYTE4	Output Current Low Byte		
BYTE5	STATUS Flags		
BYTE6	Temp		
BYTE7	Reserved		

CAN Protocol NO.	1197
CAN Baud Rate	500K
Charger Receiving CAN ID	0x1806E8F4
Charger Transmitting CAN ID	0x18FF50E8

Communication Specification:

Message1:

OUT	IN	CAN ID	Cycle (ms)
BMS	Charger	0x1806E8F4	1000
Data			
Position	Data Name		
BYTE1	Max Allowable Charging Terminal Voltage High Byte		0.1V/bit Offset: 0 e.g.: Vset =3201, its corresponding 320.1V
BYTE2	Max Allowable Charging Terminal Voltage Low Byte		
BYTE3	Max Allowable Charging Current High Byte		0.1A/bit Offset: 0 e.g.: Iset =582, its corresponding 58.2A
BYTE4	Max Allowable Charging Current Low Byte		
BYTE5	Control		0: Charger is starting up to charge.1: Battery protection, charger close output.
BYTE6	Reserved		
BYTE7	Reserved		
BYTE8	Reserved		

Message 2

Message 2

OUT	IN	CAN ID	Cycle(ms)
CCS	BCA	0x18FF50E8	1000
Data			
Position	Data Name		
BYTE1	Output Voltage High Byte		0.1V/bit Offset:0 e.g.:Vout =3201, its corresponding320.1v
BYTE2	Output Voltage Low Byte		
BYTE3	Output Current High Byte		0.1A/bit Offset:0 e.g: Iout=582, its corresponding 58.2A. Highest Byte mark: 0: Charging, 1: Discharging
BYTE4	Output Current Low Byte		
BYTE5	STATUS Flags		
BYTE6	Temp		
BYTE7	Reserved		
BYTE8	Reserved		