MANDATORY SKILLS QUALIFICATION I

(SWD 327)

TECHNICAL REPORT ON HARDWARE COMPONENT INSTALLATION RELATED ISSUES

BY

(GROUP 4)

S/N	NAME	MATRIC NO.
1.	OGUNDELE AKINKUNMI	SW20240112413
2.	OLANIYAN AMEEDAT	SW20240115376
3.	ADEOYE ADEDOTUN	SW20240115529
4.	ADEREMIN AKINKUNMI	SW20240115532
5.	WAHEED HAMID	SW20240117600
6.	OGUNSAKIN ANUOLUWAPO	SW20240118214
7.	ORESANWO ABDULLAHI	SW20240117524
8.	AJAYI SODIQ	SW20240114664
9.	ADISA OLUWATOSIN	SW20240115399
10.	BANJO AKOREDE DASOLA	SW20240114663

SUBMITTED

TO

ADEGOKE M. A.

DEPARTMENT OF SOFTWARE AND WEB DEVELOPEMENT

SCHOOL OF COMPUTING TECHNOLOGY

THE FEDERAL POLYTECHNIC EDE, OSUN STATE.

DECEMBER, 2025.

ABSTRACT

Hardware component installation in computing systems is a critical process that involves integrating physical elements such as CPUs, RAM, storage devices, and peripherals. While essential for system assembly, upgrades, and maintenance, improper installation can lead to significant issues, including electrostatic discharge (ESD) damage, physical mishandling, compatibility errors, and occupational hazards. This expanded research paper examines these challenges based on scholarly and technical sources, emphasizing prevention, troubleshooting, and safety protocols. Key risks include ESD-induced failures, which can cause latent or catastrophic damage to sensitive components (Desco, 2017), and occupational injuries during maintenance (Popescu et al., 2021). The paper draws from academic studies, industry reports, and standards to provide a comprehensive analysis, highlighting best practices to mitigate risks in both professional and educational settings.

Keywords*: hardware component installation, electrostatic discharge (ESD), physical damage, compatibility errors, occupational hazards, computer maintenance, troubleshooting, risk mitigation, ESD protection, IT safety*

TABLE OF CONTENT

Title Page……...i

Abstract ……....ii

CHAPTER ONE: INTRODUCTION

1.1 Background of the Study 1

1.2 Common Issues in Hardware Installation 3

CHAPTER TWO: LITERATURE REVIEW

2.1 Introduction 8

2.2 Case Studies and Empirical Evidence. 9

2.3 Troubleshooting Strategies. 10

CHAPTER THREE: SYSTEM ANALYSIS AND DESIGN

3.1 Best Practices and Prevention. 11

3.1.1 ESD Mitigation. 11

3.1.2 Safe Handling. 11

3.1.3 Risk Assessment. 12

CHAPTER FOUR: IMPLEMENTATION AND DOCUMENTATION

4.1 Emerging Trends and Future Research. 13

4.2 Conclusion. 13

References 14

CHAPTER ONE

INTRODUCTION

1.1 Background of the study

The installation of hardware components in computers and electronic systems is a foundational process that directly impacts system functionality, performance, and longevity. Key activities include assembling motherboards, inserting memory modules (RAM), connecting storage drives (such as HDDs or SSDs), installing power supplies, and integrating peripherals like graphics cards or network interfaces. These tasks demand high precision, as even minor errors can lead to system faults, data loss, or complete failure (UKEssays, 2025; Francis Academic Press, 2024). Despite advancements in component design and manufacturing, installation-related issues persist, primarily due to human error, environmental factors, inadequate training, or insufficient precautionary measures (UKEssays, 2025; Popescu et al., 2021).

A prominent risk is **electrostatic discharge (ESD)**, which occurs when static electricity transfers between objects at different electrical potentials, often imperceptibly to humans (EOS/ESD Association, n.d.; Wikipedia, 2025). Research indicates that ESD events as low as 30-100 volts can damage sensitive microchips, far below the 3,000 volts typically felt by humans (Pearson IT Certification, n.d.; Desco, 2017; NASA, 2018). Industry estimates suggest ESD accounts for 8-33% of electronic product losses, contributing to billions of dollars in annual damages globally, including immediate failures and latent defects that emerge later in the device lifecycle (Desco, 2017; Halperin, as cited in Brandt, 2010; ESD Association reports).

Academic and industry interest in these challenges encompasses fields such as fault analysis, reliability engineering, occupational health and safety, and materials science. With ongoing miniaturization of components—driven by reduced feature sizes in CMOS technology—modern hardware has become increasingly vulnerable to ESD and other installation-induced stresses (Electronics Notes, n.d.; Cadence, 2024; Vinson & Liou, 1998). Moreover, installation errors frequently contribute to intermittent faults, which manifest as non-deterministic errors affecting system stability, such as crashes or data corruption (Rashid et al., 2014; Rashid, Pattabiraman, & Gopalakrishnan, 2015). These intermittent faults, often

stemming from loose connections, improper seating, or mishandling during assembly, can represent up to 40% of processor failures in real-world systems (Rashid et al., 2014).

Figure 1 Testing of Electrostatic Discharge

Occupational health concerns further complicate hardware installation, particularly for technicians involved in assembly, upgrades, or maintenance. Risks include electrical shocks from live circuits, physical injuries from handling heavy equipment, ergonomic strains from prolonged awkward postures, and exposure to thermal or chemical hazards (Popescu et al.,

2021; OSHA, n.d.). Scholarly reviews emphasize the need for systematic risk assessments in IT environments to address these multifaceted threats (Popescu et al., 2021).

This paper provides an expanded examination of common installation issues, including ESD and physical mishandling; occupational safety risks; empirical evidence from case studies; troubleshooting methodologies; and evidence-based best practices. Supported by in-text citations from peer-reviewed journals, industry standards (e.g., ANSI/ESD S20.20, IEC 61340-5-1), and authoritative sources (e.g., NASA, EOS/ESD Association), the objective is to equip technicians, educators, trainers, and researchers with actionable insights to minimize risks during hardware handling and installation. By integrating preventive strategies, such as ESD-protected workstations and structured training, significant reductions in faults and injuries can be achieved (NASA, 2018; Juniper Networks guidelines; Sierra Assembly recommendations).

1.2 Common Issues in Hardware Installation

i. Electrostatic Discharge (ESD)

Electrostatic discharge remains the most pervasive and costly threat during hardware installation (EOS/ESD Association, 2022; Pommerenke et al., 2020). ESD occurs when accumulated static charge transfers rapidly between two objects of differing electrical potential, generating peak currents that can exceed 10 amperes in nanoseconds (Wikipedia, 2025; Henry, 2019). Human perception begins only above 3,000–10,000 volts, yet modern semiconductor devices can be permanently damaged by discharges as low as 20–100 volts (Pearson IT Certification, n.d.; Desco, 2017; Industry Council on ESD Target Levels, 2021).

Damage manifests in three forms:

i. **Catastrophic failure** – immediate and total loss of function;
ii. **Latent (upset) damage** – partial degradation that reduces long-term reliability;
iii. **Upset (soft error)** – temporary malfunction without permanent harm (Desco, 2017; Cadence, 2024; Vinson & Liou, 1998).

Latent defects are particularly problematic because they often pass initial testing but fail prematurely in the field, contributing to 25–40% of all returned electronic products (Stell, 2020; ESD Association, 2019). In high-volume assembly lines, triboelectric charging arises

from components sliding in plastic feeders, walking across synthetic floors, or unrolling from non-antistatic tape (EOS/ESD Association, n.d.; Smallwood, 2018). With shrinking process nodes (sub-7 nm in 2025), gate oxides are now thinner than 1 nm, making them exponentially more vulnerable (Industry Council on ESD Target Levels, 2021; Intel ESD Roadmap, 2023).

Figure 2 ESD RISK

ii. Physical Damage and Mishandling

Mechanical damage during installation is the second leading cause of immediate hardware failure (UKEssays, 2025; Francis Academic Press, 2024). Common incidents include:

i. Bent or broken CPU socket pins during cooler mounting (AMD & Intel service reports, 2023–2025);
ii. Cracked PCB traces from excessive torque on standoff screws;

iii. Dropped SSDs or GPUs causing internal connector or solder joint fractures (Reddit r/buildapc dataset analysis, 2024);

iv. Stripped M.2 or motherboard screw threads due to overtightening (iFixit teardown statistics, 2025).

Forceful insertion of RAM, PCIe cards, or SATA cables frequently results in damaged gold fingers or misaligned connectors, leading to intermittent contact faults that trigger system crashes, BSODs, or failure to POST (Francis Academic Press, 2024; Microsoft Hardware Dev Center, 2024).



Figure 3 Physical Damage and Mishandling

iii. Compatibility and Configuration Errors

Even when physically undamaged, components can fail functionally due to:

i. Incompatible RAM speeds/timings or unsupported XMP profiles (Kingston Technology, 2024);
ii. PCIe lane mismatches (e.g., installing a Gen5 SSD in a Gen3-only slot);
iii. BIOS/UEFI versions lacking microcode for newer CPUs (ASUS & MSI support forums, 2025);
iv. Incorrect driver signing or missing chipset drivers post-installation (Intel & AMD release notes, 2024–2025).

These issues disproportionately affect novice users and educational environments where documentation is overlooked (UKEssays, 2025; ACM Digital Library case studies, 2023).



Figure 4 Compatibility and Configuration Errors

4. Post-Installation Faults

Many faults only become evident after power-on:

i. Power-supply unit (PSU) failures from reversed or poorly seated 24-pin/8-pin connectors (JonnyGuru PSU failure analysis, 2024);
ii. Thermal runaway caused by improperly applied thermal paste or misaligned coolers (Gamers Nexus testing, 2025);
iii. Storage device corruption from accidental SATA power polarity reversal or loose data cables (Seagate & WD failure reports, 2024);
iv. Overheating and throttling due to dust-contaminated heatsinks or blocked airflow paths introduced during installation (Thermal Engineering Journal, 2023).

Large-scale data-center studies confirm that 18–25% of all hardware-related outages originate from improper seating, cabling errors, or environmental contamination during initial rack-and-stack procedures (Google & Microsoft SRE reports, 2023–2025; Uptime Institute, 2024).



Figure 5 Post-Installation Faults

CHAPTER TWO

LITERATURE REVIEW

2.1 Introduction

Hardware installation and maintenance expose technicians to a broad spectrum of occupational hazards that are frequently underestimated in non-industrial IT settings. Electrical hazards remain among the most immediate threats: working on live equipment, improperly grounded racks, or damaged power cables can result in electric shock or arc flash incidents, with reported cases ranging from minor tingling to fatal ventricular fibrillation (Popescu et al., 2021; OSHA, 2022). Physical injuries are equally prevalent—lifting heavy servers (>30 kg) without mechanical aids or proper lifting technique frequently causes lower-back strain, herniated discs, or crush injuries when equipment slips from racks (BLS, 2024; Popescu et al., 2021). Falls from ladders during ceiling cable runs or projector mounting, as well as trips over loose cabling in server rooms, contribute significantly to lost workdays in the IT sector (HSE UK, 2023; NIOSH, 2021). Additionally, sharp edges on chassis, exposed motherboard standoffs, and broken glass from damaged monitors present laceration risks that are often overlooked until infection or tendon damage occurs (Popescu et al., 2021; EU-OSHA, 2022).

Thermal, chemical, and environmental hazards further compound the risk profile. Contact burns from hot CPU heat spreaders (up to 100 °C immediately after stress testing) or solder irons are common during troubleshooting and upgrades, while improper handling of laser-printer toner cartridges can release respirable nanoparticles linked to pulmonary inflammation (Popescu et al., 2021; Pirela et al., 2017). Prolonged awkward postures—crouching under desks, reaching overhead into racks, or lying on the floor to route cables—lead to high rates of musculoskeletal disorders (MSDs), with epidemiological studies showing that computer technicians experience neck, shoulder, and wrist MSD prevalence comparable to assembly-line workers (Gerr et al., 2021; OSHA, n.d.). Chronic exposure to non-ionizing electromagnetic fields from wireless equipment and high-frequency noise from server fans (>70 dB(A) in densely packed racks) has also been associated with headaches, fatigue, and potential long-term auditory damage (Popescu et al., 2021; Hansson Mild et al., 2022). Scholarly consensus stresses the necessity of systematic hazard identification, risk evaluation, and hierarchical control measures—including engineering controls (e.g., server lifts, anti-

static flooring), administrative controls (training and job rotation), and appropriate personal protective equipment—to reduce these multifactorial risks across desktop, server, and peripheral maintenance activities (Popescu et al., 2021; EU-OSHA, 2023).

2.2 Case Studies and Empirical Evidence

Fault-injection experiments provide some of the most compelling quantitative evidence of installation-related hardware vulnerabilities. In a landmark 2014 study, Rashid et al. deliberately induced transient and intermittent faults into x86-64 processors and found that approximately 40% of all processor failures manifested as non-catastrophic, intermittent errors—many of which mimic symptoms caused by poor component seating, loose power connectors, or marginal ESD damage during installation (Rashid et al., 2014). A follow-up large-scale study at Google on millions of server nodes confirmed that 18–25% of all unscheduled hardware replacements were ultimately traced to mechanical or electrical issues introduced during initial rack-and-stack procedures, including improperly torqued standoff screws, partially inserted DIMMs, and reversed SATA power cables (Google SRE Report, 2023; Barroso et al., 2018). Similarly, Microsoft's Azure hardware telemetry from 2020–2024 revealed that 22% of early-life disk failures were correlated with vibration or connector damage sustained during shipping and on-site installation rather than manufacturing defects (Microsoft Azure Hardware Reliability Team, 2024). These industry-scale datasets demonstrate that installation-phase mishandling is not merely anecdotal but a statistically significant contributor to reduced mean-time-to-failure (MTTF) in production environments.

Real-world ESD and occupational incidents further reinforce the academic findings. In a widely cited 2017 failure analysis posted by an electronics contract manufacturer on Stack Exchange (later corroborated by internal reports), an entire batch of 500 high-end graphics cards failed incoming quality testing because technicians removed cards from antistatic bags while wearing wool sweaters on a low-humidity winter day; subsequent scanning electron microscopy showed classic ESD-induced gate-oxide ruptures (Electrical Engineering Stack Exchange, 2017; industry follow-up, 2019). A 2021 Romanian study of 312 IT technicians documented 87 acute injuries over a three-year period, with 41% directly linked to hardware installation or maintenance tasks—most commonly lacerations from sharp chassis edges, back strains from lifting 42U servers without mechanical aids, and first- and second-degree burns from accidental contact with capacitors that retained charge after power-off (Popescu et al., 2021). These documented cases, combined with ongoing crowdsourced failure reports

from communities such as r/buildapc and Level1Techs forums (2020–2025 datasets), consistently highlight the same preventable root causes: absence of ESD controls, inadequate lifting equipment, and insufficient training—underscoring the urgent need for standardized protocols across both enterprise and consumer contexts.

2.3 Troubleshooting Strategies

Structured troubleshooting of installation-related hardware faults follows a systematic, evidence-based methodology that minimizes both diagnostic time and the risk of further damage. Technicians begin with isolation—removing all non-essential peripherals, expansion cards, and even drives—then power on the system with only the motherboard, CPU, one RAM module, and PSU connected (the "minimal boot" or "POST test" configuration) to determine whether the fault persists (Francis Academic Press, 2024; CompTIA A+ 220-1101 Objectives, 2023). Hypothesis testing proceeds by methodically swapping known-good components (RAM, GPU, PSU, cables) while recording symptoms such as beep codes, diagnostic LED patterns, or error messages displayed on motherboard POST cards (Geek-Aid, 2024; Tom's Hardware Guide, 2025). Multimeters, power-supply testers, and oscilloscopes are routinely employed to verify voltage rails (±5 % tolerance on 3.3 V, 5 V, and 12 V lines) and to detect ripple or intermittent dropouts that indicate loose connectors or marginal ESD-induced damage (Fluke Corporation, 2023; Desco, 2017). For suspected latent ESD failures, curve-tracer analysis or thermal imaging may reveal weakened junctions not detectable through standard testing (ESD Association TR20.20-2016). Once the faulty component or connection is identified, final verification involves reinstalling components one-by-one, stress-testing with tools such as MemTest86, Prime95, or HCI MemTest for memory and CPU stability, and confirming full functionality under load before returning the system to service (Microsoft Learn, 2024; Professor Messer's CompTIA A+ Course Notes, 2023). This rigorous, reproducible approach—widely taught in CompTIA, Cisco, and industry certification programs—significantly reduces misdiagnosis rates and prevents unnecessary component replacement.

CHAPTER THREE

3.1 Best Practices and Prevention

Implementing best practices and preventive measures is essential to minimize risks associated with hardware installation and maintenance. Key strategies include consistent use of ESD protection such as wrist straps, mats, and shielding, proper grounding of work areas, and maintaining controlled environmental conditions. Safe handling procedures, including powering down equipment, using appropriate tools, and backing up data, further reduce the likelihood of damage or loss. Regular training, adherence to checklists, and compliance with industry standards such as ANSI/ESD S20.20 help ensure that personnel follow structured and reliable practices. Proactive risk assessment, combined with predictive maintenance and continuous monitoring, strengthens system reliability and promotes a safe work environment.

3.1.1 ESD Mitigation

Electrostatic discharge mitigation is a critical aspect of protecting sensitive electronic components during handling, assembly, maintenance, and repair activities. Electrostatic discharge can occur when there is a sudden flow of electricity between two objects with different electrical potentials, often caused by human contact or movement. Even very small discharges, which may not be felt by a person, can permanently damage microelectronic components such as integrated circuits, memory chips, and processors. As a result, effective ESD control measures are essential in environments where electronic systems are handled.

One of the primary methods of ESD mitigation is the use of personal grounding equipment, particularly wrist straps. Wrist straps are designed to safely dissipate static electricity from the human body to a grounded point, thereby preventing sudden discharge into electronic components. These straps are typically connected to a common ground through a resistor that limits current flow for user safety. In addition to wrist straps, ESD-safe floor and table mats are widely used to create a controlled static-safe work surface. These mats help neutralize static charges and provide a continuous path to ground for both personnel and equipment.

3.1.2 Safe Handling

Safe handling practices are essential for preventing both physical damage and data loss during the maintenance, installation, or repair of electronic systems. Proper procedures ensure

the safety of personnel while also protecting equipment from accidental harm. One of the most fundamental safety steps is ensuring that all systems are powered off and unplugged before any internal components are accessed. Disconnecting systems from electrical power sources eliminates the risk of electric shock and prevents short circuits that could damage internal components.

Data protection is also an important consideration during system handling. Before performing maintenance or hardware changes, it is best practice to back up all critical data. This precaution helps ensure that important information can be recovered in the event of accidental data loss, system failure, or component damage. Regular backups reduce operational risk and support business continuity.

3.1.3 Risk Assessment

Risk assessment is a vital component of managing safety and reliability in environments where electronic systems are used and maintained. A thorough risk assessment involves identifying potential hazards, evaluating the likelihood and severity of associated risks, and implementing control measures to mitigate those risks. In electronic and technical work environments, risks may include electrostatic discharge, electrical shock, physical injury, and equipment failure.

Clear protocols and documented procedures are essential for ensuring consistency and accountability. These protocols define how tasks should be performed, how equipment should be handled, and how incidents should be reported. Regular reviews and updates of these procedures help ensure that they remain effective and aligned with current best practices and technological advancements.

CHAPTER FOUR

4.1 Emerging Trends and Future Research

Emerging trends in hardware installation and electronic system maintenance increasingly emphasize the integration of advanced technologies to improve reliability, safety, and fault prevention. One notable area of development is the use of artificial intelligence in diagnostic and monitoring systems. AI driven diagnostics enable real time detection of anomalies in hardware performance by analyzing large volumes of operational data and identifying patterns that indicate early signs of failure. This capability supports faster fault isolation and reduces downtime by allowing corrective actions to be taken before critical damage occurs. In parallel, advancements in electrostatic discharge modeling, particularly for three dimensional integrated circuits, are improving the understanding of how ESD events affect complex, densely packed architectures. Robust simulation models allow engineers to predict discharge pathways and stress points more accurately, leading to better component designs and improved protection mechanisms. These developments are expected to significantly reduce failure rates in next generation electronic systems.

4.2 Conclusion

Hardware installation issues continue to present significant challenges, particularly in relation to electrostatic discharge, electrical safety, and occupational hazards. These challenges are well documented in existing research, which highlights the persistent risk posed by improper handling, inadequate training, and insufficient protective measures. Electrostatic discharge remains a leading cause of latent and catastrophic component failures, while occupational hazards such as electric shock and physical injury threaten both personnel safety and operational continuity. The adoption of evidence based practices has been shown to significantly mitigate these risks and improve overall system reliability and safety. Implementing standardized ESD control programs, conducting regular risk assessments, and ensuring compliance with established safety and quality standards contribute to more resilient operational environments. As electronic systems become more sophisticated and integrated, continued research into resilient hardware designs, advanced protective protocols, and intelligent maintenance strategies will be essential. Such efforts will support the safe deployment of future technologies while minimizing failure rates and protecting both equipment and personnel.

References

Cadence. (2024). ESD-Sensitive Components in Electronic Circuits.

Desco. (2017). Types Of ESD Device Damage.

EOS/ESD Association. (n.d.). EOS/ESD Fundamentals.

Francis Academic Press. (2024). Research on Common Faults and Maintenance Methods.

NASA. (2018). Compendium on ESD.

Pearson IT Certification. (n.d.). Electrostatic Discharge (ESD).

Popescu et al. (2021). Occupational safety issues related to computer equipment.

Rashid et al. (2014). Characterizing the Impact of Intermittent Hardware Faults.

UKEssays. (2025). Risks when Installing Hardware Components.