Non-contact Voltage Detector



Category: **Electrical & Electronic Test Instruments** Type: **Short SOP** Priority: **High**

6 labs

Covers these lab items: Non-contact Voltage Detector

What it is used for

A non-contact voltage detector indicates the possible presence of AC voltage without touching a conductor directly. Use it as a preliminary screening tool, not as the sole proof that a circuit is safe.

How to use

1. Inspect the detector body, tip, and battery condition for damage.
2. Read the manufacturer's instructions and confirm the detector's voltage range.
3. Test the detector on a known live source to verify operation.
4. Bring the sensing tip near the insulated wire or test point as instructed.
5. Observe the indicator light, sound, or display for a voltage indication.
6. Recheck the detector on a known live source after testing.
7. Use an appropriately rated tester and approved isolation procedure to confirm absence of voltage before electrical work.

⚠ Safety

- Do not touch bare conductors or rely on the detector alone to prove a circuit is de-energised.
- Keep hands dry and use suitable electrical PPE.
- Do not use a damaged detector or one outside its rated range.
- Follow lockout and isolation procedures before working on electrical equipment.

Care & storage

- Keep the detector clean and dry, and replace batteries as required.
- Store it safely and check operation before each use.

Disclaimer: This SOP is prepared from general information available on the internet. For detailed instructions, refer to the manufacturer's original manual / file.