Simple row operations

In this section we'll look at some different ways to manipulate rows in matrices.

Switching two rows

You can switch any two rows in a matrix without changing the value of the matrix. In this matrix, we'll switch rows 1 and 2, which we write as $R_1 \leftrightarrow R_2$.

$$\begin{bmatrix} 3 & 2 & 7 \\ 1 & -6 & 0 \end{bmatrix} \longrightarrow \begin{bmatrix} 1 & -6 & 0 \\ 3 & 2 & 7 \end{bmatrix}$$

Keep in mind that you can also make multiple row switches. For instance, in this 3×3 matrix, you could first switch the second row with the third row,

$$\begin{bmatrix} 7 & 3 & 4 \\ 1 & 6 & 1 \\ 2 & 2 & 3 \end{bmatrix} \longrightarrow \begin{bmatrix} 7 & 3 & 4 \\ 2 & 2 & 3 \\ 1 & 6 & 1 \end{bmatrix}$$

and then switch the first row with the second row.

$$\begin{bmatrix} 7 & 3 & 4 \\ 1 & 6 & 1 \\ 2 & 2 & 3 \end{bmatrix} \longrightarrow \begin{bmatrix} 2 & 2 & 3 \\ 7 & 3 & 4 \\ 1 & 6 & 1 \end{bmatrix}$$

Example

Write the new matrix after $R_3 \leftrightarrow R_2$.

$$\begin{bmatrix} 2 & 3 & -1 & 11 \\ 1 & 7 & 4 & 6 \\ 0 & -1 & -8 & -3 \end{bmatrix}$$

The operation described by $R_3 \leftrightarrow R_2$ is switching row 2 with row 3. Nothing will happen to row 1. The matrix after $R_3 \leftrightarrow R_2$ is

$$\begin{bmatrix} 2 & 3 & -1 & 11 \\ 0 & -1 & -8 & -3 \\ 1 & 7 & 4 & 6 \end{bmatrix}$$

Multiplying a row by a constant

You can multiply any row by any non-zero constant without changing the value of the matrix. For instance, if we multiply through the first row of this matrix by 2, we don't actually change the value of the matrix.

$$\begin{bmatrix} 3 & 2 & 7 \\ 1 & -6 & 0 \end{bmatrix} \longrightarrow \begin{bmatrix} 2 \cdot 3 & 2 \cdot 2 & 2 \cdot 7 \\ 1 & -6 & 0 \end{bmatrix} \longrightarrow \begin{bmatrix} 6 & 4 & 14 \\ 1 & -6 & 0 \end{bmatrix}$$

How can it be true that multiplying a row by a constant doesn't change the value of the matrix? Aren't the entires in the matrix now different? Well, to get an intuitive understanding of this, remember that a row in a matrix can represent a linear equation. For instance, the matrix

© Krista King Math

$$\begin{bmatrix} 6 & 4 & 14 \\ 1 & -6 & 0 \end{bmatrix}$$

could represent this linear system:

$$6x + 4y = 14$$

$$x - 6y = 0$$

But given $6x + 4y = 14$, we know we can divide through the equation by 2, and it doesn't change the value of the equation. In fact, dividing through by 2 just gives us $3x + 2y = 7$.

So in the same way, we can pull the 2 back out of the matrix, undoing the operation from before,

$$\begin{bmatrix} 6 & 4 & 14 \\ 1 & -6 & 0 \end{bmatrix} \longrightarrow \begin{bmatrix} 2 \cdot 3 & 2 \cdot 2 & 2 \cdot 7 \\ 1 & -6 & 0 \end{bmatrix} \longrightarrow \begin{bmatrix} 3 & 2 & 7 \\ 1 & -6 & 0 \end{bmatrix}$$

and the matrix still has the same value.

Keep in mind that you're not limited to multiplying only one row of a matrix by a non-zero constant. You can multiply as many rows as you like by a constant, and the constants don't even have to be the same. For example, we can multiply the first row of the matrix by 2 (which we write as $2R_1 \to R_1$), and multiply the second row of the matrix by 3 (which we write as $3R_2 \to R_2$,

$$\begin{bmatrix} 3 & 2 & 7 \\ 1 & -6 & 0 \end{bmatrix} \longrightarrow \begin{bmatrix} 2 \cdot 3 & 2 \cdot 2 & 2 \cdot 7 \\ 3 \cdot 1 & 3 \cdot -6 & 3 \cdot 0 \end{bmatrix} \longrightarrow \begin{bmatrix} 6 & 4 & 14 \\ 3 & -18 & 0 \end{bmatrix}$$

© Krista King Math

and we still won't have changed the value of the matrix, since those constants could be factored right back out again.

Example

Write the new matrix after $3R_1 \leftrightarrow 2R_3$.

$$\begin{bmatrix} 2 & 3 & -1 & 11 \\ 1 & 7 & 4 & 6 \\ 0 & -1 & -8 & -3 \end{bmatrix}$$

The operation described by $3R_1 \leftrightarrow 2R_3$ is multiplying row 1 by a constant of 3, multiplying row 3 by a constant of 2, and then switching those two rows. Nothing will happen to row 2. The matrix after $3R_1$ is

$$\begin{bmatrix} 6 & 9 & -3 & 33 \\ 1 & 7 & 4 & 6 \\ 0 & -1 & -8 & -3 \end{bmatrix}$$

The matrix after $2R_3$ is

$$\begin{bmatrix} 6 & 9 & -3 & 33 \\ 1 & 7 & 4 & 6 \\ 0 & -2 & -16 & -6 \end{bmatrix}$$

The matrix after $3R_1 \leftrightarrow 2R_3$ is

$$\begin{bmatrix} 0 & -2 & -16 & -6 \\ 1 & 7 & 4 & 6 \\ 6 & 9 & -3 & 33 \end{bmatrix}$$

© Krista King Math

Adding a row to another row

It's also acceptable to add one row to another. Keep in mind though that this doesn't consolidate two rows into one. Instead, we replace a row with the sum of itself and another row. For instance, in this matrix,

$$\begin{bmatrix} 3 & 2 & 7 \\ 1 & -6 & 0 \end{bmatrix}$$

we could replace the first row with the sum of the first and second rows, which we write as $R_1 + R_2 \to R_1$. When we perform that operation, we're replacing the entries in row 1, but row 2 stays the same.

$$\begin{bmatrix} 3+1 & 2-6 & 7+0 \\ 1 & -6 & 0 \end{bmatrix} \longrightarrow \begin{bmatrix} 4 & -4 & 7 \\ 1 & -6 & 0 \end{bmatrix}$$

Example

Write the new matrix after $R_1 + 4R_3 \to R_1$.

$$\begin{bmatrix} 2 & 3 & -1 & 11 \\ 1 & 7 & 4 & 6 \\ 0 & -1 & -8 & -3 \end{bmatrix}$$

© Krista King Math

The operation described by $R_1 + 4R_3 \to R_1$ is multiplying row 3 by a constant of 4, adding that resulting row to row 1, and using that result to replace row 1. The row R_3 is

$$\begin{bmatrix} 0 & -1 & -8 & -3 \end{bmatrix}$$

So the row $4R_3$ would be

$$\begin{bmatrix} 4(0) & 4(-1) & 4(-8) & 4(-3) \end{bmatrix}$$

$$\begin{bmatrix} 0 & -4 & -32 & -12 \end{bmatrix}$$

Then the row $R_1 + 4R_3$ is

$$\begin{bmatrix} 2+0 & 3+(-4) & -1+(-32) & 11+(-12) \end{bmatrix}$$

$$\begin{bmatrix} 2 & -1 & -33 & -1 \end{bmatrix}$$

The matrix after $R_1 + 4R_3 \to R_1$, which is replacing row 1 with this row we just found, is

$$\begin{bmatrix} 2 & -1 & -33 & -1 \\ 1 & 7 & 4 & 6 \\ 0 & -1 & -8 & -3 \end{bmatrix}$$

© Krista King Math