

Hex	Decimal	Meaning
adbccbda	-	Magic number (WSJT-X identifier)
00000002	2	Schema version
00000001	1	Message type (Status)
00000006	6	String length
57534a542d58	-	Application ID
000000000d6d800	14,018,560	Frequency (Hz)
00000003	3	String length
465434	-	Mode
00000006	6	String length
4f45364a4347	-	DX callsign
00000002	2	String length
2d32	-	Signal report
00000003	3	String length
465434	-	TX mode
00	0	TX enabled (false)
00	0	Transmitting (false)
00	0	Decoding (false)
00	0	TX Watchdog (false)
00000837	2103	RX audio freq (Hz)
000007d3	2003	TX audio freq (Hz)
00000005	5	String length
4b33444644	-	DE callsign (you)
00000004	4	String length
464e3230	-	DE grid
00000004	4	String length
4a4e3736	-	DX grid
ffffff	-1	Sub-mode (null/not set)
00	0	Fast mode (false)
00	0	Special op mode (None)
ffffffffffffff	-1	Frequency tolerance (null)
ffffff	-1	T/R Period (default)
00000007	7	String length
46542d39393141	-	Configuration name
00000025	37	String length
4f45364a4347204b33...	-	TX message (37 chars padded)