DHT22 library for Arduino

1.0.0

Generated by Doxygen 1.8.14

Contents

1 DHT22 temperature and humidity sensor library for Arduino **1**

2 Class Index **5**

2.1 Class List 5

3 File Index **7**

3.1 File List 7

4 Class Documentation **9**

4.1 DHT22 Class Reference 9

4.1.1 Detailed Description 9

4.1.2 Constructor & Destructor Documentation 9

4.1.2.1 DHT22() 9

4.1.3 Member Function Documentation 10

4.1.3.1 available() 10

4.1.3.2 begin() 10

4.1.3.3 readHumidity() 10

4.1.3.4 readTemperature() 11

5 File Documentation **13**

5.1 src/DHT22.cpp File Reference 13

5.1.1 Detailed Description 13

5.2 src/DHT22.h File Reference 13

5.2.1 Detailed Description 14

5.2.2 Macro Definition Documentation 14

5.2.2.1 DHT22_MIN_READ_INTERVAL 14

5.2.2.2 DHT22_NUM_DATA_BITS 14

Index **15**

Chapter 1

DHT22 temperature and humidity sensor library for Arduino

This is a AM2303 temperature and humidity sensor on a DHT22 breakout.

Library features

- Synchronous 16-bit temperature read
- Synchronous 16-bit humidity read

Hardware

Connection DHT22 - Arduino UNO

DHT22	Arduino UNO
GND	GND
VCC	5V (or 3.3V)
DAT	D2

Documentation

`AM2303 datasheet`

`DHT22 datasheet`

AM2303 specifications

- Voltage: 3.3 .. 5V
- Ultra-low power:
  - Typical 15uA dormancy
  - Typical 500uA measuring

- Single wire serial interface
- Humidity:
  - Range: 0 .. 99.9 RH (Relative Humidity)
  - Resolution: 0.1 RH
  - Accuracy: +/-2 RH (at 25 degree Celsius)
- Temperature:
  - Range: -40 .. +125 degree Celsius
  - Resolution: 0.1 degree Celsius
  - Accuracy: +/- 0.4 degree Celsius
- Minimum read interval: 2000 ms

Examples

Examples | ErriezDH22:

- Example

Usage

Initialization

```
{c++}
#include <DHT22.h>

// Connect DTH22 data pin to Arduino DIGITAL pin
#define DHT22_PIN   2

DHT22 sensor = DHT22(DHT22_PIN);

void setup()
{
    // Initialize serial port
    Serial.begin(115200);
    Serial.println(F("DHT22 temperature and humidity sensor example\n"));

    // Initialize sensor
    sensor.begin();
}
```

Read temperature and humidity

```
{c++}
void loop()
{
  // Check minimum interval of 2000 ms between sensor reads
  if (sensor.available()) {
    // Read temperature from sensor
    int16_t temperature = sensor.readTemperature();

    // Read humidity from sensor
    int16_t humidity = sensor.readHumidity();

    // Print temperature
    Serial.print(F("Temperature: "));
    Serial.print(temperature / 10);
    Serial.print(F("."));
    Serial.print(temperature % 10);
    Serial.println(F(" *C"));

    // Print humidity
    Serial.print(F("Humidity: "));
    Serial.print(humidity / 10);
    Serial.print(F("."));
    Serial.print(humidity % 10);
    Serial.println(F(" %\n"));
  }
}
```

Serial output

```
DHT22 temperature and humidity sensor example

Temperature: 17.7 *C
Humidity: 41.0 %

Temperature: 17.8 *C
Humidity: 41.1 %

...
```

Chapter 2

Class Index

2.1 Class List

Here are the classes, structs, unions and interfaces with brief descriptions:

DHT22
DHT22 sensor class 9

Chapter 3

File Index

3.1 File List

Here is a list of all documented files with brief descriptions:

src/DHT22.cpp
DHT22 (AM2303) Humidity and Temperature sensor example for Arduino 13
src/DHT22.h
DHT22 (AM2303) Humidity and Temperature sensor example for Arduino 13

Chapter 4

Class Documentation

4.1 DHT22 Class Reference

DHT22 sensor class.

`#include <DHT22.h>`

Public Member Functions

- DHT22 (uint8_t pin)
  Constructor DHT22 sensor.
- void begin ()
  Initialize sensor.
- bool available ()
  Check if new temperature or humidity read is allowed.
- int16_t readTemperature ()
  Read temperature from sensor.
- int16_t readHumidity ()
  Read humidity from sensor.

4.1.1 Detailed Description

DHT22 sensor class.

Definition at line 58 of file DHT22.h.

4.1.2 Constructor & Destructor Documentation

4.1.2.1 DHT22()

```
DHT22::DHT22 (
            uint8_t pin )  [explicit]
```

Constructor DHT22 sensor.

Parameters

pin	Data pin sensor.

Definition at line 37 of file DHT22.cpp.

4.1.3 Member Function Documentation

4.1.3.1 available()

```
bool DHT22::available ( )
```

Check if new temperature or humidity read is allowed.

The application should call this function and check if a new temperature and humidity can be read to prevent too fast sensor reads.

Returns

true: Available, interval between sensor reads >= 2000 ms. false: Not available, interval between sensor reads too short.

Definition at line 79 of file DHT22.cpp.

4.1.3.2 begin()

```
void DHT22::begin ( )
```

Initialize sensor.

Call this function from setup().

Definition at line 59 of file DHT22.cpp.

4.1.3.3 readHumidity()

```
int16_t DHT22::readHumidity ( )
```

Read humidity from sensor.

Returns

Signed humidity with last digit after the point. ~0: An error occurred

Definition at line 121 of file DHT22.cpp.

4.1.3.4 readTemperature()

```
int16_t DHT22::readTemperature ( )
```

Read temperature from sensor.

Returns the actual temperature, or a cached temperature when read interval is too short.

Returns

Signed temperature with last digit after the point ~0: An error occurred

Definition at line 99 of file DHT22.cpp.

The documentation for this class was generated from the following files:

- src/DHT22.h
- src/DHT22.cpp

Chapter 5

File Documentation

5.1 src/DHT22.cpp File Reference

DHT22 (AM2303) Humidity and Temperature sensor example for Arduino.

```
#include "DHT22.h"
```

5.1.1 Detailed Description

DHT22 (AM2303) Humidity and Temperature sensor example for Arduino.

Source: https://github.com/Erriez/ErriezDHT22

5.2 src/DHT22.h File Reference

DHT22 (AM2303) Humidity and Temperature sensor example for Arduino.

```
#include <Arduino.h>
```

Classes

- class DHT22
  DHT22 sensor class.

Macros

- #define DHT22_MIN_READ_INTERVAL 2000
  Enable debug prints to Serial.
- #define DHT22_NUM_DATA_BITS (5 ∗ 8)
- #define DEBUG_PRINTLN(...) {}
  Debug print configuration.

5.2.1 Detailed Description

DHT22 (AM2303) Humidity and Temperature sensor example for Arduino.

Source: https://github.com/Erriez/ErriezDHT22

5.2.2 Macro Definition Documentation

5.2.2.1 DHT22_MIN_READ_INTERVAL

```
#define DHT22_MIN_READ_INTERVAL 2000
```

Enable debug prints to Serial.

Minimum interval between sensor reads in milli seconds

Definition at line 40 of file DHT22.h.

5.2.2.2 DHT22_NUM_DATA_BITS

```
#define DHT22_NUM_DATA_BITS (5 * 8)
```

Number of data bits is 5 Bytes $*$ 8 bits: 1 Byte: Humidity high 1 Byte: Humidity low 1 Byte: Temperature high 1 Byte: Temperature low 1 Byte: Parity

Definition at line 48 of file DHT22.h.

Index

available
    DHT22, 10

begin
    DHT22, 10

DHT22, 9
    available, 10
    begin, 10
    DHT22, 9
    readHumidity, 10
    readTemperature, 10
DHT22.h
    DHT22_MIN_READ_INTERVAL, 14
    DHT22_NUM_DATA_BITS, 14
DHT22_MIN_READ_INTERVAL
    DHT22.h, 14
DHT22_NUM_DATA_BITS
    DHT22.h, 14

readHumidity
    DHT22, 10
readTemperature
    DHT22, 10

src/DHT22.cpp, 13
src/DHT22.h, 13