LM35 library for Arduino

1.0.0

Generated by Doxygen 1.8.14

Contents

Chapter 1

LM35 temperature sensor library for Arduino

This is an accurate LM35 analog temperature sensor library for Arduino with noise cancellation.

Library features

- Synchronous 10-bit unsigned temperature read
- Temperature range: 0.0 .. 110.0 degree Celsius
- Accuracy: 0.1 degree Celsius
- Noise cancellation
- Small footprint

Hardware

Connection LM35 - Arduino UNO

LM35	Arduino UNO
GND	GND
Vs	5V (or 3.3V)
Vout	A0 (ANALOG pin)

Notes:

- Keep wires short to prevent noise.
- This library has been tested on the Arduino UNO only which supports internal 1.1V ADC reference voltage. This may not be available with other MCU's.

LM35 pins

Documentation

DHT35 datasheet

LM35 specifications

- Supply voltage: 3.3V .. 30V
- Low power: Around 65uA
- Analog voltage interface

Examples

Examples | ErriezLM35:

- Example

Usage

Initialization

```
{c++}
#include <LM35.h>

// Connect LM35 data pin to Arduino DIGITAL pin
#define LM35_PIN   A0

LM35 lm35 = LM35(LM35_PIN);
```

Read temperature and humidity

```
{c++}
void loop()
{
  // Read unsigned temperature from sensor
  uint16_t lm35_temp = lm35.readTemperature();

  // Print temperature
  Serial.print(F("LM35: "));
  Serial.print(lm35_temp / 10);
  Serial.print(F("."));
  Serial.print(lm35_temp % 10);
  Serial.println(F(" *C"));

  // Wait some time
  delay(2000);
}
```

Serial output

```
Analog LM35 temperature sensor example

LM35: 18.1 *C
LM35: 18.2 *C
LM35: 18.2 *C

...
```

Chapter 2

Class Index

2.1 Class List

Here are the classes, structs, unions and interfaces with brief descriptions:

Chapter 3

File Index

3.1 File List

Here is a list of all documented files with brief descriptions:

Chapter 4

Class Documentation

4.1 LM35 Class Reference

LM35 sensor class.

`#include <LM35.h>`

Public Member Functions

- LM35 (uint8_t pin)
  LM35 constructor.
- uint16_t readTemperature ()
  Read analog temperature in range between 0.0 .. 110 degree Celsius.

4.1.1 Detailed Description

LM35 sensor class.

Definition at line 46 of file LM35.h.

4.1.2 Constructor & Destructor Documentation

4.1.2.1 LM35()

```
LM35::LM35 (
            uint8_t pin )  [explicit]
```

LM35 constructor.

The constructor changes the ADC to 1.1V internal ADC reference voltage for higher accuracy. This affects all ANALOG pins.

Parameters

pin	LM35 analog pin.

Definition at line 40 of file LM35.cpp.

4.1.3 Member Function Documentation

4.1.3.1 readTemperature()

```
uint16_t LM35::readTemperature ( )
```

Read analog temperature in range between 0.0 .. 110 degree Celsius.

Sample LM35 analog pin multiple times to find two identical samples to reduce noise. A maximum number of samples can be configured with macro LM35_MAX_SAMPLES. The last sampled temperature will be returned when no identical temperatures found.

A negative temperature cannot be measured, because the ADC pin can only sample between positive 0.0 and 1.1 Volt.

Returns

Divide temperature by 10 to get the temperature integer, temperature modulo 10 results in the fraction, for example: int16_t temperature = 182 means 18.2 degree Celsius.

Definition at line 64 of file LM35.cpp.

The documentation for this class was generated from the following files:

- src/LM35.h
- src/LM35.cpp

Chapter 5

File Documentation

5.1 src/LM35.cpp File Reference

Analog LM35 temperature sensor library for Arduino.

```
#include "LM35.h"
```

5.1.1 Detailed Description

Analog LM35 temperature sensor library for Arduino.

Source: https://github.com/Erriez/ErriezLM35

5.2 src/LM35.h File Reference

Analog LM35 temperature sensor library for Arduino.

```
#include <Arduino.h>
```

Classes

- class LM35

  LM35 sensor class.

Macros

- #define LM35_MAX_SAMPLES 10

  Maximum number of LM35 ADC samples.

5.2.1 Detailed Description

Analog LM35 temperature sensor library for Arduino.

Source: https://github.com/Erriez/ErriezLM35

Index