

ZTE C320 COMMANDLINE FOR MAINTENANCE

Filed Under: [GPON](#) on Saturday, December 22, 2018

*the commands below
may not work on different system version*

CHECKING ONT STATUS

GPON#show gpon onu state gpon-olt_1/2/3

OnuIndex Admin State OMCC State Phase State Channel

1/2/3:1 enable disable OffLine 1(GPON)
1/2/3:2 enable disable OffLine 1(GPON)
1/2/3:3 enable disable OffLine 1(GPON)
1/2/3:4 enable disable OffLine 1(GPON)
1/2/3:5 enable disable OffLine 1(GPON)
1/2/3:6 enable disable OffLine 1(GPON)
1/2/3:7 enable disable OffLine 1(GPON)
1/2/3:8 enable disable OffLine 1(GPON)
1/2/3:9 enable disable OffLine 1(GPON)
1/2/3:10 enable disable OffLine 1(GPON)

1/2/3:11	enable	disable	OffLine	1(GPON)
1/2/3:12	enable	disable	OffLine	1(GPON)
1/2/3:13	enable	disable	OffLine	1(GPON)
1/2/3:14	enable	disable	OffLine	1(GPON)
1/2/3:15	enable	disable	OffLine	1(GPON)
1/2/3:16	enable	disable	OffLine	1(GPON)
1/2/3:17	enable	disable	OffLine	1(GPON) => modem
1/2/3:18	enable	disable	working	1(GPON) => modem operate normaly

CHECKING ONT POWER

GPON-JKT-KBJ#show pon power attenuation gpon-onu_1/2/3:18

	OLT	ONU	Attenuation
up	Rx :no signal	Tx:N/A	N/A
down	Tx :6.892(dbm)	Rx:N/A	N/A

CHECKING ONT MAC ADDRESS

GPON-JKT-KBJ#show mac gpon onu gpon-onu_1/2/3:18
Total mac address : 0

CHEKING ONT UPTIME AND ONT HISTORY LOGS

GPON#show gpon onu detail-info gpon-onu_1/2/3:18

ONU interface: gpon-onu_1/2/3:18

Name: ONU-3:18

Type: ZTE-F660

State: ready

Configured channel: auto

Current channel: 1(GPON)

Admin state: enable

Phase state: OffLine

Config state: success

Authentication mode: sn

SN Bind: enable with SN check

Serial number: ZTEGC123456F

Password:

Description: ONU-3:18

Vport mode: gemport

DBA Mode: Hybrid

ONU Status: enable

OMCI BW Profile:

Line Profile: N/A

Service Profile: N/A

ONU Distance: N/A

Online Duration: 0h 0m 0s

FEC: none

FEC actual mode: N/A

1PPS+ToD: disable

Auto replace: disable

Multicast encryption:disable
Multicast encryption current state:N/A

	Authpass Time	OfflineTime	Cause
1	0000-00-00 00:00:00	0000-00-00 00:00:00	
2	0000-00-00 00:00:00	0000-00-00 00:00:00	
3	0000-00-00 00:00:00	0000-00-00 00:00:00	
4	0000-00-00 00:00:00	0000-00-00 00:00:00	
5	0000-00-00 00:00:00	0000-00-00 00:00:00	
6	0000-00-00 00:00:00	0000-00-00 00:00:00	
7	0000-00-00 00:00:00	0000-00-00 00:00:00	
8	0000-00-00 00:00:00	0000-00-00 00:00:00	
9	0000-00-00 00:00:00	0000-00-00 00:00:00	
10	0000-00-00 00:00:00	0000-00-00 00:00:00	

FINDING ONT BY SN NUMBER

GPON#show gpon onu by sn ZTEGC123456F

Search result

gpon-onu_1/2/3:18

CHECKING ONT VERSION

GPON#show gpon remote-onu equip gpon-onu_1/2/3:18

Vendor ID: N/A

Version: N/A
SN: N/A
Admin status: unlock
Battery monitor: false
Security mode: aes
Product code: 0
Total priority queue num: 0
Total traffic schedule num:0
Traffic management option: N/A
Operate status: N/A
Equipment ID: N/A
OMCC version: 80
Security capability: aes
Model: N/A
Survival time: N/A
Total GEM port num: 0
System uptime: 0
Region code: N/A
Product SN: N/A
Chip info: 0

CHECKNG OLT UPTIME

GPON#show system-group
System Description: C320 Version V2.1.0 Software
Started before: 6 days, 6 hours, 24 minutes
System name: GPON

CHECKING OLT BOARD

GPON#show card

Rack	Shelf	Slot	CfgType	RealType	Port	HardVer	SoftVer	Status
------	-------	------	---------	----------	------	---------	---------	--------

1	1	2	GTGH	GTGHG	16	V1.0.0	V2.1.0	INSERVICE
1	1	3	PRAM	PRAM	3	V1.0.0	V1.01	INSERVICE
1	1	4	SMXA	SMXA	3	V1.0.0	V2.1.0	INSERVICE

GTGOH = 16 Port (H = Hexa)

CHECKING OLT PROCESSOR AND MEMORY

GPON#show processor

Rack	Shelf	Slot	CPU(5s)	CPU(1m)	CPU(5m)	PhyMem(MB)	Memory
------	-------	------	---------	---------	---------	------------	--------

1	1	2	10%	13%	13%	512	38%
1	1	4	12%	8%	8%	2048	25%

CHECKING OLT CARD TEMPERATURE

GPON#show card-temperature

All cards temperature(deg c):

Rack Shelf Slot Temperature Temperature(5m) Temperature(1h) Optical-
Temp

1	1	2	30	29	29	N/A.
1	1	3	30	30	30	N/A.
1	1	4	33	32	32	N/A.

CHECKING OLT PER SLOT

GPON#show card slotno 2

Config-Type : GTGH Status : INSERVICE

Port-Number : 16

Cpu-Alarm-Threshold : 100%

Mem-Alarm-Threshold : 100%

Real-Type : GTGHG Serial-Number : 706761801136

Phy-Mem-Size : 512MB Main-CPU : PowerPC Processor

M-CODE : 140901 Hardware-VER : V1.0.0

Cpld-VER : V1.3 Fpga-VER :

OtherfirmwareVER:pm.fw(V2.1.0)

BootROM-VER : V4.0.5 2014-12-17 13:37:42

Software-VER : V2.1.0 2017-01-17 00:40:26

Cpu-Usage : 12%

Mem-Usage : 38%

C-Code : FFFFFFFFFFFFFFFFFFFFFFFFFFFFFFFFFF00EE12

Uptime : 6 Days, 6 Hours, 51 Minutes, 41 Seconds

Last restart reason : Other reason

```
GPON#show card slotno 3
```

```
Config-Type : PRAM      Status      : INSERVICE
```

Port-Number : 3

Cpu-Alarm-Threshold : 100%

Mem-Alarm-Threshold : 100%

Real-Type : PRAM Serial-Number : 712151100106

Phy-Mem-Size : Main-CPU :

M-CODE : Hardware-VER : V1.0.0

Cpld-VER : Fpga-VER :

OtherfirmwareVER:

BootROM-VER :

Software-VER :

Cpu-Usage :

Mem-Usage :

C-Code : 00

Uptime :

Last restart reason : Power-off

```
GPON#show card slotno 4
```

Config-Type : SMXA Status : INSERVICE

Port-Number : 3

Cpu-Alarm-Threshold : 100%

Mem-Alarm-Threshold : 100%

Real-Type : SMXA Serial-Number : 712068000791

Phy-Mem-Size : 2048MB Main-CPU : PowerPC Processor

OtherfirmwareVER:

Last restart reason : CLI Command

MAC:

KEREN.KEREN.KEREN

CurIP: 1.2.3.4

CurMask: 255.255.255.0

CurGateway: 1.2.3.4

CurPriDNS: 6.6.6.6

CurSecDNS: 7.7.7.7

CHECKING ONT CONFIGURATION

GPON#show run int gpon-onu_1/4/1:2

Building configuration...

!

interface gpon-onu_1/4/1:2

descriptionIRONMAN

tcont 1 profile share

gemport 1 name ngenet unicast tcont 1 dir both

gemport 1 traffic-limit downstream 300m

gemport 2 name nontonfelm unicast tcont 1 dir both

gemport 2 traffic-limit downstream 300m

gemport 3 name tilpun unicast tcont 1 dir both

gemport 3 traffic-limit downstream 300m

switchport mode hybrid vport 1

switchport vlan 212 tag vport 1

switchport mode hybrid vport 2

switchport vlan 121 tag vport 2

switchport mode hybrid vport 3

switchport vlan 122 tag vport 3

!

end

REBOOT ONT

```
gpon#config t
gpon#pon-onu-mng gpon-onu_1/2/1:3
gpon(gpon-onu-mng)#reboot
```

RESET FACTORY ONT

```
gpon#config t
gpon#pon-onu-mng gpon-onu_1/2/1:3
gpon(gpon-onu-mng)#restore factory
```

DISABLE/SHUTDOWN PORT ONT

```
gpon#config t
gpon#pon-onu-mng gpon-onu_1/2/1:3
gpon(gpon-onu-mng)#interface eth eth_0/2 state lock -->
disable/shutdown port number 2
```

ENABLE/SHUTDOWN PORT ONT

```
gpon#config t
gpon#pon-onu-mng gpon-onu_1/2/1:3
gpon(gpon-onu-mng)#interface eth eth_0/2 state unlock --> enable port
number 2
```

RELEASE RENEW ONT AS DHCP CLIENT

```
GPON#config t
Enter configuration commands, one per line. End with CTRL/Z.
GPON(config)#pon-onu
GPON(config)#pon-onu-mng gpon-onu_1/2/1:3
GPON(gpon-onu-mng)#ip-host 1 dhcp-enable false ping-response false
traceroute-response false
GPON(gpon-onu-mng)#ip-host 1 dhcp-enable true ping-response true
traceroute-response true
```

CHECKING RX/TX LEVEL UPLINK PORT

```
GPON#sho int optical-module-info xgei_1/21/1
Optical module information:xgei_1/21/1
Basic-info:
Vendor-Name   :SOU   Vendor-Pn    :SPP1
Vendor-Sn     :D9      Version-Lev  :10
Production-Date:13      Module-Type  :10GBASE-LR
Wavelength    :1310   (nm)    Connector  :LC
```

Diagnostic-info:

RxPoWer	: -10.1(dbm)	TxPower	: -1.7(dbm)
Bias-Current	: 25.724 (mA)	Laser-Rate	: 103(100Mb/s)
Temperature	: 24.184 (c)	Supply-Vol	: 3.324(v)
Alarm-thresh: -> Threshold			
RxPower-Upper	: 3 (dbm)	RxPower-Lower	: -34(dbm)
TxPower-Upper	: 9 (dbm)	TxPower-Lower	: -14(dbm)
Bias-Upper	: 131(mA)	Bias-Lower	: 0 (mA)
Voltage-Upper	: 7 (v)	Voltage-Lower	: 0 (v)
Temperature-Upper	: 90 (c)	Temperature-Lower	: -45(c)

RESET SLOT CARD

GPON#reset-card slotno 2

SWAP

*Use This for First Level Handling when you get Anomaly Process.
sometimes it can help you, but sometime isn't*

GPON#swap

SHOW VLAN SUMMARY

GPON# show vlan summary

All created vlan num: 3

Details are following:

111, 222 , 333

GPON#

GPON#show vlan 111

vlanid :111

name :VLAN00111

description :N/A

multicast-packet:flood-unknown

tpid:0x8100

port(untagged):

port(tagged):

gpon-onu_1/2/1:3:6

xgei_1/3/4

sg1

CHECKING BANDWIDTH PROFLE

GPON#show gpon profile traffic