

Blue Jeans Relay requirements

Listener Service host

- CPU: 1.5 GHz
- RAM: 1 GB
- Java 8
- Operating systems:
 - Debian, Ubuntu
 - Red Hat, Fedora, CentOS
 - Windows Server 2008 or later

Supported endpoints

Relay has been verified to work with these endpoint models, and compatibility is likely with similar models.

Push Meetings to Endpoint is a Relay feature that allows scheduled Blue Jeans meetings to be joined directly from an endpoint's built-in touchscreen or on-screen display.

MANUFACTURER	MODEL	PUSH MEETINGS TO ENDPOINT	NOTES
Avaya / Radvision	Scopia XT5000	✓	Requires version 8.3.4.18 or later.
Cisco / Tandberg	C20, C40, C60, EX60, EX90, SX10, SX20, IX5000	✓	Push Meetings to Endpoint supports TelePresence Touch.
	DX80	✓	Requires version CE8 or later.
	6000 MXP, E20		
Lifesize	Icon 400, 600	✓	Push Meetings to Endpoint supports Lifesize Phone.
	Express 220, Room 220, Team 220	✓	
Polycom	RealPresence Group 300, 500, 700	✓	Push Meetings to Endpoint supports RealPresence Touch and Touch Control.
	RealPresence Debut	✓	
	Trio 8800	✓	
	HDX 6000 HD, 7000 HD, 8000 HD, 9000	✓	Push Meetings to Endpoint requires Touch Control.
	VSX		
Sony	IPELA PCS-XG80		
StarLeaf	GT Mini 3330		Requires StarLeaf Endpoint IP API to be enabled in StarLeaf Portal.
Tely	telyHD Pro		Requires version 4.5 or later. Versions before 5.0 require a Device API license from Tely Support.
Yealink	VC800	✓	Use the Yealink admin UI, not Relay, to configure Push Meetings to Endpoint.

Supported calendar servers

- Google Calendar
- Microsoft Exchange 2010, 2013, 2016
- Microsoft Office 365, Exchange Online

Supported Blue Jeans services

- Blue Jeans Meetings
- Blue Jeans Events (join public events in Presenter or Attendee roles)