EXOS AEROSPACE SYSTEMS & TECHNOLOGIES, INC.

SOP-DVCSAN

Version 1

Generated August 13, 2026

Confidential — Internal Use Only

Table of Contents

1. Purpose
2. Scope
3. Roles and Responsibilities
4. Approved Sanitization Methods
5. Sanitization Process
6. Incident Reporting
7. Audit and Review
8. Compliance References
9. Updates and Maintenance

SOP-DVCSAN

1. Purpose

This SOP defines the process for securely sanitizing devices in compliance with NIST 800-171 and Department of Defense (DoD) standards for protecting Controlled Unclassified Information (CUI). It incorporates officially approved digital sanitization methodologies and shredding requirements to ensure data is irrecoverable before device reuse, transfer, or disposal.

2. Scope

This SOP applies to:

- Digital media (e.g., hard drives, SSDs, USB drives).
- Non-digital media (e.g., paper, microfilm).
- Devices containing CUI or other sensitive data, including devices designated for reuse, transfer, or disposal.

3. Roles and Responsibilities

1. **Company Admin:**
   - Collects and takes physical custody of devices requiring sanitization from users. Executes the sanitization process following the approved methods. Oversees adherence to sanitization procedures and regulatory requirements.
2. **Security Admin:**
   - Provides technical guidance on approved sanitization methods and remotely verifies and documents that sanitization has been completed.
   - Provides approved tools, technical support, and training for secure sanitization.

4. Approved Sanitization Methods

Digital Media:

1. **Clearing:**
   - Overwrite all data on the device using NIST 800-88 Rev. 1 compliant software tools that write random or predetermined patterns to each sector.
   - Verify the process by sampling areas of the media using forensic tools.
2. **Purging:**
   - Use **cryptographic erasure** for drives with hardware-based encryption:
     - Erase encryption keys stored on the media, rendering all data unrecoverable.
     -

Follow NIST 800-88 guidelines for cryptographic erasure.

3. **Physical Destruction:**
   - Destroy devices using DoD-approved methods:
     - **Shredding Requirements:** Shredders must produce pieces no larger than 2mm x 2mm for optical media or 5mm edge length for hard drives, per DoD standards.
     - Pulverize, disintegrate, or incinerate media to meet particle size requirements.
     - Use National Security Agency (NSA)-approved degaussers for magnetic media before destruction.

Non-Digital Media:

1. **Paper Documents:**
   - Cross-cut shredders producing particles no larger than 1mm x 5mm, per NIST SP 800-88 and DoD 5220.22-M (National Industrial Security Program Operating Manual) standards.
   - Incineration is permitted if shredding is not available.
2. **Microfilm:**
   - Shred or incinerate to meet equivalent particle size standards.
3. **Manual Sanitization (Redaction or Removal):** If reuse requires retention of part of the content (e.g., reusing a binder or folder):
   - **Remove** all CUI-labeled pages or inserts.
   - **Redact** CUI portions using approved methods (e.g., black permanent ink + reprint for reuse).
   - **Verify** no residual CUI markings, headers, or footer labels remain.

Mobile Devices:

1. Factory reset and overwrite all accessible storage using Atomus-approved mobile device management (MDM) tools.
2. Ensure encryption keys for the device are securely purged if available.

5. Sanitization Process

Step 1: Identify Devices

Company Admin collects devices requiring sanitization from users and inventories them.

- Determine whether devices contain CUI or other sensitive data.

Step 2: Select Sanitization Method

- Choose a method based on:
  - Device type.
  - Sensitivity of the stored data.

- End-of-life, reuse, or transfer requirements.

Step 3: Execute Sanitization

Company Admin executes the sanitization following the chosen method as detailed above.

- Use only Atomus-approved or NSA-listed equipment for physical destruction.

Step 4: Verification

- Validate sanitization using forensic tools to confirm no recoverable data remains.
- Before reuse, inspect each item to ensure no CUI remains visible or recoverable.

Obtain written verification from the *Security Admin*.

Step 5: Documentation

- Record the following:
  - Device ID and serial number.
  - Sanitization method used.
  - Responsible personnel.
  - Date and time of sanitization.

6. Incident Reporting

Report failed or incomplete sanitization immediately to the *Security Admin*.

- Quarantine the device to prevent potential data exposure.

7. Audit and Review

- **Annual Review:**

  Company Admin verifies adherence to sanitization processes during annual compliance checks.

8. Compliance References

1. **NIST SP 800-88 Rev. 1:**
   - Guidelines for Media Sanitization, detailing methods for clearing, purging, and destruction.
2. **DoD 5220.22-M (NISPOM):**
   - Specifies shredding and destruction requirements for paper and digital media.

9. Updates and Maintenance

- This SOP is reviewed annually.
- Non-compliance may result in corrective action, including staff retraining or disciplinary measures.

Revision History

Version	Date	Author	Change Summary
v1	Aug 11, 2026	nathaniel@atomus-cyber.com	Initial publication of "SOP-DVCSAN".

Acknowledgement & Signature

By signing below, the undersigned acknowledges that the contents of SOP-DVCSAN (Version 1) have been reviewed and approved on behalf of Exos Aerospace Systems & Technologies, Inc..

Point of Contact

NAME

Jquinn

TITLE

Chief Executive Officer, Co-Founder

SIGNATURE

DATE

Aug 13, 2026

Signed electronically on Aug 13, 2026