Growatt ShineLink-X

- Cable free, easy installation

- Dynamic IP, plug and play

- Communication distance up to 120m

- Support up to 3 devices

- Built-in memory for up to one month of data

- Online monitoring and maintenance

GROWATT

POWER
-INGO
TOMO-
RROWO

Datasheet	ShineLink-X
Communication Interface	
RF433	Yes
RF433(No barrier wall)	Up to 120 m
RF433(two walls blocking)	20 m
Power Supply	
Power consumption	<2W standby,<5W peak
Voltage range	196V~250V
Frequency	50/60Hz
General Specifications	
Dimensions(L/W/H)	105/85/26mm
Weight	< 1kg
Mounting options	Tabletop/wall-mount
Protection degree	IP30
Display	LED
Ambient temperature range	-20 to 65 °C
Humidity	0-95% (non condensing)
Features	
Remote firmware upgrade	Yes
Max. number of devices to monitor	3(RF433)
CE	