

z/OS
3.1

JES2 Initialization and Tuning Reference



Note

Before using this information and the product it supports, read the information in [“Notices” on page 473.](#)

This edition applies to IBM® z/OS® 3.1 (5655-ZOS) and to all subsequent releases and modifications until otherwise indicated in new editions.

Last updated: 2025-06-16

© **Copyright International Business Machines Corporation 1988, 2025.**

US Government Users Restricted Rights – Use, duplication or disclosure restricted by GSA ADP Schedule Contract with IBM Corp.

Contents

Figures.....	ix
Tables.....	xi
About this document.....	xvii
Who should use this document.....	xvii
How to use this document.....	xvii
Where to find more information.....	xvii
Additional information.....	xvii
How to provide feedback to IBM.....	xix
Summary of changes.....	xxi
Summary of changes for z/OS 3.1.....	xxi
Chapter 1. Introduction.....	1
Syntax Rules.....	1
Specifications.....	1
Parameter Ranges.....	1
Subscript ranges.....	2
Using wildcards.....	3
Comments.....	4
Format.....	4
Range Summary.....	4
How to read syntax diagrams.....	10
Symbols.....	10
Syntax items.....	11
Syntax examples.....	11
Sharing JES2 Initialization Statements.....	12
Displaying Static System Symbols.....	12
Rules and Recommendations for Using System Symbols.....	13
Special Considerations for Using System Symbols with NJE and RJE.....	13
Initialization Data Set Input Sources.....	13
Chapter 2. JES2 initialization statement and parameter summary tables.....	15
Chapter 3. JES2 initialization statement descriptions.....	91
APPL(jxxxxxx) - Application Characteristics Specification.....	91
Adding JES2 as a VTAM Application.....	91
Format Description for APPL(jxxxxxx).....	91
Parameter Description for APPL(jxxxxxx).....	93
BADTRACK - Defective Track Specification.....	94
Format Description for BADTRACK.....	95
Parameter Description for BADTRACK.....	95
BUFDEF - Local JES2 Buffer Definition.....	95
Format Description for BUFDEF.....	95
Parameter Description for BUFDEF.....	96
CKPTDEF - JES2 Checkpoint Definition.....	97
Defining Checkpoint Data Sets.....	97

Format Description for CKPTDEF.....	99
Parameter description for CKPTDEF.....	100
CKPTSPACE - Checkpoint space definition.....	108
Format description for CKPTSPACE.....	108
Parameter description for CKPTSPACE.....	109
COMPACT - Compaction Table Definition.....	109
Format Description for COMPACT.....	109
Parameter Description for COMPACT.....	110
CONDEF - JES2 Console Communication Definition.....	112
Format Description for CONDEF.....	112
Parameter Description for CONDEF.....	112
CONNect - Static NJE Connections.....	115
Adding Static Connections.....	115
Format Description for CONNect.....	115
Parameter Description CONNect.....	116
D INITINFO - Display initialization information.....	118
Format description for D INITINFO.....	118
Parameter description for D INITINFO.....	118
Example of D INITINFO.....	118
D LOADMOD(jxxxxxxx) - Display Load Module Definitions.....	118
Format Description for D LOADMOD(jxxxxxxx).....	119
Parameter Description for D LOADMOD(jxxxxxxx).....	120
D MODUle(jxxxxxxx) - Display Module Information.....	121
Format Description for D MODUle(jxxxxxxx).....	122
Parameter Descriptions for D MODUle(jxxxxxxx).....	124
Usage Note for D MODUle(jxxxxxxx).....	127
Examples of D MODUle(jxxxxxxx).....	127
D OPTsdef - Display JES2 start options.....	129
D SUBNET(jxxxxxxx) - Display Subnet Connections.....	130
Format Description for D SUBNET(jxxxxxxx).....	130
Parameter Description for D SUBNET(jxxxxxxx).....	130
DEBUG - JES2 Debug Option.....	131
Format Description for DEBUG.....	131
Parameter description DEBUG.....	131
DESTDEF - Defining How Destinations Are Processed.....	133
Format Description for DESTDEF.....	134
Parameter Description for DESTDEF.....	134
DEStid(xxxxxxxx) - Route Code Name.....	136
Adding Destination Identifiers.....	136
Specifying the DEStid Subscript.....	136
Format Description for DEStid(xxxxxxxx).....	137
Parameter Description for DEStid(xxxxxxxx).....	138
EDS - Specify EDS parameters.....	141
Format Description for EDS.....	141
Parameter Description for EDS.....	141
ESTBYTE - Estimated Spool Utilization for Output Exceeded.....	141
Format Description for ESTBYTE.....	141
Parameter Description for ESTBYTE.....	142
ESTIME - Default Estimated Execution Time and Options.....	142
Format Description for ESTIME.....	142
Parameter Description for ESTIME.....	143
ESTLNCT - Default Estimated Print Output and Options.....	143
Format Description for ESTLNCT.....	143
Parameter Description for ESTLNCT.....	144
ESTPAGE - Default Estimated Page Output Exceeded.....	144
Format Description for ESTPAGE.....	145
Parameter Description for ESTPAGE.....	145
ESTPUN - Default Estimated Punch Output and Options.....	145

Format Description for ESTPUN.....	146
Parameter Description for ESTPUN.....	146
EXIT(nnn) - Exit and Exit Routine Association.....	146
Format Description for EXIT(nnn).....	147
Parameter Description for EXIT(nnn).....	148
FSS(accccccc) - Functional Subsystem Definition.....	149
Adding FSS Definitions.....	149
Format Description for FSS(accccccc).....	149
Parameter Description for FSS(accccccc).....	150
GRPDEF - Group Definition.....	151
Format description for GRPDEF.....	151
Parameter description for GRPDEF.....	151
INCLUDE - Include an Initialization Data Set.....	151
Format Description for INCLUDE.....	152
Parameter Description for INCLUDE.....	152
Init(nnnn) - Initiator.....	153
Format Description for Init(nnnn).....	153
Parameter Description for Init(nnnn).....	154
INITDEF - Initiator Definition.....	155
Format Description for INITDEF.....	155
Parameter Description for INITDEF.....	155
INPUTDEF - Input Definition.....	156
Format Description for INPUTDEF.....	156
Parameter Description for INPUTDEF.....	156
INTRDR - Internal Reader.....	157
Format Description for INTRDR.....	157
Parameter Description for INTRDR.....	158
JECLDEF,JES2= - JECL Definition JES2.....	159
Format Description for JECLDEF JES2=.....	159
Parameter Description for JECLDEF,JES2=.....	159
JECLDEF, JES3= - JECL Definition, JES3.....	160
Format Description for JECLDEF,JES3=.....	160
Parameter Description for JECLDEF,JES3=.....	160
JOBCLASS - Job, Started Task, and Time Sharing User Class.....	161
Format description for JOBCLASS(class... STC TSU).....	162
Parameter description for JOBCLASS(class... STC TSU).....	169
Examples.....	179
JOBDEF - Job Definition.....	179
Format description for JOBDEF.....	180
Parameter description for JOBDEF.....	181
JOBPRTY(n) - Job Priority.....	184
Format Description for JOBPRTY(n).....	184
Parameter Description for JOBPRTY(n).....	185
L(nnnnn).JT(n) - Job Transmitter.....	186
Format Description for L(nnnnn).JT(n).....	186
Parameter Description for L(nnnnn).JT(n).....	186
L(nnnnn).ST(n) - SYSOUT Job Transmitter.....	187
Format Description for L(nnnnn).ST(n).....	188
Parameter Description for L(nnnnn).ST(n).....	189
LINE(nnnnn) - NJE/RJE BSC Lines.....	190
Format Description for LINE(nnnnn) - BSC.....	191
Parameter Description for LINE(nnnnn) - BSC.....	194
LINE(nnnnn) - NJE/RJE SNA Lines.....	198
Format Description for LINE(nnnnn) - SNA.....	199
Parameter Description for LINE(nnnnn) - SNA.....	202
LINE(nnnnn) - NJE TCP/IP lines.....	205
Format Description for LINE(nnnnn) - TCP/IP.....	206
Parameter Description for LINE(nnnnn) - TCP/IP.....	207

LOADmod(jxxxxxxx) - Load Installation Exit Routine Modules.....	209
Format Description for LOADmod(jxxxxxxx).....	209
Parameter Description for LOADmod(jxxxxxxx).....	209
LOGON(nnn) - Identification of JES2 to VTAM.....	210
Format Description for LOGON(nnn).....	210
Parameter Description for LOGON(nnn).....	211
MASDEF - Multi-Access Spool Definition.....	212
Format Description for MASDEF.....	213
Parameter description for MASDEF.....	213
MEMBer(nn) - Define Members of a Multi-Access Spool Configuration.....	217
Format Description for MEMBer.....	217
Parameter Description for MEMBer.....	218
NAME - Naming the Module to Change Through the JES2 Patching Facility.....	219
Format Description for NAME.....	219
Parameter Description for NAME.....	220
NETACCT - Define Network/JES2 Account Number Correspondence.....	220
Format Description for NETACCT.....	221
Parameter Description for NETACCT.....	221
NETSERV(nnn) - Define NJE over TCP/IP server address space.....	223
Format Description for NETSERV(nnn).....	223
Parameter Description for NETSERV(1-nnn).....	224
NJEDEF - Network Job Entry Definition.....	225
Format Description for NJEDEF.....	226
Parameter Description for NJEDEF.....	227
NODE(xxxxxxxx) - Define a Network Node to JES2.....	230
Format Description for NODE(xxxxxxxx).....	231
Parameter Description for NODE(xxxxxxxx).....	236
OFF(n).JR - Offload Job Receiver.....	242
Format Description for OFF(n).JR.....	243
Parameter Description for OFF(n).JR.....	245
OFF(n).JT - Offload Job Transmitter.....	248
Format Description for OFF(n).JT.....	249
Parameter Description for OFF(n).JT.....	251
OFF(n).SR - Offload SYSOUT Receiver.....	255
Format Description for OFF(n).SR.....	255
Parameter Description for OFF(n).SR.....	261
Examples for OFF(n).SR.....	267
OFF(n).ST - Offload SYSOUT Transmitter.....	267
Format Description for OFF(n).ST.....	268
Parameter Description for OFF(n).ST.....	271
Examples for OFF(n).ST.....	278
OFFLOAD(n) - Offload Device.....	278
Format Description for OFFLOAD(n).....	278
Parameter Description for OFFLOAD(n).....	280
OPTsdef - Start Options Processing Definitions.....	283
OUTCLASS(v) - SYSOUT Class Characteristics.....	285
Format Description for OUTCLASS(v).....	285
Parameter Description for OUTCLASS(v).....	287
OUTDEF - Job Output Definition.....	288
Format Description for OUTDEF.....	289
Parameter Description for OUTDEF.....	289
OUTPRTY(n) - Job Output Priority.....	292
Format Description for OUTPRTY(n).....	292
Parameter Description for OUTPRTY(n).....	293
PCEDEF - Processor Control Element Definition.....	295
Format Description for PCEDEF.....	295
Parameter Description for PCEDEF.....	295
POLICYLIB(xxxxxxxx) - Define a concatenation for JES2 policy import.....	296

Format Description for POLICYLIB(xxxxxxxx)	296
Parameter Description for POLICYLIB(xxxxxxxx)	297
PRINTDEF - Local Print Environment Definition	298
Format Description for PRINTDEF	298
Parameter Description for PRINTDEF	298
PROCLIB(xxxxxxxx) - Dynamic PROCLIB definition	302
Format Description for PROCLIB	303
Parameter description for PROCLIB	304
PRT(nnnnn) - Local Printer	306
Adding Printer Attributes	306
Format Description for PRT(nnnnn)	306
Parameter Description for PRT(nnnnn) (All Printers)	313
Parameter Description for FSS Printers Only:	323
Parameter Description for Non-Impact Printers (JES & FSS mode)	325
PUN(nn) - Local Card Punch	326
Format Description for PUN(nn)	326
Parameter Description for PUN(nn)	330
PUNCHDEF - Local Card Punch Environment Definition	336
Format Description for PUNCHDEF	336
Parameter Description for PUNCHDEF	336
R(nnnn).PR(m) - Remote Printer	336
Format Description for R(nnnn).PR(m)	337
Parameter Description for R(nnnn).PR(m)	343
R(nnnnn).PU(m) - Remote Card Punch	353
Format Description for R(nnnnn).PU(m)	353
Parameter Description for R(nnnnn).PU(m)	357
R(nnnnnn).RD(m) - Remote Card Reader	364
Format Description for R(nnnnnn).RD(m)	365
Parameter Description for R(nnnnnn).RD(m)	366
RDR(nn) - Local Card Reader	367
Format Description for RDR(nn)	368
Parameter Description for RDR(nn)	371
RECVOPTS - Recovery Intervention Rate	373
Format Description for RECVOPTS	373
Parameter Description for RECVOPTS	373
REDirect(vvvvvvvv) - Direct Output of Display Commands	376
Adding Applications	377
Format Description for REDirect(vvvvvvvv)	377
Parameter Description for REDirect(vvvvvvvv)	377
REP - Replacing Code Through the JES2 Patching Facility	379
Format Description for REP	379
Parameter Description for REP	380
REQJOBID - Specify JESLOG Characteristics	387
Format Description for REQJOBID	387
Parameter Description for REQJOBID	387
RESGROUP - Resource Group	388
RMT(nnnnn) - BSC RJE Workstation	389
Format Description for RMT(nnnnn) (BSC)	389
Parameter Description for RMT(nnnnn) (BSC)	393
RMT(nnnnn) - SNA RJE Workstation	398
Format Description for RMT(nnnnn) (SNA)	398
Parameter Description for RMT(nnnnn) (SNA)	402
SMFDEF - JES2 SMF Buffer Definition	405
Format Description for SMFDEF	405
Parameter Description for SMFDEF	405
SOCKET(xxxxxxxx) - Define NJE/TCP IP address and port	406
Format Description for SOCKET(xxxxxxxx)	406
Parameter Description for SOCKET(xxxxxxxx)	408

SPOOL - Bind spool volumes.....	409
Format Description for SPOOL.....	410
Parameter description for SPOOL.....	410
SPOOLDEF - Spool Volume Definition.....	410
SSI(nnn) - Subsystem Interface Definition.....	416
Format Description for SSI(nnn).....	417
Parameter Description for SSI(nnn).....	417
SUBMITLIB(xxxxxxx) - JCL library definition.....	417
Format description for SUBMITLIB(xxxxxxx).....	418
Parameter description for SUBMITLIB(xxxxxxx).....	419
SUBMITRDR - Submit reader.....	420
Format Description for SUBMITRDR.....	420
Parameter description for SUBMITRDR.....	422
SUBTDEF - Define General Purpose Subtasks.....	423
Format Description for SUBTDEF.....	423
Parameter Description for SUBTDEF.....	423
TPDEF - Teleprocessing Definitions.....	423
Format Description for TPDEF.....	424
Parameter Description for TPDEF.....	424
TRACE(n) - Initial tracing value setting.....	428
Format Description for TRACE(n).....	428
Parameter Description for TRACE(n).....	429
TRACEDEF - Trace Facility Definition.....	430
Format Description for TRACEDEF.....	430
Parameter Description for TRACEDEF.....	430
VERIFY - Verifying Code Through the JES2 Patching Facility.....	432
Format Description for VERIFY.....	433
Parameter description for VERIFY.....	433
ZAPJOB.....	439
Format Description for ZAPJOB.....	440
Parameter Description for ZAPJOB.....	440
Appendix A. Sample JES2 initialization data set.....	441
Appendix B. Obsolete keywords.....	469
Appendix C. Accessibility.....	471
Notices.....	473
Terms and conditions for product documentation.....	474
IBM Online Privacy Statement.....	475
Policy for unsupported hardware.....	475
Minimum supported hardware.....	475
Programming Interface Information.....	476
Trademarks.....	476
Index.....	477

Figures

1. Examples of Valid Console IDs..... 378

2. Examples of JES2 Patching Format..... 386

3. Examples of JES2 AMASPZAP Format..... 387

4. Examples of JES2 Patching Format..... 438

5. Examples of JES2 AMASPZAP Format..... 439

Tables

1. Initialization Parameter Character Specifications and Their Meanings.....	1
2. Coding asterisks on initialization statements.....	2
3. JES2 initialization statements with "dual" processing.....	3
4. Numeric Only (used for most devices, such as PRT, PUN, LINE, RMT).....	5
5. Symbolic Only	6
6. Numeric and Symbolic.....	7
7. JES2 processing of initiators.....	8
8. Syntax examples.....	11
9. Initialization Statement - APPL(jxxxxxxx).....	15
10. Initialization Statement - BADTRACK.....	16
11. Initialization Statement - BUFDEF.....	16
12. Initialization Statement - CKPTDEF.....	17
13. Initialization Statement - CKPTSPACE.....	18
14. Initialization Statement - COMPACT.....	18
15. Initialization Statement - CONDEF.....	19
16. Initialization Statement - CONNECT.....	20
17. Initialization Statement - DEBUG.....	20
18. Initialization Statement - DESTDEF.....	21
19. Initialization Statement - DESTID(xxxxxxxx).....	22
20. Initialization Statement - ESTBYTE.....	23
21. Initialization Statement - ESTIME.....	23
22. Initialization Statement - ESTLNCT.....	23
23. Initialization Statement - ESTPAGE.....	24

24. Initialization Statement - ESTPUN.....	24
25. Initialization Statement - EXIT(nnn).....	25
26. Initialization Statement - FSS(accccccc).....	25
27. Initialization Statement - GRPDEF.....	26
28. Initialization Statement - INCLUDE.....	26
29. Initialization Statement - INIT(nnnn).....	27
30. Initialization Statement - INITDEF.....	28
31. Initialization Statement - INPUTDEF.....	28
32. Initialization Statement - INTRDR.....	28
33. Initialization Statement - JECLDEF, JES2=.....	29
34. Initialization Statement - JECLDEF, JES3=.....	30
35. Initialization Statement - JOBCLASS(v STC TSU).....	32
36. Initialization Statement - JOBDEF.....	35
37. Initialization Statement - JOBPRTY.....	37
38. Initialization Statement - L(nnnn).ST(n).....	37
39. Initialization Statement - L(nnnn).JT(n).....	38
40. Initialization Statement - LINE(nnnnn) - BSC.....	39
41. Initialization Statement - LINE(nnnnn) - SNA.....	41
42. Initialization Statement - LINE(nnnnn) - TCP/IP.....	42
43. Initialization Statement - LOADmod(jxxxxxxx).....	43
44. Initialization Statement - LOGON(nnn).....	44
45. Initialization Statement - MASDEF.....	44
46. Initialization Statement - MEMBER(xxxx).....	45
47. Initialization Statement - NAME.....	46
48. Initialization Statement - NETACCT.....	46

49. Initialization Statement - NETSERV (nnn).....	46
50. Initialization Statement - NJEDEF.....	47
51. Initialization Statement - NODE(xxxxxxxx).....	48
52. Initialization Statement - OFF(n).JR.....	50
53. Initialization Statement - OFF(n).JT.....	52
54. Initialization Statement - OFF(n).SR.....	53
55. Initialization Statement - OFF(n).ST.....	54
56. Initialization Statement - OFFLOAD(n).....	56
57. Initialization Statement - OPTsdef.....	57
58. Initialization Statement - OUTCLASS(v).....	58
59. Initialization Statement - OUTDEF.....	58
60. Initialization Statement - OUTPRTY(n).....	60
61. Initialization Statement - PCEDEF.....	60
62. Initialization Statement - PRINTDEF.....	61
63. Initialization Statement - PROClib.....	62
64. Initialization Statement - PRT(nnnn).....	63
65. Initialization Statement - PRT(nnnn) (FSS-only parameters).....	66
66. Initialization Statement - PUN(nn).....	67
67. Initialization Statement - PUNCHDEF.....	68
68. Initialization Statement - R(nnnn).PR(m).....	69
69. Initialization Statement - R(nnnn).PU(m).....	72
70. Initialization Statement - R(nnnn).RD(m).....	75
71. Initialization Statement - RDRnn.....	77
72. Initialization Statement - RECVopts(type).....	77
73. Initialization Statement - REDIRect.....	78

74. Initialization Statement - REP.....	78
75. Initialization Statement - REQJOBID.....	79
76. Initialization Statement - RMT(nnnnn) - BSC.....	79
77. Initialization Statement - RMT(nnnnn) - SNA.....	81
78. Initialization Statement - SMFDEF.....	83
79. Initialization Statement - SOCKET(xxxxxxxx).....	83
80. Initialization Statement - SPOOL.....	84
81. Initialization Statement - SPOOLDEF.....	84
82. Initialization Statement - SSI(nnn).....	85
83. Initialization Statement - SUBMITLIB.....	86
84. Initialization Statement - SUBMITRDR.....	87
85. Initialization Statement - SUBTDEF.....	87
86. Initialization Statement - TPDEF.....	87
87. Initialization Statement - TRACE(nnn).....	88
88. Initialization Statement - TRACEDEF.....	89
89. Initialization Statement - VER.....	89
90. Initialization Statement - ZAPJOB.....	90
91. Example for ROUTINES parameter on EXIT(nnn) statement.....	148
92. JOBCLASS attribute for DSENQSHR.....	171
93. Interaction of PRINTDEF and PRT(n) parameters that JES2 uses to calculate the output checkpoint interval.....	299
94. PROCLIB commands and results.....	302
95. Patch Name to CSECT Reference.....	380
96. Other Area that can be Patched.....	384
97. JES2 BUFSIZE Defaults for RJE Workstations.....	394
98. The number of track groups per volume listed by device type (and TGSIZE=30).....	415

99. Patch Name to CSECT Reference.....	433
100. Obsolete keywords for JES2 initialization statements or commands.....	469
101. Obsolete keywords for JES2 commands.....	470

About this document

This document describes JES2 initialization statements and their parameters and provides summary charts that highlight details of the statements. This document is specifically designed for installations running z/OS (5650-ZOS).

The associated *z/OS JES2 Initialization and Tuning Guide* describes the general functions of JES2 and provides information describing JES2 initialization, JES2 processing, network job entry (NJE), remote job entry (RJE) for JES2, and factors affecting performance.

Who should use this document

This document is intended for JES2 system programmers or for anyone responsible for initializing or tuning JES2.

How to use this document

Use this document in conjunction with *z/OS JES2 Initialization and Tuning Guide*, which provides guidance information for the initialization and tuning of your JES2 system. This document documents all JES2 initialization statements, in alphabetic order. This document also includes a summary table of the JES2 initialization statements and their primary parameters.

Most referenced publications are abbreviated throughout the text; their full titles appear in “Where to find more information” on page xvii. Additionally, be aware of how this document uses references to 3800 printers:

3800 Printer

Unless specifically noted, all references to 3800 printers refer to the 3800-1, 3800-3, 3800-6 (that is, the 3800 models 1, 3, and 6).

Where to find more information

This document references the following publications for further details about specific topics. Abbreviated forms of these titles are used throughout this document. The following table lists all full titles that are not listed in *z/OS Information Roadmap*. See that document for all z/OS publications.

Title
<i>MVS Remote Workstation Generation</i>
<i>PSF for z/OS: Customization</i>
<i>Advanced Function Presentation: Printer Information</i>

Additional information

Additional information about z/OS elements can be found in the following documents.

Title	Order Number	Description
<i>z/OS Introduction and Release Guide</i>	GA32-0887	Describes the contents and benefits of z/OS as well as the planned packaging and delivery of this new product.

Title	Order Number	Description
<i>z/OS Planning for Installation</i>	GA32-0890	Contains information that lets users: • Understand the content of z/OS • Plan to get z/OS up and running • Install the code • Take the appropriate migration actions • Test the z/OS system
<i>z/OS Information Roadmap</i>	SA23-2299	Describes the information associated with z/OS including z/OS documents and documents for the participating elements.
<i>z/OS Release Upgrade Reference Summary</i>	SA23-2300	Describes the changes to messages for individual elements of z/OS. Note: This document is provided in softcopy only on the message bookshelf of the z/OS collection kit.

How to provide feedback to IBM

We welcome any feedback that you have, including comments on the clarity, accuracy, or completeness of the information. For more information, see [How to send feedback to IBM](#).

Summary of changes

This information includes terminology, maintenance, and editorial changes. Technical changes or additions to the text and illustrations for the current edition are indicated by a vertical line to the left of the change.

Note: IBM z/OS policy for the integration of service information into the z/OS product documentation library is documented on the z/OS Internet Library under [IBM z/OS Product Documentation Update Policy](http://www.ibm.com/docs/en/zos/latest?topic=zos-product-documentation-update-policy) (www.ibm.com/docs/en/zos/latest?topic=zos-product-documentation-update-policy).

Summary of changes for z/OS 3.1

The following content is new, changed, or no longer included in z/OS 3.1.

New

The following content is new.

April 2024 refresh

- [“POLICYLIB\(xxxxxxxx\) - Define a concatenation for JES2 policy import”](#) on page 296 is added.

September 2023 release

- Initialization statement RESGROUP - Resource Group is added. For more information, see [“RESGROUP - Resource Group”](#) on page 388.
- RESOURCE and JESCANCEL parameters are added. For more information, see [“Format description for JOBCLASS\(class...|STC|TSU\)”](#) on page 162 and [“Parameter description for JOBCLASS\(class...|STC|TSU\)”](#) on page 169.

Changed

The following content is changed.

October 2024 refresh

- [SPOOLDEF Parameters](#) is updated.

April 2024 refresh

- [“Parameter Description for INPUTDEF”](#) on page 156 is updated.
- Clarification is added for the OUTDEF statement. See [“Format Description for OUTDEF”](#) on page 289.
- [“Parameter Description for TPDEF”](#) on page 424 is updated.

September 2023 release

- Added JESCANCEL=RESTRICTED example. For more information, see [“Examples”](#) on page 179.
- Added JESCANCEL parameter to the JOBCLASS Initialization Statement. For more information, see [Table 35](#) on page 32.
- Modules were added to the 'Patch Name to CSECT Reference' table. For more information, see [“Parameter Description for REP”](#) on page 380.
- Added RGDNUM keyword to CKPTSPACE. For more information, see [“Format description for CKPTSPACE”](#) on page 108.
- Added RGDNUM keyword to CKPTSPACE. For more information, see [“Parameter description for CKPTSPACE”](#) on page 109.

Chapter 1. Introduction

This is a general introduction to using the JES2 initialization statements. It includes a discussion of syntax rules and a table summarizing the primary parameters on each initialization statement.

Syntax Rules

The following general syntax rules apply to the coding of most initialization statements and commands (exceptions to these rules are explained within each individual statement or command description). Coded examples of initialization statements and commands are used to illustrate the general syntax rules.

Specifications

Specifying JES2 initialization statements and commands involves using numeric values, alphabetic values, upper or lower case characters and blanks.

- You must code as written upper-case operands as they appear in the syntax diagrams. Also, punctuation such as commas, parentheses, and single quotation marks are not metasymbols; if present in the syntax diagrams they **must** be coded. Parameters shown in lower case are **not** to be coded as written; they denote variables that are explained in the description of the particular parameter for the initialization statement or command.
- You must code numbers and upper-case letters exactly as shown.
- You must substitute specific information or specific values for lower-case letters, which represent variables.
- Blanks are used to separate the statement object from the operands. Blanks are not allowed within the statement object.
- [Table 1 on page 1](#) defines the character specifications as they appear in the syntax diagrams.

Table 1. Initialization Parameter Character Specifications and Their Meanings

Character	Meaning
a	Alphabetic (A-Z)
c	All EBCDIC characters (except , () - =)
n	Numeric (0-9)
m	Numeric (0-9)
h	Hexadecimal (0-9 and A-F)
j	Alphabetic (A-Z) and the special characters (\$, #, @)
v	Alphabetic (A-Z) and numeric (0-9)
x	Alphabetic (A-Z), numeric (0-9), and the special characters (\$, #, @)

Parameter Ranges

Some commands have parameters that allow you to specify a range of values. The following explains the ranges for parameters with subscripts (**nnnn**), (**nnn**), or (**n**):

- (**nnnn**) - denotes that you may specify a range for the subscript as follows:

nnnn

A specific numeric value.

nnnn-nnnn

A specific numeric range (for example, 2-5 or 5-2 where 5-2 is interpreted as having all the values from 2 to 5)

nnnn-*

A generic numeric range (for example, 3-* denotes a range from 3 to the highest value allowed).

***-nnnn**

A generic numeric range (for example, *-3 denotes a range from the highest value allowed to 3).

A generic value that denotes all values in a defined range.

- **(nnn)** - denotes that you may specify a range for the subscript in the same way as (nnnn), where (nnn) is 1-255.
- **(n)** - denotes that you may specify a value (0-9) or a generic range (*).

Note:

1. For display commands, you can omit the subscript. If omitted, this denotes a generic value to include all values in a defined range. For example, the command \$D MEMBER is equivalent to \$D MEMBER(*).
2. Using the ALL parameter on any type of display command that may involve up to 30,000 jobs is not recommended.

Subscript ranges

Ranges appear in JES2 initialization statements and commands as subscripts of the name associated with the initialization statement.

```
REDIRect(vvvvvvvv)
$ADD REDIRect(vvvvvvvv)
```

Note: The name of the initialization statement and the target of the command are the same.

All KEYWORD= ranges must be coded explicitly; whereas subscript ranges can either be coded explicitly or as a generic range using the asterisk (*). The use of parenthesis with a generic range is optional for all numeric ranges, but is required for symbolic (character) ranges. Throughout this book the parentheses are included for consistency and clarity of presentation. It is recommended that you use parentheses when you specify a range.

- Example: Initialization statement (generic subscript)

```
NODE(5-*) PATHMGR=NO
```

- Example: Commands (generic subscript)

```
$d jobclass(d-*),qhld=yes,qhld
$Doff(*-5).JT,CLASS=a,b,c,z
$D OFF(1-10).ST
```

How JES2 interprets the use of the asterisk in specifying the subscript depends on how it is used in the command or statement. [Table 2 on page 2](#) shows how the asterisk is coded to indicate various ranges.

Table 2. Coding asterisks on initialization statements

RANGE	INTERPRETATION and RESULT
*	All values in the range (for nodes and jobclasses) Statement: NODE(*) COMPACT=1,.->All nodes Command: \$d jobclass(*),. -->All jobclasses

Table 2. Coding asterisks on initialization statements (continued)

RANGE	INTERPRETATION and RESULT
n-*	Range from n to highest value Statement: NODE(5-*) compact=2 -->5 to highest value Command: \$Dnode(3-*)NAME=XRAY -->3 to highest value
-m	Range from highest descending to m Statement: PRT(-1) ws=(W,Q,R/) -->highest to 1 Command: \$d jobclass(*-C),qhheld=yes -->highest to C
c*	All values starting with char "c" Statement: APPL(OUT*).JT All APPLs starting with OUT Command: \$d jobclass(A*),... -->All jobclasses starting with A

Note: When specified in a numeric range, the asterisk **always** indicates the highest defined value in either the ascending (n-*) or descending (*-m) order.

Statement Range Considerations

Care should be taken when using the asterisk on initialization statements and commands. Processing times can increase. For example, the statement `NODE(*)` increases processing time drastically, although no additional nodes are actually created, and no changes are made to nodes outside the defined range. Likewise, the command, `$T NODE(*)`, increases processing time.

However, initialization statement processing is different. As an example, for the PRT(nnnn) initialization statement:

1. PRT(*) resets values previously established.
2. PRT(1-*) defines values not yet established.

The following table lists JES2 initialization statements that have this "dual" form of processing.

JES2 initialization statements with "dual" processing				
EXIT(nnnn)	L(nnn).JT(n)	OFF(n).JT	PRT(nnnn)	R(nnn).RD(n)
JOBCLASS(nnnn)	L(nnn).ST(n)	OFF(n).ST	PUN(nnnn)	REDIRect(nnn)
JOBPRTY(nnnn)	LOGON(nnn)	OFF(n).SR	RDR(nnn)	SSI(nnn)
UTCLASS(nnnn)	MEMBER(nnnn)	OFF(n).JR	R(nnn).PR(n)	RMT(nnn)
OUTPRTY(nnnn)	NODE(nnn)	OFFLOAD(nnn)	R(nnn).PU(n)	TRACE(nnn)
PROCLIB(nnn)				

Using wildcards

Several initialization statements and commands can use wildcards (a form of generic specification) to specify a subset that matches a combination of characters (mask). JES2 use two kinds of wildcards:

- Multiple-character wildcard, which is specified by an asterisk (*). The asterisk means zero or more characters of any kind can be used here. For example, AB* matches ABC, ABCDEFG, or ABCXXE.

An example of using a multiple-character wildcard follows:

Statement: APPL(OUT33*) compact=1...

```
Command:    $d node(out*),qhld=yes,qhld
```

- Single-character wildcard, which is specified by a question mark (?). The question mark means any single character can be used here. For example, ABC?E?? matches ABCDEFG or ABC1E23 but not ABCXXE.

An example of using a single-character wildcard follows:

```
Statement:  APPL(OUT?3?) compact=22,....
```

```
Command:    $d node(out?A),qhld=yes,qhld
```

Each individual description of a JES2 initialization statement or JES2 command gives explicit details on how to use wildcards, if supported.

Comments

Comments can be either added at the end of a statement or included within the statement. Use a slash-asterisk (/*) as the delimiter and an asterisk-slash (*/) as the ending delimiter.

- All the statements following a slash-asterisk (/*) are treated as comments until an asterisk-slash (*/) is found. If the ending delimiter cannot be found, and an end-of-file is detected, JES2 issues the \$HASP003 INVALID SYNTAX error message.
- The work selection parameter specifications (WS=) cannot have embedded comments.

Format

JES2 initialization parameter statements consist of variable-length statements that conform to one of the following syntax rules, unless otherwise noted. Statements may be coded free-form in columns 1 through 71. Column 72 may be used as a continuation character, but is not required. A trailing comma indicates a continuation. The input is **free-format**, such that blanks between words and syntax symbols are insignificant as illustrated in the following example:

```
PARAMETER [/* COMMENT */]  
PARAMETER=value      [/* COMMENT */]  
PARAMETER=value1-value2 [/* COMMENT */]  
PARAMETER=(value1,value2,...valuen) [/* COMMENT */]  
PARAMETER=(Pa,Pb,Pc,...Pn) [/* COMMENT */]  
PARAMETER= Pa,Pb,Pc,...Pn [/* COMMENT */]  
INITPARM      , [/* COMMENT */]
```

Where:

Pa-Pn

= the syntax structure of one of the forms (1-4) notes immediately above.

Note: Each initialization statement is placed in an 8K statement buffer for processing. The initialization statement, its comments, and its required control information must all fit into the 8K buffer. The supported length of a specific initialization statement depends on the amount of control information that must be added as each record of the statement is read from the initialization data set and placed into the buffer. If the supported initialization statement length is exceeded, an error message, \$HASP4402, following initialization statement (including comments), exceeds the size of the statement buffer, is issued.

Range Summary

The following tables summarize and illustrate how you should code JES2 initialization statements and commands using subscripts. [Table 4 on page 5](#), [Table 5 on page 6](#), and [Table 6 on page 7](#) focus your attention to the NAME of the initialization statement or the object of the command. You can use these tables as a reference to guide your coding. Section [“Examples of numeric and symbolic subscripts” on page 8](#) makes you aware of how JES2 processes numbers and names.

JES2 initialization statement and command subscript coding

Table 4. Numeric Only (used for most devices, such as PRT, PUN, LINE, RMT)	
Specification	Explanation and Examples
NAMEnn	number nn RMT44 BUFSIZE=3500,COMPRESS=YES \$T R5.PU1,JOBNAME=todeko,RANGE=(1,6),...
NAME(nn)	number nn RMT(3) BUFSIZE=4096,COMPRESS=NO \$D R(3).PU(22),COMP,FLUSH,LRECL
NAMEnn-mm	Ascending or descending range nn to mm LINE5-2 COMPRESS=NO,JRNUM=2,JTNUM=2,... \$T RMT5-1,MFORM=T,SHAR=Y,TRANSPAR=N
NAME(nn-mm)	Ascending or descending range nn to mm PRT(25-22) CREATOR=fredonia,DEVFCB=TABX \$D PUN(11-10),CR,F,JOB
NAMEnn-*	Ascending range from nn to maximum possible value LINE5-* COMPRESS=NO,JRNUM=2,JTNUM=2,... \$T RMT5-*,MFORM=T,SHAR=Y,TRANSPAR=N
NAME(nn-*)	Ascending range from nn to maximum possible value RDR3-* XEQDEST=seattle \$T rdr(11-*),tr=yes,Q
NAME*-nn	Descending range from maximum possible value to nn LINE*-5 LOG=YES,TR=YES,SRNUM=224 \$S line *-1
NAME(*-nn)	Descending range from maximum possible value to nn LINE(*-12) LOG=YES,TR=YES \$T line (*-10),DISCON=QUIESCE
NAME(*)	All values, but holes not filled in by create requests RMT(*) BUFSIZE=512,COMPRESS=YES \$T RMT(*),BUFSIZE=1024,COMPRESS=NO
NAME(mm,nn)	Multiple subscripts LINE(2,6) LOG=YES,TR=YES \$tline(1,3),DISCON=QUIESCE

Table 4. Numeric Only (used for most devices, such as PRT, PUN, LINE, RMT) (continued)

Specification	Explanation and Examples
NAME(mm,nn-pp)	Multiple subscripts (one subscript is a range) Note that if the subscripts are processed individually, it is possible for a particular element to be processed multiple times (that is, for NAME(1-3,2), element 2 is processed twice). <pre>rdi(1,10-15,22) AUTH=(JOB=YES) \$D rdi(2,4-8,11),AUTH=JOB</pre>
NAME	When allowed, equivalent to NAME(*). <pre>d PRT \$D L.jir</pre>
Note: Valid Names: PRT, PUN, LINE, RMT.	

Table 5. Symbolic Only . REDIRECT, APPL, JOBCLASS, OUTCLASS, SPOOL

Specification	Explanation and Examples
NAME(xxxx)	Explicit subscript <pre>REDIR(CN320) DA=cn330 \$T REDIR(cn3e0),du=cn320 \$ADD redir(cn3e0)</pre>
NAME'xxxx'	Explicit character string <pre>APPL'jmaxsum' compact=65,node=3 \$dappl'maxsum',compact,line,logmode,...</pre>
NAME('xxxx')	Explicit subscript as a character string <pre>JOBCLASS('A') COMMAND=DISPLAY,HOLD=YES \$d jobclass('c')</pre>
NAME(xxxx-yyyy)	Explicit symbolic range. Wildcard characters may be specified in ranges, but they are not treated as wild cards. <pre>OUTCLASS(a-j) blnktrnc=no,trkcell=no \$Toutclass(2-3),outdisp=(purge,..</pre>
NAME('xxx'-'yyyy')	Explicit symbolic range as characters <pre>REDIR('CN320'-'cn321') DA=cn444 \$T REDIR('cn3e0'-'cn4e0'),du=cn320</pre>
NAME(X*Y?Z)	* and ? are treated as wildcard characters <pre>APPL(jmax*) compact=65,node=3 \$dappl'maxs?m',compact,line,logmode,...</pre>
NAME'X*Y?Z'	* and ? are NOT treated as wildcard characters <pre>OUTCLASS'a*',blnktrnc=no,trkcell=no \$djob'T?cobell'</pre>

Table 5. Symbolic Only . REDIRECT, APPL, JOBCLASS, OUTCLASS, SPOOL (continued)	
Specification	Explanation and Examples
NAME(xxxx,yyyy)	Multiple keywords must be in parenthesis, may include ranges, wild cards, or quoted strings. If the subscripts are processed individually, it is possible for a particular element to be processed multiple times. <pre>JOBCLASS('A','B',C*,D),HOLD=YES \$d jobclass('c'- 'd',e,f,g*)</pre>
NAME	When allowed, this is equivalent to NAME(*). Holes are never filled on create requests. <pre>JOBCLASS \$djob,cards</pre>

Table 6. Numeric and Symbolic. NODE, MEMBER, INIT	
Specification	Explanation and Examples
NAMEnn	Numeric subscript <pre>NODE001 auth=(net=yes),compact=65 \$dnode4</pre>
NAME(nn)	Symbolic name nn (if it exists, else numeric value nn) <pre>MEMBER(3) NAME=100 \$tmember(100),IND=YES</pre>
NAME'nn'	Name nn <pre>INIT'3' name=backup,class=z \$Si'3',status=halted</pre>
NAMEnn-mm	Numeric range. <pre>INIT01-05 class=x,y,z,start=no \$di01-02,class>x,status=halted</pre>
NAME(nn-mm)	Numeric range. The expected performance would be as a symbolic range, and if nothing exists in range, as a numeric range. <pre>NODE(001-022) auth=(net=yes),... \$dnode(4-9)</pre>
NAME('nn-mm')	Symbolic range. <pre>MEMBER('100-115') NAME=wilcox \$dmember('100-112'),IND=YES</pre>
NAME(xxxx-mm)	Symbolic range. See note 3. <pre>NODE(nyork-102) auth=(net=yes),compact=65 \$dnode(atlanta-155)</pre>
NAME(nn-xxxx)	Symbolic range. See note 2. <pre>INIT(01-txs) class=x,y,z,start=no \$di(5-last)_02,class>x,status=halted</pre>

Table 6. Numeric and Symbolic. NODE, MEMBER, INIT (continued)	
Specification	Explanation and Examples
NAME(yyyy-xxxx)	Symbolic range. <pre>NODE(gaith-seattle) auth=(net=yes),... \$dnnode(atlanta-columbus)</pre>
NAME(nn,'xxxx')	Multiple subscripts, may mix any valid flavors (numerics, symbolics, ranges, wild cards). See note 1. <pre>NODE(100,'alpha'-'sigma',102) PATHMGR=no \$d member (3,'beta',1-5),IND=YES</pre>
Note: 1. If the subscripts are processed individually, it is possible for a particular element to be processed multiple times. 2. To avoid confusion, it is recommended that when both numerics and symbolics are allowed, symbolic names (typically specified through a NAME=parameter) either include at least one alphabetic character, or match the numeric value exactly (for example, INIT(1) NAME=1). 3. Any numeric is allowed. Symbolic is only allowed when both numeric and symbolic are allowed. 4. All ranges are considered numeric unless at least one of the range limits is forced to be a symbolic. Holes are filled only on numeric ranges.	

Examples of numeric and symbolic subscripts

The following table illustrates how numeric and symbolic subscripts are processed. The table is based on the following initialization statements for system initiators.

To avoid confusion, it is recommended that when both numeric and symbolic subscripts are allowed, symbolic names (specified using the NAME= parameter) either include at least one alphabetic character or match the numeric value exactly (for example, INIT(1) NAME=1). This example illustrates the confusion that can occur when this is not done.

Based on these initiator definitions, JES2 interprets the initiator number and its name as follows:

Table 7. JES2 processing of initiators	
Example Initiator Statements	
<pre>INIT1 NAME=3 INIT2 NAME=2 INIT3 NAME=1 INIT4 NAME=4A INIT5 NAME=10 INIT6 NAME=6 INIT7 NAME=7 INIT8 NAME=8 INIT9 NAME=9 INIT10 NAME=10 INIT11 NAME=11</pre>	
Command Example	JES2 Processing Interpretation
<pre>\$dinit1 \$HASP892 INIT(1) NAME=3</pre>	Initiator number 1

Table 7. JES2 processing of initiators (continued)

Example Initiator Statements

```
INIT1 NAME=3
INIT2 NAME=2
INIT3 NAME=1
INIT4 NAME=4A
INIT5 NAME=10
INIT6 NAME=6
INIT7 NAME=7
INIT8 NAME=8
INIT9 NAME=9
INIT10 NAME=10
INIT11 NAME=11
```

Command Example

JES2 Processing Interpretation

```
$dinit(1)
$HASP892 INIT(3) NAME=1
```

Initiator with name "1" exists.

```
$dinit(5)
$HASP892 INIT(5) NAME=10
```

Initiator with name "5" does not exist, use init number 5.

```
$dinit'1'
$HASP892 INIT(3) NAME=1
```

Initiator with name "1"

```
$dinit3-4
$HASP892 INIT(3) NAME=1
$HASP892 INIT(4) NAME=4A
```

Initiator in numeric range of 3-4.

```
$dinit(3-4)
$HASP892 INIT(3) NAME=1
$HASP892 INIT(4) NAME=4A
```

Initiator in numeric range of 3-4.

```
$dinit('3'-'4')
$HASP892 INIT(1) NAME=3
```

Initiator with names in EBCDIC range '3' to '4'

```
$dinit(3-4b)
$HASP892 INIT(1) NAME=3
$HASP892 INIT(4) NAME=4A
```

4b is non-numeric, therefore, initiator in EBCDIC range '3'-'4b'

```
$dinit('1'-'2')
$HASP892 INIT(2) NAME=2
$HASP892 INIT(3) NAME=1
$HASP892 INIT(5) NAME=10
$HASP892 INIT(10) NAME=10
$HASP892 INIT(11) NAME=11
```

All initiators between EBCDIC '1' to '2' in HEX that is 'F1404040' to 'F2404040'

```
$dinit('1'-'10')
$HASP892 INIT(3) NAME=1
$HASP892 INIT(5) NAME=10
$HASP892 INIT(10) NAME=10
```

All initiators between EBCDIC '1' to '10' in HEX that is 'F1404040' to 'F1F04040'

Table 7. JES2 processing of initiators (continued)

Example Initiator Statements

```
INIT1 NAME=3
INIT2 NAME=2
INIT3 NAME=1
INIT4 NAME=4A
INIT5 NAME=10
INIT6 NAME=6
INIT7 NAME=7
INIT8 NAME=8
INIT9 NAME=9
INIT10 NAME=10
INIT11 NAME=11
```

Command Example

JES2 Processing Interpretation

```
$dinit(4-*)
$HASP892 INIT(4) NAME=4A
$HASP892 INIT(5) NAME=10
$HASP892 INIT(6) NAME=6
$HASP892 INIT(7) NAME=7
$HASP892 INIT(8) NAME=8
$HASP892 INIT(9) NAME=9
$HASP892 INIT(10) NAME=10
$HASP892 INIT(11) NAME=11
```

Numeric range (4 is numeric and * represents the maximum numeric value)

```
$dinit(4a-*)
$HASP892 INIT(4) NAME=4A
$HASP892 INIT(6) NAME=6
$HASP892 INIT(7) NAME=7
$HASP892 INIT(8) NAME=8
$HASP892 INIT(9) NAME=9
```

Ascending EBCDIC range '4A' to '*', in HEX that is 'F4C14040' to 'FFFFFFFF'

Note: There are exceptions to the processing results above. When using JES2 Commands for JOB, STC, TSU, JOBQ, a numeric subscript (JOB(nn)) is always treated as numeric unless enclosed in quotation marks. Also, job names consisting of all numerics are not valid but may occur in error scenarios, such as when a job is incorrectly submitted or received from NJE.

How to read syntax diagrams

Syntax diagrams define syntax diagram symbols, items that may be contained within the diagrams (keywords, variables, delimiters, operators, fragment references, operands) and provides syntax examples that contain these items.

Syntax diagrams pictorially display the order and parts (options and arguments) that comprise a command statement. They are read from left to right and from top to bottom, following the main path of the horizontal line.

For users accessing IBM Documentation with a screen reader, syntax diagrams are provided in dotted decimal format.

Symbols

The following symbols may be displayed in syntax diagrams:

Symbol
Definition

► —
Indicates the beginning of the syntax diagram.

—►
Indicates that the syntax diagram is continued to the next line.

- Indicates that the syntax is continued from the previous line.
- Indicates the end of the syntax diagram.

Syntax items

Syntax diagrams contain many different items. Syntax items include:

- **Keywords** - a command name or any other literal information.
- **Variables** - variables are italicized, appear in lowercase, and represent the name of values you can supply.
- **Delimiters** - delimiters indicate the start or end of keywords, variables, or operators. For example, a left parenthesis is a delimiter.
- **Operators** - operators include add (+), subtract (-), multiply (*), divide (/), equal (=), and other mathematical operations that may need to be performed.
- **Fragment references** - a part of a syntax diagram, separated from the diagram to show greater detail.
- **Separators** - a separator separates keywords, variables or operators. For example, a comma (,) is a separator.

Note: If a syntax diagram shows a character that is not alphanumeric (for example, parentheses, periods, commas, equal signs, a blank space), enter the character as part of the syntax.

Keywords, variables, and operators may be displayed as required, optional, or default. Fragments, separators, and delimiters may be displayed as required or optional.

Item type

Definition

Required

Required items are displayed on the main path of the horizontal line.

Optional

Optional items are displayed below the main path of the horizontal line.

Default

Default items are displayed above the main path of the horizontal line.

Syntax examples

The following table provides syntax examples.




Table 8. Syntax examples	
Item	Syntax example
Required item. Required items appear on the main path of the horizontal line. You must specify these items.	
Required choice. A required choice (two or more items) appears in a vertical stack on the main path of the horizontal line. You must choose one of the items in the stack.	
Optional item. Optional items appear below the main path of the horizontal line.	

Table 8. Syntax examples (continued)

Item	Syntax example
Optional choice. An optional choice (two or more items) appears in a vertical stack below the main path of the horizontal line. You may choose one of the items in the stack.	
Default. Default items appear above the main path of the horizontal line. The remaining items (required or optional) appear on (required) or below (optional) the main path of the horizontal line. The following example displays a default with optional items.	
Variable. Variables appear in lowercase italics. They represent names or values.	
Repeatable item. An arrow returning to the left above the main path of the horizontal line indicates an item that can be repeated. A character within the arrow means you must separate repeated items with that character. An arrow returning to the left above a group of repeatable items indicates that one of the items can be selected, or a single item can be repeated.	
Fragment. The fragment symbol indicates that a labeled group is described under the main syntax diagram. Syntax is occasionally broken into fragments if the inclusion of the fragment would overly complicate the main syntax diagram.	

Sharing JES2 Initialization Statements

Two or more instances of JES2 can share initialization statements while retaining unique values in those statements. A single initialization statement can affect multiple instances of JES2, allowing you to view the environment as a *single image* with one point of control.

System symbols can represent unique values in shared initialization statements. Each MVS system can define its own values to system symbols. When shared statements are processed, each MAS member replaces the system symbols with its own values.

Before you use system symbols in JES2 initialization statements, you must understand the types of system symbols, the elements that comprise them, and the general rules for using them. See [z/OS MVS Initialization and Tuning Reference](#) for details about planning to use system symbols. Then read the rest of this section for specific information about using system symbols in JES2 initialization statements.

Displaying Static System Symbols

You can enter the MVS DISPLAY SYMBOLS command to display the static system symbols and associated substitution texts that are in effect for a system. The output from DISPLAY SYMBOLS shows you the system symbols that you can specify in JES2 initialization statements. See the description of DISPLAY SYMBOLS in [z/OS MVS System Commands](#) for the command syntax.

Rules and Recommendations for Using System Symbols

The general rules and recommendations for using system symbols are described in [z/OS MVS Initialization and Tuning Reference](#).

As an example, suppose that you require two members (named SYS1 and SYS2) to share the following LOGON(2) initialization statement.

```
LOGON(2) APPLID=jes&SYSNAME;...
```

You have defined &SYSNAME; as SYS1 on member SYS1, and &SYSNAME; as SYS2 on member SYS2. Following symbolic substitution, the LOGON(2) statement for each member appears as:

```
LOGON(2) APPLID=JESSYS1,... /* Init statement for member SYS1 */  
LOGON(2) APPLID=JESSYS2,... /* Init statement for member SYS2 */
```

Do not code system symbols in JES2 initialization statements that are to be processed by members that are below the JES2 SP 5.2 level. Those members cannot substitute text for system symbols in JES2 initialization statements.

Special Considerations for Using System Symbols with NJE and RJE

Use double ampersand notation (&&) when using system symbols on initialization statements entered through RJE workstations or on initialization statements being sent from one node to another (through NJE). The double ampersand notation defers processing of the system symbols until they reach the receiving location.

For more information about using double ampersand notation, see the section on using system symbols in [z/OS MVS Initialization and Tuning Reference](#).

Initialization Data Set Input Sources

The variable-length statements described above are provided from the following sources:

- One source of parameter input is the HASPPARM data sets, specified through a DD statement in the JES2 cataloged procedure. The DDname used is specified in the HASPPARM=ddname initialization option. JES2 only examines columns 1-71 of the input image from this source.
- The MVS logical PARMLIB concatenation as specified on the PARMLIB statements of the LOADxx member of SYS1. PARMLIB can also be used as a source of parameter input. The logical PARMLIB is used when the PARM='MEMBER=mmmmmmm' initialization option is specified or when the INCLUDE initialization statement is used. JES2 only examines columns 1-71 of the input from this source.
- The INCLUDE initialization statement can be used to obtain parameter input from any data set. JES2 examines only columns 1-71 of the input from this source.
- When JES2 initialization processing is in **console mode**, statements (1 to 120 characters in length) can be entered at the console with a HASP WTOR reply. These statements must be syntactically complete (that is, continuation is not permitted on subsequent statements).
- Initialization statement processing exit routines (Exit 19) are presented with each variable-length statement and can add new statements. The new statements must also be of variable length as described above. (See [z/OS JES2 Installation Exits](#) for further information on exits and their specification.)

Initialization statements can be specified by the input source in any order. Parameters can also be specified in any order. When a statement or parameter is specified, that value is used until that statement or parameter is specified again. That is, if the same parameter occurs more than once or if the same parameter occurs more than once for a statement, JES2 will use the value of the last one it reads.

Chapter 2. JES2 initialization statement and parameter summary tables

The following tables list each of the JES2 initialization statements, their parameters, and the valid range of values that might be specified and the default value for each. This listing can serve as a quick reference to the statement syntax and valid allowable characters also. There are many display-only parameters that can appear on initialization statements. These are not shown in the following tables, but can be viewed by displaying the initialization statement (for example, D NJEDEF).

You can change initialization parameter settings through six methods that vary in their impact to the JES2 member. The following list provides the hierarchy, beginning with the easiest and least disruptive method, and ending with the most difficult and disruptive method for the JES2 member:

1. Operator command
2. Hot start
3. Quick start
4. Single-member warm start
5. All-member warm start
6. Cold start

The 'Minimum Action to Modify' column in the initialization statement summary tables cites the least disruptive way to change the parameter. You can change most parameters through any method more disruptive than the minimum action to modify. All exceptions to this hierarchy are noted in this table and the full parameter descriptions under each initialization statement.

Table 9. Initialization Statement - APPL(jxxxxxxx)					
Parameter	Range	Default	Related parameter or statement	Minimum action to modify	Location
Initialization Statement - APPL(jxxxxxxx)					
avvvvvvv	N/A	None. Must specify.	NJEDEF	\$T APPL command	“APPL(jxxxxxxx) - Application Characteristics Specification” on page 91
COMPACT	0-99	Value of COMPACT on NODE	NODE	\$T APPL command	“Parameter Description for APPL(jxxxxxxx)” on page 93
CONNECT	0-1440	DEFAULT/0	NJEDEF, NODE	\$T APPL command	“Parameter Description for APPL(jxxxxxxx)” on page 93
LINE	0-32767	None	NJEDEF	\$T APPL command	“Parameter Description for APPL(jxxxxxxx)” on page 93
LOGMODE	N/A	Name defaults to blanks	NJEDEF	\$T APPL command	“Parameter Description for APPL(jxxxxxxx)” on page 93
LOGON	0-999	0	LOGON (n)	\$T APPL command	“Parameter Description for APPL(jxxxxxxx)” on page 93

Table 9. Initialization Statement - APPL(jxxxxxxx) (continued)					
Parameter	Range	Default	Related parameter or statement	Minimum action to modify	Location
NODE	1-32767 or 1-8 characters.	None. Must specify.	NODE	\$T APPL command	“Parameter Description for APPL(jxxxxxxx)” on page 93
REST	0-2000	Value of REST on NODE	NODE	\$T APPL command	“Parameter Description for APPL(jxxxxxxx)” on page 93

Table 10. Initialization Statement - BADTRACK					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - BADTRACK					
VOL	5-6 characters	None. Must specify.	N/A	Hot start	“Parameter Description for BADTRACK” on page 95
ADDR	Cyl-head addr. for device	None. Must specify.	N/A	Hot start	“Parameter Description for BADTRACK” on page 95

Table 11. Initialization Statement - BUFDEF					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - BUFDEF					
BELOWBUF	N/A	(See note below)	INTRDR, PUN PRT, RDR, PRINTDEF, PUNCHDEF, NJEDEF	\$T BUFDEF command (to increase LIMIT) Hot start (to decrease LIMIT)	“Parameter Description for BUFDEF” on page 96
EXTBUF	N/A	(See note below)	INTRDR, PUN PRT, RDR, PRINTDEF, PUNCHDEF, NJEDEF	\$T BUFDEF command (to increase LIMIT) Hot start (to decrease LIMIT)	“Parameter Description for BUFDEF” on page 96
Note: See the full description of this parameter in the parameter definition with this initialization statement.					

Table 12. Initialization Statement - CKPTDEF					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - CKPTDEF					
CKPT1	N/A	(See note below)	N/A	Checkpoint Reconfiguration Dialog	“Parameter description for CKPTDEF” on page 100
CKPT2	N/A	(See note below)	N/A	Checkpoint Reconfiguration Dialog	“Parameter description for CKPTDEF” on page 100
CKPTOPT	N/A	Highest	OPTSDEF	Hot start	“Parameter description for CKPTDEF” on page 100
DUPLEX	N/A	ON	MODE	\$T CKPTDEF command	“Parameter description for CKPTDEF” on page 100
LOGSIZE	1-4000	(See note below)	MODE	Cold start or All-member warm start if RECONFIG is a start option.	“Parameter description for CKPTDEF” on page 100
MODE	N/A	DUPLEX	DUPLEX	\$T CKPTDEF command or all-member warm start	“Parameter description for CKPTDEF” on page 100
NEWCKPT1	N/A	(See note below)	N/A	\$T CKPTDEF command or cold start	“Parameter description for CKPTDEF” on page 100
NEWCKPT2	N/A	(See note below)	N/A	\$T CKPTDEF command or cold start	“Parameter description for CKPTDEF” on page 100
OPVERIFY	N/A	YES	N/A	\$T CKPTDEF command or cold start	“Parameter description for CKPTDEF” on page 100
RECONFIG	N/A	No	OPTSDEF	\$T CKPTDEF command	“Parameter description for CKPTDEF” on page 100
VERSIONS	N/A	(See note below)	N/A	\$T CKPTDEF command	“Parameter description for CKPTDEF” on page 100

Table 12. Initialization Statement - CKPTDEF (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
VOLATILE	N/A	(See note below)	CKPT1 CKPT2	\$T CKPTDEF command or cold start	“Parameter description for CKPTDEF” on page 100
Note: See the full description of this parameter in the parameter definition with this initialization statement.					

Table 13. Initialization Statement - CKPTSPACE					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - CKPTSPACE					
BERTNUM	1-2,500,000	Greater of the two values: (JOBNUM + JOENUM/4 + 100) or 399 (See note below)		\$T CKPTSPACE command	“Parameter description for CKPTSPACE” on page 109
BERTWARN	1–99	80		\$T CKPTSPACE command	“Parameter description for CKPTSPACE” on page 109
Note: This parameter can be increased by using a \$T CKPTSPACE command after an \$ACTIVATE command is issued in the MAS.					

Table 14. Initialization Statement - COMPACT					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - COMPACT					
Name	1-8 characters	value of NUMBER	NUMBER	Hot start	“Parameter Description for COMPACT” on page 110
CHARS	(See note below)	None	N/A	Hot start	“Parameter Description for COMPACT” on page 110
NUMBER	1-99	None. Must specify.	NAME	Hot start	“Parameter Description for COMPACT” on page 110
Note: See the full description of this parameter in the parameter definition with this initialization statement.					

Table 15. Initialization Statement - CONDEF					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - CONDEF					
AUTOCMD	2-9999	20	N/A	Hot start	"Parameter Description for CONDEF" on page 112
BUFNUM	4-9999	100	BUFWARN	\$T CONDEF command to increase Hot start to decrease	"Parameter Description for CONDEF" on page 112
BUFWARN	0-100	80	BUFNUM	\$T CONDEF command	"Parameter Description for CONDEF" on page 112
CMDNUM	4-9999	BUFNUM	BUFNUM	\$T CONDEF command	"Parameter Description for CONDEF" on page 112
CONCHAR	single character	\$	N/A	\$T CONDEF command (See notes 1 and 2)	"Parameter Description for CONDEF" on page 112
DISPLEN	50-70	64	MFORM on K command	\$T CONDEF command	"Parameter Description for CONDEF" on page 112
DISPMAX	10 - 21410084647	100	N/A	\$T CONDEF command	"Parameter Description for CONDEF" on page 112
MASMSG	10-999	200	N/A	\$T CONDEF command	"Parameter Description for CONDEF" on page 112
RDIRAREA	single character	Z	REDIRECT	\$T CONDEF command	"Parameter Description for CONDEF" on page 112
RDRCHAR	single character	\$	CONCHAR	\$T CONDEF command	"Parameter Description for CONDEF" on page 112
SCOPE	N/A	SYSTEM	CONCHAR	Single-member warm start	"Parameter Description for CONDEF" on page 112
Note: 1. See the full description of this parameter in the parameter definition with this initialization statement. 2. If you modify this parameter value and then restart JES2 with a hot start, the parameter value in effect before termination is used.					

Table 16. Initialization Statement - CONNECT					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - CONNECT					
NODEA	1-32767 or 1-8 characters	None. Must specify.	NODE	\$ADD CONNECT command to add \$DEL CONNECT command to delete	"Parameter Description CONNect" on page 116
NODEB	1-32767 or 1-8 characters	None. Must specify.	NODE	\$ADD CONNECT command to add \$DEL CONNECT command to delete	"Parameter Description CONNect" on page 116
MEMBerA	1-7 (See note below)	1	MASDEF	\$ADD CONNECT command to add \$DEL CONNECT command to delete	"Parameter Description CONNect" on page 116
MEMBerB	1-7 (See note below)	1	MASDEF	\$ADD CONNECT command to add \$DEL CONNECT command to delete	"Parameter Description CONNect" on page 116
PATHMGR	N/A	(See note below)	NODE	\$T CONNECT command	"Parameter Description CONNect" on page 116
REST	2-8000	0	NODE	\$T CONNECT command	"Parameter Description CONNect" on page 116
Note: See the full description of this parameter in the parameter definition with this initialization statement.					

Table 17. Initialization Statement - DEBUG					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - DEBUG					
DEBUG	N/A	NO	CKPTDEF	\$T DEBUG operator command	"Parameter description DEBUG" on page 131

Table 17. Initialization Statement - DEBUG (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
BERT	N/A	YES	CKPTDEF	\$T DEBUG operator command	N/A
CKPT	N/A	NO	CKPTDEF	\$T DEBUG operator command	“Parameter description DEBUG” on page 131
EDS	N/A	NO	CKPTDEF	\$T DEBUG operator command	“Parameter description DEBUG” on page 131
MEMBER_STATUS	N/A	NO	CKPTDEF	\$T DEBUG operator command	“Parameter description DEBUG” on page 131
MISC	N/A	NO	CKPTDEF	\$T DEBUG operator command	“Parameter description DEBUG” on page 131
QVERIFY	N/A	NO	CKPTDEF	\$T DEBUG operator command	“Parameter description DEBUG” on page 131
STORAGE	N/A	NO	CKPTDEF	\$T DEBUG operator command	“Parameter description DEBUG” on page 131
SYMREC	N/A	NO	N/A	\$T DEBUG operator command	“Parameter description DEBUG” on page 131
VERBOSE	N/A	NO	CKPTDEF	\$T DEBUG operator command	“Parameter description DEBUG” on page 131
VERSION	N/A	NO	CKPTDEF	\$T DEBUG operator command	“Parameter description DEBUG” on page 131

Table 18. Initialization Statement - DESTDEF					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - DESTDEF					
LOCALNUM	1-32767	32767	DESTID	Single-member warm start	“Parameter Description for DESTDEF” on page 134
Ndest	N/A	Node.	DESTID	All-member warm start	“Parameter Description for DESTDEF” on page 134

Table 18. Initialization Statement - DESTDEF (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
NODENAME	N/A	OPTIONAL	DESTID	All-member warm start	“Parameter Description for DESTDEF” on page 134
R RM RMTdest	N/A	Remote	DESTID	All-member warm start	“Parameter Description for DESTDEF” on page 134
Udest	N/A	Splocal	DESTID	All-member warm start	“Parameter Description for DESTDEF” on page 134
SHOWUSER	N/A	NOlocal	DESTID	\$T DESTDEF command	“Parameter Description for DESTDEF” on page 134

Table 19. Initialization Statement - DESTID(xxxxxxxx)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - DESTID(xxxxxxxx)					
xxxxxxxx	1-8 characters	None. (See note 2)	NODE, RMT, DESTDEF	\$T DESTID(xxxxxxxx) command (See note 2)	“DESTid(xxxxxxxx) - Route Code Name” on page 136
DEST	(See note below.)	None.	NODE, RMT, DESTDEF	\$T DESTID(xxxxxxxx) command (See note 2)	“DESTid(xxxxxxxx) - Route Code Name” on page 136
PRIMARY	N/A	No	DESTDEF	\$T DESTID(xxxxxxxx) command (See note 2)	“DESTid(xxxxxxxx) - Route Code Name” on page 136
Note: - See the full description of this parameter in the parameter definition with this initialization statement. - If you modify this parameter value and then restart JES2 with a hot start, the parameter value in effect before termination is used.					

Table 20. Initialization Statement - ESTBYTE					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - ESTBYTE					
INT	1-99999	99999	N/A	\$T ESTBYTE command	"Parameter Description for ESTBYTE" on page 142
NUM	1-999999	99999	/*JOBPARM	\$T ESTBYTE command	"Parameter Description for ESTBYTE" on page 142
OPT	0-2	0	N/A	\$T ESTBYTE command	"Parameter Description for ESTBYTE" on page 142

Table 21. Initialization Statement - ESTIME					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - ESTIME					
INT	1-99	1	N/A	\$T ESTIME command	"Parameter Description for ESTIME" on page 143
NUM	1-9999	2	/*JOBPARM	\$T ESTIME command	"Parameter Description for ESTIME" on page 143
OPT	N/A	NO	N/A	\$T ESTIME command	"Parameter Description for ESTIME" on page 143

Table 22. Initialization Statement - ESTLNCT					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - ESTLNCT					
INT	1-9999999	2000	N/A	\$T ESTLNCT command	"Parameter Description for ESTLNCT" on page 144
NUM	1-999999	2	/*JOBPARM	\$T ESTLNCT command	"Parameter Description for ESTLNCT" on page 144

Table 22. Initialization Statement - ESTLNCT (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
OPT	0-2	0	N/A	\$T ESTLNCT command	“Parameter Description for ESTLNCT” on page 144

Table 23. Initialization Statement - ESTPAGE					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - ESTPAGE					
INT	1-99999999	10	N/A	\$T ESTPAGE command	“Parameter Description for ESTPAGE” on page 145
NUM	1-99999999	40	/*JOBPARM	\$T ESTPAGE command	“Parameter Description for ESTPAGE” on page 145
OPT	0-2	0	N/A	\$T ESTPAGE command	“Parameter Description for ESTPAGE” on page 145

Table 24. Initialization Statement - ESTPUN					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - ESTPUN					
INT	1-99999999	2000	N/A	\$T ESTPUN command	“Parameter Description for ESTPUN” on page 146
NUM	1-99999999	100	/*JOBPARM	\$T ESTPUN command	“Parameter Description for ESTPUN” on page 146
OPT	0-2	0	N/A	\$T ESTPUN command	“Parameter Description for ESTPUN” on page 146

Table 25. Initialization Statement - EXIT(nnn)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - EXIT(nnn)					
nnn	0-255	N/A	N/A	(See notes 1 and 2)	“EXIT(nnn) - Exit and Exit Routine Association” on page 146
ROUTines	1-8 characters	None	LOADMOD	Single-member warm start (See notes 1 and 2)	“Parameter Description for EXIT(nnn)” on page 148
STATUS	N/A	ENABLED	N/A	\$T EXIT(nnn) command (See notes 1 and 2)	“Parameter Description for EXIT(nnn)” on page 148
TRace	N/A	YES	TRACEDEF	\$T EXIT(nnn) command (See notes 1 and 2)	“Parameter Description for EXIT(nnn)” on page 148
Note: 1. See the full description of this parameter in the parameter definition with this initialization statement. 2. If you modify this parameter value and then restart JES2 with a hot start, the parameter value in effect before termination is used.					

Table 26. Initialization Statement - FSS(accccccc)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - FSS(accccccc)					
accccccc	1-8 characters	None	PROC	\$T FSS command (if address space inactive). (See notes 1 and 2)	“FSS(accccccc) - Functional Subsystem Definition” on page 149
AUTOSTOP	N/A	NO	N/A	\$T FSS command (See notes 1 and 2)	“FSS(accccccc) - Functional Subsystem Definition” on page 149
HASPFSSM	1-8 characters	HASPFSSM	N/A	\$T FSS command (if address space inactive). (See notes 1 and 2)	“FSS(accccccc) - Functional Subsystem Definition” on page 149

Table 26. Initialization Statement - FSS(accccccc) (continued)

Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
PROC	1-8 characters	FSS subscript	PRT	\$T FSS command (if address space inactive). (See notes 1 and 2)	“FSS(accccccc) - Functional Subsystem Definition” on page 149

Note:

1. See the full description of this parameter in the parameter definition with this initialization statement.
2. If you modify this parameter value and then restart JES2 with a hot start, the parameter value in effect before termination is used.

Table 27. Initialization Statement - GRPDEF

Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - GRPDEF					
\$ZJCNUM	1-500000	1000	N/A	\$T GRPDEF command	“Parameter description for GRPDEF” on page 151
\$ZJCWARN	1-99	80	\$ZJCNUM	\$T GRPDEF command	“Parameter description for GRPDEF” on page 151
CONCURRENT_MAX	0-200	0	N/A	\$T GRPDEF command	“Parameter description for GRPDEF” on page 151
JOBGROUP_JOB_MAX	10-2000	2000	N/A	\$T GRPDEF command	“Parameter description for GRPDEF” on page 151

Table 28. Initialization Statement - INCLUDE

Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - INCLUDE					
DSName	1-44 characters, 1-8 characters	(See note below)	N/A	Operator command	“Parameter Description for INCLUDE” on page 152
MEMBER	1- 8 characters	(See note below)	N/A	Operator command	“Parameter Description for INCLUDE” on page 152
PARMLIB	1- 8 characters	(See note below)	N/A	Operator command	“Parameter Description for INCLUDE” on page 152

Table 28. Initialization Statement - INCLUDE (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
UNIT	N/A	(See note below)	N/A	Operator command	“Parameter Description for INCLUDE” on page 152
VOLser	1–6 characters	(See note below)	N/A	Operator command	“Parameter Description for INCLUDE” on page 152
Note: See the full description of this parameter in the parameter definition with this initialization statement.					

Table 29. Initialization Statement - INIT(nnnn)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - INIT(nnnn)					
nnnn	1-9999	None	INITDEF	Single-member warm start (See notes 1 and 2)	“Init(nnnn) - Initiator” on page 153
CLASS	(See note below.)	A	N/A	\$T I[vvvv] command (See notes 1 and 2)	“Init(nnnn) - Initiator” on page 153
NAME	1-4 characters	EBCDIC form of nnnn	N/A	Single-member warm start (See notes 1 and 2)	“Init(nnnn) - Initiator” on page 153
START	N/A	YES	N/A	\$S I[vvvv] command to start \$P I[vvvv] command to stop (See notes 1 and 2)	“Init(nnnn) - Initiator” on page 153
Note: 1. See the full description of this parameter in the parameter definition with this initialization statement. 2. If you modify this parameter value and then restart JES2 with a hot start, the parameter value in effect before termination is used.					

Table 30. Initialization Statement - INITDEF					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - INITDEF					
PARTNUM	0-9999	3	INIT	Single-member warm start (See notes 1 and 2)	"INITDEF - Initiator Definition" on page 155
Note: 1. See the full description of this parameter in the parameter definition with this initialization statement. 2. If you modify this parameter value and then restart JES2 with a hot start, the parameter value in effect before termination is used.					

Table 31. Initialization Statement - INPUTDEF					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - INPUTDEF					
JES3JECL	N/A	IGNORE	JECLDEF	\$T INPUTDEF command	"Parameter Description for INPUTDEF" on page 156
NULLJCL	N/A	IGNORE	N/A	\$T INPUTDEF command	"Parameter Description for INPUTDEF" on page 156

Table 32. Initialization Statement - INTRDR					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - INTRDR					
Auth	N/A	NO/NO/NO	N/A	\$T INTRDR command (See notes 1, 2, and 3)	"Parameter Description for INTRDR" on page 158
BATCH	N/A	YES	INTRDR	Warm start (See notes 1, 2, and 3)	"Parameter Description for INTRDR" on page 158
CLASS	1-8 character job class name	A	N/A	\$T INTRDR command (See notes 1, 2, and 3)	"Parameter Description for INTRDR" on page 158

Table 32. Initialization Statement - INTRDR (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
HOLD	N/A	NO	N/A	\$T INTRDR command (See notes 1, 2, and 3)	"Parameter Description for INTRDR" on page 158
PRTYINC	0-15	0	PRTYLIM	\$T INTRDR command (See notes 1, 2, and 3)	"Parameter Description for INTRDR" on page 158
PRTYLIM	0-15	15	PRTYINC	\$T INTRDR command (See notes 1, 2, and 3)	"Parameter Description for INTRDR" on page 158
SYSaff	N/A	Null	N/A	\$T INTRDR command (See notes 1 and 3)	"Parameter Description for INTRDR" on page 158
TRACE	N/A	NO	TRACEDEF	\$T INTRDR command (See notes 1, 2, and 3)	"Parameter Description for INTRDR" on page 158
Note: 1. See the full description of this parameter in the parameter definition with this initialization statement. 2. If you modify this parameter value and then restart JES2 with a hot start, the parameter value in effect before termination is used. 3. This parameter cannot be set during initialization.					

Table 33. Initialization Statement - JECLDEF, JES2=					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - JECLDEF, JES2=					
JOBPARM	N/A	PROCESS	N/A	\$T JECLDEF,JES2= command	"Parameter Description for JECLDEF,JES2=" on page 159
MESSAGE	N/A	PROCESS	N/A	\$T JECLDEF,JES2= command	"Parameter Description for JECLDEF,JES2=" on page 159

Table 33. Initialization Statement - JECLDEF, JES2= (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
NETACCT	N/A	PROCESS	N/A	\$T JECLDEF,JES2= command	“Parameter Description for JECLDEF,JES2=” on page 159
NOTIFY	N/A	PROCESS	N/A	\$T JECLDEF,JES2= command	“Parameter Description for JECLDEF,JES2=” on page 159
OUTPUT	N/A	PROCESS	N/A	\$T JECLDEF,JES2= command	“Parameter Description for JECLDEF,JES2=” on page 159
PRIORITY	N/A	PROCESS	N/A	\$T JECLDEF,JES2= command	“Parameter Description for JECLDEF,JES2=” on page 159
ROUTE	N/A	PROCESS	N/A	\$T JECLDEF,JES2= command	“Parameter Description for JECLDEF,JES2=” on page 159
SETUP	N/A	PROCESS	N/A	\$T JECLDEF,JES2= command	“Parameter Description for JECLDEF,JES2=” on page 159
XEQ	N/A	PROCESS	N/A	\$T JECLDEF,JES2= command	“Parameter Description for JECLDEF,JES2=” on page 159
XMIT	N/A	PROCESS	N/A	\$T JECLDEF,JES2= command	“Parameter Description for JECLDEF,JES2=” on page 159

Table 34. Initialization Statement - JECLDEF, JES3=					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - JECLDEF, JES3=					
DATASET	N/A	IGNORE	INPUTDEF	\$T JECLDEF,JES3= command	“Parameter Description for JECLDEF,JES3=” on page 160

Table 34. Initialization Statement - JECLDEF, JES3= (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
ENDDATASET	N/A	IGNORE	INPUTDEF	\$T JECLDEF,JES3= command	“Parameter Description for JECLDEF,JES3=” on page 160
FORMAT	N/A	IGNORE	INPUTDEF	\$T JECLDEF,JES3= command	“Parameter Description for JECLDEF,JES3=” on page 160
MAIN	N/A	IGNORE	INPUTDEF	\$T JECLDEF,JES3= command	“Parameter Description for JECLDEF,JES3=” on page 160
NET	N/A	IGNORE	INPUTDEF	\$T JECLDEF,JES3= command	“Parameter Description for JECLDEF,JES3=” on page 160
NETACCT	N/A	IGNORE	INPUTDEF	\$T JECLDEF,JES3= command	“Parameter Description for JECLDEF,JES3=” on page 160
OPERATOR	N/A	IGNORE	INPUTDEF	\$T JECLDEF,JES3= command	“Parameter Description for JECLDEF,JES3=” on page 160
PAUSE	N/A	IGNORE	INPUTDEF	\$T JECLDEF,JES3= command	“Parameter Description for JECLDEF,JES3=” on page 160
PROCESS	N/A	IGNORE	INPUTDEF	\$T JECLDEF,JES3= command	“Parameter Description for JECLDEF,JES3=” on page 160
ENDPROCESS	N/A	IGNORE	INPUTDEF	\$T JECLDEF,JES3= command	“Parameter Description for JECLDEF,JES3=” on page 160
ROUTE	N/A	IGNORE	INPUTDEF	\$T JECLDEF,JES3= command	“Parameter Description for JECLDEF,JES3=” on page 160

Table 35. Initialization Statement - JOBCLASS(v STC TSU)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - JOBCLASS(v STC TSU)					
v	1-8 character job class name	N/A	JOB	N/A	"JOBCLASS - Job, Started Task, and Time Sharing User Class" on page 161
ACCT	N/A	NO	JOB	Cold start or \$T JOBCLASS	"Parameter description for JOBCLASS(class... STC TSU)" on page 169
ACTIVE	Yes or No	YES	JOB	Cold start or \$T JOBCLASS	"Parameter description for JOBCLASS(class... STC TSU)" on page 169
AUTH	N/A	ALL	N/A	Cold start or \$T JOBCLASS	"Parameter description for JOBCLASS(class... STC TSU)" on page 169
BLP	N/A	NO	LABEL(dd)	Cold start or \$T JOBCLASS	"Parameter description for JOBCLASS(class... STC TSU)" on page 169
COMMAND	N/A	VERIFY	N/A	Cold start or \$T JOBCLASS	"Parameter description for JOBCLASS(class... STC TSU)" on page 169
CONDPURG	Yes or No	No	N/A	Cold start or \$T JOBCLASS	"Parameter description for JOBCLASS(class... STC TSU)" on page 169
COPY	N/A	NO	TYPRUN(JOB)	Cold start or \$T JOBCLASS	"Parameter description for JOBCLASS(class... STC TSU)" on page 169
DUPL_JOB	N/A	DELAY	N/A	Cold start or \$T JOBCLASS	"Parameter description for JOBCLASS(class... STC TSU)" on page 169
GROUP	N/A	N/A	JOB	Cold start or \$T JOBCLASS	"Parameter description for JOBCLASS(class... STC TSU)" on page 169
HOLD	N/A	NO	TYPRUN(JOB)	Cold start or \$T JOBCLASS	"Parameter description for JOBCLASS(class... STC TSU)" on page 169
IEFUJP	N/A	YES	SYSOUT(DD)	Cold start or \$T JOBCLASS	"Parameter description for JOBCLASS(class... STC TSU)" on page 169
IEFUSO	N/A	YES	OUTLIM(DD)	Cold start or \$T JOBCLASS	"Parameter description for JOBCLASS(class... STC TSU)" on page 169

Table 35. Initialization Statement - JOBCLASS(v STC TSU) (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
JESCANCEL	ALLOWED or RESTRICTED	ALLOWED	JOB	Cold start or \$T JOBCLASS	"Parameter description for JOBCLASS(class... STC TSU)" on page 169
JESLOG	(See note below.)	NOSPIN	JESMSGLG, JESSYSMSG	Cold start or \$T JOBCLASS	"Parameter description for JOBCLASS(class... STC TSU)" on page 169
JOBRC	MAXRC, LASTRC	MAXRC	JOBCLASS	Cold start or \$T JOBCLASS	"Parameter description for JOBCLASS(class... STC TSU)" on page 169
JOURNAL	N/A	YES	RD(JOB EXEC)	Cold start or \$T JOBCLASS	"Parameter description for JOBCLASS(class... STC TSU)" on page 169
LOG	N/A	YES	JOB	Cold start or \$T JOBCLASS	"Parameter description for JOBCLASS(class... STC TSU)" on page 169
MODE	JES or WLM	JES	N/A	Cold start or \$T JOBCLASS	"Parameter description for JOBCLASS(class... STC TSU)" on page 169
MSGCLASS	A-Z, 0-9	A	N/A	Cold start or \$T JOBCLASS	"Parameter description for JOBCLASS(class... STC TSU)" on page 169
MSGLEVEL	0-2, 0-1 (See note below)	(0,1)	JOB	Cold start or \$T JOBCLASS	"Parameter description for JOBCLASS(class... STC TSU)" on page 169
OUTDisp	N/A	(See note below)	N/A	Cold start or \$T JOBCLASS	"Parameter description for JOBCLASS(class... STC TSU)" on page 169
OUTPUT	N/A	YES	TSO/E TRANSMIT	Cold start or \$T JOBCLASS	"Parameter description for JOBCLASS(class... STC TSU)" on page 169
PERFORM	0-255	000	JOB EXEC	Cold start or \$T JOBCLASS	"Parameter description for JOBCLASS(class... STC TSU)" on page 169
PGMRNAME	N/A	NO	JOB	Cold start or \$T JOBCLASS	"Parameter description for JOBCLASS(class... STC TSU)" on page 169
PROCLIB	00-99 or 2-8 characters	00	PROCnn(JES2)	Cold start or \$T JOBCLASS	"Parameter description for JOBCLASS(class... STC TSU)" on page 169

<i>Table 35. Initialization Statement - JOBCCLASS(v STC TSU) (continued)</i>					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
PROMO_RATE	0-255	0	N/A	Cold start or \$T JOBCCLASS	“Parameter description for JOBCCLASS(class... STC TSU)” on page 169
QHELD	N/A	NO	N/A	Cold start or \$T JOBCCLASS	“Parameter description for JOBCCLASS(class... STC TSU)” on page 169
REGION	0-2047M	1M	REGION(JOB)	Cold start or \$T JOBCCLASS	“Parameter description for JOBCCLASS(class... STC TSU)” on page 169
RESTART	N/A	NO	/*JOBPARM	Cold start or \$T JOBCCLASS	“Parameter description for JOBCCLASS(class... STC TSU)” on page 169
SCAN	N/A	NO	TYPRUN(JOB)	Cold start or \$T JOBCCLASS	“Parameter description for JOBCCLASS(class... STC TSU)” on page 169
SCHENV	N/A	N/A	N/A	Cold start or \$T JOBCCLASS	“Parameter description for JOBCCLASS(class... STC TSU)” on page 169
SWA	N/A	BELOW	N/A	Cold start or \$T JOBCCLASS	“Parameter description for JOBCCLASS(class... STC TSU)” on page 169
TIME	0-357912, 0-59	(30,0)	TIME on JOB EXEC	Cold start or \$T JOBCCLASS	“Parameter description for JOBCCLASS(class... STC TSU)” on page 169
TYPE6	N/A	YES	BUFNUM on SMFDEF	Cold start or \$T JOBCCLASS	“Parameter description for JOBCCLASS(class... STC TSU)” on page 169
TYPE26	N/A	YES	BUFNUM on SMFDEF	Cold start or \$T JOBCCLASS	“Parameter description for JOBCCLASS(class... STC TSU)” on page 169
XBM	1-8 characters	Null	N/A	Cold start or \$T JOBCCLASS	“Parameter description for JOBCCLASS(class... STC TSU)” on page 169
XEQCOUNT	0-2M	N/A	N/A	Cold start or \$T JOBCCLASS	“Parameter description for JOBCCLASS(class... STC TSU)” on page 169
Note: See the full description of this parameter in the parameter definition with this initialization statement.					

Table 36. Initialization Statement - JOBDEF					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - JOBDEF					
ACCTFLD	N/A	OPTIONAL	JOB	\$T JOBDEF command	"Parameter description for JOBDEF" on page 181
BAD_JOBNAME_CHAR	N/A	?	N/A	\$T JOBDEF command (See note 6)	"Parameter description for JOBDEF" on page 181
CISUB_PER_AS	1-25	5	N/A	\$T JOBDEF command	"Parameter description for JOBDEF" on page 181
CNVT_ENQ	WAIT, FAIL	FAIL	N/A	\$T JOBDEF command	"Parameter description for JOBDEF" on page 181
CNVT_SCHENV	N/A	IGNORE	N/A	\$T JOBDEF command	"Parameter description for JOBDEF" on page 181
DUPL_JOB	N/A	DELAY	N/A	\$T JOBDEF command	"Parameter description for JOBDEF" on page 181
INTERPRET	N/A	INIT	N/A	\$T JOBDEF command	"Parameter description for JOBDEF" on page 181
JNUMWARN	1-99	80	RANGE	\$T JOBDEF command (See note 6)	"Parameter description for JOBDEF" on page 181
JOBNUM	10-1,000,000 (See note 7)	1000	None	\$T JOBDEF command (See note 6)	"Parameter description for JOBDEF" on page 181
JOBWARN	1-99	80	N/A	\$T JOBDEF command (See note 6)	"Parameter description for JOBDEF" on page 181

Table 36. Initialization Statement - JOBDEF (continued)

Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
NFY_SUBJECT	N/A	See parameter description	N/A	\$T JOBDEF command	“Parameter description for JOBDEF” on page 181
PRTYHIGH	0-15	10	N/A	\$T JOBDEF command (See note 6)	“Parameter description for JOBDEF” on page 181
PRTYJECL	N/A	YES	/*PRIORITY (See note 3)	\$T JOBDEF command	“Parameter description for JOBDEF” on page 181
PRTYJOB	N/A	NO	PRTY(JOB) (See notes 1 and 5)	\$T JOBDEF command	“Parameter description for JOBDEF” on page 181
PRTYLOW	0-15	5	N/A	\$T JOBDEF command (See note 6)	“Parameter description for JOBDEF” on page 181
PRTYRATE	0-1440	0	JOBPRTY, OUTPRTY	\$T JOBDEF command (See note 6)	“Parameter description for JOBDEF” on page 181
RANGE	1-999999	1-9999	JNUMWARN	\$T JOBDEF command (See notes 1 and 4)	“Parameter description for JOBDEF” on page 181
RASSIGN				\$T JOBDEF command	“Parameter description for JOBDEF” on page 181
SUP_EVENTLOG_SMF	N/A	NO	NONE	\$T JOBDEF command	“Parameter description for JOBDEF” on page 181

Table 36. Initialization Statement - JOBDEF (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Notes: 1. See the full description of this parameter in the parameter definition with this initialization statement. 2. If you modify this parameter value and then restart JES2 with a hot start, the parameter value in effect before termination is used. 3. This parameter cannot be set during initialization. 4. If you modify this parameter value and then restart JES2 with any type of warm or hot start, the parameter value in effect before termination is used. 5. This refers to the PRTY parameter on the JCL JOB statement. 6. This parameter cannot be modified through a hot start, quick start, or single-member warm start. 7. This parameter can be increased by using a \$T JOBDEF command after an \$ACTIVATE command is issued in the MAS.					

Table 37. Initialization Statement - JOBPRTY					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - JOBPRTY					
n	1-9	None. Must specify.	N/A	Single-member Warm start	“JOBPRTY(n) - Job Priority” on page 184
PRIORITY	0-15	(See note below)	N/A	\$T JOBPRTY(n) command	“Parameter Description for JOBPRTY(n)” on page 185
TIME	1-279620	(See note below)	N/A	\$T JOBPRTY(n) command	“Parameter Description for JOBPRTY(n)” on page 185
Note: See the full description of this parameter in the parameter definition with this initialization statement.					

Table 38. Initialization Statement - L(nnnn).ST(n)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - L(nnnn).ST(n)					
nnnnn	1-32767	None	N/A	Single-member warm start	“L(nnnnn).ST(n) - SYSOUT Job Transmitter” on page 187

Table 38. Initialization Statement - L(nnnnn).ST(n) (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
n	1-7	None	N/A	Single-member warm start	“L(nnnnn).ST(n) - SYSOUT Job Transmitter” on page 187
LIMIT	0-4294967295	0-4294967295	N/A	\$T L(nnnnn).ST(n) command	“Parameter Description for L(nnnnn).ST(n)” on page 189
OUTDISP	N/A	N/A	N/A	\$T L(nnnnn).ST(n) command	“Parameter Description for L(nnnnn).ST(n)” on page 189
PLIM	0-4294967295	0-4294967295	N/A	\$T L(nnnnn).ST(n) command	“Parameter Description for L(nnnnn).ST(n)” on page 189
WS	N/A	(1)	LIMIT, PLIM, OUTDISP	\$T L(nnnnn).ST(n) command	“Parameter Description for L(nnnnn).ST(n)” on page 189

Table 39. Initialization Statement - L(nnnn).JT(n)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - L(nnnn).JT(n)					
nnnnn	1-32767	None	N/A	Single-member warm start	“Parameter Description for L(nnnnn).JT(n)” on page 186
n	1-7	None	N/A	Single-member warm start	“Parameter Description for L(nnnnn).JT(n)” on page 186
LIMIT	0-4294967295	0-4294967295	N/A	\$T L(nnnnn).JT(n) command	“Parameter Description for L(nnnnn).JT(n)” on page 186
WS	N/A	(1)	LIMIT	\$T L(nnnnn).JT(n) command	“Parameter Description for L(nnnnn).JT(n)” on page 186

Table 40. Initialization Statement - LINE(nnnnn) - BSC					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - LINE(nnnnn) - BSC					
nnnnn	1-32767	None. Must Specify.	NODE, RMT	Single-member warm start	"LINE(nnnnn) - NJE/RJE BSC Lines" on page 190
AUTODISC	N/A	YES	N/A	\$T LINE(nnnnn) command	"Parameter Description for LINE(nnnnn) - BSC" on page 194
CODE	N/A	A	N/A	\$T LINE(nnnnn) command	"Parameter Description for LINE(nnnnn) - BSC" on page 194
COMPRESS	N/A	YES	RMT	\$T LINE(nnnnn) command	"Parameter Description for LINE(nnnnn) - BSC" on page 194
CONNECT	0-1440	DEFAULT/0	NJEDEF, NODE	\$T LINE(nnnnn) command	"Parameter Description for LINE(nnnnn) - BSC" on page 194
Discon	N/A	No	N/A	\$T LINE(nnnnn) command	"Parameter Description for LINE(nnnnn) - BSC" on page 194
DUPLEX	N/A	HALF	N/A	\$T LINE(nnnnn) command	"Parameter Description for LINE(nnnnn) - BSC" on page 194
INTERFAC	N/A	A	N/A	\$T LINE(nnnnn) command	"Parameter Description for LINE(nnnnn) - BSC" on page 194
JRNUM	0-7	NJEDEF JRNUM parm.	SRNUM	\$T LINE(nnnnn) command	"Parameter Description for LINE(nnnnn) - BSC" on page 194
JTNUM	0-7	NJEDEF JTNUM parm.	STNUM	\$T LINE(nnnnn) command	"Parameter Description for LINE(nnnnn) - BSC" on page 194
LINECCHR	N/A	EBCDIC	N/A	\$T LINE(nnnnn) command	"Parameter Description for LINE(nnnnn) - BSC" on page 194

<i>Table 40. Initialization Statement - LINE(nnnnn) - BSC (continued)</i>					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
LOG	N/A	NO	N/A	\$T LINE(nnnnn) command	“Parameter Description for LINE(nnnnn) - BSC” on page 194
NODE	N/A	N/A	N/A	\$T LINE(nnnnn) command	“Parameter Description for LINE(nnnnn) - BSC” on page 194
Password	1-8 characters	None	/*SIGNON or LOGON	\$T LINE(nnnnn) command	“Parameter Description for LINE(nnnnn) - BSC” on page 194
REST	0-2000	0	NODE	\$T LINE(nnnnn) command	“Parameter Description for LINE(nnnnn) - BSC” on page 194
RESTART	0-1440	NO	N/A	\$T LINE(nnnnn) command	“Parameter Description for LINE(nnnnn) - BSC” on page 194
SPEED	N/A	LOW	N/A	\$T LINE(nnnnn) command	“Parameter Description for LINE(nnnnn) - BSC” on page 194
SRNUM	0-7	NJEDEF SRNUM parm.	JRNUM	\$T LINE(nnnnn) command	“Parameter Description for LINE(nnnnn) - BSC” on page 194
START	N/A	NO	N/A	N/A	“Parameter Description for LINE(nnnnn) - BSC” on page 194
STNUM	0-7	NJEDEF STNUM parm.	JTNUM	\$T LINE(nnnnn) command	“Parameter Description for LINE(nnnnn) - BSC” on page 194
TRaceio	N/A	NO	N/A	\$T LINE(nnnnn) command	“Parameter Description for LINE(nnnnn) - BSC” on page 194
TRANSPAR	N/A	NO	N/A	\$T LINE(nnnnn) command	“Parameter Description for LINE(nnnnn) - BSC” on page 194

Table 40. Initialization Statement - LINE(nnnnn) - BSC (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
UNIT	line addresses	Null	RMT	\$T LINE(nnnnn) command	"Parameter Description for LINE(nnnnn) - BSC" on page 194

Table 41. Initialization Statement - LINE(nnnnn) - SNA					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - LINE(nnnnn) - SNA					
nnnnn	1-32767	None. Must specify.	NODE, RMT	Single-member warm start	"LINE(nnnnn) - NJE/RJE SNA Lines" on page 198
COMPRESS	N/A	YES	RMT	\$T LINE(nnnnn) command	"Parameter Description for LINE(nnnnn) - SNA" on page 202
CONNECT	0-1440	DEFAULT/0	NJEDEF, NODE	\$T LINE(nnnnn) command	"Parameter Description for LINE(nnnnn) - SNA" on page 202
Discon	N/A	No	N/A	\$T LINE(nnnnn) command	"Parameter Description for LINE(nnnnn) - SNA" on page 202
JRNUM	0-7	NJEDEF JRNUM parm.	SRNUM	\$T LINE(nnnnn) command	"Parameter Description for LINE(nnnnn) - SNA" on page 202
JTNUM	0-7	NJEDEF JTNUM parm.	STNUM	\$T LINE(nnnnn) command	"Parameter Description for LINE(nnnnn) - SNA" on page 202
LOG	N/A	NO	N/A	\$T LINE(nnnnn) command	"Parameter Description for LINE(nnnnn) - SNA" on page 202
NODE	N/A	N/A	N/A	\$T LINE(nnnnn) command	"Parameter Description for LINE(nnnnn) - SNA" on page 202
Password	1-8 characters	None	/*SIGNON or LOGON	\$T LINE(nnnnn) command	"Parameter Description for LINE(nnnnn) - SNA" on page 202

<i>Table 41. Initialization Statement - LINE(nnnnn) - SNA (continued)</i>					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
REST	0-2000	0	NODE	\$T LINE(nnnnn) command	“Parameter Description for LINE(nnnnn) - SNA” on page 202
RESTART	0-1440	NO	N/A	\$T LINE(nnnnn) command	“Parameter Description for LINE(nnnnn) - SNA” on page 202
SRNUM	0-7	NJEDEF SRNUM parm.	JRNUM	\$T LINE(nnnnn) command	“Parameter Description for LINE(nnnnn) - SNA” on page 202
START	N/A	NO	N/A	N/A	“Parameter Description for LINE(nnnnn) - SNA” on page 202
STNUM	0-7	NJEDEF STNUM parm.	JTNUM	\$T LINE(nnnnn) command	“Parameter Description for LINE(nnnnn) - SNA” on page 202
TRaceio	N/A	NO	N/A	\$T LINE(nnnnn) command	“Parameter Description for LINE(nnnnn) - SNA” on page 202
UNIT=SNA	N/A	N/A	RMT	\$T LINE(nnnnn) command	“Parameter Description for LINE(nnnnn) - SNA” on page 202

<i>Table 42. Initialization Statement - LINE(nnnnn) - TCP/IP</i>					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - LINE(nnnnn) - TCP/IP					
nnnnn	1-65535	None. Must specify.	NODE, RMT	Single-member warm start	“LINE(nnnnn) - NJE TCP/IP lines” on page 205
CONNECT	0-1440	DEFAULT/0	NJEDEF, NODE	\$T LINE(nnn) command	“Parameter Description for LINE(nnnnn) - TCP/IP” on page 207
JRNUM	0-7	NJEDEF JRNUM parm.	SRNUM	\$T LINE(nnn) command	“Parameter Description for LINE(nnnnn) - TCP/IP” on page 207

Table 42. Initialization Statement - LINE(nnnnn) - TCP/IP (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
JTNUM	0-7	NJEDEF JTNUM parm.	STNUM	\$T LINE(nnn) command	“Parameter Description for LINE(nnnnn) - TCP/IP” on page 207
NODE	N/A	N/A	N/A	\$T LINE(nnn) command	“Parameter Description for LINE(nnnnn) - TCP/IP” on page 207
Password	1-8 characters	None	/*SIGNON or LOGON	\$T LINE(nnnnn) command	“Parameter Description for LINE(nnnnn) - TCP/IP” on page 207
REST	0-2000	0	NODE	\$T LINE(nnnnn) command	“Parameter Description for LINE(nnnnn) - TCP/IP” on page 207
RESTART	0-1440	NO	N/A	\$T LINE(nnnnn) command	“Parameter Description for LINE(nnnnn) - TCP/IP” on page 207
SRNUM	0-7	NJEDEF SRNUM parm.	JRNUM	\$T LINE(nnn) command	“Parameter Description for LINE(nnnnn) - TCP/IP” on page 207
START	N/A	NO	N/A	N/A	“Parameter Description for LINE(nnnnn) - TCP/IP” on page 207
STNUM	0-7	NJEDEF STNUM parm.	JTNUM	\$T LINE(nnn) command	“Parameter Description for LINE(nnnnn) - TCP/IP” on page 207
TRaceio	N/A	NO	N/A	\$T LINE(nnnnn) command	“Parameter Description for LINE(nnnnn) - TCP/IP” on page 207
UNIT	3-4 characters	N/A	RMT	\$T LINE(nnnnn) command	“Parameter Description for LINE(nnnnn) - TCP/IP” on page 207

Table 43. Initialization Statement - LOADmod(jxxxxxxx)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - LOADmod(jxxxxxxx)					
jxxxxxxx	1-8 characters	None. Must specify.	N/A	Single-member warm start	“LOADmod(jxxxxxxx) - Load Installation Exit Routine Modules” on page 209
STORage	N/A	PVT	N/A	Hot start	“Parameter Description for LOADmod(jxxxxxxx)” on page 209

Table 44. Initialization Statement - LOGON(nnn)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - LOGON(nnn)					
nnn	1-999	N/A	NODE, RMT	Single-member warm start	“LOGON(nnn) - Identification of JES2 to VTAM” on page 210
APPLID	1-8 characters	JES2	N/A	\$T LOGON(nnn) command	“Parameter Description for LOGON(nnn)” on page 211
LOG	N/A	None	N/A	\$T LOGON(nnn) command	“Parameter Description for LOGON(nnn)” on page 211
Password	1-8 characters	None	N/A	\$T LOGON(nnn) command	“Parameter Description for LOGON(nnn)” on page 211
RESTART	0-1440	NO	N/A	\$T LOGON(nnn) command	“Parameter Description for LOGON(nnn)” on page 211
START	N/A	NO	N/A	N/A	“Parameter Description for LOGON(nnn)” on page 211
TRaceio	N/A	NO	N/A	\$T LOGON(nnn) command	“Parameter Description for LOGON(nnn)” on page 211

Table 45. Initialization Statement - MASDEF					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - MASDEF					
AUTOEMEM	N/A	OFF	RESTART	\$T MASDEF command	“Parameter description for MASDEF” on page 213
CKPTLOCK	N/A	ACTION	N/A	\$T MASDEF command during initialization	“Parameter description for MASDEF” on page 213
CYCLEMGT	N/A	MANUAL	HOLD, DORMANCY	\$T MASDEF command	“Parameter description for MASDEF” on page 213
DORMANCY	0-3000, 100-6000	(100,500)	HOLD	\$T MASDEF command	“Parameter description for MASDEF” on page 213

Table 45. Initialization Statement - MASDEF (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
ENFSCOPE	N/A	SYSPLEX	N/A	\$T MASDEF operator command or cold start	“Parameter description for MASDEF” on page 213
ESUBSYS	N/A	HASP	N/A	Single-member warm start	“Parameter description for MASDEF” on page 213
HOLD	0-99999999	99999999	DORMANCY	\$T MASDEF command	“Parameter description for MASDEF” on page 213
LOCKOUT	500-15000	1000	N/A	\$T MASDEF command	“Parameter description for MASDEF” on page 213
OWNMEMB	1-4 characters	(See note below)	(See note below)	Single-member warm start	“Parameter description for MASDEF” on page 213
RESTART	N/A	NO	AUTOEMEM	\$T MASDEF command	“Parameter description for MASDEF” on page 213
SHARED	N/A	CHECK	N/A	\$T MASDEF command (not on warm start)	“Parameter description for MASDEF” on page 213
SYNCTOL	0-300	120	N/A	\$T MASDEF command	“Parameter description for MASDEF” on page 213
XCFGRPNM	N/A	Local node name	N/A	All-member warm start	“Parameter description for MASDEF” on page 213
Note: See the full description of this parameter in the parameter definition with this initialization statement.					

Table 46. Initialization Statement - MEMBER(xxxx)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - MEMBER(xxxx)					
NAME	1-4 characters	None. Must specify.	N/A	Single-member warm start	“Parameter Description for MEMBer” on page 218

Table 47. Initialization Statement - NAME					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - NAME					
member	1-8 characters	None. Must specify.	REP, VER	N/A	“Parameter Description for INCLUDE” on page 152
csect *	1-8 characters	None. Must specify.	REP, VER	N/A	“Parameter Description for NAME” on page 220

Table 48. Initialization Statement - NETACCT					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - NETACCT					
NACCT	1-8 characters	None. Must specify.	NTHRU	Single-member warm start	“Parameter Description for NETACCT” on page 221
NTHRU	1-8 characters	Value of NACCT	NACCT	Single-member warm start	“Parameter Description for NETACCT” on page 221
JACCT	1-4 characters	None. Must specify.	JTHRU	Single-member warm start	“Parameter Description for NETACCT” on page 221
JTHRU	1-4 characters	Value of JACCT	JACCT	Single-member warm start	“Parameter Description for NETACCT” on page 221
TYPE	N/A	None	/*NETACCT	Single-member warm start	“Parameter Description for NETACCT” on page 221 Jim

Table 49. Initialization Statement - NETSERV (nnn)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - NETSERV (nnn)					
nnn	1-999	N/A	NODE, SOCKET	Single-member warm start	“NETSERV(nnn) - Define NJE over TCP/IP server address space” on page 223
RESTART	0-1440	NO	N/A	\$T NETSRV command	“Parameter Description for NETSERV(1-nnn)” on page 224

<i>Table 49. Initialization Statement - NETSERV (nnn) (continued)</i>					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
SOCKET	1-8 characters	None. Must specify.	N/A	\$T NETSRV command	“Parameter Description for NETSERV(1-nnn)” on page 224
START	N/A	NO	N/A	N/A	“Parameter Description for NETSERV(1-nnn)” on page 224
STACK	0-8 characters	blanks (all stacks)	N/A	\$T NETSRV command	“Parameter Description for NETSERV(1-nnn)” on page 224
TRaceio	N/A	NO	N/A	\$T NETSRV command	“Parameter Description for NETSERV(1-nnn)” on page 224

<i>Table 50. Initialization Statement - NJEDEF</i>					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - NJEDEF					
CONNECT	1-1440	YES/10	APPL, LINE, NODE, and SOCKET	\$T NJEDEF command	“Parameter Description for NJEDEF” on page 227
DELAY	10-999	120	N/A	\$T NJEDEF command	“Parameter Description for NJEDEF” on page 227
HDRBUF	N/A	N/A	L(nnnnn).ST(m)	\$T NJEDEF command	“Parameter Description for NJEDEF” on page 227
JRNUM	0-7	1 (See note below)	SRNUM	Hot start	“Parameter Description for NJEDEF” on page 227
JTNUM	0-7	1 (See note below)	STNUM	Hot start	“Parameter Description for NJEDEF” on page 227
LINENUM	0-32767	0	LINE	Hot start	“Parameter Description for NJEDEF” on page 227
MAILMSG	N/A	NO	N/A	\$T NJEDEF command	“Parameter Description for NJEDEF” on page 227
MAXHOP	0-65535	0	N/A	\$T NJEDEF command	“Parameter Description for NJEDEF” on page 227

Table 50. Initialization Statement - NJEDEF (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
NODENUM	1-32767	1	NODE	All-member warm start (to increase) Cold start (to decrease)	“Parameter Description for NJEDEF” on page 227
OWNNODE	1-32767	1	N/A	Cold start	“Parameter Description for NJEDEF” on page 227
PATH	1-8	1	RESTTOL	Hot start	“Parameter Description for NJEDEF” on page 227
RESTMAX	0-79992000	79992000	N/A	\$T NJEDEF command	“Parameter Description for NJEDEF” on page 227
RESTNODE	1-2000	100	N/A	\$T NJEDEF command	“Parameter Description for NJEDEF” on page 227
RESTTOL	0-8000	0	PATH	\$T NJEDEF command	“Parameter Description for NJEDEF” on page 227
SRNUM	0-7	1 (See note below)	JRNUM	Hot start	“Parameter Description for NJEDEF” on page 227
STNUM	0-7	1 (See note below)	JTNUM	Hot start	“Parameter Description for NJEDEF” on page 227
TIMEtol	0-1500 minutes	1440	N/A	\$T NJEDEF command	“Parameter Description for NJEDEF” on page 227
Note: See the full description of this parameter in the parameter definition with this initialization statement.					

Table 51. Initialization Statement - NODE(xxxxxxxx)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - NODE(xxxxxxxx)					
xxxxxxxx	1-NODENUM on NJEDEF	None. Must specify.	NJEDEF	Single-member warm start (See note 1)	“Parameter Description for SOCKET(xxxxxxxx)” on page 408

Table 51. Initialization Statement - NODE(xxxxxxxx) (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
jxxxxxxx	1-8 characters	None. Must specify.	N/A	Single-member warm start (See note 2)	“Format Description for NODE(xxxxxxxx)” on page 231
COMPACT	0-99	0	APPL	\$T NODE(xxxxxxxx) command	“Parameter Description for NODE(xxxxxxxx)” on page 236
CONNECT	0-1440	NO	LINE, APPL, NJEDEF, and SOCKET	\$T NODE(xxxxxxxx) command	“Parameter Description for NODE(xxxxxxxx)” on page 236
Auth	N/A	(Device=Y, Job=Y, Net=N, System=YES)	N/A	\$T NODE(xxxxxxxx) command	“Parameter Description for NODE(xxxxxxxx)” on page 236
ENDNODE	N/A	NO	N/A	Hot start (at local node) \$T NODE(xxxxxxxx) command (for other nodes)	“Parameter Description for NODE(xxxxxxxx)” on page 236
HOLD	N/A	NONE	NJEDEF	\$T NODE(xxxxxxxx) command	“Parameter Description for NODE(xxxxxxxx)” on page 236
JES3_LOCAL_CHK	N/A	NO	N/A	\$T NODE(xxxxxxxx) command	“Parameter Description for NODE(xxxxxxxx)” on page 236
LINE	1-32767	None	APPL	\$T NODE(xxxxxxxx) command (for inactive node)	“Parameter Description for NODE(xxxxxxxx)” on page 236
LOGMODE	N/A	(See note 1)	APPL	\$T NODE(xxxxxxxx) command (for inactive node)	“Parameter Description for NODE(xxxxxxxx)” on page 236
LOGON	0-999		LOGON	\$T NODE(xxxxxxxx) command	“Parameter Description for NODE(xxxxxxxx)” on page 236
NAME	1-8 characters	Nnnnnn, where xxxxxxxx is subscript	DESTID	\$T NODE(xxxxxxxx) command (See notes below)	“Parameter Description for NODE(xxxxxxxx)” on page 236
Password	1-8 characters	None	N/A	\$T NODE(xxxxxxxx) command (See note 2)	“Parameter Description for NODE(xxxxxxxx)” on page 236

Table 51. Initialization Statement - NODE(xxxxxxxx) (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
PATHMGR	N/A	YES	CONNECT	\$T NODE(xxxxxxxx) command (for inactive node)	“Parameter Description for NODE(xxxxxxxx)” on page 236
PENCRYPT	N/A	NO	N/A	\$T NODE(xxxxxxxx) command	“Parameter Description for NODE(xxxxxxxx)” on page 236
PRIVATE	N/A	NO	N/A	\$T NODE(xxxxxxxx) command (for inactive node)	“Parameter Description for NODE(xxxxxxxx)” on page 236
RECeive	N/A	BOTH	N/A	\$T NODE(xxxxxxxx) command	“Parameter Description for NODE(xxxxxxxx)” on page 236
REST	2-8000	0	APPL	\$T NODE(xxxxxxxx) command	“Parameter Description for NODE(xxxxxxxx)” on page 236
SENTREST	N/A	ACCEPT	PATHMGR	\$T NODE(xxxxxxxx) command	“Parameter Description for NODE(xxxxxxxx)” on page 236
SUBnet	1-8 characters	None	N/A	\$T NODE(xxxxxxxx) command	“Parameter Description for NODE(xxxxxxxx)” on page 236
TRace	N/A	No	N/A	\$T NODE(xxxxxxxx) command	“Parameter Description for NODE(xxxxxxxx)” on page 236
TRAnsmit	N/A	BOTH	N/A	\$T NODE(xxxxxxxx) command	“Parameter Description for NODE(xxxxxxxx)” on page 236
Note: 1. See the full description of this parameter in the parameter definition with this initialization statement. 2. If you modify this parameter value and then restart JES2 with a hot start, the parameter value in effect before termination is used.					

Table 52. Initialization Statement - OFF(n).JR					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - OFF(n).JR					
n	1-8	None. Must Specify.	OFFLOAD	Single-member warm start	“OFF(n).JR - Offload Job Receiver” on page 242

Table 52. Initialization Statement - OFF(n).JR (continued)

Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Class	1-36 single character job classes or 1-8 multi-character job classes	Null	WS	\$T OFF(n).JR command	“Parameter Description for OFF(n).JR” on page 245
CREator	1-8 characters	Null	WS	\$T OFF(n).JR command	“Parameter Description for OFF(n).JR” on page 245
Hold	N/A	Null	N/A	\$T OFF(n).JR command	“Parameter Description for OFF(n).JR” on page 245
JOBname	1-8 characters	Null	N/A	\$T OFF(n).JR command	“Parameter Description for OFF(n).JR” on page 245
MOD	N/A	Null	N/A	\$T OFF(n).JR command	“Parameter Description for OFF(n).JR” on page 245
NOTify	N/A	NO	N/A	\$T OFF(n).JR command	“Parameter Description for OFF(n).JR” on page 245
RANGE (See note below)	1-2147483647	J1-2147483647	N/A	\$T OFF(n).JR command	“Parameter Description for OFF(n).JR” on page 245
Routecde	N/A	Null	N/A	\$T OFF(n).JR command	“Parameter Description for OFF(n).JR” on page 245
START	N/A	YES	\$S OFFLOAD	\$S OFF(n).JR command to start \$P OFF(n).JR command to stop	“Parameter Description for OFF(n).JR” on page 245
SYSaff	N/A	Null	N/A	\$T OFF(n).JR command	“Parameter Description for OFF(n).JR” on page 245
WS	(See note below)	(CLASS/)	N/A	\$T OFF(n).JR command	“Parameter Description for OFF(n).JR” on page 245
Note: See the full description of this parameter in the parameter definition with this initialization statement.					

Table 53. Initialization Statement - OFF(n).JT					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - OFF(n).JT					
n	1-8	None. Must Specify.	OFFLOAD	Single-member warm start	“OFF(n).JT - Offload Job Transmitter” on page 248
Class	1-36 single character job classes or 1-8 multi-character job classes	Null	WS	\$T OFF(n).JT command	Class
CREator	1-8 characters	Null	WS	\$T OFF(n).JT command	Class
DISP	N/A	DELETE	N/A	\$T OFF(n).JT command	Class
Hold	N/A	Null	N/A	\$T OFF(n).JT command	Class
JOBname	1-8 characters	Null	N/A	\$T OFF(n).JT command	Class
LIMIT	0-4294967295	0-4294967295	N/A	\$T OFF(n).JT command	Class
NOTify	N/A	NO	N/A	\$T OFF(n).JT command	Class
RANGE (See note below)	1-999,999	J1-999,999	N/A	\$T OFF(n).JT command	Class
Routecde	N/A	Null	N/A	\$T OFF(n).JT command	Class
START	N/A	YES	\$S OFFLOAD	\$S OFF(n).JT command to start \$P OFF(n).JT command to stop	Class
SYSaff	1-7 affinities	Null	N/A	\$T OFF(n).JT command	Class
Volume	5-6 characters	Null	N/A	\$T OFF(n).JT command	Class
WS	(See note below.)	(CLASS/)	N/A	\$T OFF(n).JT command	Class
Note: See the full description of this parameter in the parameter definition with this initialization statement.					

Table 54. Initialization Statement - OFF(n).SR					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - OFF(n).SR					
n	1-8	None. Must specify.	OFFLOAD(n)	Single-member warm start	"OFF(n).SR - Offload SYSOUT Receiver" on page 255
Burst	N/A	Null	N/A	\$T OFF(n).SR command	"Parameter Description for OFF(n).SR" on page 261
CReator	1-8 characters	Null	WS	\$T OFF(n).SR command	"Parameter Description for OFF(n).SR" on page 261
FC®B C	1-4 characters	Null	N/A	\$T OFF(n).SR command	"Parameter Description for OFF(n).SR" on page 261
FLash O	1-4 characters	Null	N/A	\$T OFF(n).SR command	"Parameter Description for OFF(n).SR" on page 261
Forms	1-8 characters	Null	N/A	\$T OFF(n).SR command	"Parameter Description for OFF(n).SR" on page 261
HOLD	N/A	Null	N/A	\$T OFF(n).SR command	"Parameter Description for OFF(n).SR" on page 261
JOBname	1-8 characters	Null	N/A	\$T OFF(n).SR command	"Parameter Description for OFF(n).SR" on page 261
MOD	N/A	Null	N/A	\$T OFF(n).SR command	"Parameter Description for OFF(n).SR" on page 261
NOTify	N/A	NO	N/A	\$T OFF(n).SR command	"Parameter Description for OFF(n).SR" on page 261
OUTDisp	N/A	Any disposition	N/A	\$T OFF(n).SR command	"Parameter Description for OFF(n).SR" on page 261
PRMode	1-8 characters	Null	N/A	\$T OFF(n).SR command	"Parameter Description for OFF(n).SR" on page 261
Queue	1-15 classes	null	N/A	\$T OFF(n).SR command	"Parameter Description for OFF(n).SR" on page 261
RANGE (See note below)	1-2147483647	J1-2147483647	N/A	\$T OFF(n).SR command	"Parameter Description for OFF(n).SR" on page 261

Table 54. Initialization Statement - OFF(n).SR (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Routecde	(See note below)	1-4 route codes	Null	\$T OFF(n).SR command	“Parameter Description for OFF(n).SR” on page 261
START	N/A	YES	N/A	\$S OFF(n).SR command to start \$P OFF(n).SR command to stop	“Parameter Description for OFF(n).SR” on page 261
UCS T	1-4 characters	Null	N/A	\$T OFF(n).SR command	“Parameter Description for OFF(n).SR” on page 261
Writer	1-8 characters	Null	N/A	\$T OFF(n).SR command	“Parameter Description for OFF(n).SR” on page 261
WS	(See note below)	(Q,OUTDisp)	N/A	\$T OFF(n).SR command	“Parameter Description for OFF(n).SR” on page 261
Note: See the full description of this parameter in the parameter definition with this initialization statement.					

Table 55. Initialization Statement - OFF(n).ST					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - OFF(n).ST					
n	1-8	None. Must specify.	OFFLOAD(n)	Single-member warm start	“OFF(n).ST - Offload SYSOUT Transmitter” on page 267
Burst	N/A	Null	N/A	\$T OFF(n).ST command	“Parameter Description for OFF(n).ST” on page 271
CREator	1-8 characters	Null	WS	\$T OFF(n).ST command	“Parameter Description for OFF(n).ST” on page 271
DISP	N/A	DELETE	N/A	\$T OFF(n).ST command	“Parameter Description for OFF(n).ST” on page 271
FCB C	1-4 characters	Null	N/A	\$T OFF(n).ST command	“Parameter Description for OFF(n).ST” on page 271
FLash O	1-4 characters	Null	N/A	\$T OFF(n).ST command	“Parameter Description for OFF(n).ST” on page 271

<i>Table 55. Initialization Statement - OFF(n).ST (continued)</i>					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Forms	1-8 characters	Null	N/A	\$T OFF(n).ST command	“Parameter Description for OFF(n).ST” on page 271
HOLD	N/A	Null	N/A	\$T OFF(n).ST command	“Parameter Description for OFF(n).ST” on page 271
JOBname	1-8 characters	Null	N/A	\$T OFF(n).ST command	“Parameter Description for OFF(n).ST” on page 271
LIMIT (See note below)	0-4294967295	0-4294967295	N/A	\$T OFF(n).ST command	“Parameter Description for OFF(n).ST” on page 271
NOTify	N/A	NO	N/A	\$T OFF(n).ST command	“Parameter Description for OFF(n).ST” on page 271
OUTDisp	N/A	WRITE and KEEP	N/A	\$T OFF(n).ST command	“Parameter Description for OFF(n).ST” on page 271
PLIM (See note below)	0-4294967295	0-4294967295	N/A	\$T OFF(n).ST command	“Parameter Description for OFF(n).ST” on page 271
PRMode	1-8 characters	Null	N/A	\$T OFF(n).ST command	“Parameter Description for OFF(n).ST” on page 271
Queue	1-15 classes	Null	N/A	\$T OFF(n).ST command	“Parameter Description for OFF(n).ST” on page 271
RANGE (See note below)	1-65534	J1-999999	N/A	\$T OFF(n).ST command	“Parameter Description for OFF(n).ST” on page 271
Routecde	(See note below)	N/A	Null	\$T OFF(n).ST command	“Parameter Description for OFF(n).ST” on page 271
START	N/A	YES	N/A	\$S OFF(n).ST command to start \$P OFF(n).ST command to stop	“Parameter Description for OFF(n).ST” on page 271
UCS T	1-4 characters	Null	N/A	\$T OFF(n).ST command	“Parameter Description for OFF(n).ST” on page 271

<i>Table 55. Initialization Statement - OFF(n).ST (continued)</i>					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Volume (See note below)	5-6 characters	Null	N/A	\$T OFF(n).ST command	“Parameter Description for OFF(n).ST” on page 271
Writer	1-8 characters	Null	N/A	\$T OFF(n).ST command	“Parameter Description for OFF(n).ST” on page 271
WS	(See note below)	(Q,OUTDisp)	N/A	\$T OFF(n).ST command	“Parameter Description for OFF(n).ST” on page 271
Note: See the full description of this parameter in the parameter definition with this initialization statement.					

<i>Table 56. Initialization Statement - OFFLOAD(n)</i>					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - OFFLOAD(n)					
n	1-8	None. Must specify.	OFF(n).Jx, OFF(n).Sx	Single-member warm start	“OFFLOAD(n) - Offload Device” on page 278
ARCHIVE	N/A	ONE	N/A	\$T OFFLOAD(n) command	“Parameter Description for OFFLOAD(n)” on page 280
DSN (See note below)	1-44 characters	None. Must specify.	N/A	\$T OFFLOAD(n) command	“Parameter Description for OFFLOAD(n)” on page 280
LABEL (See note below)	N/A	SL	N/A	\$T OFFLOAD(n) command	“Parameter Description for OFFLOAD(n)” on page 280
PROTECT (See note below)	N/A	NO	N/A	\$T OFFLOAD(n) command	“Parameter Description for OFFLOAD(n)” on page 280
RETPD (See note below)	1-9999	30	N/A	\$T OFFLOAD(n) command	“Parameter Description for OFFLOAD(n)” on page 280
UNIT (See note below)	1-59	1	N/A	\$T OFFLOAD(n) command	“Parameter Description for OFFLOAD(n)” on page 280

<i>Table 56. Initialization Statement - OFFLOAD(n) (continued)</i>					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
VALIDATE	N/A	YES	N/A	\$T OFFLOAD(n) command	“Parameter Description for OFFLOAD(n)” on page 280
VOLS	1-255	255	N/A	\$T OFFLOAD(n) command	“Parameter Description for OFFLOAD(n)” on page 280
Note: See the full description of this parameter in the parameter definition with this initialization statement.					

<i>Table 57. Initialization Statement - OPTsdef</i>					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - OPTsdef					
CKPTOPT	N/A	(See note below)	CKPTDEF	Hot start	OPTsdef Parameters
COLD_START_MODE	N/A	DEFAULT	UNACT	Hot start	OPTsdef Parameters
CONSOLE (See note below)	N/A	NO	CONSOLE start option	Hot start	OPTsdef Parameters
LIST	N/A	(See note below)	LISTOPT	Hot start	OPTsdef Parameters
LISTOPT	N/A	(See note below)	LISTOPT start option	Hot start	OPTsdef Parameters
LOG	N/A	(See note below)	LOGOPT	Hot start	OPTsdef Parameters
LOGOPT	N/A	(See note below)	LOGOPT start option	Hot start	OPTsdef Parameters
RECONFIG	N/A	(See note below)	RECONFIG start option	Hot start	OPTsdef Parameters
REQMSG	N/A	(See note below)	REQ start option	Hot start	OPTsdef Parameters
SPOOL (See note below)	N/A	NOVALIDATE	SPOOL start option	All-member warm start	OPTsdef Parameters
Note: See the full description of this parameter in the parameter definition with this initialization statement.					

Table 58. Initialization Statement - OUTCLASS(v)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - OUTCLASS(v)					
v (See note 2)	A-Z, 0-9	None. Must specify.	SYSOUT	Single-member warm start	“OUTCLASS(v) - SYSOUT Class Characteristics” on page 285
COMPRESS	N/A	NO	N/A	\$T OUTCLASS(v)	“Parameter Description for OUTCLASS(v)” on page 287
BLNKTRNC	N/A	YES	N/A	Single-member warm start	“Parameter Description for OUTCLASS(v)” on page 287
OUTDisp	N/A	(See notes 1 and 2)	N/A	\$T OUTCLASS(v) command (See notes below)	“Parameter Description for OUTCLASS(v)” on page 287
OUTPUT	N/A	PRINT	N/A	Single-member warm start	“Parameter Description for OUTCLASS(v)” on page 287
TRKCELL	N/A	YES	N/A	Single-member warm start	“Parameter Description for OUTCLASS(v)” on page 287
Note: 1. See the full description of this parameter in the parameter definition with this initialization statement. 2. If you modify this parameter value and then restart JES2 with a hot start, the parameter value in effect before termination is used.					

Table 59. Initialization Statement - OUTDEF					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - OUTDEF					
COPIES	1-255	255	/*JOBPARM (See note 2.)	\$T OUTDEF command	“Parameter Description for OUTDEF” on page 289
DMNDSET	N/A	NO	USERSET	Single-member warm start	“Parameter Description for OUTDEF” on page 289
DSLIMIT	N/A	10M	N/A	\$T OUTDEF command	“Parameter Description for OUTDEF” on page 289

Table 59. Initialization Statement - OUTDEF (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
JOENUM	10-2,500,000 (See note 6)	2.5 x (JOBNUM on JOBDEF)	JOBDEF	\$T OUTDEF command (See note 5)	“Parameter Description for OUTDEF” on page 289
JOEWARN	1–99	80	N/A	\$T OUTDEF command (See note 5)	“Parameter Description for OUTDEF” on page 289
LDEV_OPT	N/A	NO	N/A	\$T OUTDEF command	“Parameter Description for OUTDEF” on page 289
OUTTIME	N/A	CREATE	N/A	\$T OUTDEF command	“Parameter Description for OUTDEF” on page 289
PRTYHIGH	0-255	255	N/A	\$T OUTDEF command (See note 5)	“Parameter Description for OUTDEF” on page 289
PRTYLOW	0-255	0	PRTYRATE on JOBDEF	\$T OUTDEF command (See note 5)	“Parameter Description for OUTDEF” on page 289
PRTYOUT	N/A	NO	PRTY(JCL)* (See note 3)	\$T OUTDEF command	“Parameter Description for OUTDEF” on page 289
PRYORATE	0-1440	0	PRTY(JCL) (See note 3)	\$T OUTDEF command (See note 5)	“Parameter Description for OUTDEF” on page 289
SAPI_OPT	N/A	NO	N/A	\$T OUTDEF command (See notes below)	“Parameter Description for OUTDEF” on page 289
SEGLIM	1-99999	100	N/A	\$T OUTDEF command (See notes below)	“Parameter Description for OUTDEF” on page 289
STDFORM	1-8 characters	STD	N/A	Single-member warm start	“Parameter Description for OUTDEF” on page 289
USERSET	N/A	NO	PRTY(JCL) (See note 3)	Single-member warm start	“Parameter Description for OUTDEF” on page 289

Table 59. Initialization Statement - OUTDEF (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
WS_OPT	N/A	NO	N/A	\$T OUTDEF command Single-member warm start	“Parameter Description for OUTDEF” on page 289
Note: 1. See the full description of this parameter in the parameter definition with this initialization statement. 2. If you modify this parameter value and then restart JES2 with a hot start, the parameter value in effect before termination is used. 3. This refers to the PRTY parameter on the JCL OUTPUT statement. 4. If you modify this parameter value and then restart JES2 with any type of warm or hot start, the parameter value in effect before termination is used. 5. This parameter cannot be modified through a hot start, quick start, or single-member warm start. 6. This parameter can be increased by using a \$T OUTDEF command after an \$ACTIVATE command is issued in the MAS.					

Table 60. Initialization Statement - OUTPRTY(n)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - OUTPRTY(n)					
n	1-9	None. Must specify.	N/A	Single-member warm start	“OUTPRTY(n) - Job Output Priority” on page 292
PAGE	1-16777215	(See note below)	TIME on JOBDEF	\$T OUTPRTY(n) command	“Parameter Description for OUTPRTY(n)” on page 293
PRIORITY	0-255	(See note below)	PAGE, RECORD	\$T OUTPRTY(n) command	“Parameter Description for OUTPRTY(n)” on page 293
RECORD	1-16777215	(See note below)	PRIORITY	\$T OUTPRTY(n) command	“Parameter Description for OUTPRTY(n)” on page 293
Note: See the full description of this parameter in the parameter definition with this initialization statement.					

Table 61. Initialization Statement - PCEDEF					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - PCEDEF					

<i>Table 61. Initialization Statement - PCEDEF (continued)</i>					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
CNVTNUM	1-25	10	N/A	Hot start	“Parameter Description for PCEDEF” on page 295
OUTNUM	1-25	10	N/A	Hot start	“Parameter Description for PCEDEF” on page 295
PSONUM	1-10	2	N/A	Hot start	“Parameter Description for PCEDEF” on page 295
PURGENUM	1-25	10	N/A	Hot start	“Parameter Description for PCEDEF” on page 295
SPINNUM	3-10	3	N/A	Hot start	“Parameter Description for PCEDEF” on page 295
STACNUM	1-10	2	TSO/E STATUS and CANCEL	Hot start	“Parameter Description for PCEDEF” on page 295

<i>Table 62. Initialization Statement - PRINTDEF</i>					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - PRINTDEF					
CCWNUM	1-233	BUFSIZE / 80	SPOOLDEF	Single-member warm start	“Parameter Description for PRINTDEF” on page 298
DBLBUFR	N/A	YES	N/A	Single-member warm start	“Parameter Description for PRINTDEF” on page 298
FCB	1-4 characters	6	PRT(nnnn)	Single-member warm start	“Parameter Description for PRINTDEF” on page 298
LINECT	0-254	61	/*JOBPARM, / *OUTPUT, JCL JOB, JCL OUTPUT	\$T PRINTDEF command	“Parameter Description for PRINTDEF” on page 298
NEWPAGE	N/A	ALL	PRT(nnnn) R(nnnn).PR(m)	\$T PRINTDEF command	“Parameter Description for PRINTDEF” on page 298
NIFCB	1-4 characters	****	PRT(nnnn)	Single-member warm start	“Parameter Description for PRINTDEF” on page 298

<i>Table 62. Initialization Statement - PRINTDEF (continued)</i>					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
NIFLASH	1-4 characters	****	PRT(nnnn)	Single-member warm start	“Parameter Description for PRINTDEF” on page 298
NIUCS	1-8 characters	GF10	PRT(nnnn)	Single-member warm start	“Parameter Description for PRINTDEF” on page 298
RDBLBUFR	N/A	NO	R(nnnn).PR(m)	Single-member warm start	“Parameter Description for PRINTDEF” on page 298
SEPPAGE	N/A	(See note below)	N/A	\$T PRINTDEF command	“Parameter Description for PRINTDEF” on page 298
TRANS	N/A	YES	N/A	Single-member warm start	“Parameter Description for PRINTDEF” on page 298
UCS	1-4 characters	0	N/A	Single-member warm start	“Parameter Description for PRINTDEF” on page 298
Note: See the full description of this parameter in the parameter definition with this initialization statement.					

<i>Table 63. Initialization Statement - PROCLib</i>					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - PROCLib					
xxxxxxxx	1–8	(See note below)	N/A	Operator command	“Parameter description for PROCLIB” on page 304
DD(nnn)	N/A	(See note below)	N/A	Operator command	“Parameter description for PROCLIB” on page 304
DSName	1–44,1–8	(See note below)	N/A	Operator command	“Parameter description for PROCLIB” on page 304
UNIT	N/A	(See note below)	N/A	Operator command	“Parameter description for PROCLIB” on page 304
VOLser	1–6 characters	(See note below)	N/A	Operator command	“Parameter description for PROCLIB” on page 304
UNCONDitional CONDitional	N/A	(See note below)	N/A	Operator command	“Parameter description for PROCLIB” on page 304

Table 63. Initialization Statement - PROCLib (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
NAME	N/A	(See note below)	N/A	Operator command	“Parameter description for PROCLIB” on page 304
Note: See the full description of this parameter in the parameter definition with this initialization statement.					

Table 64. Initialization Statement - PRT(nnnn)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - PRT(nnnn)					
nnnn (See note 1)	1-32767	None	PRINTDEF	Single-member warm start (See note 3)	“PRT(nnnnn) - Local Printer” on page 306
BURST	N/A	NO	SYSOUT	\$T PRTnnnnn command (See note 3)	“Parameter Description for Non-Impact Printers (JES & FSS mode)” on page 325
CKPTLINE	0-32767	0	/*JOBPARM	\$T PRTnnnnn command	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313
CKPTPAGE	0-32767	100	CKPTLINE	\$T PRTnnnnn command	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313
Class Queue	1-15 classes	AJ	SYSOUT	\$T PRTnnnnn command	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313
CREATOR	1-8 characters	Null	N/A	\$T PRTnnnnn command	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313
DEVFCB	1-4 characters	None	N/A	\$T PRTnnnnn command	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313
FCB C	1-4 characters	FCB NIFCB on PRINTDEF	PRINTDEF, DEVFCB	\$T PRTnnnnn command (See note 3)	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313
FLASH O	1-4 characters	NIFLASH on PRINTDEF	PRINTDEF	\$T PRTnnnnn command (See note 3)	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313

<i>Table 64. Initialization Statement - PRT(nnnn) (continued)</i>					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Forms	1-8 characters	STDFORM on OUTDEF	OUTDEF	\$T PRTnnnnn command (See note 3)	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313
JOBname	1-8 characters	Null	N/A	\$T PRTnnnnn command	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313
LIMit	0-4294967295	0-4294967295	N/A	\$T PRTnnnnn command	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313
MARK	N/A	NO	MODE	\$T PRTnnnnn command (See note 3)	“Parameter Description for Non-Impact Printers (JES & FSS mode)” on page 325
MODE	N/A	(See note 1)	FSS, UNIT	\$T PRTnnnnn command	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313
NEWPAGE	N/A	DEFAULT	PRINTDEF	\$T PRTnnnnn command	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313
Pause	N/A	NO	N/A	\$T PRTnnnnn command	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313
PRMode	1-8 characters	LINE	PRTY(JCL) (See note 2)	\$T PRTnnnnn command	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313
Range (See notes below)	1-65534	J1-999999	N/A	\$T PRTnnnnn command	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313
Routecde	1-4 route codes	LOCAL	/*ROUTE, / *OUTPUT, JCL OUTPUT	\$T PRTnnnnn command	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313
Sep	N/A	YES	PRINTDEF	\$T PRTnnnnn command (See note 3)	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313
SEPCHARS	N/A	DEFAULT	PRINTDEF	\$T PRTnnnnn command	“Parameter Description for Non-Impact Printers (JES & FSS mode)” on page 325
SEPDS	N/A	NO	N/A	\$T PRTnnnnn command (See note 3)	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313

<i>Table 64. Initialization Statement - PRT(nnnn) (continued)</i>					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
SETUP	N/A	HALT	N/A	\$T PRTnnnnn command (See note 3)	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313
START	N/A	YES	FSS, UNIT	\$S PRT(nnnnn) command -- or -- \$P PRT(nnnnn) command	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313
TRACE	N/A	NO	TRACEDEF	\$T PRTnnnnn command (See note 3)	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313
TRANS	N/A	DEFAULT	PRINTDEF	\$T PRTnnnnn command	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313
TRKCELL	N/A	NO	PRINTDEF	\$T PRTnnnnn command (See note 3)	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313
UCS T	1-4 characters	UCS NIUCS on PRINTDEF	PRINTDEF	\$T PRTnnnnn command (See note 3)	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313
UCSVerify	N/A	NO	N/A	\$T PRTnnnnn command	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313
UNIT	Device addresses	Null	N/A	\$T PRTnnnnn command (See note 3)	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313
Volume	5-6 characters	Null	N/A	\$T PRTnnnnn command	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313
Writer	1-8 characters	None	N/A	\$T PRTnnnnn command	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313
WS	N/A (See note 1)	(W,Q,r,PRM/ F,T,C)	N/A	\$T PRTnnnnn command	“Parameter Description for PRT(nnnnn) (All Printers)” on page 313

Table 64. Initialization Statement - PRT(nnnn) (continued)

Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Note: 1. See the full description of this parameter in the parameter definition with this initialization statement. 2. This refers to the PRTY parameter on the JCL OUTPUT statement. 3. For FSS-controlled printers only, if you modify this parameter value and then reconnect the printer on a hot start, the value in effect before termination is used.					

Table 65. Initialization Statement - PRT(nnnn) (FSS-only parameters)

Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - PRT(nnnn) (FSS-only parameters)					
nnnnn	1-32767	None (See note 2)	PRINTDEF	Single-member warm start	“PRT(nnnnn) - Local Printer” on page 306
CKPTMODE	N/A	PAGE	CKPTPAGE, CKPTSEC	\$T PRTnnnnn command	“Parameter Description for FSS Printers Only:” on page 323
CKPTSEC	0-32767	0	TIMECKPT	\$T PRTnnnnn command	“Parameter Description for FSS Printers Only:” on page 323
COPYMARK	N/A	DATASET	MODE	\$T PRTnnnnn command (See note 2)	“Parameter Description for FSS Printers Only:” on page 323
FSS	1-8 characters	None	MODE	\$T PRTnnnnn command	“Parameter Description for FSS Printers Only:” on page 323
MODE	N/A	(See note 2)	FSS	\$T PRTnnnnn command	“Parameter Description for FSS Printers Only:” on page 323
NPRO	0-3600	300	FSS (See note below.)	\$T PRTnnnnn command	“Parameter Description for FSS Printers Only:” on page 323
PLIM	0-4294967295	0-4294967295	N/A	\$T PRTnnnnn command	“Parameter Description for FSS Printers Only:” on page 323
PRESELCT	N/A	YES	N/A	\$T PRTnnnnn command (See note 2)	“Parameter Description for FSS Printers Only:” on page 323

Table 65. Initialization Statement - PRT(nnnn) (FSS-only parameters) (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Note: 1. See the full description of this parameter in the parameter definition with this initialization statement. 2. For FSS-controlled printers only, if you modify this parameter value and then reconnect the printer on a hot start, the value in effect before termination is used.					

Table 66. Initialization Statement - PUN(nn)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - PUN(nn)					
nn	1-99	N/A (See note 3.)	N/A	Single-member warm start	“PUN(nn) - Local Card Punch” on page 326
Class Queue	1-15 classes	BK	N/A	\$T PUNnn command	“Parameter Description for PUN(nn)” on page 330
CKPTLINE	0-32767	100	CKPTPAGE	\$T PUNnn command	“Parameter Description for PUN(nn)” on page 330
CKPTPAGE	1-32767	1	CKPTLINE	\$T PUNnn command	“Parameter Description for PUN(nn)” on page 330
CRreator	1-8 characters	Null	N/A	\$T PUNnn command	“Parameter Description for PUN(nn)” on page 330
Forms	1-8 characters	STDFORM on OUTDEF	OUTDEF	\$T PUNnn command	“Parameter Description for PUN(nn)” on page 330
JOBname	1-8 characters	Null	N/A	\$T PUNnn command	“Parameter Description for PUN(nn)” on page 330
LIMit	0-4294967295	0-4294967295	N/A	\$T PUNnn command	“Parameter Description for PUN(nn)” on page 330
Pause	N/A	NO	N/A	\$T PUNnn command	“Parameter Description for PUN(nn)” on page 330
PRMode	1-8 characters	LINE	PRTY(JCL) (See note 2)	\$T PUNnn command	“Parameter Description for PUN(nn)” on page 330
RANGE	1-65534	J1-999999	N/A	\$T PUNnn command	“Parameter Description for PUN(nn)” on page 330

Table 66. Initialization Statement - PUN(nn) (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Routecde	1-4 route codes	LOCAL	/*OUTPUT, / *ROUTE, JCL OUTPUT	\$T PUNnn command	“Parameter Description for PUN(nn)” on page 330
Sep	N/A	YES	N/A	\$T PUNnn command	“Parameter Description for PUN(nn)” on page 330
SETUP	N/A	HALT	N/A	\$T PUNnn command	“Parameter Description for PUN(nn)” on page 330
SEPDS	N/A	NO	N/A	\$T PUNnn command	“Parameter Description for PUN(nn)” on page 330
START	N/A	YES	UNIT	\$S PUNnnnn command -- or -- \$P PUNnnnn command	“Parameter Description for PUN(nn)” on page 330
TRACE	N/A	YES	TRACEDEF	\$T PUNnn command	“Parameter Description for PUN(nn)” on page 330
UNIT	Device addresses	Null	N/A	\$T PUNnn command	“Parameter Description for PUN(nn)” on page 330
Volume	5-6 characters	None	N/A	\$T PUNnn command	“Parameter Description for PUN(nn)” on page 330
Writer	1-8 characters	None	N/A	\$T PUNnn command	“Parameter Description for PUN(nn)” on page 330
WS	N/A	(W,Q,R,PRM/F)	N/A	\$T PUNnn command	“Parameter Description for PUN(nn)” on page 330
Note: 1. See the full description of this parameter in the parameter definition with this initialization statement. 2. This refers to the PRTY parameter on the JCL OUTPUT statement.					

Table 67. Initialization Statement - PUNCHDEF					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - PUNCHDEF					

Table 67. Initialization Statement - PUNCHDEF (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
CCWNUM	1-235	BUFSIZE on SPOOLDEF / 80	SPOOLDEF	Single-member warm start	“Parameter Description for PUNCHDEF” on page 336
DBLBUFR	N/A	NO	N/A	Single-member warm start	“Parameter Description for PUNCHDEF” on page 336
RDBLBUFR	N/A	NO	R(nnnnn).PU(m)	Single-member warm start	“Parameter Description for PUNCHDEF” on page 336

Table 68. Initialization Statement - R(nnnn).PR(m)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - R(nnnn).PR(m)					
nnnnn	1-RMT(nnnnn)	None	RMT(nnnnn)	Single-member warm start	“Parameter Description for R(nnnn).PR(m)” on page 343
m	1-7	None	RMT(nnnnn)	Single-member warm start	“Parameter Description for R(nnnn).PR(m)” on page 343
ASIS	1-7	NO	RMT(nnnnn)	\$T Rnnnnn.PRm command	“Parameter Description for R(nnnn).PR(m)” on page 343
CCTL	N/A	YES	SELECT	\$T Rnnnnn.PRm command	“Parameter Description for R(nnnn).PR(m)” on page 343
CKPTLINE	0-32767	0	/*JOBPARM, / *OUTPUT, JCL OUTPUT	\$T Rnnnnn.PRm command	“Parameter Description for R(nnnn).PR(m)” on page 343
CKPTPAGE	1-32767	1	CKPTLINE	\$T Rnnnnn.PRm command	“Parameter Description for R(nnnn).PR(m)” on page 343

<i>Table 68. Initialization Statement - R(nnnn).PR(m) (continued)</i>					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Class Queue	1-15 classes	AJ	N/A	\$T Rnnnnn.PRm command	“Parameter Description for R(nnnn).PR(m)” on page 343
CMPCT	N/A	Value on RMT(nnnnn)	RMT(nnnnn)	\$T Rnnnnn.PRm command	“Parameter Description for R(nnnn).PR(m)” on page 343
COMPACT	0-99	0	RMT(nnnnn)	\$T Rnnnnn.PRm command	“Parameter Description for R(nnnn).PR(m)” on page 343
COMPRESS	N/A	Value on RMT(nnnnn)	RMT(nnnnn)	\$T Rnnnnn.PRm command	“Parameter Description for R(nnnn).PR(m)” on page 343
CREATOR	1-8 characters	Null	N/A	\$T Rnnnnn.PRm command	“Parameter Description for R(nnnn).PR(m)” on page 343
DEVFCB	1-4 characters	None	N/A	\$T Rnnnnn.PRm command	“Parameter Description for R(nnnn).PR(m)” on page 343
EJECT	N/A	YES	N/A	\$T Rnnnnn.PRm command	“Parameter Description for R(nnnn).PR(m)” on page 343
FCB C	1-4 characters	FCB NIFCB on PRINTDEF	PRINTDEF	\$T Rnnnnn.PRm command	“Parameter Description for R(nnnn).PR(m)” on page 343
FCBLOAD	N/A	NO	RMT(nnnnn)	\$T Rnnnnn.PRm command	“Parameter Description for R(nnnn).PR(m)” on page 343
Forms	1-8 characters	STDFORM on OUTDEF	OUTDEF	\$T Rnnnnn.PRm command	“Parameter Description for R(nnnn).PR(m)” on page 343
JOBname	1-8 characters	Null	N/A	\$T Rnnnnn.PRm command	“Parameter Description for R(nnnn).PR(m)” on page 343

<i>Table 68. Initialization Statement - R(nnnn).PR(m) (continued)</i>					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
LIMit	0-4294967295	0-4294967295	N/A	\$T Rnnnnn.PRm command	"Parameter Description for R(nnnn).PR(m)" on page 343
LRECL	1-255	120	PRWIDTH	\$T Rnnnnn.PRm command	"Parameter Description for R(nnnn).PR(m)" on page 343
NEWPAGE	N/A	DEFAULT	PRINTDEF	\$T Rnnnnn.PRm command	"Parameter Description for R(nnnn).PR(m)" on page 343
PRMode	1-8 characters	LINE (See note 1)	PRTY(JCL) (See note 2)	\$T Rnnnnn.PRm command	"Parameter Description for R(nnnn).PR(m)" on page 343
PRWIDTH	1-255	120	LRECL	\$T Rnnnnn.PRm command	"Parameter Description for R(nnnn).PR(m)" on page 343
RANGE	1-65534	J1-999999	N/A	\$T Rnnnnn.PRm command	"Parameter Description for R(nnnn).PR(m)" on page 343
Routecde	1-4 route codes	Rnnnn	RMT(nnnnn)	\$T Rnnnnn.PRm command	"Parameter Description for R(nnnn).PR(m)" on page 343
SELECT	N/A	PRINTnn	LRECL, CCTL	\$T Rnnnnn.PRm command	"Parameter Description for R(nnnn).PR(m)" on page 343
Sep	N/A	YES	PRINTDEF	\$T Rnnnnn.PRm command	"Parameter Description for R(nnnn).PR(m)" on page 343
SEPDS	N/A	NO	N/A	\$T Rnnnnn.PRm command	"Parameter Description for R(nnnn).PR(m)" on page 343
SETUP	N/A	HALT	N/A	\$T Rnnnnn.PRm command	"Parameter Description for R(nnnn).PR(m)" on page 343

Table 68. Initialization Statement - R(nnnn).PR(m) (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
START	N/A	YES	N/A	\$S Rnnnnn.PRTm command -- or -- \$P Rnnnnn.PRTm command	"Parameter Description for R(nnnn).PR(m)" on page 343
SUSPEND	N/A	YES	N/A	\$T Rnnnnn.PRm command	"Parameter Description for R(nnnn).PR(m)" on page 343
TRACE	N/A	YES	TRACEDEF	\$T Rnnnnn.PRm command	"Parameter Description for R(nnnn).PR(m)" on page 343
TRANS	N/A	DEFAULT	PRINTDEF	\$T Rnnnnn.PRm command (inactive only)	"Parameter Description for R(nnnn).PR(m)" on page 343
UCS T	1-4 characters	UCS on PRINTDEF	PRINTDEF	\$T Rnnnnn.PRm command	"Parameter Description for R(nnnn).PR(m)" on page 343
Volume	5-6 characters	Null	N/A	\$T Rnnnnn.PRm command	"Parameter Description for R(nnnn).PR(m)" on page 343
Writer	1-8 characters	None	N/A	\$T Rnnnnn.PRm command	"Parameter Description for R(nnnn).PR(m)" on page 343
WS	N/A	(W,Q,R,PRM, LIM/F)	N/A	\$T Rnnnnn.PRm command	"Parameter Description for R(nnnn).PR(m)" on page 343
Note: 1. See the full description of this parameter in the parameter definition with this initialization statement. 2. This refers to the PRTY parameter on the JCL OUTPUT statement.					

Table 69. Initialization Statement - R(nnnn).PU(m)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - R(nnnn).PU(m)					

Table 69. Initialization Statement - R(nnnnn).PU(m) (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
nnnnn	1-RMT(nnnnn)	None	RMT(nnnnn)	Single-member warm start	“R(nnnnn).PU(m) - Remote Card Punch” on page 353
m	1-7	None	RMT(nnnnn)	Single-member warm start	“Parameter Description for R(nnnnn).PU(m)” on page 357
CCTL	N/A	YES	SELECT	\$T Rnnnnn.PUm command	“Parameter Description for R(nnnnn).PU(m)” on page 357
CKPTLINE	1-32767	100	N/A	\$T Rnnnnn.PUm command	“Parameter Description for R(nnnnn).PU(m)” on page 357
CKPTPAGE	1-32767	1	N/A	\$T Rnnnnn.PUm command	“Parameter Description for R(nnnnn).PU(m)” on page 357
Class Queue	1-15 classes	BK	N/A	\$T Rnnnnn.PUm command	“Parameter Description for R(nnnnn).PU(m)” on page 357
CMPCT	N/A	Value on RMT(nnnnn)	RMT(nnnnn)	\$T Rnnnnn.PUm command	“Parameter Description for R(nnnnn).PU(m)” on page 357
COMPACT	0-99	0	RMT(nnnnn)	\$T Rnnnnn.PUm command	“Parameter Description for R(nnnnn).PU(m)” on page 357
COMPRESS	N/A	Value on RMT(nnnnn)	RMT(nnnnn)	\$T Rnnnnn.PUm command	“Parameter Description for R(nnnnn).PU(m)” on page 357
CREATOR	1-8 characters	Null	N/A	\$T Rnnnnn.PUm command	“Parameter Description for R(nnnnn).PU(m)” on page 357
FLUSH	YES NO	YES	YES	\$T Rnnnnn.PUm command	“Parameter Description for R(nnnnn).PU(m)” on page 357

<i>Table 69. Initialization Statement - R(nnnnn).PU(m) (continued)</i>					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Forms	1-8 characters	STDFORM on OUTDEF	OUTDEF	\$T Rnnnnnn.PUm command	“Parameter Description for R(nnnnn).PU(m)” on page 357
JOBname	1-8 characters	Null	N/A	\$T Rnnnnnn.PUm command	“Parameter Description for R(nnnnn).PU(m)” on page 357
LIMit	1-4294967295	1-4294967295	N/A	\$T Rnnnnnn.PUm command	“Parameter Description for R(nnnnn).PU(m)” on page 357
LRECL	1-255	80	N/A	\$T Rnnnnnn.PUm command	“Parameter Description for R(nnnnn).PU(m)” on page 357
PRMode	1-8 characters	LINE (See notes below)	PRTY(JCL)* (See note 2)	\$T Rnnnnnn.PUm command	“Parameter Description for R(nnnnn).PU(m)” on page 357
RANGE	1-65534	J1-65534	N/A	\$T Rnnnnnn.PUm command	“Parameter Description for R(nnnnn).PU(m)” on page 357
Routecde	1-4 route codes	Rnnnn	RMT(nnnnn)	\$T Rnnnnnn.PUm command	“Parameter Description for R(nnnnn).PU(m)” on page 357
SELECT	N/A	PUNCHnn	CCTL, LRECL	\$T Rnnnnnn.PUm command	“Parameter Description for R(nnnnn).PU(m)” on page 357
Sep	N/A	YES	N/A	\$T Rnnnnnn.PUm command	“Parameter Description for R(nnnnn).PU(m)” on page 357
SEPDS	N/A	NO	N/A	\$T Rnnnnnn.PUm command	“Parameter Description for R(nnnnn).PU(m)” on page 357
SETUP	N/A	HALT	N/A	\$T Rnnnnnn.PUm command	“Parameter Description for R(nnnnn).PU(m)” on page 357

Table 69. Initialization Statement - R(nnnn).PU(m) (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
START	N/A	YES	N/A	\$S Rnnnnn.PUm command -- or -- \$P Rnnnnn.PUm command	"Parameter Description for R(nnnnn).PU(m)" on page 357
SUSPEND	N/A	YES	N/A	\$T Rnnnnn.PUm command	"Parameter Description for R(nnnnn).PU(m)" on page 357
TRACE	N/A	YES	TRACEDEF	\$T Rnnnnn.PUm command	"Parameter Description for R(nnnnn).PU(m)" on page 357
Volume	5-6 characters	Null	N/A	\$T Rnnnnn.PUm command	"Parameter Description for R(nnnnn).PU(m)" on page 357
Writer	1-8 characters	None	N/A	\$T Rnnnnn.PUm command	"Parameter Description for R(nnnnn).PU(m)" on page 357
WS	N/A	(W,Q,R,PRM, LIM/F)	N/A	\$T Rnnnnn.PUm command	"Parameter Description for R(nnnnn).PU(m)" on page 357
Note: 1. See the full description of this parameter in the parameter definition with this initialization statement. 2. This refers to the PRTY parameter on the JCL OUTPUT statement.					

Table 70. Initialization Statement - R(nnnn).RD(m)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - R(nnnn).RD(m)					
nnnnn	1-RMT(nnnnn)	None	RMT(nnnnn)	Single-member warm start	"R(nnnnnn).RD(m) - Remote Card Reader" on page 364
m	1-7	None	N/A	Single-member warm start	"R(nnnnnn).RD(m) - Remote Card Reader" on page 364

Table 70. Initialization Statement - R(nnnn).RD(m) (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Class	1-15 classes	A	N/A	\$T Rnnnnn.RDm command	"Parameter Description for R(nnnnnn).RD(m)" on page 366
HOLD	N/A	NO	N/A	\$T Rnnnnn.RDm command	"Parameter Description for R(nnnnnn).RD(m)" on page 366
MSGCLASS	A-Z, 0-9	A	JOB	\$T Rnnnnn.RDm command	"Parameter Description for R(nnnnnn).RD(m)" on page 366
PRIOINC	0-15	0	PRIOLIM	Command	"Parameter Description for R(nnnnnn).RD(m)" on page 366
PRIOLIM	0-15	15	PRIOINC	\$T Rnnnnn.RDm command	"Parameter Description for R(nnnnnn).RD(m)" on page 366
PRTDEST	N/A	Route code on RMT	/*ROUTE	\$T Rnnnnn.RDm command	"Parameter Description for R(nnnnnn).RD(m)" on page 366
PUNDEST	N/A	Route code on RMT	/*ROUTE	\$T Rnnnnn.RDm command	"Parameter Description for R(nnnnnn).RD(m)" on page 366
START	N/A	YES	N/A	\$S Rnnnnn.RDm command -- or -- \$P Rnnnnn.RDm command	"Parameter Description for R(nnnnnn).RD(m)" on page 366
TRACE	N/A	YES	TRACEDEF	\$T Rnnnnn.RDm command	"Parameter Description for R(nnnnnn).RD(m)" on page 366
XEQDEST	N/A	LOCAL	N/A	\$T Rnnnnn.RDm command	"Parameter Description for R(nnnnnn).RD(m)" on page 366

Table 71. Initialization Statement - RDRnn					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - RDRnn					
nn	1-99	None. Must specify.	N/A	Single-member warm start	“RDR(nn) - Local Card Reader” on page 367
Auth	N/A	NO/NO/NO	N/A	\$T RDRnn command	“RDR(nn) - Local Card Reader” on page 367
Class	1-8 character execution class name	A	JOB	\$T RDRnn command	“RDR(nn) - Local Card Reader” on page 367
HOLD	N/A	NO	N/A	\$T RDRnn command	“RDR(nn) - Local Card Reader” on page 367
MSGCLASS	A-Z, 0-9	A	JOB	\$T RDRnn command	“RDR(nn) - Local Card Reader” on page 367
PRIOINC	0-15	0	PRIOLIM	\$T RDRnn command	“RDR(nn) - Local Card Reader” on page 367
PRIOLIM	0-15	15	PRIOINC	\$T RDRnn command	“RDR(nn) - Local Card Reader” on page 367
PRTDEST	N/A	LOCAL	/*ROUTE	\$T RDRnn command	“RDR(nn) - Local Card Reader” on page 367
PUNDEST	N/A	LOCAL	/*ROUTE	\$T RDRnn command	“RDR(nn) - Local Card Reader” on page 367
START	N/A	YES	\$S RDR	\$S RDRnn command -- or -- \$P RDRnn command	“RDR(nn) - Local Card Reader” on page 367
TRACE	N/A	YES	TRACEDEF	\$T RDRnn command	“RDR(nn) - Local Card Reader” on page 367
UNIT	Device addresses	Null	N/A	\$T RDRnn command	“RDR(nn) - Local Card Reader” on page 367
XEQDEST	N/A	LOCAL	N/A	\$T RDRnn command	“RDR(nn) - Local Card Reader” on page 367

Table 72. Initialization Statement - RECVopts(type)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - RECVopts(type)					

Table 72. Initialization Statement - RECVopts(type) (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
type	(See note below.)	ALL	N/A	Single-member warm start	“Parameter Description for RECVOPTS” on page 373
COUNT	1-99	(See note below)	INTERVAL	\$T RECVopts command	“Parameter Description for RECVOPTS” on page 373
INTERVAL	1-9999	(See note below)	COUNT	\$T RECVopts command	“Parameter Description for RECVOPTS” on page 373
Note: See the full description of this parameter in the parameter definition with this initialization statement.					

Table 73. Initialization Statement - REDirect					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - REDirect					
vvvvvvvv	(See note below)	N/A	N/A	Single-member warm start	“REDirect(vvvvvvvv) - Direct Output of Display Commands” on page 376
command	N/A	N/A	N/A	\$T REDirect command	“REDirect(vvvvvvvv) - Direct Output of Display Commands” on page 376
consolid	N/A	Entry console	N/A	\$T REDirect command	“REDirect(vvvvvvvv) - Direct Output of Display Commands” on page 376
Note: See the full description of this parameter in the parameter definition with this initialization statement.					

Table 74. Initialization Statement - REP					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - REP					
csect *	1-8 characters	None	NAME, VER	N/A	“Parameter Description for REP” on page 380
address *	1-8 digits	None	NAME, VER	N/A	“Parameter Description for REP” on page 380

Table 74. Initialization Statement - REP (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
data	Up to 71 bytes	None, must specify.	NAME, VER	N/A	“Parameter Description for REP” on page 380

Table 75. Initialization Statement - REQJOBID					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - REQJOBID					
JESLOG	N/A	(See note below)	N/A	Operator command	“Parameter Description for REQJOBID” on page 387
Note: See the full description of this parameter in the parameter definition with this initialization statement.					

Table 76. Initialization Statement - RMT(nnnnn) - BSC					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - RMT(nnnnn) - BSC					
nnnnn	1-32767	None. Must specify	R(nnnnn).PR(m) R(nnnnn).PU(m) R(nnnnn).RD(m)	\$ADD RMT(nnnnn) command	“RMT(nnnnn) - SNA RJE Workstation” on page 398
BLOCK	N/A	YES	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (BSC)” on page 393
BUFEXPAN	N/A	0	PRWIDTH on R(nnnnn).PR(m)	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (BSC)” on page 393
BUFSIZE	127-3960	(See note below)	/*SIGNON	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (BSC)” on page 393
COMPRESS	N/A	NO	HTABS, LINE(nnnnn)	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (BSC)” on page 393
CONDEST	1-32767 (See note below)	nnnnn	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (BSC)” on page 393

<i>Table 76. Initialization Statement - RMT(nnnnn) - BSC (continued)</i>					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
CONS	NO	NO	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (BSC)” on page 393
DEVTYPE	(See note below)	2770	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (BSC)” on page 393
Discintv	0-8160	0	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (BSC)” on page 393
HTABS	N/A	NO	COMPRESS	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (BSC)” on page 393
LINE	0-32767	0 (non-dedicated)	LINE(nnnnn)	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (BSC)” on page 393
LOCAL190	N/A	ACTION	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (BSC)” on page 393
MFORM	N/A	T	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (BSC)” on page 393
MRF2780	N/A	NO	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (BSC)” on page 393
MSGPRT	N/A	YES	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (BSC)” on page 393
MULTILV	N/A	NO	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (BSC)” on page 393
NUMPRT	0-7	1	R(nnnnn).PR(m)	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (BSC)” on page 393
NUMPUN	0-7	0	R(nnnnn).PU(m)	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (BSC)” on page 393
NUMRDR	0-7	1	R(nnnnn).RD(m)	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (BSC)” on page 393
Password	1-8 characters	None	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (BSC)” on page 393

Table 76. Initialization Statement - RMT(nnnnn) - BSC (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
RECFM	N/A	VARIABLE	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (BSC)” on page 393
RMT150	N/A	NO	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (BSC)” on page 393
Routecde	1-32767	nnnn	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (BSC)” on page 393
SHARABLE	N/A	DEFAULT (See note below)	LINE=	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (BSC)” on page 393
TRANSPAR	N/A	NO	LINE(nnnnn)	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (BSC)” on page 393
WAITIME	0-30	1	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (BSC)” on page 393
Note: See the full description of this parameter in the parameter definition with this initialization statement.					

Table 77. Initialization Statement - RMT(nnnnn) - SNA					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - RMT(nnnnn) - SNA					
nnnnn	1-32767	None. Must specify	R(nnnnn).PR(m)) R(nnnnn).PU(m)) R(nnnnn).RD(m))	\$ADD RMT(nnnnn) command	“RMT(nnnnn) - SNA RJE Workstation” on page 398
Autolog	N/A	NO	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (SNA)” on page 402
BUFSIZE	256-3840	256	/*SIGNON	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (SNA)” on page 402
COMPACT	N/A	NO	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (SNA)” on page 402
COMPRESS	N/A	NO	HTABS, LINE(nnnnn)	\$T RMT(nnnn) command	“Parameter Description for RMT(nnnnn) (SNA)” on page 402

<i>Table 77. Initialization Statement - RMT(nnnnn) - SNA (continued)</i>					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
CONDEST	1-32767 (See note below)	nnnnn	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (SNA)” on page 402
CONS	NO	NO	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (SNA)” on page 402
DEVTYPE	(See note below)	N/A	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (SNA)” on page 402
Discintv	0-8160	0	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (SNA)” on page 402
LINE	0-32767	0 (non-dedicated)	LINE(nnnnn)	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (SNA)” on page 402
LOCAL190	N/A	ACTION	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (SNA)” on page 402
LUNAME	1-8 characters	None	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (SNA)” on page 402
MFORM	N/A	T	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (SNA)” on page 402
MSGPRT	N/A	YES	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (SNA)” on page 402
NUMPRT	0-7	1	R(nnnnn).PR(m)	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (SNA)” on page 402
NUMPUN	0-7	0	R(nnnnn).PU(m)	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (SNA)” on page 402
NUMRDR	0-7	1	R(nnnnn).RD(m)	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (SNA)” on page 402
Password	1-8 characters	None	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (SNA)” on page 402
RMT150	N/A	NO	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (SNA)” on page 402

Table 77. Initialization Statement - RMT(nnnnn) - SNA (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Routecde	1-32767	nnnnn	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (SNA)” on page 402
START	N/A	NO	LUNAME	\$S RMTnnnnn command -- or -- \$P RMTnnnnn command	“Parameter Description for RMT(nnnnn) (SNA)” on page 402
SETUP	N/A	MSG	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (SNA)” on page 402
WAITIME	0-30	1	N/A	\$T RMT(nnnnn) command	“Parameter Description for RMT(nnnnn) (SNA)” on page 402
Note: See the full description of this parameter in the parameter definition with this initialization statement.					

Table 78. Initialization Statement - SMFDEF					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - SMFDEF					
BUFNUM	0-1000	5	PRT, OFFLOAD(n), PCEDEF	Single-member warm start	“Parameter Description for SMFDEF” on page 405
BUFWARN	0-100	80	N/A	\$T SMFDEF command	“Parameter Description for SMFDEF” on page 405

Table 79. Initialization Statement - SOCKET(xxxxxxxx)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - SOCKET(xxxxxxxx)					
CONNECT	0-1440	DEFAULT/0	NJEDEF, NODE	\$T SOCKET command	“Parameter Description for SOCKET(xxxxxxxx)” on page 408
IPADDR	1-255 characters	*LOCAL	N/A	\$T SOCKET command	“Parameter Description for SOCKET(xxxxxxxx)” on page 408

Table 79. Initialization Statement - SOCKET(xxxxxxxx) (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
LINE	0-65535	0	NJEDEF	\$T SOCKET command	“Parameter Description for SOCKET(xxxxxxxx)” on page 408
NODE	1-8 characters	0	N/A	\$T SOCKET command	“Parameter Description for SOCKET(xxxxxxxx)” on page 408
NETSRV	1-999	0	N/A	\$T SOCKET command	“Parameter Description for SOCKET(xxxxxxxx)” on page 408
PORT	0-32767	175 or 2252	SECURE	\$T SOCKET command	“Parameter Description for SOCKET(xxxxxxxx)” on page 408
REST	N/A	0	N/A	\$T SOCKET command	“Parameter Description for SOCKET(xxxxxxxx)” on page 408
SECURE	N/A	NO	N/A	\$T SOCKET command	“Parameter Description for SOCKET(xxxxxxxx)” on page 408

Table 80. Initialization Statement - SPOOL					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - SPOOL					
volser	N/A	None. Must specify.	\$T SPOOLDEF	Single-member warm start	“Parameter description for SPOOL” on page 410
Sysaff	ANY, memname, ()	None.	N/A	Cold start	“Parameter description for SPOOL” on page 410
DSNAME	1-44 characters	None.	N/A	Cold start	“Parameter description for SPOOL” on page 410

Table 81. Initialization Statement - SPOOLDEF					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - SPOOLDEF					
ADVANCED_FORMAT	N/A	DISABLED	N/A	\$T SPOOLDEF	SPOOLDEF Parameters
BUFSIZE	1944-3992	3992	N/A	Cold start	SPOOLDEF Parameters

Table 81. Initialization Statement - SPOOLDEF (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
DSNAME	1-44 characters	SYS1. HASPACE	N/A	Cold start	SPOOLDEF Parameters
FENCE	N/A	NO	N/A	\$T SPOOLDEF command (not on a warm start)	SPOOLDEF Parameters
LARGEDS	N/A	FAIL	N/A	\$T SPOOLDEF command (not on a warm start)	SPOOLDEF Parameters
SPOOLNUM	1-253	32	N/A	Cold start (See note 5)	SPOOLDEF Parameters
TGSPACE (MAX=)	1-13264947 2	16288	TGSPACE= (MAX=)	\$T SPOOLDEF command	SPOOLDEF Parameters
TGSIZE	1-255	30	N/A	\$T SPOOLDEF command	SPOOLDEF Parameters
TGSPACE (WARN=)	0-100	80	N/A	\$T SPOOLDEF command (See note 4)	SPOOLDEF Parameters
TRKCELL	1-120	3	OUTCLASS(v)	Cold start	SPOOLDEF Parameters
Volume	4-5 characters	SPOOL	N/A	Cold start (See note 2)	SPOOLDEF Parameters
Note: 1. See the full description of this parameter in the parameter definition with this initialization statement. 2. This parameter value can only be set on a cold start. 3. If you modify this parameter value and then restart JES2 with a hot start, the parameter value in effect before termination is used. 4. This parameter cannot be modified through a hot start, quick start or single member warm start. 5. This parameter can be increased with a \$T SPOOLDEF command after an \$ACTIVATE command has been issued in the MAS.					

Table 82. Initialization Statement - SSI(nnn)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - SSI(nnn)					
nnn (See note 1)	1-255	None. Must specify.	N/A	\$T SSI(nnn) command	“SSI(nnn) - Subsystem Interface Definition” on page 416

Table 82. Initialization Statement - SSI(nnn) (continued)					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
TRACE (See note 1)	N/A	NO	N/A	\$T SSI(nnn) command (See note 2)	“Parameter Description for SSI(nnn)” on page 417
Note: 1. See the full description of this parameter in the parameter definition with this initialization statement. 2. If you modify this parameter value and then restart JES2 with a hot start, the parameter value in effect before termination is used.					

Table 83. Initialization Statement - SUBMITLIB					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - SUBMITLIB(nnnnnnnn)					
xxxxxxxx	1–8 characters	(See note below)	N/A	Operator command	“SUBMITLIB(xxxxxxxxx) - JCL library definition” on page 417
DD(nnn)	1–255	(See note below)	N/A	Operator command	“SUBMITLIB(xxxxxxxxx) - JCL library definition” on page 417
DSName	1–44 characters	(See note below)	N/A	Operator command	“SUBMITLIB(xxxxxxxxx) - JCL library definition” on page 417
UNIT	1–8 characters	(See note below)	N/A	Operator command	“SUBMITLIB(xxxxxxxxx) - JCL library definition” on page 417
VOLser	1–6 characters	(See note below)	N/A	Operator command	“SUBMITLIB(xxxxxxxxx) - JCL library definition” on page 417
PATH	1–88 characters	(See note below)	N/A	Operator command	“SUBMITLIB(xxxxxxxxx) - JCL library definition” on page 417
UNCONDitional CONDitional	N/A	(See note below)	N/A	Operator command	“SUBMITLIB(xxxxxxxxx) - JCL library definition” on page 417
NAME	1–8 characters	(See note below)	N/A	Operator command	“SUBMITLIB(xxxxxxxxx) - JCL library definition” on page 417
Note: See the full description of this parameter in the parameter definition with this initialization statement.					

Table 84. Initialization Statement - SUBMITRDR					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - SUBMITRDR					
Auth	N/A	NO/NO/NO	N/A	\$T SUBMITRDR command	“SUBMITRDR - Submit reader” on page 420
CLASS	1-8 character	A	N/A	\$T SUBMITRDR command	“SUBMITRDR - Submit reader” on page 420
DD_default	1-8 character	Null	SUBMITLIB	\$T SUBMITRDR command	“SUBMITRDR - Submit reader” on page 420
HOLD	N/A	NO	N/A	\$T SUBMITRDR command	“SUBMITRDR - Submit reader” on page 420
PRTYINC	0-15	0	PRTYLIM	\$T SUBMITRDR command	“SUBMITRDR - Submit reader” on page 420
PRTYLIM	0-15	15	PRTYINC	\$T SUBMITRDR command	“SUBMITRDR - Submit reader” on page 420
TRACE	N/A	NO	TRACEDEF	\$T SUBMITRDR command	“SUBMITRDR - Submit reader” on page 420
See the full description of this parameter in the parameter definition with this initialization statement.					

Table 85. Initialization Statement - SUBTDEF					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - SUBTDEF					
GSUBNUM	1-50	10	N/A	Hot start	“Parameter Description for SUBTDEF” on page 423

Table 86. Initialization Statement - TPDEF					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - TPDEF					
AUTOINTV	10-600	32	N/A	\$T TPDEF command	“Parameter Description for TPDEF” on page 424

<i>Table 86. Initialization Statement - TPDEF (continued)</i>					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
BSCBUF	(See note below)	(See note below)	BSCBUF	\$T TPDEF command (to increase LIMIT) Hot start (to decrease LIMIT for WARN)	“Parameter Description for TPDEF” on page 424
SBABUF	(See note below)	(See note below)	SNABUF	\$T TPDEF command (to increase LIMIT) Hot start (to decrease LIMIT) (for WARN)	“Parameter Description for TPDEF” on page 424
MBUFSIZE	128-3960	400	RMT(nnnnn)	Hot start	“Parameter Description for TPDEF” on page 424
RMTMSG	1-255	100	BUFNUM on CONDEF	\$T TPDEF command	“Parameter Description for TPDEF” on page 424
RMTNUM	0-32767	(See note below)	RMT(nnnnn)	Hot start	“Parameter Description for TPDEF” on page 424
SESSIONS= (LIMIT=)	1-32767	(See note below)	LINE(nnnnn)	Hot start	“Parameter Description for TPDEF” on page 424
SESSIONS= (WARN=)	0-100	80	LINE(nnnnn)	Hot start	“Parameter Description for TPDEF” on page 424
Note: See the full description of this parameter in the parameter definition with this initialization statement.					


<i>Table 87. Initialization Statement - TRACE(nnn)</i>					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - TRACE(nnn)					
nnn	1-255	None. Must specify.	N/A	Single-member warm start	“TRACE(n) - Initial tracing value setting” on page 428
START	N/A	NO	TRACEDEF	\$T TRACE command	“Parameter Description for TRACE(n)” on page 429

Table 88. Initialization Statement - TRACEDEF					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - TRACEDEF					
ACTIVE	N/A	NO	TRACE(n)	\$T TRACEDEF command (See notes 1 and 2)	“Parameter Description for TRACEDEF” on page 430
LOG	(See notes below)	(CLASS=A, SIZE=500, START=NO)	N/A	\$T TRACEDEF command (See notes 1 and 2)	“Parameter Description for TRACEDEF” on page 430
PAGES	1-1250	9 (See notes below)	N/A	Single-member warm start (See notes 1 and 2)	“Parameter Description for TRACEDEF” on page 430
TABLES	0-2500	3	PAGES	\$T TRACEDEF command (See notes 1 and 2)	“Parameter Description for TRACEDEF” on page 430
TABWARN	0-100	80	TABLES	\$T TRACEDEF command (See notes 1 and 2)	“Parameter Description for TRACEDEF” on page 430
Note: 1. See the full description of this parameter in the parameter definition with this initialization statement. 2. If you modify this parameter value and then restart JES2 with a hot start, the parameter value in effect before termination is used.					


Table 89. Initialization Statement - VER					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - VER					
csect *	1-8 characters	None	REP, NAME	N/A	“Parameter description for VERIFY” on page 433
address *	1-8 digits	None	REP, NAME	N/A	“Parameter description for VERIFY” on page 433
data	71 characters	None	REP, NAME	N/A	“Parameter description for VERIFY” on page 433

Table 90. Initialization Statement - ZAPJOB					
Parameter	Range	Default	Related Parameter or Statement	Minimum Action to Modify	Location
Initialization Statement - ZAPJOB					
JOBNAME	1-8 characters	None	N/A	N/A	“Parameter Description for ZAPJOB” on page 440
JOBID	1-8 characters	None	N/A	N/A	“Parameter Description for ZAPJOB” on page 440
JOBKEY	1-8 characters	None	N/A	N/A	“Parameter Description for ZAPJOB” on page 440
JQEINDEX	1-4 characters	None	N/A	N/A	“Parameter Description for ZAPJOB” on page 440
JQEOFF	1-6 characters	None	N/A	N/A	“Parameter Description for ZAPJOB” on page 440

APPL(jxxxxxxx) - Application Characteristics Specification



Selection limiting keywords



Notes:

¹ Omit the comma between initialization statement and first keyword.

Parameter Description for APPL(jxxxxxxx)

COMPACT=nn

Specifies the compaction table number (0-99) to be used for outbound compaction in communicating with this application at the specified node. Zero denotes no compaction.

If you do not specify this parameter, it defaults to the value for COMPACT specified on the NODE(xxxxxxxx) initialization statement, which defines the node indicated by the NODE=nnnn parameter on this statement.

CONNECT= (Yes|No|DEFAULT,interval)

Specifies whether an NJE connection should be automatically attempted for this APPL statement. If DEFAULT is specified, processing defers to the CONNECT=(YES|NO) value that is specified on the associated NODE statement. The *interval* is the approximate time (in minutes) between attempted

connections. The valid range for *interval* is 0 to 1440. A value of 0 indicates that the default interval (from NJEDEF CONNECT=) should be used. The default CONNECT value is DEFAULT, and the default *interval* is 0.

LINE=nnnnn

A dedicated line used for the SNA NJE session associated with this application. Range is 0–65535.

Default: 0 (No line is dedicated)

LOGMODE=avvvvvv

Specifies the logon mode table entry name for this application. This name will determine which entry in the VTAM application logon mode table is to be used to provide a set of session parameters for the application program if the program participates as the secondary end of a session. This parameter is valid only for NJE applications. The name specified should follow the VTAM naming conventions for a logon mode table entry name. See *z/OS Communications Server: SNA Programming* for more information about the logon mode table.

The name defaults to blanks, and VTAM uses the logon mode table entry referenced by the application (jxxxxxxx).

LOGON=logon

Specifies the device control table (DCT) to which this application is to be connected.

NODE=nnnnn | xxxxxxxx

Specifies the node number (1 to 32767) or the symbolic node name of the node at which this JES2 application is defined to VTAM. If you code the symbolic name:

- The symbolic name must also be defined on the NAME= parameter of the NODE initialization statement for the referenced node, or defined on a DESTID initialization statement.
- The NODE statement where the name is defined or the DESTID statement where the name is defined must be placed before the APPL statement in the initialization stream.

This parameter is required.

REST=nnnn

Specifies an integer (0-2000), which represents the resistance rating of the connection as viewed by the installation manager and coordinated with other installations. See *z/OS JES2 Initialization and Tuning Guide* for details concerning selecting a resistance value.

If you do not specify this parameter, it defaults to the value for REST=, specified on the NODE(xxxxxxx) initialization statement, which defines the node indicated by the NODE=xxxxxxx parameter on this statement.

BADTRACK - Defective Track Specification


Use the BADTRACK initialization statement to specify a range of track addresses of defective tracks on a specific spool volume. This definition should be specified identically on each member in the MAS. JES2 will not attempt to use tracks identified as defective. As a result of listing track groups on this initialization statement, JES2:

- Places the corresponding track group in a pool of permanently defective track groups. The entire track group is considered defective if one of its tracks is specified as defective.
- Does not issue messages for these track groups that it normally issues during an all-member warm start to inform the operator of the defective tracks.

You can add or remove the specification of defective tracks during any JES2 start. Removal of a BADTRACK statement will allow JES2 to attempt recovery of the track group.

Note: If a BADTRACK statement is removed, JES2 reformats the track group and puts it back into service at the next all-member JES2 warm start or within 1 week, whichever occurs first.

Format Description for BADTRACK



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for BADTRACK

VOL=xxxxxx

Specifies the 5- to 6-character volume serial number on which the defective tracks are. If you specify a volume that has not yet been formatted by JES2, the entire volume will be formatted and then the associated track group will be removed from availability.

This parameter has no default. This parameter must be specified.

Modification: Hot start.

ADDR=(cccchhhh[-cccchhhh])

Specifies a track address or a range of track addresses of defective tracks where cccc is the hexadecimal cylinder identifier and hhhh is the hexadecimal head identifier. The starting and ending track addresses are in the same format as in the \$HASP094 message, which is issued when the I/O error occurs. Because the track group is the basic unit of allocation, the member is unable to allocate tracks within a defective track group. This means that the actual range of tracks removed may be larger than that specified by this parameter.


This parameter has no default and must be specified. If you specify a range of addresses, the starting address must be smaller than the ending address.

Modification: Hot start.

BUFDEF - Local JES2 Buffer Definition

The BUFDEF statement defines the local buffers to JES2.

Format Description for BUFDEF



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for BUFDEF

BELOWBUF=

Specifies the maximum number of buffers that JES2 allocates **below** 16 megabytes in virtual storage and a usage warning level for those buffers. JES2 uses these buffers to store data records read in from spool.

LIMIT=nnnn

Specifies the maximum number of buffers (10-2000) JES2 allocates below 16 megabytes in virtual storage.

If the BELOWBUF parameter is not specified, the following formula is used to calculate initial value for BELOWBUF:

```
BELOWBUF=LIMIT=
20
+ 1 * (number of RDRnn statements)
+ N2 * (number PRTnn statements - N1)
+ N1 * N2 * (nnn from TRKCELL=nnn on SPOOLDEF)
+ N3 * (number PUNnn statements)
+ (1 + N4 + N5) * (number of LINEnn statements)

WHERE
N1 = Number of printers specifying TRKCELL=YES
N2 = 2 if DBLBUFR=YES on PRINTDEF, else 1
N3 = 2 if DBLBUFR=YES on PUNCHDEF, else 1
N4 = 2 if RDBLBUFR=YES on PRINTDEF, else 1
N5 = 2 if RDBLBUFR=YES on PUNCHDEF, else 1
```

Note: Most of the input values to this formula are for active devices at peak load periods on a single member of your multi-access spool complex.

Note: Use this parameter to increase the limit for the JNUM resource that is reported on the HASP050 message.

Performance Considerations: Because all JES2 buffers are maintained in a dynamic pool until required by an active function, the appropriate number of buffers should be based on the predicted coincident occurrence of the various functions at your installation. This can vary considerably from the value determined by the formula above. If you have calculated a reasonable value for LIMIT= based on past system usage, you can continue to use that value.

If, however, you have no such past data upon which to base this value, the following guidelines and formula above provides a basis upon which to initially set this value.

- JES2 normally requires at least 100 spool buffers. Even if your estimate of required buffers is less than 100, it should prove to be a good initial value unless your use of virtual storage is constrained.
- Normally 450 spool buffers are required for normal JES2 operations for installations with up to 150 remote workstations that are active during peak load periods.

Modification: \$T BUFDEF operator command to increase the limit. Hot start to decrease the limit.

WARN=nnn|80

Specifies a threshold percentage (0-100) of the maximum buffer use at which JES2 issues the \$HASP050 message to warn the operator of a resource shortage. If you do not want JES2 to issue a message, specify zero for this parameter.

Modification: \$T BUFDEF operator command.

EXTBUF=

Specifies information about the control block buffers. JES2 allocates these buffers **above** 16 megabytes in virtual storage; JES2 control blocks read in from spool reside here.

LIMIT=nnnn

Specifies the maximum number of buffers (10-9999) JES2 allocates above 16 megabytes in virtual storage. The "Performance Considerations" listed under BELOWBUF=LIMIT=nnnn also apply for this parameter.

If the EXTBUF parameter is not specified, the following formula is used to calculate initial value for EXTBUF:

```
EXTBUF=LIMIT=
20
+ 4 * (number of RDRnn statements)
+ N2 * (number PRTnn statements - N1)
+ N1 * N2 * (nnn from TRKCELL=nnn on SP00LDEF)
+ N3 * (number PUNnn statements)
+ (4 + N4 + N5) * (number of LINEnnn statements)
+ 2 * (number of JQRP PCEs)
+ 1 * (number of CNVT PCEs)
+ 3 * (number of OUTPUT PCEs)
+ 4 * (number of PURGE PCEs)
+ 2 * MIN(50,nnn/1024 from JOBNUM=nnn on JOBDEF)
```

WHERE

```
N1 = Number of printers specifying TRKCELL=YES
N2 = 2 if DBLBUFR=YES on PRINTDEF, else 1
N3 = 2 if DBLBUFR=YES on PUNCHDEF, else 1
N4 = 2 if RDBLBUFR=YES on PRINTDEF, else 1
N5 = 2 if RDBLBUFR=YES on PUNCHDEF, else 1)
```

The number of JQRP PCEs has no external and is set to 10

The number of CNVT, OUTPUT, and PURGE PCEs is set on the PCEDEF initialization statement

Note: Most of the input values to this formula are for active devices at peak load periods on a single member of your multi-access spool complex.

Modification: \$T BUFDEF operator command to increase the limit. Hot start to decrease the limit.

WARN=nnn|80

Specifies a threshold percentage (0-100) of the maximum buffer use at which JES2 issues the \$HASPO50 message to warn the operator of a resource shortage. If you do not want JES2 to issue a message, specify zero for this parameter.

CKPTDEF - JES2 Checkpoint Definition

The CKPTDEF statement defines the JES2 checkpoint data sets, their respective backup data sets, and the mode of the checkpoint configuration.

Follow these coding rules when specifying the checkpoint data sets:

- Specify CKPT1= and CKPT2= or both, and include INUSE=Yes along with one of the following:
 - DSName= and VOLume= (if the checkpoint resides on DASD)
 - STRname= (if the checkpoint resides on a coupling facility structure)
- Naming restrictions for the DSName= and VOLume= specifications (if the checkpoint is on DASD) and the STRname= specification (if the checkpoint is on coupling facility) are as follows:
 - CKPTn (STRname) cannot be the same as NEWCKPTn (STRname).
 - CKPT1 (DSName and VOLser or STRname) cannot be the same as CKPT2 or NEWCKPT2 (DSName and VOLser or STRname).
 - NEWCKPT1 (DSName and VOLser or STRname) cannot be the same as NEWCKPT2 (DSName and VOLser or STRname) or CKPT2 (DSName and VOLser or STRname).

Defining Checkpoint Data Sets

The values specified on this statement are initial values only. If any are changed after initialization by operator command, or by use of the checkpoint reconfiguration dialog, many of these initial values will be


ignored on a hot or warm start as shown in the following list. However, JES2 honors all new values if you specify the RECONFIG option.


Use the RECONFIG option with caution, because severe queue damage can result if you use the incorrect checkpoint data set(s) on a restart. (See *z/OS JES2 Initialization and Tuning Guide* for further explanation of the start options.)

Note that JES2:

- Ignores CKPT1= and CKPT2= specifications on a hot start.
- Ignores NEWCKPT1= and NEWCKPT2= specifications except on a cold start or if RECONFIG is added to the warm start command.
- Ignores MODE= and LOGSIZE= specifications on a warm start unless RECONFIG is added to the warm start command.
- Preserves respecification of NEWCKPT1= and NEWCKPT2= by \$T across a warm start unless RECONFIG is also added to the warm start command.

Format Description for CKPTDEF





Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter description for CKPTDEF

CKPT1=

Specifies the status of the primary checkpoint data set (in DUPLEX mode) or the alternately used primary data set (in DUAL mode) from which JES2 reads and writes the checkpoint record. If this data set resides on DASD, specify its name and volume serial number. If this data set resides on a coupling facility, specify its structure name.

This data set can be:

- The only checkpoint data sets defined (MODE=DUPLEX and DUPLEX=OFF) or (MODE=DUAL, INUSE=Yes, and CKPT2 INUSE=No)
- Used as the primary data set backed up by a duplex data set (MODE=DUPLEX and DUPLEX=ON)
- Used as one of two-alternately used checkpoint data sets (MODE=DUAL).

If neither data set (CKPT1 or CKPT2) is defined at initialization, the operator is prompted for name and device information following initialization processing.

DSName=jxx...x

Specifies a 1-44 character name (hyphens (-) can be included for any character except the first) which is used as the name of the primary checkpoint data set. This data set is normally named SYS1.JESCKPT1, but you can provide another name if you prefer. For example, you would be naming it TESTING.HASPCCKPT if you specified the following initialization statement:

```
CKPTDEF    CKPT1=(DSN=TESTING.HASPCCKPT,...)
```

The DSN= parameter and the VOLSER= subparameter are mutually exclusive with the STRname= parameter.

If you do not define a structure on the coupling facility to contain the checkpoint data sets, you must specify a data set name for either CKPT1 or CKPT2 or both. If you do not, JES2 enters the checkpoint reconfiguration dialog.

Modification: Operator response to reconfiguration dialog messages only if the data set is specified as not in use (INUSE=No).

Note: To avoid potential confusion, IBM suggests that the name specified here not match the DSN= parameter specification on the SPOOLDEF initialization statement.

STRname=jxx...x

Specifies the 1-16 character name of the coupling facility structure to be used for a checkpoint data set. This structure must have been defined in the coupling facility policy. The name can contain numeric, uppercase alphabetic, dollar sign (\$), at sign (@), number sign (#), or underscore (_) characters.

This subparameter is mutually exclusive with the DSNNAME= and VOLSER= subparameters.

The STRname= parameter has no default; you must specify it to place a checkpoint data set in a structure on the coupling facility.

VOLser=xxxxxx

Specifies the volume serial number on which the data set specified by the DSNname= parameter resides.

The DSNNAME= parameter and the VOLSER= subparameter are mutually exclusive with the STRname= parameter.

Modification: Operator response to reconfiguration dialog messages only if the data set is specified as not in use (INUSE=No).

Performance Considerations: Because the checkpoint data set is frequently referenced, particularly in multi-access spool configurations, it should not be on any volume that contains high-usage data sets. For example, performance can be seriously degraded if you allow all or part of SYS1.HASPACE (or the data set name that is specified on the DSNNAME= parameter on the SPOOLDEF statement) to also reside on the volume that contains SYS1.JESCKPTn (or the data set name that is specified on the DSNname= parameter). Only low-usage data sets (if any) should be allocated on the same volume as the checkpoint data set.

Also, you should not issue a RESERVE against a designated VOLser volume; this too degrades system performance.

INUSE=Yes|No

Specifies whether this data set is defined to a JES2 multi-access spool configuration as a checkpoint data set.

Modification: Operator response to reconfiguration dialog messages.

Note:

1. At least one checkpoint data set (CKPT1 or CKPT2) must be designated as INUSE=Yes in order that JES2 has a checkpoint data set to use.
2. Operating in DUAL mode (with alternating primary data sets) (MODE=DUAL) requires both CKPT1 and CKPT2 be specified as INUSE=Yes
3. Operating in DUAL mode (with only one primary data set) (MODE=DUAL) requires either CKPT1 or CKPT2 be specified as INUSE=Yes
4. Operating in DUPLEX mode (with a backup data set) (MODE=DUPLEX,DUPLEX=ON) requires both CKPT1 and CKPT2 be specified as INUSE=Yes
5. Operating in DUPLEX mode (without a backup data set) (MODE=DUPLEX,DUPLEX=OFF) requires either CKPT1 or CKPT2 be specified as INUSE=Yes

CKPT2=

Specifies the status of the duplex or alternately used checkpoint data set for either:

- The data set used as the back up copy of the primary data set defined by CKPT1 (MODE=DUPLEX and DUPLEX=ON)
- The second of two alternately used checkpoint data sets (MODE=DUAL).

If this data set resides on DASD, specify its name and volume serial number. If this data set resides on a coupling facility, specify its structure name.

If CKPT2 is not defined at initialization, JES2 assumes that no backup checkpoint data set is required; the operator is not prompted to supply this information.

DSName=jxx...x

Specifies a 1- to 44-character name (hyphens (-) can be included for any character except the first) which is used as the name of the primary checkpoint data set.

If you do not define a structure on the coupling facility to contain one or more checkpoint data sets, you must specify this data set name if the data set is required; JES2 prompts the operator to supply a name only if this data set is in use.

The DSNAMES= subparameter and the VOLSER= subparameter are mutually exclusive with the STRNAME= subparameter.

Modification: Operator response to reconfiguration dialog messages only if this data set is specified as not in use (INUSE=No).

Note:

1. If MODE=DUPLEX, CKPT2 is not used as a backup (duplex) data set to CKPT1 unless DUPLEX=ON is also specified or defaulted.
2. To avoid potential confusion, IBM suggests that the name specified here not match the DSNAMES= parameter specification on the SPOOLDEF initialization statement.

STRname=jxx...x

Specifies the 1- to 16-character name of the coupling facility structure to be used for a checkpoint data set. This structure must have been defined in the coupling facility policy. The name can contain numeric, uppercase alphabetic, dollar sign (\$), at sign (@), pound sign (#), or underscore (_) characters.

This subparameter is mutually exclusive with the DSNAMES= and VOLSER= subparameters.

The STRNAME= parameter has no default; you must specify it to place a checkpoint data set in a structure on the coupling facility.

VOLser=xxxxxx

Specifies the volume serial number on which the data set specified by the DSName= parameter resides.

You must specify this volume serial if it is required; however, JES2 prompts the operator to supply this information if this data set is in use.

Modification: Operator response to reconfiguration dialog messages only if the data set is specified as not in use (INUSE=No).

Note: The volume serial number that is specified for CKPT2 need not be different from that specified for CKPT1.

INUSE=Yes|No

Specifies whether this data set is defined to a JES2 multi-access spool configuration as a checkpoint data set.

Modification: Operator response to reconfiguration dialog messages.

Note: At least one checkpoint data set (CKPT2 or CKPT1) must be designated as INUSE=Yes in order that JES2 has a checkpoint data set to use.

CKPTOPT=HIGHEST|CKPT1|CKPT2

Specifies which checkpoint data set is to be used when JES2 is restarted.

CKPT1

Specifies that JES2 is to use the CKPT1 data set as the source of the checkpoint for building the JES2 work queues.

CKPT2

Specifies that JES2 is to use the CKPT2 data set as the source of the checkpoint for building the JES2 work queues.

HIGHEST

Specifies that JES2 is to determine which checkpoint data set contains the most recent checkpoint, and use that data set for building the JES2 work queues.

Modification: Hot start. This parameter uses the option that is specified when JES2 is started.

Note: This parameter **must never** be specified in the PARMLIB member where your installation's initialization statements are defined. It can only be entered during JES2 initialization while in CONSOLE mode. See *z/OS JES2 Initialization and Tuning Guide* for more details on CONSOLE mode.

DUPLEX=ON|OFF

Specifies whether duplexing is turned on (ON) or off (OFF). If DUPLEX=ON is specified or defaulted, you are able to use the CKPT2 data set to replace the primary (CKPT1) checkpoint data set if that data set becomes unavailable.

If a checkpoint resides on a coupling facility structure, JES2 forces this parameter to MODE=DUPLEX.

Note:

1. DUPLEX=ON only has meaning if MODE=DUPLEX is also specified. That is, the entire multi-access spool configuration must be operating in DUPLEX mode, then you can set duplexing on or off for each individual member.
2. DUPLEX=ON need not be defined on each member of a multi-access spool configuration; however, it is recommended that you do so when operating in duplex mode. Those members that have turned duplexing off (DUPLEX=OFF) does not write to the backup checkpoint data set.
3. The DUPLEX value does not affect the CKPT1 or CKPT2 INUSE setting of the multi-access spool configuration.

Attention: If you specify MODE=DUPLEX and DUPLEX=OFF, you have turned off checkpoint data set duplexing for this particular multi-access spool member; a backup copy of the checkpoint data set is not maintained for this member. If you set DUPLEX=OFF on all members of the multi-access spool configuration, an I/O error occurring on CKPT1 can prove rather disastrous to the single-member or multi-access spool configuration if JES2 also fails.

Modification: \$T CKPTDEF operator command.

LOGSIZE=nnnn

The LOGSIZE parameter specifies the number (1-4000) of 4K-blocks of storage that is used for the change log portion of the checkpoint data set.

Although JES2 allocates a change log for both DUPLEX or DUAL mode, the change log is only used in DUAL mode. JES2 computes a default value by the following algorithm:

Note: Although JES2 allocates space for the change log when operating in DUPLEX mode, the change log is not actually used. If MODE=DUAL:

```

    If number of 4K-blocks that fit on TRACK1
    of CKPT1>=1
        and
        number of 4K-blocks that fit on TRACK1 of CKPT2>=1
        then
        LOGSIZE= lesser of the number of 4K blocks that fit on
                   CKPT1 and CKPT2
        -- OR --
    If the number of 4K-blocks that fit on CKPT1<1
        or
        number of 4K-blocks that fit on CKPT2<1
        then
        LOGSIZE=1

```

Modification: Cold start or all-member warm start if RECONFIG is specified as a start option.

Performance Considerations: For increased performance, prevent the updates from overflowing the change log. If the used portion of the change log can be contained on the first track, it can be read at the same time as all the other records on track 1 during the READ1 portion of the checkpoint cycle.

Trace ID 17 can provide data on the size of the active portion of the change log and assist your tuning of the size specification that is required here. See [z/OS JES2 Diagnosis](#) for more information about Trace ID 17.

MODE=DUAL|DUPLEX

Specifies whether the multi-access spool configuration uses the data set defined by CKPT2= as the alternate primary checkpoint data set (DUAL) or as the backup to the CKPT1 data set (DUPLEX).

DUAL

Specifies that the data set specified by CKPT2 be used as the alternate primary checkpoint data set. The two data sets, which are specified by CKPT1= and CKPT2=, are used in a “flip-flop” alternating scheme. (See [z/OS JES2 Initialization and Tuning Guide](#) for a further discussion of DUAL mode processing.)

If any checkpoint data set resides on a coupling facility (STRname= is coded for CKPT1, CKPT2, NEWCKPT1, or NEWCKPT2), JES2 forces the MODE= parameter to DUPLEX.

DUPLEX

Specifies that the data set specified by CKPT2 be used as the backup to the primary checkpoint data set. The data set specified by CKPT1= is the primary checkpoint data set and the data set specified by CKPT2= is the backup (duplex) checkpoint data set. (See [z/OS JES2 Initialization and Tuning Guide](#) for a further discussion of DUPLEX mode processing.)

Note:

1. If you specify MODE=DUAL, the DUPLEX= specification is ignored.
2. If you specify MODE=DUPLEX and DUPLEX=OFF for a specific member of the multi-access spool configuration, that member does not use or allocate a backup (CKPT2=) checkpoint data set.
3. If you specify MODE=DUPLEX and DUPLEX=ON for a specific member of the multi-access spool configuration, that member uses the data set defined by CKPT2= as the backup checkpoint data set.
4. The MODE= parameter must be specified the same for all members of the multi-access spool configuration.
5. The MODE= parameter can be changed through Operator Command.

Performance Considerations: If you specify MODE=DUAL on CKPTDEF, also specifying HOLD=99999999 on the MASDEF statement causes performance degradation. If you must use HOLD=99999999 on MASDEF, be certain to also specify MODE=DUPLEX on CKPTDEF.

Modification: Operator command.

NEWCKPT1=

Specifies the checkpoint data set that can be used to replace the data set defined by CKPT1= should that data set experience an I/O error or otherwise be unavailable. If this data set resides on DASD, specify its name and volume serial number. If this data set resides on a coupling facility, specify its structure name.

If this data set is not defined, the operator can define it at the time it is needed either within the checkpoint reconfiguration dialog or by a \$T CKPTDEF,NEWCKPT1={(DSName=,VOLser=) | (STRname=)} command.

Note: IBM highly recommends that you define this data set in your initialization data set. It is only defined by this statement; it is not allocated and therefore does not require any storage space until it is used.

If you do not specify a value for this parameter, a \$D CKPTDEF,NEWCKPT1 operator command displays the following:

```
$HASP829 CKPTDEF NEWCKPT1=(DSNAME=,VOLSER=)
```

DSName=jxx...x

Specifies a 1- to 44-character name (hyphens (-) can be included for any character except the first) which is to be used as the name of the backup checkpoint data set to the data set defined by CKPT1=.

You must specify that this checkpoint resides on either a coupling facility structure (STRname=) or on DASD (DSName= and VOLser=). If you do not specify either STR= or DSN= and VOL=, the operator is prompted to supply a data set name, by the \$HASP273/\$HASP272 message pair.

The DSNAME= subparameter and the VOLSER= subparameter are mutually exclusive with the STRname= subparameter.

Modification: \$T CKPTDEF operator command or cold start.

STRname=jxx...x

Specifies the 1-to 16-character name of the coupling facility structure to be used as a checkpoint data set. This structure must have been defined in the coupling facility policy. The name can contain numeric, uppercase alphabetic, dollar sign (\$), at sign (@), number sign (#), or underscore (_) characters.

This subparameter is mutually exclusive with the DSNAME= and VOLSER= subparameters.

The STRname= parameter has no default; you must specify it to place a checkpoint data set in a structure on the coupling facility.

Modification: \$T CKPTDEF operator command or cold start.

VOLser=xxxxxx

Specifies the volume serial number on which the data set specified by the DSName= parameter resides.

If you do not define a structure on the coupling facility to contain the checkpoint data set(s), you must specify this volume name if you require a NEWCKPT1 data set. If you do not specify a volume name, when this data set is needed, **the operator is prompted to supply a serial number**, by the \$HASP273/\$HASP272 message pair.

The DSNAME= parameter and the VOLSER= parameter are mutually exclusive with the STRname= parameter.

Modification: \$T CKPTDEF operator command or cold start.

Note: The volume serial number that is specified for NEWCKPT1 need not be different from that specified for CKPT1, CKPT2, or NEWCKPT2 although if more than one checkpoint data set resides on the same volume your member can suffer performance degradation. (See *z/OS JES2 Initialization and Tuning Guide* for further data set placement information.) However, it is recommended that this volume be different from those volumes defined for either of the primary checkpoint (CKPT1 and CKPT2) data sets.

NEWCKPT2=

Specifies the checkpoint data set that can be used to replace the data set defined by CKPT2= should that data set experience an I/O error or otherwise be unavailable. If this data set resides on DASD, specify its name and volume serial number. If this data set resides on a coupling facility, specify its structure name.

If this data set is not defined, the operator can define it at the time it is needed either within the checkpoint reconfiguration dialog or by a \$T CKPTDEF,NEWCKPT2=[(DSName=,VOLser=) | (STRname=)] command.

Note: IBM highly recommends that you define this data set in your initialization data set. It is only defined by this statement; it is not allocated and therefore does not require any storage space until it is used.

DSName=jxx...x

Specifies a 1- to 44-character name (hyphens (-) can be included for any character except the first) which is to be used as the name of the backup checkpoint data set to the data set defined by CKPT2=.

You must specify that this checkpoint resides on either a coupling facility structure (STRname=) or on DASD (DSName= and VOLser=). If you do not specify either STR= or DSN= and VOL=, **the operator is prompted to supply a data set name**, by the \$HASP273/\$HASP272 message pair.

Modification: \$T CKPTDEF operator command or cold start.

STRname=jxx...x

Specifies the 1-to 16-character name of the coupling facility structure to be used as a checkpoint data set. This structure must have been defined in the coupling facility policy. The name can contain numeric, uppercase alphabetic, dollar sign (\$), at sign (@), number sign (#), or underscore (_) characters.

This subparameter is mutually exclusive with the DSNAME= and VOLSER= subparameters.

The STRname= parameter has no default; you must specify it to place a checkpoint data set in a structure on the coupling facility.

Modification: \$T CKPTDEF operator command or cold start.

VOLser=xxxxxx

Specifies the volume serial number on which the data set specified by the DSName= parameter resides.

You must specify this volume name if you require an NEWCKPT2 data set. If you do not specify a volume name, when this data set is needed, **the operator is prompted to supply a serial number**; which can then be done by responding to the \$HASP273/\$HASP272 message pair.

This subparameter is mutually exclusive with the STRname= subparameter.

Modification: \$T CKPTDEF operator command or cold start.

Note: The volume serial number that is specified for NEWCKPT2 need not be different from that specified for CKPT1, CKPT2, or NEWCKPT1. However, it is recommended it be different from those volumes that are defined for either of the primary checkpoint (CKPT1 and CKPT2) data sets.

OPVERIFY=Yes|No

Specifies whether (Yes) or not (No) JES2 prompts the operator during the checkpoint reconfiguration to verify or alter the default reconfiguration action. This parameter only applies to I/O error conditions when a NEWCKPTn value is defined. The operator is not consulted if JES2 can connect (coupling facility) or allocate (DASD) the NEWCKPTn data set.

If you enable operator verification (OPVERIFY=Yes), JES2 prompts the operator during the checkpoint reconfiguration dialog **entered by JES2 for I/O errors only** to respond to message pairs \$HASP273 and \$HASP272 or \$HASP278 and \$HASP272.

```
$HASP273 JES2 CKPTn DATA SET WILL BE ASSIGNED TO NEWCKPTn dsname ON
VOLUME volser

$HASP272 ENTER RESPONSE

                                -or-

$HASP278 UNABLE TO LOCATE OR UNABLE TO USE CKPTn|NEWCKPTn dsname ON
VOLUME volser DOES NOT EXIST OR IS NOT USABLE

$HASP272 ENTER RESPONSE
```

If the original member driving the checkpoint reconfiguration failed and a new member replaces it as the driving member, the OPVERIFY parameter no longer applies. JES2 notifies the operator and does not automatically forward members. Not forwarding members automatically can prevent cascading member failure, which would result in the loss of all checkpoint data in the MAS and require a JES2 cold start.

If you suppress operator verification (that is, if you specify OPVERIFY=NO), JES2:

- Replaces the checkpoint data set with its replacement data set defined on the NEWCKPTn parameter of the CKPTDEF statement.
- Creates a replacement checkpoint data set automatically when a NEWCKPTn setting cannot be located.

This new checkpoint data set is always defined on DASD. JES2 dynamically allocates a new coupling facility structure only if a structure policy has been defined; JES2 cannot create a structure policy even if the original checkpoint was defined as a coupling facility structure.

Note: If JES2 determines that the new checkpoint resides upon a volatile coupling facility (regardless of the OPVERIFY=No and VOLATILE=(ALLCKPT=IGNORE) or VOLATILE=(ONECKPT=IGNORE) settings), the operator is prompted to respond to message \$HASP237.

Modification: \$T CKPTDEF operator command or cold start.

RECONFIG=Yes|No

RECONFIG= Yes specifies that JES2 uses the checkpoint data sets defined in CKPT1 and CKPT2, regardless of what checkpoints had been used previously. You should specify Yes only for the following conditions:

- A previously unavailable checkpoint data set becomes available.
- A previously available checkpoint data set becomes unavailable.
- Both checkpoint data sets become unavailable so that you must restart JES2 from an emergency checkpoint data set.

RECONFIG= NO instructs JES2 to use the checkpoint data sets specified in CKPT1 and CKPT2 to start checkpoint processing. If JES2 detects that CKPT1 and CKPT2 are not the most recent checkpoint data sets, JES2 uses the data sets specified in these two parameters to locate the most recent checkpoint data sets.

Note:

1. RECONFIG=Yes is only valid on an all-member restart.
2. This parameter **must never** be specified in the PARMLIB member where your installation's initialization statements are defined; it can only be specified in console mode.

VERSIONS=(NUMBER=nn[,WARN=mmm])

Provides information JES2 uses to create and manage copies, or versions, of the checkpoint data set to be made available to application programs.

NUMBER=nn

Specifies the maximum number of copies that JES2 maintains. It can be between 2 and 50 (inclusive). A number that is too low can result in an application program deciding to use a copy that does not contain the most recent checkpoint data.

Note: Use this parameter to increase the limit for the JNUM resource that is reported on the HASP050 message.

This parameter defaults to 0, indicating that JES2 determines the maximum number of versions to maintain.

Modification: \$T CKPTDEF operator command.

WARN=mmm

Specifies a threshold percentage (0-100) of the maximum number of copies (versions) that are in use. When the specified percentage is reached, JES2 alerts the operator through the \$HASP050 message. If you do not want JES2 to issue a message, specify zero for this parameter.

This parameter defaults to 80.

Modification: \$T CKPTDEF operator command

VOLATILE=

Specifies how JES2 should respond when a checkpoint data set that resides on a coupling facility enters the state where, if power to the coupling facility is lost, all data on the coupling facility is lost.

Before modifying this parameter see *z/OS JES2 Initialization and Tuning Guide*.

ONECKPT={WTOR|DIALOG|IGNORE}

Specifies the action that should be taken if the coupling facility on which a checkpoint data set resides becomes volatile (unstable). JES2 uses the ONECKPT= subparameter settings if:

- Only one of the two checkpoint data sets resides on a coupling facility structure, and that coupling facility has become volatile.
- Both checkpoint data sets reside on a coupling facility, but only one becomes volatile.

WTOR

Specifies that JES2 issues a WTOR so the operator can determine whether to suspend or continue the use of the checkpoint data set that resides on a coupling facility structure.

DIALOG

Specifies that JES2 enters the checkpoint reconfiguration dialog if a coupling facility becomes volatile.

IGNORE

Specifies that JES2 ignores the volatile status of the coupling facility.

ALLCKPT={WTOR|DIALOG|IGNORE}

Specifies the action that should be taken if all available checkpoint data sets (INUSE=Yes) that reside on a coupling facility become volatile (unstable). If you have only one checkpoint residing on a coupling facility, JES2 uses the ALLCKPT subparameter settings.

WTOR

Specifies that JES2 issues a WTOR when all available checkpoints residing on coupling facilities become volatile, so the operator can determine whether to suspend or continue the use of the checkpoint(s).

DIALOG

Specifies that JES2 enters the checkpoint reconfiguration dialog if all available checkpoints residing on coupling facilities become volatile.

IGNORE


Specifies that JES2 ignores the volatile status of the coupling facility. JES2 ignores this action setting if ONECKPT=WTOR|DIALOG. Instead, JES2 uses the ONECKPT setting.

Modification: \$T CKPTDEF operator command or cold start.

CKPTSPACE - Checkpoint space definition

The CKPTSPACE statement defines how much space JES2 allocates in the JES2 checkpoint for various data structures.


Format description for CKPTSPACE



Notes:

¹ Omit the comma between initialization statement and first keyword

COMPACT



Notes:

- ¹ Omit the comma between initialization statement and first keyword
- ² CHARS can be coded up to 247 times

Parameter Description for COMPACT

NAME=vvvvvvvv

Specifies the 1- to 8-character table name that can be used in the JCL to reference the compaction table.

This parameter defaults to the table number specified by the NUMBER= parameter on this statement.

Modification: Hot start.

CHARS=(dd,m1,m2,...mn,x1,x2,...xn)

Defines the compaction table as follows:

dd

A decimal number (3-16) that specifies the number of master characters in this COMPACT statement.

m1,m2,...,mn

Specifies master characters to be compacted. Master characters can be compacted when they occur as pairs, in any combination, such that each pair is transmitted in 8 binary bits (rather than 16).

x1,x2,...,xn

Represents nonmaster characters that are not compacted. When the compaction processing routines encounter nonmaster characters, the characters are not compacted, but they do not cause JES2 to exit the compaction routines. When characters not specified in the COMPACT statement are encountered, the compaction routines are exited and are reentered only when again encountering master or nonmaster characters.

The number of master characters specified determines the number of nonmaster characters required as follows:

Number of Master Characters	Required Number of Nonmaster Characters
3	244
4	236
5	226
6	214
7	200
8	184
9	166
10	146
11	124
12	100
13	74
14	46
15	16
16	0

Each m (master) or x (nonmaster) value is a single character or a hexadecimal value representing a single EBCDIC character. However, the six special characters (right parenthesis, left parenthesis, blank, comma, hyphen, and apostrophe) and all lower case alphabetic characters must be represented in hexadecimal form.. The length of the m and x list must equal the number of master and nonmaster characters shown in the list above. For example, if 14 master characters are specified, then 46 nonmaster characters must be specified. If the number of master and nonmaster characters does not match the list, the compaction statement is ignored.

This parameter has no default.

Modification: Hot start.

NUMBER=nn

Specifies the number (1-99) assigned to this compaction table for reference by the user and JES2. If more than one compaction table is specified with the same identification (nn), the last valid table processed is used. Referencing a nonexistent compaction table causes compaction for the device or data set involved to be suppressed; the \$HASP211 error message is issued.

An example of specifying a compaction table follows:

```
COMPACT  NAME=DATASET2,          /* comp tab name */
          CHARS=(15,             /* no. master chars */
                0,1,2,3,4,5,6,7,8,9,A,E,I,O,U, /* master chars */
                B,C,D,F,G,H,K,L,M,N,P,      /* non-master char */
                $,40,6B,5D,4D),             /* */
          NUMBER=2                /* compact table no. */
```

This example specifies the compaction table DATASET2 (that is, table number 2) with 15 master characters (0-9 and the vowels A,E,I,O,U) and 16 nonmaster characters (B,C,D,F,G,H,K,L,M,N,P, a dollar sign, a blank (X'40'), a comma (X'6B'), a right parenthesis (X'5D'), and a left parenthesis (X'4D').

The four special characters noted above in the example (that is, a blank, a comma, a right parenthesis, and a left parenthesis), hyphens, apostrophes, and all lower case alphabetic characters must be coded in hexadecimal notation. Hexadecimal values for other than these six characters can be coded in the compaction statement by putting the hexadecimal representation in the character string; they can be intermixed with EBCDIC values. For example:

```
COMPACT  NAME=DATASET3,          /* comp table name */
          CHARS=(16,             /* no. mast chars */
                F1,F2,3,4,5,F6,F7,8,F9,      /* master chars */
                A,E,I,D6,E4,40,X),          /* */
```

```
NUMBER=3                /* compact table number */
```

This example specifies the compaction table DATASET3 (that is, table number 3) with 16 master characters (both hexadecimal and EBCDIC representations) and no nonmaster characters.

Note: Hexadecimal 00 (NULL) is reserved and not accepted as either a master or nonmaster character.

This parameter value must be specified.


Modification: Hot start.

For more details, see *z/OS JES2 Initialization and Tuning Guide*.

CONDEF - JES2 Console Communication Definition

The CONDEF statement defines the JES2 console communication environment.

Format Description for CONDEF



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for CONDEF

AUTOCMD=nnnnn|20

Specifies the number (2-9999) of automatic commands that can be active concurrently in JES2. The value should be large enough to permit operators to leave a JES2 dynamic display in each user defined ("out of line") area of all graphic display consoles and one on each printer console controlled by MVS.

For additional information, see the description of the \$T A command in *z/OS JES2 Commands*.

Modification: Hot start.

BUFNUM=nnnn|100

Specifies the maximum number (4-9999) of console message buffers to be provided for JES2 from private storage (above 16-megabytes in virtual storage). The value specified for BUFNUM will be rounded up to the next page boundary to take advantage of available storage.

You must specify enough buffers to accommodate all message processing. When using NJE or RJE, you need more message buffers, especially for console support for multileaving terminals. If you do not specify BUFNUM= large enough, JES2 will fail during initialization.

If there is a large amount of console activity and buffers are unavailable, JES2 discards certain noncritical messages to avoid any delay in processing. These messages include: RJE-oriented messages, execution-time job overflow messages, and certain I/O error messages on JES2-controlled devices.

For multileaving terminal consoles, if the number of messages received exceeds the number of buffers specified by BUFNUM=, JES2 spools the excess messages and prints them later. Normal message processing resumes when the console accepts the messages queued before exceeding the BUFNUM= limit.

Note: Use this parameter to increase the limit for the JNUM resource that is reported on the HASP050 message.

Performance Considerations: Use BUFNUM=1000 as a minimum starting value and increase the value using the \$T CONDEF command if the \$HASP050 message indicates a shortage. Because console messages must wait for buffers, too small a value slows the system.

As a rough approximation, estimate the BUFNUM= value as follows:

```
BUFNUM=
(PARTNUM= on INITDEF statement) x 2
+ number of typically active readers (i.e., local, remote, internal)
+ number of typically active printers (i.e., local, remote)
+ number of typically active punches (i.e., local, remote)
```

Use the larger of the two values: either 1000 or the value specified above.

Modification: \$T CONDEF operator command to increase the limit. Hot start to decrease the limit.

BUFWARN=nnn|80

Specifies the percentage (0-100) of use of console message buffers at which the operator will be alerted by message \$HASP050. If you specify 0, no alert will be given.

Modification: \$T CONDEF operator command.

CMDNUM=nnnnn

Specifies the maximum number (4-9999) of console message buffers to be allocated for command processing for JES2 from common storage.

JES2 refuses any commands entered after the command that exceeds the CMDNUM= limit. If you queue a large number of commands to JES2, too large a value may lead to an excessively large allocation of ECSA virtual storage.

Note: Use this parameter to increase the limit for the JNUM resource that is reported on the HASP050 message.

Default: BUFNUM parameter

Modification: \$T CONDEF operator command to increase or decrease the limit.

CONCHAR=c|\$

Specifies the character that will be used to identify JES2 commands from local consoles. If a command from a local console begins with the character specified for CONCHAR, JES2 assumes that the command is a JES2 command and attempts to process it.

The value you specify should be a special character that is not used as the first character of any command of any other subsystem that may be operated concurrently with JES2. The character should be one of the following:

1/2 | (% : . & + _ # < ! - > @ " / ? = ~ *

If the CONCHAR parameter is changed to a character other than its default (\$), the commands will vary from their documented format in *z/OS JES2 Commands*, the messages will vary from the format in *z/OS JES2 Messages*, and the character chosen will be on the consoles and hardcopy log.

You must use the default CONCHAR= character (\$) on JES2 commands imbedded in the JES2 initialization data set regardless of what you specify for CONCHAR=.

Note: To use the MVS ROUTE *ALL command to expand the scope of a command (so that a command can be routed to all the members of the MAS), each member of the MAS must have the same CONCHAR character. See *z/OS JES2 Commands* for more information about the scope of each command, and about using JES2 and MVS commands together.

Modification: \$T CONDEF operator command. You cannot modify this parameter on a hot start.

DISPLEN=nnn|64

Specifies the length (50-70 characters) of output lines for most multi-line display and diagnostic messages. If you specify too low a number, single-line command responses can wrap around your console. If you enter the \$N nnnn,Mn command, the node and specific multi-access spool (MAS) member appear at the start of each line. If you specify DISPLEN=70 and the node and specific MAS member total eight characters, your console only displays the first 62 characters of the message.

Modification: \$T CONDEF operator command.

DISPMAX=nnnnnnnn|100

Specifies the maximum (10-9999999) lines of output that JES2 allows before the \$SCAN facility ends the output because of excessive output. This option does not affect all the JES2 commands. Commands that use a range of values as an operand, could cause an enormous amount of output. DISPMAX= will limit the output without limiting the range of objects the command will affect. For example, if you enter \$T NODE(*),RECEIVE=JOBS, the command will change all nodes, and then start to display them. DISPMAX= will stop the display after the number of lines specified, but all nodes will be changed.

Modification: \$T CONDEF operator command.

The DISPMAX= parameter is not honored when:

1. Output is displayed for error conditions.
2. Output is destined for an out-of-line area on the MCS console, or a command is issued with the explicit L= parameter that specifies an out-of-line area or L=Z. In this case, the output will still be ended at the maximum of 9999999 lines.

MASMSG=nnn|200

Specifies the maximum number (10-999) of messages or commands that will be queued between any two members of a multi-access spool configuration before messages are discarded. This count also applies to the number of input messages or commands queued for the system.

Modification: \$T CONDEF operator command.

RDIRAREA=c|Z

Specifies a character representing the default console out-of-line area JES2 uses to direct display responses for commands subject to redirection. Redirectable commands that do not include an L= and are not named on a REDIRECT initialization statement, or a \$ADD or \$T statement, will have their responses directed to the RDIRAREA specification. See *z/OS MVS Planning: Operations* for information on out-of-line display areas and how to define them.

This parameter defaults to Z, which specifies that the response will be in-line.

Modification: Hot Start or \$T CONDEF operator command.

RDRCHAR=c|\$

Specifies the character that will be used to identify all JES2 operator commands entered from a local or remote card reader. If a JES2 control card is read (/ * in columns 1 and 2) that contains this character in column 3, JES2 will assume that the card is a JES2 command statement and will attempt to process the command.

The specification should be one of the following characters:

1/2 | (% : . & + _ # < ! - > @ " / ? = ~ *

If this parameter is changed to a value other than its default, the command control statement will vary from the format given in *z/OS MVS JCL Reference*. You can use the same character as that specified for the CONCHAR parameter on this initialization statement.

Modification: \$T CONDEF operator command.

SCOPE=SYSTEM | SYSPLEX

Specifies whether the command prefix specified on the CONCHAR parameter is recognized by this MVS system only, or by all MVS systems in the sysplex.

SCOPE=SYSTEM specifies that the prefix is recognized by this MVS system, but if the command was entered on a different MVS system, that system would not recognize or send the command to this system.

SCOPE=SYSPLEX specifies that the prefix is recognized as belonging to this system no matter which MVS system in the sysplex the command was entered on, and, if necessary, is routed to the correct MVS system for processing by this subsystem.

See *z/OS JES2 Initialization and Tuning Guide* for a discussion of how to correctly specify SCOPE= in a sysplex to provide unique CONCHAR= character definitions for multiple JES2 images.

Modification: Single-member warm start.

CONNect - Static NJE Connections

Use the **CONNECT** statement to define a permanent connection between two nodes, each of which is defined by a related **NODE** initialization statement. The **NodeA=** parameter provides a means of describing a job entry subsystem as being connected to another job entry subsystem described by the **NodeB=** parameter. The connection must be defined among the initialization parameters of both members involved in the connection, and among the initialization parameters of any other members in the network which are to know that the connection exists.

Note: Incorrect use of the CONNect statement may adversely affect the network. The CONNect statement has to appear after the NODE(xxxxxxx) statements in the initialization deck if the NodeA/NodeB parameters on the CONNect statement are specified using the symbolic node name. Before using the CONNect statement, see [z/OS JES2 Initialization and Tuning Guide](#) for more information on static connections.


Adding Static Connections

This statement and all its parameters can be added after initialization with the **\$ADD CONNECT operator command**.


Format Description for CONNect




Modification keywords




Selection limiting keywords




MEMBERA




MEMBERB



NODEA



NODEB



Notes:

- ¹ Omit the comma between initialization statement and first keyword

Parameter Description CONNECT

NodeA=xxxxxxxx | nnnnn

Specifies the symbolic node name (xxxxxxxx) or node number (nnnnn) of the node at the NodeA end of the connection. The name must be specified on the NAME= parameter of the NODE initialization statement for the referenced node.

Note:

1. If coding the symbolic node name for this parameter, the NODE(xxxxxxxxx) statement where the node name is defined must be placed before the CONNECT statement in the initialization stream.

2. NODEA and NODEB may appear in any order when defining a static connection, that is NODEA does not have to be your node or the other end. When JES2 resolves the static connection, the order may be different than what was entered on the command when you issue a \$DCONNECT. This is because the node with the smallest number will always be assigned to NODEA. The end result is the same.

This parameter must be specified.

Modification: \$ADD CONNECT operator command or \$DEL CONNECT operator command.

MemberA=n|1

This value is 1; it specifies the member number of NodeA.

Note: Most supported NJE nodes require this parameter to be defaulted or set to 1. This parameter should only be used if the documentation for the NJE product on the node specified by NodeA= requires it. Improper specification of this field can cause portions of your NJE network to be unreachable. IBM suggests that you do not specify this parameter and allow it to default.

Modification: \$ADD CONNECT operator command or \$DEL CONNECT operator command.

NodeB=xxxxxxx | nnnnn

Specifies the symbolic node name (xxxxxxx) or node number (nnnnn) of the node at the NodeB end of the connection. The name must be specified on the NAME= parameter of the NODE(xxxxxxx) initialization statement for the referenced node.

Note:

1. If coding the symbolic node name for this parameter, the NODE(xxxxxxx) statement where the node name is defined must be placed before the CONNECT statement in the initialization stream.
2. NODEA and NODEB may appear in any order when defining a static connection, that is NODEA does not have to be your node or the other end. When JES2 resolves the static connection, the order may be different than what was entered on the command when you issue a \$DCONNECT. This is because the node with the smallest number will always be assigned to NODEA. The end result is the same.

This parameter must be specified, even for non-JES2 nodes.

Modification: \$ADD CONNECT operator command or \$DEL CONNECT operator command.

MemberB=n|1

This value is 1; it specifies the member number of NodeB.

Note: Most supported NJE nodes require this parameter to be defaulted or set to 1. This parameter should only be used if the documentation for the NJE product on the node specified by NodeB= requires it. Improper specification of this field can cause portions of your NJE network to be unreachable. IBM suggests that you do not specify this parameter and allow it to default.

Modification: \$ADD CONNECT operator command or \$DEL CONNECT operator command.

PATHMGR= Yes | No | RESET

Specifies whether or not this connection supports path manager protocols. PATHMGR=RESET specifies that the value of PATHMGR= should be reset to the default.

If PATHMGR=Yes was specified on both of the related NODE(xxxxxxx) initialization statements, then this parameter defaults to PATHMGR=Yes. Otherwise, this parameter defaults to PATHMGR=No.

Modification: \$T CONNECT operator command.

REST=nnnn

For connections between subsystems of different nodes, an integer between 2 and 8000 that specifies the total path resistance of the connection (see [z/OS JES2 Initialization and Tuning Guide](#) for more information). This value will be set to zero for connections between subsystems of the same node.


This parameter defaults to 0; however, neither 0 nor 1 is valid if explicitly specified.

Modification: \$T CONNECT operator command.

D INITINFO - Display initialization information

The D INITINFO statement displays JES2 initialization information. It displays the command used to start JES2, the initialization decks used with a count of cards read, and the list of data sets included in the STEPLIB concatenation in the JES2 PROC.

Format description for D INITINFO



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter description for D INITINFO

STARTCMD

Displays the command, if applicable, that was used to start this instance of the JES2 address space.

Modification: Hot start.

HASPPARM

Displays the data sets that have been read thus far for the JES2 initialization statements, and the number of cards that have been read from each data set. Up to 256 data sets can be displayed.

Modification: Hot start.

STEPLIB

Displays the STEPLIB DD concatenation that is currently set for JES2.

Modification: Hot start.

Example of D INITINFO

The following command displays JES2 initialization information:

```

$HASP825 INITINFO  --- Command used to start JES2
$HASP825           S JES2,M=SP00LZ21,PARM=(WARM,NOREQ)
$HASP825           --- HASPPARM data sets read
$HASP825           DSN=SYS1.PARMLIB(SP00LZ21),VOLSER=J2SHR2,
$HASP825           CARDS=458,
$HASP825           DSN=SYS1.PARMLIB(DYNEXITD),CARDS=121,
$HASP825           DSN=CONSOLE,CARDS=1
$HASP825           --- STEPLIB Concatenation
$HASP825           DSN=NULL.JES2000.LINKLPA,VOLSER=J2SPA1,
$HASP825           DSN=SYS1.SRVLIB.JES2000.LINKLPA,
$HASP825           VOLSER=J2SPA1,
$HASP825           DSN=SYS2.LINKLIB,VOLSER=ZDR21,
$HASP825           DSN=SYS1.MIGLIB,VOLSER=ZDR21

```


D LOADMOD(jxxxxxxx) - Display Load Module Definitions

To display information that would be useful for diagnosing JES2 problems. Use this command to get the virtual address where a load module has been loaded in storage, exit routines included in the load module, its length, the RMODE, and the area of storage where the load module is located.

This command has parameters you can use as a filtering technique to limit the type of information to search, or the amount of information to display.

One or more parameters on this command accepts wild cards. Parameter descriptions will note that.

D LOADMOD(jxxxxxxx)



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for D LOADMOD(jxxxxxxx)

jxxxxxxx

Specifies the JES2 load module name for which information is to be displayed. Specify the load module name (for example, HASCLINK) to obtain specific load module information, or an asterisk (`*`) to obtain information for **all** load modules. You can also specify wild cards for the load module name. The following load modules cannot be displayed:

- HASPFSSM
- HASJES20
- Load modules beginning with the characters HASM.

ADDReSS

Displays the hexadecimal address of the load module in storage.

LENgth

Displays the load module's exact hexadecimal length.

RMODE[=24|ANY]

Displays the link-edit attributes of the load module. Optionally, you can specify one of the following keywords to display load modules that reside in a particular area:

Value

Meaning

24

Display only those load modules that reside below 16 megabytes of virtual storage.

ANY

Display only those load modules that reside above 16 megabytes of virtual storage.

ROUTines

Displays the routines that are defined using the \$ENTRY macros in a module. These routines are available for use through the EXIT(nnn) initialization statement.

Only routine names in installation-provided modules or in IBM-provided sample exit modules will be included.

SPLevel[=CHECK|NOCHECK]

Displays the value the module assigned to the SPLEVEL= parameter on the \$MODULE macro. Optionally, you can display only those modules that have assigned a specific value to the \$MODULE SPLEVEL= parameter by coding one of the following keywords:

Value**Meaning****CHECK**

Display only those modules that specified CHECK on the \$MODULE SPLEVEL= parameter.

NOCHECK

Display only those modules that specified NOCHECK on the \$MODULE SPLEVEL= parameter.

STORAGE[=CSA|PVT|LPA|PRIVATE]

Displays the type of storage in which the load module resides. Optionally, you can specify an area of storage.

Code one of the following keywords:

Value**Meaning****CSA**

Display only those load modules that are loaded into common storage.

PVT|PRIVATE

Display only those load modules that are loaded into the private storage of the JES2 address space.

LPA

Display only those load modules that are loaded into link pack area storage.

TABLES

Displays any DYNAMIC tables which are defined in this module, along with the type of table.

D MODule(jxxxxxxx) - Display Module Information

This is a display-only statement that displays information about loaded assembly modules, including installation-written exit routines.

The display for each module includes the module name and any of the following information:


- The storage address where the module is loaded and the module length.
- The module's assembly environment.
- Any exit points defined within the module.
- The number of the last APAR applied to the module.
- The name of the load module that contains the assembly module.
- The level of the MVS macro library used during assembly of the module.
- The names of any exit routines that are included in the module.
- The value that the module assigned to the \$MODULE SPLEVEL= parameter.
- For IBM-provided JES2 modules, the display can also include an indication of the module type.


The information is displayed in message \$HASP468 on the master console.

D MODule(jxxxxxxx)

This statement displays information similar to that displayed by the \$D MODule command. In addition, this statement can provide information about modules that are in storage during JES2 initialization but are no longer in storage when the \$D MODule command can be issued.

Format Description for D MODule(jxxxxxxx)





Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Descriptions for D MODule(jxxxxxxx)

MODule{(jxxxxxxx|*)}

Identifies the JES2 module for which information is to be displayed.

- To display information about a specific module, code *jxxxxxxx* where *jxxxxxxx* is the module name. For example, to display information about module HASPNUC, code:

```
D MODule(HASPNUC)
```

- To display information about a specific group of modules, code a portion of the module name followed by an asterisk. For example, to display information about all modules whose name begins with HASPN, code:

```
D MODule(HASPN*)
```

- To display information about all modules, code

```
D MODule(*)
```

ADDR

The display is to include the hexadecimal address where the module is loaded into storage. If a module is not in storage, an address of 00000000 is displayed.

ASSEMBLY

The display is to include the date and time the module was assembled.

ENViron[=FSS|JES2|MIXED|SUBTASK |USER|DOC|IPCS|?]

This parameter either requests that the display for each module include the value of the module's \$MODule ENVIRON= parameter or it filters on the value of each module's \$MODule ENVIRON= parameter to limit the set of modules for which information is displayed.

- To request that the display for each module include the value of the \$MODule ENVIRON= parameter on the D MODule statement, code ENV without the equal sign and a keyword value.
- To request that the parameter act as a filter, on the D MODule statement code ENV= followed by a keyword value.

When this parameter acts as a filter, information for each module is displayed only if the value you code on the D MODule ENV= parameter matches the value on the module's \$MODule ENVIRON= parameter.

Valid key-word values for the D MODule ENV= parameter and their meanings are:

Value

Meaning

?

Display all modules.

DOC

Display only those modules assembled with an environment of DOC.

FSS

Display only those modules that are assembled for the FSS address space environment.

IPCS

Display only those modules that were assembled for the JES2 IPCS command.

JES2

Display only those modules that are assembled for the JES2 address space main task environment.

MIXED

Display only those modules that are assembled for multiple environments.

SUBTASK

Display only those modules that are assembled for the JES2 address space subtask environment.

USER

Display only those modules that are assembled for the multi-address-space user environment.

The following examples show how you might code this parameter:

- If you code:

```
D MODule(*) ENV
```

information is displayed for all modules and includes the value of the module's \$MODule ENVIRON= parameter.

- If you code:

```
D MODule(*) ENV=JES2
```

the display includes only those modules that were assembled for the JES2 environment: that is, the modules whose \$MODule macro specifies ENVIRON=JES2.

EXITPTS

The display is to include the exit points defined in the module. If the module being displayed issued the \$EXIT macro, the display includes the exit points defined by that macro. An exit point is a number from 0 through 255. For example, if the module defined exit point 31, the display shows **EXITPTS=(31)**.

If the module did not issue the \$EXIT macro, the display shows

EXITPTS=().

FMID

Displays the FMID of the release of JES2.

IBMJES2[=BASE|No|SAMPLE]

This parameter requests that the display for each module include a field that indicates the category of the module. The categories are: a base module in the JES2 product, a JES2-provided sample exit routine, or any other JES2 module that's not provided as part of the JES2 product.

Alternately, this parameter acts as a filter. As a filter, the parameter limits the display to only those modules that fall into one of the three module categories just mentioned.

- To request that the display include the category of each module, code IBMJES2 omitting the equal sign and the keyword values.
- To request that the parameter act as a filter, code IBMJES2= followed by a keyword value. The keyword values and their meanings are:

Value**Meaning****BASE**

Limit the display to only base modules in the JES2 product.

SAMPLE

Limit the display to JES2-provided sample exit routines.

NO

Limit the display to JES2 modules that are not base modules or JES2-provided sample exit routines.

LASTapar[=aannnnn|NONE]

This parameter requests that the display for each module include the number of the last APAR applied to the module.

Alternately, this parameter acts as a filter. As a filter, the parameter limits the display to only those modules that have a specific APAR applied as the last APAR or to those modules that have no APARs applied.

- To request that the display include the number of the last APAR applied to each module, code LASTAPAR without coding the equal sign and a keyword value. For IBM-provided modules, the display includes the APAR number, or if no APAR has been applied, the display is the string NONE.

For non-IBM modules that contain a character constant with the label APARNUM, the display includes the value of the character constant. For non-IBM modules that do not contain this constant, the display includes the value of the &UVERS global variable.

- To request that the parameter act as a filter, code LASTAPAR= followed by a keyword value. The keyword values and their meanings are:

Value

Meaning

aannnnn

Limit the display to only those modules that have APAR *aannnnn* applied as their last APAR.

NONE

Limit the display to only those modules that have no APARs applied.

LASTPTF

Displays the latest PTF maintenance applied to this module.

LENgth=nnnnnn

This parameter displays the module hexadecimal length. The length that is displayed is the module's approximate length within 8 bytes of the accurate length. The display is to include the module length. The length that's displayed is the module's approximate length and is generally within 8 bytes of the actual module length.

LOADmod[=accccccc]

This parameter requests that the display for each module include the name of the load module that contains the assembly module.

Alternately, this parameter acts as a filter. As a filter, the parameter limits the display to only those assembly modules that are contained within a specific load module.

- To request that the display for each assembly module include the name of the containing load module, code LOAD without coding the equal sign and the name of a load module.
- To request that the parameter act as a filter, code LOAD= followed by a load module name. The display will include only those assembly modules that are contained within the named load module.

LONG

Displays additional information:

VERSION

Displays the version of JES2.

UVERSION

Displays the user version of JES2.

MACLevel[=1|2|3|4|5|6]

This parameter requests that the display for each module include the level of the MVS macro library used during assembly of the module.

Alternately, this parameter acts as a filter. As a filter, the parameter limits the display to only those modules that used a specific MVS macro library during assembly.

- To request that the display for each module include the level of the MVS macro library used during assembly, code MACL without coding the equal sign and a numerical value.
- To request that the parameter act as a filter, code MACL= followed by a numerical value. The numerical values and their meanings are:

Value**Meaning****1**

Display only those modules that used the level 1 MVS macro library, MVS/SP Version 1, Release 3.

2

Display only those modules that used the level 2 MVS macro library, MVS/SP Version 2.

3

Display only those modules that used the level 3 MVS macro library, MVS/SP Version 3.

4

Display only those modules that used the level 4 MVS macro library, MVS/ESA Version 4.

5

Display only those modules that used the level 5 MVS macro library, OS/390® Release 1 and MVS/ESA SP Version 5.

6

Display only those modules that used the level 6 MVS macro library, OS/390 Release 2.

ROUTINES

Displays routines and their addresses within the module. Only routines defined through \$ENTRY are displayed. When used as a filter, displays only the module containing the routine, and only the specified routine address unless LONG is also specified.

SPLevel[=CHECK|NOCHECK]

This parameter requests that the display for each module include the value the module assigned to the SPLEVEL= parameter on the \$MODule macro.

Alternately, this parameter acts as a filter. As a filter, the parameter limits the display to only those modules that have assigned a specific value to the \$MODule SPLEVEL= parameter.

- To request that the display for each module include the value assigned to the \$MODule SPLEVEL= parameter, code SPLEVEL without coding the equal sign and a keyword value.
- To request that the parameter act as a filter, code SPLEVEL= followed by one of the following keywords:

Value**Meaning****CHECK**

Display only those modules that specified CHECK on the \$MODule SPLEVEL= parameter.

NOCHECK

Display only those modules that specified NOCHECK on the \$MODule SPLEVEL= parameter.

TABLES

Displays any DYNAMIC tables which are defined in this module, along with the type of table.

Usage Note for D MODule(jxxxxxxx)

You can place this statement anywhere within the initialization stream.

Examples of D MODule(jxxxxxxx)

1. For all JES2 modules, display all applicable information.

```
D MODule(*)
$HASP468 MODule(HASCD AU) ADDRESS=02FF7000, ASSEMBLY=(09/12/92,
$HASP468 16.07), ENVIRON=USER, EXITPTS=(),
$HASP468 IBMJES2=BASE, LASTAPAR=NONE,
$HASP468 LENGTH=0002D0, LOADMOD=HASCD AU,
$HASP468 MACLEVEL=4, SPLEVEL=CHECK
$HASP468 MODule(HASCD SAL) ADDRESS=02FF2000, ASSEMBLY=(09/12/92,
$HASP468 16.07), ENVIRON=USER,
$HASP468 EXITPTS=(31,34,48), IBMJES2=BASE,
```

D MODuLe(jxxxxxxx)

```
$HASP468 LASTAPAR=NONE, LENGTH=004CA0,
$HASP468 LOADMOD=HASCDSAL, MACLEVEL=4,
$HASP468 SPLEVEL=CHECK
$HASP468 MODuLe(HASCDSOC) ADDRESS=02FEF000, ASSEMBLY=(09/12/92,
$HASP468 16.07), ENVIRON=USER, EXITPTS=(30,33),
$HASP468 IBMJES2=BASE, LASTAPAR=NONE,
$HASP468 LENGTH=002A68, LOADMOD=HASCDSOC,
$HASP468 MACLEVEL=4, SPLEVEL=CHECK
$HASP468 MODuLe(HASCDSS) ADDRESS=02FED000, ASSEMBLY=(09/12/92,
$HASP468 16.07), ENVIRON=USER, EXITPTS=(),
$HASP468 IBMJES2=BASE, LASTAPAR=NONE,
$HASP468 LENGTH=001190, LOADMOD=HASCDSS,
$HASP468 MACLEVEL=4, SPLEVEL=CHECK
:
```

2. For all JES2 modules whose last applied service was APAR OY52946, display all applicable information.

D MODuLe(*) LASTAPAR=OY52946

```
$HASP468 MODuLe(HASPMMSG) ADDRESS=00051000, ASSEMBLY=(09/12/92,
$HASP468 16.15), ENVIRON=JES2, EXITPTS=(),
$HASP468 IBMJES2=BASE, LASTAPAR=OY52946,
$HASP468 LENGTH=009E40, LOADMOD=HASJES20,
$HASP468 MACLEVEL=4, SPLEVEL=CHECK
$HASP468 MODuLe(HASPNATS) ADDRESS=0005B000, ASSEMBLY=(10/02/92,
$HASP468 19.34), ENVIRON=JES2, EXITPTS=(),
$HASP468 IBMJES2=BASE, LASTAPAR=OY52946,
$HASP468 LENGTH=002830, LOADMOD=HASJES20,
$HASP468 MACLEVEL=4, SPLEVEL=CHECK
$HASP468 MODuLe(HASPNPM) ADDRESS=00062000, ASSEMBLY=(10/02/92,
$HASP468 19.34), ENVIRON=JES2, EXITPTS=(),
$HASP468 IBMJES2=BASE, LASTAPAR=OY52946,
$HASP468 LENGTH=007F70, LOADMOD=HASJES20,
$HASP468 MACLEVEL=4, SPLEVEL=CHECK
$HASP468 MODuLe(HASPSTAB) ADDRESS=000B8000, ASSEMBLY=(10/02/92,
$HASP468 19.34), ENVIRON=JES2, EXITPTS=(),
$HASP468 IBMJES2=BASE, LASTAPAR=OY52946,
$HASP468 LENGTH=014A18, LOADMOD=HASJES20,
$HASP468 MACLEVEL=4, SPLEVEL=CHECK
```

3. For all JES2 modules, display the loaded address.

D MODuLe(*) ADDR

```
$HASP468 MODuLe(HASCDAU) ADDRESS=02FF7000
$HASP468 MODuLe(HASCDSAL) ADDRESS=02FF2000
$HASP468 MODuLe(HASCDSOC) ADDRESS=02FEF000
$HASP468 MODuLe(HASCDSS) ADDRESS=02FED000
$HASP468 MODuLe(HASCGGKY) ADDRESS=02FEC000
$HASP468 MODuLe(HASCGGST) ADDRESS=02FEB000
$HASP468 MODuLe(HASCHAM) ADDRESS=00B67000
$HASP468 MODuLe(HASCJBST) ADDRESS=02FE7000
$HASP468 MODuLe(HASCJBTR) ADDRESS=02FE5000
:
```

4. For all JES2 modules for which APAR OY52964 was the last APAR applied, display the module name and loaded address.

D MODuLe(*) LASTAPAR=OY52946, ADDR

```
$HASP468 MODuLe(HASPMMSG) ADDRESS=00051000
$HASP468 MODuLe(HASPNATS) ADDRESS=0005B000
$HASP468 MODuLe(HASPNPM) ADDRESS=00062000
$HASP468 MODuLe(HASPSTAB) ADDRESS=000B8000
```

5. For all JES2 modules whose name begins with the string 'HASPI', display the module name and the number of the last APAR applied.

D MODuLe(HASPI*) LASTAPAR

```
$HASP468 MODuLe(HASPIRA) LASTAPAR=NONE
$HASP468 MODuLe(HASPIRDA) LASTAPAR=NONE
$HASP468 MODuLe(HASPIRMA) LASTAPAR=NONE
$HASP468 MODuLe(HASPIRPL) LASTAPAR=NONE
$HASP468 MODuLe(HASPIRRE) LASTAPAR=NONE
$HASP468 MODuLe(HASPIRSI) LASTAPAR=NONE
```


6. For all JES2 modules in load module HASPINIT, display module name, assembly date and time, and the macro level at which the module was assembled.

```
D MODuLe(*) LOADMOD=HASPINIT,MACLEVEL,ASSEMBLY
$HASP468 MODuLe(HASPIRA) MACLEVEL=4,ASSEMBLY=(09/12/92,16.14)
$HASP468 MODuLe(HASPIRDA) MACLEVEL=4,ASSEMBLY=(09/12/92,16.14)
$HASP468 MODuLe(HASPIRMA) MACLEVEL=4,ASSEMBLY=(09/24/92,16.24)
$HASP468 MODuLe(HASPIRPL) MACLEVEL=4,ASSEMBLY=(09/12/92,16.14)
$HASP468 MODuLe(HASPIRRE) MACLEVEL=4,ASSEMBLY=(09/12/92,16.14)
$HASP468 MODuLe(HASPIRSI) MACLEVEL=4,ASSEMBLY=(09/12/92,16.14)
```

D OPTsdef - Display JES2 start options

Display JES2 start options.

Format description



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter description

CKPTOPT

Displays which checkpoint data set JES2 read as the source for building the JES2 work queues during the last restart.

COLD_START_MODE

Displays the activation level used for the cold start mode (DEFAULT, Z11, Z22).

CONSOLE

Displays the value of the CONSOLE option.

HASPPARM

Displays the name of the data definition (DD) statement that defines the data set containing the initialization statements that JES2 is to use for initialization.

LIST

Displays whether or not JES2 lists the current and subsequent initialization statements on the printer defined by the HASPLIST DD statement.

LISTOPT

Displays the value of the LISTOPT start option.

LOG

Displays whether or not JES2 copies subsequent initialization statements to the printer specified by the HASDCPY console.

LOGOPT

Displays the value of the LOGOPT start option which specifies whether or not JES2 logs the initialization statements to a device (if specified).

D SUBNET(jxxxxxxx)

RECONFIG

Displays the value of the RECONFIG start option which specifies whether the operator can specify RECONFIG to override any/all previous checkpoint forwarding.

REQMSG

Displays the value of the REQINOREQ start option which specifies whether JES2 issues the \$HASP400 ENTER REQUESTS message.

SPOOL

Displays whether this member performed a spool validation on its last restart, and whether validation was forced.

STARTopt

Displays the type of start that was specified in the initialization options (FORMAT, COLD, WARM).


STARTYPE

Displays the type of start that was actually performed (FORMAT, COLD, ALL-MEMBER WARM, SINGLE-MEMBER WARM, QUICK, HOT).

D SUBNET(jxxxxxxx) - Display Subnet Connections

Display subnet connections.

Format Description for D SUBNET(jxxxxxxx)



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for D SUBNET(jxxxxxxx)

(jxxxxxxx|*)

Specify the 1- to 8-alphanumeric or special (\$, #, or @) character subnet name to obtain information for a specific subnet or specify an asterisk(*) to obtain information for **all** subnets.

NODE=nnnn


Specifies the node number of the subnet connection.

DEBUG - JES2 Debug Option

The DEBUG statement defines whether JES2 will record and monitor specified JES2 activities. The information recorded as a result of selecting this option can only be made available through a dump of the JES2 address space.

Performance Considerations: Be aware that if you specify CKPT=, or VERSION= parameters, in a production environment, specifying Yes on these options will affect JES2 performance because it causes JES2 to use noticeably more processor cycles.

Format Description for DEBUG



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter description DEBUG

DEBUG=Yes|No

Specifies whether (Yes) or not (No) you require JES2 to record certain JES2 events and to monitor certain JES2 activities. Specifying DEBUG=Yes requests JES2 to record **all** events that are listed individually on this statement.

Modification: \$T DEBUG operator command.

DEBUG=Yes|No

Specifies whether (Yes) or not (No) you require JES2 to record certain JES2 events and to monitor certain JES2 activities. Specifying DEBUG=Yes requests JES2 to record all events that are listed individually on this statement except VERBOSE= and MEMBER_STATUS= (which are unaffected). Specifying DEBUG=No requests JES2 to stop recording all events that are listed individually on this statement except MEMBER_STATUS= (which is unaffected).

Modification: \$T DEBUG operator command.

BERT=Yes|No

Specifies whether (Yes) or not (No) JES2 provides error code \$BR3 to inform the operator that a data error has been detected in a chain of BERTs.

Modification: \$T DEBUG operator command.

CKPT=Yes|No

Specifies whether (Yes) or not (No) JES2 should verify the integrity of the checkpoint data set.

Modification: \$T DEBUG operator command.

EDS=Yes|No

Specifies whether (YES) or not (NO) JES2 email sender task in JES2 EDS address space should provide additional diagnostic information during communication with the z/OSMF server.

Modification: \$T DEBUG operator command.

MEMBER_STATUS=No|Yes

Specifies whether (YES) or not (NO) JES2 issues the \$HASP1701 message when the status of a member has changed.

Modification: \$T DEBUG operator command.

MISC=Yes|No

Specifies whether (Yes) or not (No) JES2 provides occurrence counting of certain JES2 events.

Modification: \$T DEBUG operator command.

QVERIFY=Yes|No

Specifies whether (Yes) or not (No) JES2 is to perform a verification of the job, output, and BERT data areas and queues every time the JES2 checkpoint is read. This is intended to detect various types of errors in the checkpoint data read by the current system. If an error is detected, JES2 issues a disastrous error with label KVRFYERR.

JES2 does not attempt to correct the error, report it and continue. This might result in the KVRFYERR disastrous error being issued every time that the checkpoint is read until the error is corrected (for example by a hot start).

Due to the significant additional overhead of this process, it is intended for use only in a test environment or to capture data for which all other diagnostic tools have failed.

Modification: \$T DEBUG operator command.

SECURITY=Yes|No

Specifies whether (Yes) or not (No) JES2 provides more RACF® security logging related to the \$HASP186 error message. YES specifies that JES2 requests RACF to log access violations, including warning mode violations, for JES2 output work selection for:

- JES2 devices (such as local and remote printers and punches, and NJE and offload SYSOUT transmitters)
- External writer (XWTR) requests
- SYSOUT Application Program Interface (SAPI) requests (SSI function code 79).

If an access violation occurs, and you have DEBUG SECURITY=YES, JES2 issues message \$HASP186 after RACF issues message ICH408I. The LOGSTR that JES2 passes to RACF identifies the problem as one of the following:

- JES2 Work Selection Screening
- External Writer Work Selection Screening
- SYSOUT Application Program Interface (SAPI) requests (SSI function code 79).

Modification: \$T DEBUG operator command.

STORAGE=Yes|No

Specifies whether (Yes) or not (No) JES2 provides \$HASP095 error code GW3 to inform the operator that \$RETNWORK macro processing detected that the storage being returned was modified beyond the length that is specified by the associated \$GETWORK macro invocation.

Modification: \$T DEBUG operator command.

SYMREC=Yes|No

Specifies whether (Yes) or not (No) when JES2 requests that MVS write a symptom record to the LOGREC data set, JES2 issues message \$HASP805 *jobname* SYMREC ISSUED FROM *module* WITH A DESCRIPTION OF *desc*. Although the message is useful to inform you of errors, some symptom records are informational and you might not want to receive this message whenever JES2 requests a symptom record. Symptom records are written to the LOGREC data set regardless of this specification.

Note: You can use the DEBUGMSG=No specification on the \$SYMTAB macro to suppress the \$HASP805 message even when SYMREC=Yes is specified here.

Modification: \$T DEBUG operator command.

TIMECLOCK=Yes|No

Specifies whether (Yes) or not (No) JES2 takes a disastrous error (TIMERROR) when a job's hold time and SCHENV-delay time added to arrival time exceeds current clock value.

Modification: \$T DEBUG operator command.

VERBOSE=Yes|No

Specifies whether (Yes) or not (No) JES2 should use a more verbose form of messaging. For example, messages associated with MEMBER_STATUS=YES is issued with additional text. Other messages that normally are only placed in the hardcopy are directed to the console.

Modification: \$T DEBUG operator command.

VERSION=Yes|No

Specifies whether (Yes) or not (No) JES2 should verify the integrity of a newly created checkpoint version.

Modification: \$T DEBUG operator command.

DESTDEF - Defining How Destinations Are Processed

SYSOOT and jobs can be directed to various devices and nodes by JES2 destination processing. How those destinations are interpreted and displayed is controlled by the DESTDEF initialization statement.

Some destination prefixes have special meanings to JES2, which can cause difficulties for installations that may want to define userids that use these prefixes. JES2 recognizes a special meaning for destinations of the form 'Nnnnn', 'Rmmmm', 'RMmmmm', 'RMTmmmm', 'Unnnn', 'NnnnnRmmmm' (where 'nnnn' and 'mmmm' represent numbers from 0 to 32767 unless otherwise defined). Destinations of this form are called explicit destinations.

DESTDEF applies to all destinations that JES2 processes except those specified through the DEST= parameter of the DESTID initialization statement.

JES2 destinations are composed of two parts:

- A first-level destination indicating a particular node.
- A second-level destination indicating a remote workstation, special local route code, or userid.

An installation can remove the special meaning JES2 processing assumes for the prefixes 'N', 'R', 'RM', 'RMT', and 'U' by specifying 'USER' on the Ndest=, Rdest=, RMdest=, RMTdest= and Udest= parameters. If 'USER' is specified for a particular prefix, it no longer has special meaning in JES2 processing and can be used as a user destination (including TSO/E userids).

The Rdest= and Ndest= parameters also apply to JES2 destinations that specify both a node and a remote (NnnnnRmmmm).


DESTDEF

Destinations displayed for SYSOUT routed to a user routing at the local node can be confused with other destinations. To eliminate confusion, specify the SHOWUSER=WITHlocal parameter so that destinations with user routings are displayed with a 'LOCAL.' prefix. For example, at the destination node, 'LOCAL.JOHN' is displayed as the routing for SYSOUT with a user routing of 'JOHN'.

If an installation is using RJE devices and has specified Rdest=USER, at least one DESTID statement must be defined for each RJE device. If more than one destid is defined with any particular RJE routing, at least one of the destids must be defined with PRIMARY=YES. For example, if remote 5 is defined, then 'DESTID(xxxxxxx) DEST=N1.R5,PRIMARY=YES' must also be defined so that JES2 displays the route code 'N1.R5' consistently.

For more examples of how JES2 resolves the display of multiple destids with the same routing, see [z/OS JES2 Initialization and Tuning Guide](#).

Format Description for DESTDEF



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for DESTDEF

LOCALNUM=nnnnn|32767

Specifies the maximum special local routing allowed on this member.

Any destination that starts with a 'U' followed by a number that is less than or equal to the LOCALNUM parameter specification is converted to a special local route code. JES2 assumes that a destination greater than the LOCALNUM= parameter specification has no special meaning.

Note: If you also specify Udest=USER, this parameter is ignored.

Modification: Single-member warm start.

Ndest=Node|User

Specifies whether JES2 interprets destinations of the form 'Nnnnn' and 'NnnnnRmmmm' as node 'nnnn'(Node) or as userid destinations (User).

'nnnn' is a number from 1 to the value specified on the NODENUM= parameter of the NJEDEF statement. Specifying Ndest=Node makes the destination 'Nnnnn' synonymous with the NAME= parameter of the NODE(xxxxxxx) initialization statement.

Modification: All-member warm start or JES2 cold start.

NODENAME=REQUIRED|OPTIONAL

NODENAME=REQUIRED indicates that when specifying a userid for a destination, it must be prefixed with a node name. This applies to JES2 commands, JCL, and dynamic allocation (SVC 99) requests. The /*NOTIFY JECL statement accepts just a userid. For example, if DESTDEF NODENAME=REQUIRED and a DEST= userid is coded on a DD statement, that statement will result in a JCL error. In order to route the SYSOUT data set to a userid, you must prefix the userid with a node name. For example, to route output to userid SMITH at node NEWYORK, even if NEWYORK is the local node, you would specify DEST=NEWYORK.SMITH.

NODENAME=OPTIONAL indicates that userids are allowed to be specified without a node specification. In order to route a data set to a userid on the local node, you do not have to specify the node name. For example, to route a data set to userid JONES at the local node, you can just code DEST=JONES.

Note: If you type in a destid for the destination incorrectly and this value conforms to the syntax rules for a userid on the local node, the value will be accepted as a userid.

Modification: All-member warm start or JES2 cold start.

Rdest=Remote|User

Specifies whether JES2 interprets destinations of the form 'Rmmmm' and 'NnnnnRmmmm' as an RJE remote workstation 'mmmm' (Remote) or a userid (User).

Note: Remote destinations of the form R0xxxxxx are interpreted as userids when you specify RDEST=User or when xxxxxx is greater than 32767. If xxxxxx is between 9999 and 32767 and you specify RDEST=Remote, the "0" is truncated. (That is, your remote destinations take the form of R9999 to R32767.)

Modification: All-member warm start or JES2 cold start.

RMdest=Remote|User

Specifies whether JES2 interprets destinations of the form 'RMmmmm' as an RJE remote workstation 'mmmm' (Remote) or a userid (User).

Modification: All-member warm start or JES2 cold start.

RMTdest=Remote|User

Specifies whether JES2 interprets destinations of the form 'RMTmmmm' as remote RJE workstation 'mmmm' (Remote) or a userid (User).

Modification: All-member warm start or JES2 cold start.

SHOWUSER=No|local|WITH|local

Specifies whether (WITH|local) JES2 destinations for the local node which have user routings are displayed with a 'LOCAL.' prefix or not (No|local).

SHOWUSER=WITH|local would have output routed to a TSO/E userid of TOM at the local node display as 'LOCAL.TOM'. For the same example, SHOWUSER=No|local would display only 'TOM'.

When RDEST, NDEST, or UDEST are specified as USER, SHOWUSER=WITH|local should be specified to avoid possible confusion when user routings conflict with special local (U3), remote workstation (R5), and node (N1) explicit routings.

SHOWUSER affects how destinations are presented to SDSF. This parameter can affect their security profiles. To evaluate the impact of SHOWUSER, see the [z/OS SDSF Operation and Customization](#) before specifying the parameter.

Modification: \$T DESTDEF operator command.

Udest=Splocal|User

Specifies whether JES2 interprets destinations of the form 'Unnnn' as special local (Splocal) device routing 'nnnn' or a userid (User). 'nnnn' is a number from 1 to the value specified on the DESTDEF LOCALNUM= parameter.

Note:

1. When Udest=Splocal, DESTDEF LOCALNUM= specifies the maximum number JES2 allows for a special local routing. For example, if UDEST=Splocal and LOCALNUM=5, JES2 would interpret a destination of 'U3' as a special local route code, but a destination of 'U7' as a userid.
2. LOCALNUM= specifies the maximum number of **special local routing destinations only**, it is honored only if you also specify UDEST=Splocal.

Modification: All-member warm start or JES2 cold start.

DEStid(xxxxxxx) - Route Code Name

The DEStid(xxxxxxx) statement specifies an installation-defined name for a JES2 route code. By defining DEStid names for route codes, the users and operators can refer to the DEStid names instead of the explicit names provided by JES2 (such as 'Nnnnnn' where 'nnnn' represents a number from 0 to 32767). If you modify this statement and then restart JES2 with a hot start, the parameter value in effect before termination will be used. This statement can be modified through the \$T DEStid command.

Adding Destination Identifiers

This statement and all its parameters can be added after initialization with the **\$ADD DEStid operator command**.

A JES2 route code consists of a first-level destination that represents the target node for the job or SYSOUT and a second-level destination that represents a destination at a node. Installations can define DEStids for:

- First-level destinations that specify a node name as destination.

```
DEStid(SANJOSE) DEST=N5
```

- Second-level destinations that specify a remote workstation, special local route code, or a userid.

```
DEStid(REMOTE3) DEST=R3
```

- Identifiers that specify both a node and a remote workstation, special local route code, or a userid at that node.

```
DEStid(PLOTTER) DEST=N3.U4
```

DEStids can be referred to in the DEST parameter of the JCL data definition (DD) statements or output statement for SYSOUT data set; in dynamic allocation of SYSOUT; or in the TSO/E OUTPUT command. Also, operators may use DEStids in many JES2 operator commands.

Specifying the DEStid Subscript

The DEStid subscript (xxxxxxx) specifies the 1- to 8-character name that users and operators may use to refer to the JES2-defined destinations. The characters in the name must not be a valid explicit destination unless you specify USER on the corresponding DESTDEF initialization statement parameters. That is, the name must not be in a form that looks like a valid explicit destination. Consider the following example definition:

```
If you code:
    DESTDEF RMTDEST=USER
```

```
then:      DEStid(RMT5) DEST=R5
is valid and possibly useful.
```


RMTDEF=USER defines destinations such as R5 as a userid rather than a remote workstation name of the form RMT5. DEStid(RMT5) points to R5, a route code defined by initialization statement RMT(5), ROUTECDE=5. RMT5 is then interpreted as remote number 5 instead of userid RMT5. All other destinations of the form RMTmmmmm would be considered as a userid, unless there was a DEStid statement of the form DEStid(RMTmmmmm) DEST=Rmmmmm to define RMTmmmmm as a remote workstation.

If you do not specify USER for the DESTDEF initialization statement parameters, IBM suggests that you avoid potential confusion when routing SYSOUT from one destination to another by **not** specifying the following forms of TSO/E userid names on a JES2 member:


- Nnnnn
- Rmmmm
- RMmmmm
- RMTmmmm
- NnnnnRmmmm
- Unnnn
- ANYLOCAL|LOCAL
- Any DEStid name defined on a DEStid(xxxxxxx) initialization statement
- Any DEStid name added through a \$ADD DEStid(xxxxxxx) operator command
- Any name specified on the NAME= parameter of the NODE(xxxxxxx) initialization statement
- Any name specified on the NAME= parameter of the \$T NODE(xxxxxxx) operator command.

The subscript can be either a specific destination name (MYDEST1) or a generic destination name (MYD*). You **cannot** alter the DEST= parameter value with a generic request such as \$T DEStid(MYD*),DEST=N3, but you can display the value through a generic request using the \$D DEStid(MYD*) command. Using an asterisk as a filter can be useful when installations have used a particular set of characters (for example NYC) to create all their destination names.


Format Description for DEStid(xxxxxxx)



Modification keywords



Selection limiting keywords



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for DEStid(xxxxxxxx)

(xxxxxxxx)

The 1-8 character symbolic destination name affected by this statement.

DEST=

Specifies a route code JES2 can use to route data.

When specifying only the node (first-level destination):

nodename|Nnnnn

References only the nodal portion (first-level destination) of a JES2 route code.

nodename

Specify a symbolic nodename. For example, if NODE(10) is defined with NAME=ALBANY, then an installation can create a DEStid(NYCAP) with DEST=ALBANY.

Nnnnn

Specify N followed by a numeric value (1-32767). For example, DEStid(NYCAP) DEST=N10.

When specifying only the destination at a node (second-level destination):

LOCAL|ANYLOCAL|Rmmmm|RMmmmm|RMTmmmm|Unnnn|userid

References only the destination at a node (second-level destinations).

When these DEStids are referenced, users must specify either an explicit first-level destination or allow JES2 to assign a default first-level destination. JES2 determines the first-level portion of the destination from one of the following:

- /*ROUTE PRT JES2 control statement
- /*ROUTE PUN JES2 control statement
- The output route code associated with the device through which the job entered the member.

For example, DEStid(REMOTE5) DEST=R5 defines a second-level destination. Using the DEStids DEStid(NYCAP) DEST=ALBANY and DEStid(NYCAP) DEST=N10, JCL can route a data set to R5 at N10 by specifying DEST=NYCAP.REMOTE5.

However, if the JCL only specifies DEST=REMOTE5, the nodal portion of the destination is obtained from the default routing of the job. (A job submitted from N10 without any /*ROUTE JES2 control statements has a default nodal routing of N10, regardless of where in the network it executes.)

Valid destinations:

LOCAL|ANYLOCAL

Data is not associated with any specific routing.

Rmmmm|RMmmmm|RMTmmmm

Specify R, RM, or RMT, followed by a numeric value (0 - 32767). For example, 'R17' represents remote workstation 17.

Unnnn

Specify U followed by a numeric value in the range of 1 through the value specified on the LOCALNUM= parameter of the DESTDEF statement. For example, 'U19' represents special local routing 19.

Use the LOCALNUM= parameter on the DESTDEF initialization statement to specify the highest number for a special local route code. JES2 assumes that numbers beyond this range are userids.

userid

Specifies a 1- to 8-character string that is interpreted on the destination node. For example, the string 'TANYA' represents a userid (assuming that there are no DESTids that define TANYA at the destination node).

When specifying both the node and a destination at that node (first- and second-level destinations):

NnnnnRmmmm|node.destination

Allows an installation to define the complete JES2 route code (destination at a specified node). JES2 does not use information from the default routing.

NnnnnRmmmm

Specify N, followed by a numeric value (1 - 32767), then R followed by a numeric value (0 - 32767). For example, N5R7 indicates remote 7 at node 5.

node.destination

Specify a first-level destination, followed by a period; followed by either a second-level destination or a complete destination.

If 'destination' is a second-level destination, the routing associated with this DESTid is the composite of 'node' and 'destination'.

For the following examples, assume that node 1 is the local node:

- 'N1.R3' indicates data routed to remote 3 at the local node.
- 'N2.R5' indicates data routed to whatever 'R5' is at node 2.
- 'N5.BOB' indicates data is routed to whatever 'BOB' is at node 5.

If 'destination' is a complete destination, the final routing associated with this DESTid depends on 'node'.

For the following examples, assume that node 1 is the local node:

- 'N2.N2R3' indicates data routed to remote 3 at node 2 because the first-level destination of 'destination' matches 'node'.
- 'N5.N2R3' indicates data routed to 'N2R3' at node 5 because the first-level destination of 'destination' does not match 'node' and 'node' is not the local node. If node 5 has not explicitly defined 'N2R3', node 5 routes the data to destination 'R3' at node 2.
- 'N1.N5R3' results in an error because the first-level destination of 'destination' does not match 'node' and 'node' is the local node.

Note that you can use existing DEStids or node names (those previously defined in the initialization stream) to create new DEStids. However, if you create a DEStid using a symbolic DEST= parameter, and that name is used as:

- a subscript in a subsequent DEStid initialization statement or node name in a subsequent NODE initialization statement.

JES2 will consider the first DEStid statement specified to be in error. In general, whenever an initialization statement changes the destination that a previous DEStid statement would resolve to, JES2 marks the DEStid statement as an error.

For example, assume that the following DEStids are defined:

```
DEStid(ALBANY)    DEST=N10
DEStid(REMOTE5)  DEST=R5
DEStid(BIGAPPLE) DEST=N7
DEStid(TWINTOWR) DEST=TALLBLDG
```

You can define:

```
DEStid(CAPITOL) DEST=ALBANY.REMOTE5
```

The routing associated with 'CAPITOL' is N10.R5.

You can define:

```
DEStid(NYC)      DEST=BIGAPPLE
```

The routing associated with 'NYC' is N7.

If you define:

```
DEStid(TALLBLDG) DEST=R10
or
NODE(5) NAME=TALLBLDG
```

JES2 treats the DEStid(TWINTOWR) statement as an error, and issues error message \$HASP512. To route TWINTOWR output to R10, place the DEStid(TALLBLDG) statement before the DEStid(TWINTOWR) statement in the initialization stream.

A DEStid pointing to itself does not change the status of the destination:

```
DEStid(PRT5) DEST=PRT5
```

This is considered redundant. The status of PRT5 is not changed.

PRIMARY={Yes|No}

Specifies whether (Yes) or not (No) to use this DEStid for job and SYSOUT routing. This means use for display purposes as well as pass via subsystem interface calls, such as FSI. Use this parameter if multiple DEStids have the same routing.

When searching for a DEStid to display/provide via subsystem invocation for a job's or SYSOUT's routing, JES2 selects:

1. Node name (DEStid with STATUS=NODENAME) if routed to a node.
2. First DEStid found that specifies PRIMARY=YES.
3. If only one DEStid is found, that DEStid is used.
4. If multiple DEStids are found, no DEStid is used (and routing is displayed/provided explicitly).

If USER is specified for either the Ndest=, Udest=, or R|RM|RMTdest= parameters on the DESTDEF initialization statement and multiple DEStids can match the routing of a job or SYSOUT data set, then at least one of these multiple DEStids must specify PRIMARY=Yes. If not, products such as SDSF may have problems altering the routing of a job or SYSOUT data set to any of these multiply defined DEStids.

Because PRIMARY=Yes can affect SDSF's security procedures, consult the [z/OS SDSF Operation and Customization](#) before using this parameter.

EDS - Specify EDS parameters

The EDS initialization statement defines configuration parameters of JES2 Email Delivery Services (EDS). See description of EDS in *z/OS JES2 Initialization and Tuning Guide*.

Format Description for EDS



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for EDS

EMAIL STACK=name

Specifies the name of the TCP/IP stack to be used for EDS email support (to connect to z/OSMF server), when the Common INET (CINET) configuration is being used.

If not specified, the default TCP/IP stack is used. When only an INET configuration is being used, specification of a stack name is ignored.

Modification: \$T EDS operator command.

Scope: Single member.

JOBIFY STACK=name

Specifies the name of the TCP/IP stack to be used for EDS job notification support (to connect to the target of the job notification request), when the Common INET (CINET) configuration is being used.

If not specified, the default TCP/IP stack is used. When only an INET configuration is being used, specification of a stack name is ignored.


Modification: \$T EDS operator command.

Scope: Single member.

ESTBYTE - Estimated Spool Utilization for Output Exceeded

The ESTBYTE statement specifies the amount of spool space used before the \$HASP375 (ESTIMATED BYTES EXCEEDED) message is initially written to the operator, the interval at which it is repeated, and the action JES2 takes if the output exceeds the estimate. Your installation can provide an output overflow installation exit routine (Exit 9) to override this statement on a per-job basis.

Format Description for ESTBYTE



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for ESTBYTE

NUM=nnnnnn|99999

Specifies the number (1-999999), in thousands of bytes of spool space, after which message \$HASP375 is written to inform the operator that the job's estimated output has been exceeded. The user can override the spool utilization value specified on this parameter by using the BYTES= keyword defined on the /*JOBPARM control statement.

Modification: \$T ESTBYTE operator command or cold start. If you modify this parameter value and then restart JES2 with a warm or hot start, the parameter value in effect before termination is used.

INT=nnnnn|99999

Specifies the interval (1-99999), in thousands of bytes of spool space, at which message \$HASP375 is repeated. The message is first issued when the estimated bytes (NUM= value) is exceeded.

Modification: \$T ESTBYTE operator command or cold start. If you modify this parameter value and then restart JES2 with a warm or hot start, the parameter value in effect before termination is used.

OPT=0|1|2

Specifies the action JES2 takes when a job exceeds the estimated spool utilization as specified by the NUM= parameter. The following are the options and subsequent action:

0

Job is allowed to continue execution

1

Job is canceled without a dump

2

Job is canceled with a dump (if a dump statement was coded for this job step)

Modification: Hot start or \$T ESTBYTE operator command.


ESTIME - Default Estimated Execution Time and Options

The ESTIME statement specifies the default elapsed wall clock time for a job, the interval at which the \$HASP308 (ESTIMATED TIME EXCEEDED) message is written to the operator and whether the JES2 elapsed time job monitor feature is supported.

Note: If changed by the \$T command after a job was submitted, the ESTIME parameters are affected as follows:

- the INT= and OPT= values are effected immediately and are reflected during job execution
- the NUM= value remains equal to the value when the job was submitted. It takes affect for only newly submitted jobs.

Format Description for ESTIME



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for ESTIME

NUM=nnnn|2

Specifies the default estimated execution time (1-9999), in minutes after which \$HASP308 is written to inform the operator that the job's estimated execution time has been exceeded. This value is used if you do not specify a value for the estimated execution time in the accounting field of your JOB statement or on a /*JOBPARM control statement.

Modification: \$T ESTIME operator command or cold start. If you modify this parameter value and then restart JES2 with a warm or hot start, the parameter value in effect before termination is used.

INT=nn|1

Specifies the interval (1-99), in minutes, at which message \$HASP308 is repeated. The message is first issued when the estimated execution time (NUM= value) is exceeded.

Modification: \$T ESTIME operator command or cold start. If you modify this parameter value and then restart JES2 with a warm or hot start, the parameter value in effect before termination is used.

OPT=Yes|No

Specifies whether the JES2 elapsed time Job Monitor feature is supported. **Yes** specifies that the \$HASP308 message is issued as specified on the NUM= and INT= keywords. **No** specifies that the \$HASP308 message not be issued.

Modification: Hot start or \$T ESTIME operator command.


ESTLNCT - Default Estimated Print Output and Options

The ESTLNCT statement specifies the default estimated print line count for a batch job, the interval at which the \$HASP375 (ESTIMATED LINES EXCEEDED) message is written to the operator, and the action JES2 takes if the output exceeds the estimate. Your installation can provide an output overflow installation exit routine (Exit 9) to override this statement for each batch job processed.

Note: If changed by the \$T command after a job was submitted, the ESTLNCT parameters are affected as follows:

- the INT= and OPT= values are effected immediately and are reflected during job execution
- the NUM= value remains equal to the value when the job was submitted. It takes affect for only newly submitted jobs.

Format Description for ESTLNCT



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for ESTLNCT

NUM=nnnnnn|2

Specifies the default estimated print line count (1-999999), in thousands of lines, for a job after which message \$HASP375 is written to inform the operator that the job's estimated line count has been exceeded. This value is used if you do not specify a value for the estimated print line count in the accounting field of your JOB statement or by using the LINES= keyword on a /*JOBPARM control statement, or by using the LINES=keyword on the JOB statement.

Modification: \$T ESTLNCT operator command or cold start. If you modify this parameter value and then restart JES2 with a warm or hot start, the parameter value in effect before termination is used.

INT=nnnnnn|2000

Specifies the interval (1-9999999), in lines, at which message \$HASP375 is repeated. The message is initially issued when the output estimate (NUM= value) for the batch job is exceeded.

Modification: \$T ESTLNCT operator command or cold start. If you modify this parameter value and then restart JES2 with a warm or hot start, the parameter value in effect before termination is used.

OPT=0|1|2

Specifies the action JES2 takes when a batch job exceeds the estimated number of output lines.

JES2 DOES not abend the output (even though OPT=1/2) if the print line count exceeded the estimated with JES-managed data set (JESMSGGLG, JESYSMSG) only.

The following are the options and subsequent action:

0

Job is allowed to continue execution

1

Job is canceled without a dump

2

Job is canceled with a dump (if a dump statement was coded for this job step)

Modification: Hot start or \$T ESTLNCT operator command.


ESTPAGE - Default Estimated Page Output Exceeded

The ESTPAGE statement specifies the number of pages produced for a batch job before the \$HASP375 (ESTIMATED PAGES EXCEEDED) message is initially written to the operator, the interval at which it is repeated, and the action JES2 takes if the output exceeds the estimate. This statement is only used by page-mode output; the number of pages generated by line-mode data is not recognized here nor is the \$HASP375 message generated by line-mode data. Your installation can provide an output overflow installation exit routine (Exit 9) to override this statement for each batch job processed.

Note: If changed by the \$T command after a job was submitted, the ESTPAGE parameters are affected as follows:

- the INT= and OPT= values are effected immediately and are reflected during job execution
- the NUM= value remains equal to the value when the job was submitted. It takes affect for only newly submitted jobs.

Format Description for ESTPAGE



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for ESTPAGE

NUM=nnnnnnnn|40

Specifies the number of pages (1-99999999) following which message \$HASP375 is written to inform the operator that the job's estimated output has been exceeded. The user can override the spool utilization value specified on this parameter by using the PAGES= keyword defined on the /*JOBPARM control statement.

Modification: \$T ESTPAGE operator command or cold start. If you modify this parameter value and then restart JES2 with a warm or hot start, the parameter value in effect before termination is used.

INT=nnnnnnnn|10

Specifies the interval (1-99999999), in number of pages, at which message \$HASP375 is repeated. The message is first issued when the estimated number of pages (NUM= value) is exceeded.

Modification: \$T ESTPAGE operator command or cold start. If you modify this parameter value and then restart JES2 with a warm or hot start, the parameter value in effect before termination is used.

OPT=0|1|2

Specifies the action JES2 takes when a job exceeds the estimated page output as specified by the NUM= parameter. The following are the options and subsequent action:

0

Job is allowed to continue execution.

1

Job is canceled without a dump.

2

Job is canceled with a dump (if a dump statement was coded for this job step).

Modification: Hot start or \$T ESTPAGE operator command.


ESTPUN - Default Estimated Punch Output and Options

The ESTPUN statement specifies the default estimated punched card output for a job, the interval at which the \$HASP375 (ESTIMATED CARDS EXCEEDED) message is written to the operator, and the action JES2 takes when the output is exceeded. You can provide an output overflow installation exit routine (Exit 9) to override this statement on a per-job basis.

Note: If changed by the \$T command after a job was submitted, the ESTPUN parameters are affected as follows:

- the INT= and OPT= values are effected immediately and are reflected during job execution
- the NUM= value remains equal to the value when the job was submitted. It takes affect for only newly submitted jobs.

Format Description for ESTPUN



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for ESTPUN

NUM=nnnnnnnn|100

Specifies the default estimated punched card output (0-99999999) for a job after which the \$HASP375 message is written to inform the operator that the estimated punch card output has been exceeded. This value is used if you do not specify a value for the estimated punch card count in the accounting field of your JOB statement or by using the CARDS= keyword on the /*JOBPARM control statement, or by using the CARDS= keyword on the JOB statement.

Modification: \$T ESTPUN operator command or cold start. If you modify this parameter value and then restart JES2 with a warm or hot start, the parameter value in effect before termination is used.

INT=nnnnnnnn|2000

Specifies the interval (1-99999999), in cards, at which message \$HASP375 is written to inform the operator that a job has exceeded its estimated output. The message is initially issued when the output estimate (NUM= value) for the job is exceeded.

Modification: \$T ESTPUN operator command or cold start. If you modify this parameter value and then restart JES2 with a warm or hot start, the parameter value in effect before termination is used.

OPT=0|1|2

Specifies the action JES2 takes when a job exceeds the estimated number of cards. The following are the options and subsequent action:

- 0**
job is allowed to continue execution
- 1**
job is canceled without a dump
- 2**
job is canceled with a dump (if a dump statement was coded for this job step)

Modification: Hot start or \$T ESTPUN operator command.

EXIT(nnn) - Exit and Exit Routine Association


Use the EXIT(nnn) statement to associate a JES2 exit with one or more installation-supplied routines. You also use this statement to enable or disable the JES2 exit and to specify whether tracing is to be performed for the exit. (See *z/OS JES2 Installation Exits* for further information about JES2 exits and installation-supplied exit routines.)

The exit number, nnn, is a value from 1 to 255 which identifies the JES2 exit. If the exit number supplied is not defined in the JES2 member, message \$HASP857 WARNING - EXIT(nnn) NOT DEFINED WITHIN CURRENTLY LOADED JES2 MODULES will be issued. (Exit 0, pre-initialization, does not require or use an EXIT(nnn) statement.) The subscript (nnn) specifies the exit identifier (1-255) of the installation-supplied exit routine(s) to be called when the specified exit is taken. No more than 255 installation-supplied

routines can be associated with an exit. See *z/OS JES2 Installation Exits* for information on identifying installation-supplied exit routines to JES2. You must specify at least one installation-supplied routine name.

Note: If you modify EXIT(nnn) parameter values and then restart JES2 with a hot start, the parameter values in effect before termination will be used. JES2 uses the exits that were enabled before JES2 termination.

Format Description for EXIT(nnn)



Notes:

- ¹ Omit the comma between initialization statement and first keyword
- ² ROUTINES can be coded up to 255 times

Parameter Description for EXIT(nnn)

ROUTINES=(+/-routine)

Specifies a list of routines to replace the existing one, that is to add routines to the end of the list, to remove routines from the beginning of the list, or both. The "+" indicates the routine names to add to the end of the routine list. The "-" indicates routine names to be removed from the beginning of the routine list. If there is no "+" or "-" prefix for a routine name, then the previous prefix is used. If the non-prefix routine name is the first element in the specified list, then the list is a replacement of the existing one. [Table 91 on page 148](#) shows an example of specifying the routine list (cumulative list).

<i>Table 91. Example for ROUTINES parameter on EXIT(nnn) statement</i>	
ROUTINES=specification	Resulting routine list
A,B,C	A,B,C
+D	A,B,C,D
-B	A,C,D
+E,F,G	A,C,D,E,F,G
-C,D,+H,I	A,E,F,G,H,I
X,Y,Z,-X,+A	Y,Z,A

The added routine names are resolved to the address of the most recently loaded routine with a matching name. The existing routines in the list are not effected. As the example in [Table 91 on page 148](#), when +D is specified, the address of the most recently loaded routine named D is associated with the exit. However, the addresses associated with A, B, and C are not affected, even if a \$ADD LOADMOD was done for a new module with routine B in it.

Note: \$\$\$\$LOAD and \$\$\$\$DEL are reserved names. If you specify them, you will receive a \$HASP003 RC=06 message indicating that the value contains invalid data.

Modification: \$T EXIT(nnn) operator command.

STATUS=ENABLED|DISABLED

Specifies the initial status of the exit. If the exit is disabled, no exit routines can be invoked at this exit.

Whether or not the installation exit routines associated with an enabled exit are executed is dependent upon:

- Whether the enabled status of the exit has been overridden by the \$T EXIT(nnn) operator command.
- Whether the job being processed is eligible to use the exit, as determined by your installation's setting of the job exit mask for that job. (See [z/OS JES2 Installation Exits](#) for information on how to use the job exit mask and [z/OS JES2 Commands](#) for information on how to use the \$T EXIT(nnn) command.)

Modification: \$T EXIT(nnn) operator command.

TRACE=Yes|No

Specifies whether the execution of this exit is to be traced. To trace an exit, you must also provide the following initialization statements:

```
TRACE(n) START=Yes
TRACEDEF ACTIVE=Yes
```

This parameter setting can be overridden by the \$T EXIT(nnn) operator command. Exit tracing is also controlled by trace ID 13, the TRACE(n) and TRACEDEF initialization statements, and the \$TRACE command. (See [z/OS JES2 Initialization and Tuning Guide](#), the TRACE(n) and TRACEDEF initialization statements in this chapter, and [z/OS JES2 Commands](#) for a description of the \$TRACE command for further information concerning the tracing facility.)

Modification: \$T EXIT(nnn) operator command.

FSS(accccccc) - Functional Subsystem Definition

The FSS(accccccc) statement defines a functional subsystem to JES2. Use the FSS= keyword on the applicable device initialization statement to associate a JES2 device to a functional subsystem. Each FSS(accccccc) statement **must** have a unique functional subsystem name (subscript).

The subscript (accccccc) specifies the 1- to 8-character functional subsystem name. Each FSS(accccccc) statement must have a unique name. If more than one statement includes the same accccccc specification, all specifications on the last-defined FSS(accccccc) statement will override any previously defined.


The subscript can be a specific FSS name (for example, FSS2) or a more generic form such as *PSF**, ***, or a range of FSSs. See “Subscript ranges” on page 2 for details.

If you modify FSS(accccccc) parameters and then restart JES2 with a hot start, JES2 uses the FSSs that were defined before JES2 termination.


Adding FSS Definitions

This statement and all its parameters can be added after initialization with the **\$ADD FSS(accccccc) operator command** operator command.


Format Description for FSS(accccccc)



Modification keywords



Selection limiting keywords



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for FSS(accccccc)

PROC=cccccccc

Specifies the 1–8 character name of the procedure in the **PROC**xx concatenation that are used for the started tasks that contains the JCL required to start the functional subsystem.

This parameter defaults to the value specified as the FSS subscript name (cccccccc).

Modification: \$T FSS operator command (if the address space is inactive).

AUTOSTOP=Yes|No

Specifies whether (Yes) or not (No) the FSS address space is to be stopped (shut down) if all the devices attached to the FSS are drained.

Note: If an error occurs while the FSS address space is stopping, you may must issue an MVS CANCEL to end the address space before starting another printer to this FSS.

Modification: \$T FSS operator command.

HASPFSSM=cccccccc|HASPFSM

Specifies the 1–8 character name of the load module to be loaded into the functional subsystem address space. This load module contains the various JES2-supplied FSI service routines.

If your installation uses the default libraries and module names for the JES2 component, as distributed by IBM, omit this parameter or code HASPFSSM=HASPFSM. If your installation manages the JES2 components in another way, ensure that the correct level of the HASPFSSM module is available to an FSS address space when an FSS is started.

For example, if your installation manages multiple versions of JES2 in libraries that are specified as a STEPLIB in JES2 cataloged JCL procedures, a similar library structure is required for HASPFSSM. The appropriate version of HASPFSSM must be available to the address space of the FSS through a //STEPLIB DD statement in the cataloged JCL procedure for the FSS.


If the load module specified by HASPFSSM= is not found during the start of the FSS address space, or if it is found but its version and structure do not match the rest of the JES2 component, JES2 returns an error code to the FSS that is attempting to connect to JES2.

Modification: \$T FSS operator command (if the address space is inactive).

GRPDEF - Group Definition

The GRPDEF statement defines the characteristics that are assigned to jobs groups that enter the JES2 member.

Format description for GRPDEF



Parameter description for GRPDEF

CONCURRENT_MAX=nnn|0

Specifies the number of dependent jobs that can be defined within a single concurrent set within a job group. The maximum is 200. Valid values are 0-200. A value of 0 indicates that concurrent sets will not be allowed in job groups.

Modification: \$T GRPDEF operator command.

JOBGROUP_JOB_MAX=nnnn|2000

Specifies the maximum number of dependent jobs that can be defined within a single job group. Valid values are 10-2000.

Modification: \$T GRPDEF operator command can be used to increase or decrease the number of dependent jobs within a single job group.

ZJCNUM=nnnnnn|1000

Specifies the number of Zone Job Containers (ZJCs) to create in the checkpoint to store job groups and their associated objects. The maximum number that can be specified is 500000.

Modification: \$T GRPDEF operator command can be used to increase or decrease the number of ZJCs.

ZJCWARN=nnn|80

Specifies the percentage (1-99) of ZJCs that have been used for job group objects at which the operator is to be alerted with message \$HASP050 JES2 RESOURCE SHORTAGE.

Modification: \$T GRPDEF operator command. Note that this parameter can not be modified through a hot start, quick start, or single-member warm start.

INCLUDE - Include an Initialization Data Set


The INCLUDE initialization statement allows a new initialization data set to be processed. JES2 will immediately start reading records from the new data set and processing them. When all statements in the included data set have been processed, JES2 initialization resumes processing records from the original data set. INCLUDE statements can be nested (included initialization data set can include other data sets). JES2 can detect a nested include loop (for example, data set A includes data set B that then includes data set A). If JES2 detects a loop, the include request will fail.

Note:

INCLUDE

1. A D INCLUDE statement displays the data set from which JES2 is currently reading initialization statements. This displays data sets that were included using the INCLUDE statement and from initialization data sets specified in the JES2 PROC.
2. When a data set being included reaches end of file, then all pending statements and comments are considered to be complete. Statements and comments cannot be continued past the end of an included data set.

Format Description for INCLUDE



Notes:

- ¹ Omit the comma between initialization statement and first keyword

Parameter Description for INCLUDE

DSName=jxxx...x(jxxxxxxx)

Specifies a 1– to 44–character data set name with optional 1– to 8–character member name, enclosed in parentheses, where JES2 initialization statements to be processed reside.

Modification: T INCLUDE operator statement.

MEMBER=xxxxxxx

Includes another member from the data set that JES2 is using. If JES2 is using the logical PARMLIB data set, this includes another member of that data set. If we are in console mode because of a PARM=CONSOLE statement, this is an error. If JES2 is in console mode, because of the inclusion of a CONSOLE statement or an error in an initialization statement, then the data set that contained the CONSOLE or bad statement is used.

Modification: T INCLUDE operator statement.

PARMLib_member=xxxxxxx

Includes a member from the logical PARMLIB data set.

UNIT=hhhh|/hhhh|nnnn|ccccccc

If the JES2 initialization data set to be included is not cataloged, then the unit information for the device containing the data set must be specified in one of the following ways:

hhhh | /hhhh

specifies a 3– or 4–digit hexadecimal device number. Device numbers can be specified by any of the following formats:

- UNIT=hhh
- UNIT=/hhh
- UNIT=/hhhh

where hhh and hhhh represent the device numbers. A slash (/) must precede a 4 digit device number.

nnnn

Specifies a device name.

CCCCCCCC

Specifies a 1- to 8-character group name assigned to the device or group of devices that contain the non-cataloged initialization data set to be included.

Modification: T INCLUDE operator statement.

VOLser=xxxxxx

If the JES2 initialization data set to be included is not cataloged, then this specifies a 1– to 6–character volume serial number on which the data set to be included resides.

Modification: T INCLUDE operator statement.


Init(nnnn) - Initiator

The Init(nnnn) statement specifies the characteristics of one logical initiator. Initiators are numbered consecutively (I(1)-I(9999)) for the number of initiators specified by the PARTNUM= parameter on the INITDEF statement. JES2 does not recognize subscripts, nnnn, of a value greater than PARTNUM= on INITDEF and therefore cannot define such initiators.


The subscript can be a specific initiator or a more generic form such as 9-* (implying 9-9999) or * (implying 1-9999). The subscript allows you to define initiators in groups rather than individually.

Note: If you modify Init(nnnn) parameters and then restart JES2 with a hot start, JES2 uses the initiators that were defined before JES2 termination. The Init(nnnn) statement affects JES2-controlled initiators. It does not affect WLM-controlled initiators.

Format Description for Init(nnnn)



Modification keywords



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for Init(nnnn)

Class=classlist|(class,class)

Specifies the classes which are associated with the initiator. Classes associated with the initiator but ineligible to select work are not displayed in the list (but are matched on a filter).

The *classlist* variable specifies a list of single character job classes A–Z and 0–9: for example, 'ABCDEF'. A maximum of 36 classes can be specified.

The *class* variable specifies a comma-separated list of job classes or job class groups (each 1–8 characters in length). A maximum of eight items can be specified in the list: for example, (CLASS1,CLASS2,CLASS3).

Specifying a comma-separated list of 1-character job classes for the Class selection limiting keyword will result in the consideration of initiators defined with either a classlist of job classes or a comma-separated list of job classes.

Wildcards can also be specified: see [“Subscript ranges”](#) on page 2 for details.

NAME=vvvv

Specifies a name that the operator can use to refer to this initiator; vvvv may be a 1–4 character name (A–Z, 0–9). More than one initiator can be assigned the same name allowing any operator command with that name to affect all initiators having that name.

This parameter defaults to the low order *nnnn* of the Init(*nnnn*) specification; leading zeros are converted to blanks.

Note: Initiator control commands affect all initiators based on the assigned or default name. The internal representation of the initiators' names are in four EBCDIC characters. Therefore, when you issue a JES2 initiator control command with a range of initiators, all the initiators whose EBCDIC names fall within the EBCDIC command range are affected. It is possible for the command to affect a range different from that which was intended.

For example, if all of the initiators are named 1–20 (using defaults), and A1–A2 (specified on the NAME parameter), then entering a \$DI1-10 command displays initiators 1–10, A1–A2. This is because A1 and A2 collate above 1 (X'404040F1') and below 10 (X'4040F1F0').

If you specify names using this parameter, explicitly specify all names on commands to avoid problems with name ranges.

Modification: Single-member warm start.

START=Yes|No

START=Yes specifies that this initiator is started automatically when JES2 starts processing.

START=No specifies that this initiator is started by operator command.

Note: If you modify this parameter value and then restart JES2 with a hot start, the parameter values in effect before termination will be used.


Modification: **\$S I[nnnn]** operator command or **\$P I[nnnn]** operator command.

INITDEF - Initiator Definition

The INITDEF statement specifies the number of JES2 logical (batch) initiators to be defined.

Note: If you modify INITDEF parameters and then restart JES2 with a hot start, JES2 uses the initiators that were defined before JES2 termination. The INITDEF statement does not affect the number of WLM-controlled initiators.

Format Description for INITDEF



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for INITDEF

PARTNUM=nnnn|3

Specifies the number (0-9999) of JES2 logical (batch) initiators to be defined.

- The actual number of initiators that you can start varies by installation. The maximum number of allowable initiators that can be started depends on factors such as the amount of available auxiliary storage.
- PARTNUM=3 is the default. If you omit the INITDEF initialization statement from the JES2 initialization stream, "3" initiators are initialized, all set with CLASS=A and START=YES.
- If you specify PARTNUM=0, JES2 does not define any logical initiators and therefore does not create an associated \$PIT.

- JES2 does not recognize JES2–controlled initiators that are numbered greater than the PARTNUM= specification.

Modification: Single-member warm start.

INPUTDEF - Input Definition

The INPUTDEF statement controls how JES2 input processing is performed.

Format Description for INPUTDEF



Parameter Description for INPUTDEF

JES3JECL=IGNORE|PROCESS

Specifies what JES2 input processing is to do when it encounters JES3 JECL statements. Valid options are:

IGNORE

JES3 JECL statements are not recognized and are ignored.

This is the default.

PROCESS

Whenever a JES3 JECL statement is encountered, attempt to process it either directly or by translating it into a JCL or a JES2 JECL statement.

This parameter has MAS member scope and applies to all input sources.

Modification: \$T INPUTDEF command.

NULLJCL=IGNORE|EOF

Specifies what JES2 input processing is to do when it encounters a null JCL card (// with no operands) while processing JCL cards. This operand has no effect on a // card that is used as the delimiter for instream data sets. Valid options are:

IGNORE

Does not process this as anything special and continues reading the current job.

This is normal JES2 behavior.

This is the default.

EOF

The NULLJCL=EOF option causes JES2 to honor JES3 NULL JCL semantics. A NULL statement finalizes a job but will not affect subsequent jobs. All other JCL statements are skipped until the next job statement. If multiple jobs are submitted via INTRDR in a single file, all valid jobs after a NULL JCL statement are processed. For example, consider the following:

```

//TEST1 JOB MSGCLASS=A
//STEP1 EXEC PGM=IEFBR14
//
//STEP2 EXEC PGM=IEFBR14
//TEST2 JOB MSGCLASS=A
//STEP1 EXEC PGM=IEFBR14
    
```

The "//" statement in the example will finalize job TEST1 and "// STEP2 EXEC PGM=IEFBR14" will be skipped. Job TEST2 will be submitted.

This parameter has MAS member scope and applies to all input sources.

This parameter has MAS member scope and applies to all input sources.


Modification: \$T INPUTDEF command.

INTRDR - Internal Reader

The INTRDR statement specifies the characteristics of **all** JES2 internal readers that are used to submit batch jobs. An internal reader is a special SYSOUT data set that other programs can use to submit jobs, control statements, and commands to JES2. Jobs that allocate internal reader and time-sharing users use the internal readers to submit jobs. Internal reader characteristics are specified by the following parameters:

Note: If you modify INTRDR parameters and then restart JES2 with a hot start, the parameter values in effect before termination will be used. (For further information, see [z/OS JES2 Initialization and Tuning Guide](#).)

Format Description for INTRDR



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for INTRDR

Auth=(Job=Yes|No,Device=Yes|No,System=Yes|No)

Specifies the command authority for internal readers. These values authorize certain JES2 commands to be submitted through an internal reader.

Note: This parameter has no effect when the associated resource class and profile in RACF 1.9 or higher are active. For more information about using JES2 security facilities, see [z/OS JES2 Initialization and Tuning Guide](#).

Job=Yes|No

Specifies that the device can (Yes) or cannot (No) issue commands that require job authority.

Device=Yes|No

Specifies that the device can (Yes) or cannot (No) issue commands that require device authority.

System=Yes|No

Specifies that the device can (Yes) or cannot (No) issue commands that require system authority.

This parameter affects JES2 control statements only. Use the AUTH parameter of the JOBCCLASS initialization statement to specify the authorization for JCL statements. (JES2 control statements begin with /* in columns 1 and 2. JCL statements begin with // in columns 1 and 2.)

Modification: \$T INTRDR operator command.

BATCH=Yes|No

Specifies whether internal readers can be used to process batch jobs in addition to time-sharing LOGONs and started tasks (Yes), or are to be dedicated exclusively to time sharing LOGONs and started tasks (No). If BATCH=No is specified, you can submit jobs only through real (local) card readers, RJE, NJE, or through spool reload.

Modification: Warm start.

Class=class

Specifies the default job class to be assigned to all jobs submitted through an internal reader that do not specify a job class in the CLASS operand of their JOB statements.

Modification: \$T INTRDR operator command.

Hold=Yes|No

Specifies that all jobs submitted through an internal reader are to be held (Yes) or not held (No) after JCL conversion until they are released for execution by the operator.

All internal readers are treated as a single facility; therefore, if one internal reader is held, all internal readers are held. This can be particularly troublesome if TSO/E users are submitting jobs and the operator has held the internal readers. This can be overcome by several operating techniques:

- All jobs submitted through an internal reader can be assigned a class and that class can be held by a JES2 parameter library entry or the \$H Qn operator command.
- Jobs submitted by the internal reader can use the TYPRUN=HOLD parameter on the JOB statement.
- Jobs submitted through an internal reader can be individually held with the \$H J operator command.

Modification: \$T INTRDR operator command.

PRTYINC=nn|0

Specifies an integer (0-15) to be **added** to the selection priorities of all jobs submitted through internal readers. If the total of this number and a job's priority exceeds the value specified by PRTYLIM=, JES2 will assume the priority specified by PRTYLIM=.

Modification: \$T INTRDR operator command.

PRTYLIM=nn|15

Specifies the maximum priority level (0-15) that can be assigned to jobs submitted through an internal reader. If a job's priority (with or without the increment specified by PRTYINC=) exceeds this level, it will be reduced to this level.

Modification: \$T INTRDR operator command.

HONORLIM=Yes/No|HONOR=Yes/No

Specifies whether data sets sent to the internal reader are to be counted towards the byte limit for a job.

Modification: \$T INTRDR operator command.

TRace=Yes|P|No

Specifies whether tracing is activated or deactivated for all internal readers. To trace an internal reader, you must also provide the following initialization statements:

TRACE(n) START=YES
TRACEDEF ACTIVE=YES


Note: Specifying TRACE=P is same as specifying TRACE=Yes.

This parameter setting can be overridden by the \$T INTRDR operator command. Internal reader tracing is also controlled by trace IDs 11 and 12, the TRACE(n) and TRACEDEF initialization statements, and the \$TRACE command. (See *z/OS JES2 Initialization and Tuning Guide*, the TRACE(n) and TRACEDEF initialization statements in this chapter, and *z/OS JES2 Commands* for a description of the \$TRACE command for further information concerning the tracing facility.)

JECLDEF,JES2= - JECL Definition JES2

The JECLDEF JES2 statement controls how JES2 input processing handles various JES2 and JES3 JECL statements.

Format Description for JECLDEF JES2=



Parameter Description for JECLDEF,JES2=

JES2=

Specifies how JES2 JECL statements are to be processed. Keywords exist for each JECL card type. Each keyword has the following valid options:

PROCESS

The specific JES2 JECL statement is processed.
This is the default.

WARN

The specific JES2 JECL statement is processed but a warning message is issued indicating that the installation intends to discontinue use of this statement in the future and that it should no longer be used.

FAIL

An error message is generated for the specific JES2 JECL statement. The job does not execute.

IGNORE

The specific JES2 JECL statement is ignored.

This parameter has MAS member scope and applies to all input sources.


Modification: \$T JECLDEF command.

JECLDEF, JES3= - JECL Definition, JES3

The JECLDEF JES3 statement controls how JES2 input processing handles various JES2 and JES3 JECL statements.

Note: Processing of JES3 JECL statements must be activated on INPUTDEF before the keywords on this parameter have any effect.

Format Description for JECLDEF,JES3=



Parameter Description for JECLDEF,JES3=

JES3=

Specifies how JES3 JECL statements are to be processed when INPUTDEF JEC3JECL=PROCESS. Keywords exist for each JECL card type. Each keyword has one of two sets of options depending upon whether the keyword can be processed by the current version of JES2 or not. Those that cannot be processed by the current level of JES2, do not have the PROCESS option. Each keyword has the following valid options:

PROCESS

The specific JES3 JECL statement is processed (translated or directly processed).

This is the default.

WARN

The specific JES3 JECL statement is processed but a warning message is issued indicating that the installation intends to discontinue use of this statement in the future and that it should no longer be used.

FAIL

An error message is generated for the specific JES3 JECL statement. The job does not execute.

IGNORE

The specific JES3 JECL statement is ignored.

This parameter has MAS member scope and applies to all input sources.

Modification: \$T JECLDEF command.

JOBCLASS - Job, Started Task, and Time Sharing User Class


The JOBCLASS(*class*...|STC|TSU) statement specifies the characteristics to be associated with one or more job classes, job class groups, started task (STC) jobs or time sharing user (TSU) classes. You can specify the following types of job classes:

- One of the 36 predefined one-character *class* names, by specifying a single alphabetic character (A-Z) or numeric character (0-9).
- The predefined TSU or STC job class.
- A user-defined job class from 2-8 alphanumeric characters.
- A maximum of 512 job class names are supported.
- One or more job class group names can also be specified.


Note:


1. The JOBCLASS statement has no effect on APPC transaction programs.
2. Use the JOBCLASS, STC initialization statement to define the characteristics to be associated with started tasks. You can override some of the default characteristics defined by JOBCLASS(STC) by specifying an override value on the appropriate keyword of the JOB JCL statement for that started task.
3. A range of values that includes the letter "S" includes class S and also STC, and similarly including the letter "T" includes class T and also TSU (except when the range ends with "S" or "T"). This can lead to unexpected data returned by JES2.
4. JOBCLASS(*) includes STC and TSU. This can lead to unexpected data returned by JES2.
5. JOBCLASS(?) includes only the 1-character classes (A-Z and 0-9) and therefore none of the 2-8 character class names or STC or TSU.
6. Not all JOBCLASS parameters are allowed on JOBCLASS(STC) and JOBCLASS(TSU) initialization statements. See each parameter description for restrictions.
7. JOBCLASS values are stored in the checkpoint and are MAS-wide in scope.
8. No priority is given to job classes that are specified within a job class group. The job classes are processed in a round-robin manner.


Format description for JOBCLASS(class...|STC|TSU)



Modification keywords









Notes:


¹ Omit the comma between initialization statement and first keyword


² *auth* can be coded up to 4 times

Selection limiting keywords









Parameter description for JOBCLASS(class...|STC|TSU)

ACCT=Yes|No

Specifies whether an account number is required (Yes) or not required (No) on a JCL JOB statement. This parameter is not allowed on either the JOBCLASS(STC) or JOBCLASS(TSU) initialization statements.

Modification: \$T JOBCLASS operator command or cold start

ACTIVE=[Yes|No]

Specifies whether or not the specified job class is active. Active job classes can be used on new jobs that are submitted. The ACTIVE parameter has no effect on jobs once they have been submitted. This parameter does not apply to the STC and TSU job classes.

AUTH=ALL|SYS|IO|CONS|INFO

Specifies the MVS operator command groups that are to be executed. The groups include:

SYS

system commands

IO

input/output commands

CONS

console commands

INFO

information commands (such as display)

ALL

all operator command types

For an explanation of operator command groups and the relationship of JES2 to MVS command groups, see *z/OS JES2 Commands* and *z/OS MVS System Commands*, respectively.

This parameter affects JCL statements only. Use the AUTH= parameter of the INTRDR and RDR initialization statement to specify the authorization for JES2 job entry control (JECL) statements. (JES2 control statements begin with /* in columns 1 and 2. JCL statements begin with // in columns 1 and 2).

Modification: \$T JOBCLASS operator command or cold start

BLP=Yes|No

Specifies that either the bypass label processing parameter in the label field of a DD statement is to be ignored (No) and processed as no label, or that bypass label processing is performed as requested (Yes) and the label parameter is processed as it appears.

Modification: \$T JOBCLASS operator command or cold start.

COMMAND=DISPLAY|EXECUTE|IGNORE|VERIFY

Specifies the disposition of MVS commands read from the '// COMMAND' statement (or the '// command' statement) of the JCL input stream as follows.

DISPLAY

The command is displayed and scheduled for execution.

EXECUTE

The command is scheduled for execution. This is the default for JOBCLASS(STC) and JOBCLASS(TSU).

IGNORE

The command is ignored (that is, interpreted as a “no operation”).

VERIFY

Specifies that the system displays the command, asks the operator whether the command should be executed, and if the operator replies “YES”, schedules the command for execution. This is the default for JOBCLASS(A-Z, 0–9).

Modification: \$T JOBCLASS operator command or cold start

CONDPURG=Yes|No

Specifies whether (YES) or not (NO) system data sets (such as JESMSG and SYMSG) in this job class are to be conditionally purged. This parameter is not allowed on the JOBCLASS(class) initialization statement.

Modification: \$T JOBCLASS or cold start.

COPY=Yes|No

COPY=Yes specifies that jobs in this job class are to be queued for output processing as though TYPRUN=COPY was specified on the JOB statement for these jobs.

The default value of this parameter is No, which specifies that jobs in this job class are to be queued as usual. NO is ignored if the TYPRUN=COPY parameter is specified on the JOB statement for a job.

Note: This parameter is not allowed on **JOBCLASS(STC)** and **JOBCLASS(TSU)** initialization statements.

Modification: \$T JOBCLASS operator command or cold start.

DESC=

Specifies an 80 character string of any description.

This parameter has a MAS scope.

Modification: \$T JOBCLASS operator command or cold start.

DSENQSHR{=ALLOW|AUTO|DISALLOW}

Indicates how the system manages changes in data set disposition between job steps. When a step includes a DD statement with OLD, NEW or MOD on the DISP (disposition) keyword, and a later step requests the same data set as SHR, this parameter controls whether the system can change the

serialization on the data set to shared control; permitting this change allows other jobs to share that data set. The value that is specified interacts with the value that is specified for DSENQSHR on the JOB card to determine the behavior:

ALLOW

The system is allowed to change the serialization on the data set to shared control if the JOB card specifies ALLOW.

AUTO

The system is allowed to change the serialization on the data set to shared control if the JOB card specifies ALLOW or USEJC.

DISALLOW

The system is not allowed to change the serialization on the data set to shared control.

Note: Specifying DSENQSHR=AUTO restricts any job that is converted with the class to run only on the z/OS V2R1 version of MVS, or later. If earlier levels of MVS are active in the MAS (JESPLEX), then this additional system restriction could prevent some jobs from running.

Table 92. JOBCLASS attribute for DSENQSHR				
LANGUAGE	JOBCLASS attribute for DSENQSHR			
JCL		AUTO	ALLOW	DISALLOW
	ALLOW	yes	yes	no
	USEJC	yes	no	no
	DISALLOW	no	no	no

When yes is indicated, the system is allowed to change the data set serialization to shared control and other jobs might share that data set with this job.

DUPL_JOB=NODELAY|DELAY

Specifies whether or not JES2 is allowed to concurrently execute batch jobs with the same name in the same MAS. If DUPL_JOB=DELAY is specified, JES2 is not allowed to execute batch jobs with the same name in the same MAS at the same time.

Note: DUPL_JOB on a JOBCLASS specification is ignored if JOBDEF DUPL_JOB=NODELAY. If JOBDEF DUPL_JOB=DELAY, that specification can be overridden on a jobclass basis by specifying DUPL_JOB=NODELAY on the JOBCLASS statement.

Modification: \$T JOBCLASS operator command or cold start.

GDGBIAS{=JOB|STEP}

Displays how relative references to a generation data set in a DD JCL statement are resolved. This is processed by the z/OS converter.

JOB

Relative references to a generation data set are resolved on a job basis. The system establishes the relationship between the relative generation number and the absolute generation number when the generation data set is first referenced in the job. This relationship is consistent throughout the job.

STEP

Relative references to a generation data set are resolved on a job step basis. The system establishes the relationship between the relative generation number and the absolute generation number when the generation data set is first referenced in each job step. Each job step that references the generation data set establishes a new relationship.

GROUP=name

Specifies the 2-8 character name of the job class group that the specified job class is associated with. The group name cannot match any existing job class name (including the default 1-character job class names). This parameter does not apply to the STC and TSU job classes.

HOLD=Yes|No

HOLD=Yes specifies that jobs in this job class are to be held until a RELEASE command for the job is issued by the operator (\$A J).

This parameter defaults to No. No is ignored if the TYPRUN=HOLD parameter is specified on the JOB statement for a job.

Note: This parameter is not allowed on **JOBCLASS(STC)** and **JOBCLASS(TSU)** initialization statements.

Modification: \$T JOBCLASS operator command or cold start.

IEFUJP=Yes|No

IEFUJP=No specifies that the IEFUJP exit is not to be taken when a job is purged. IEFUJP receives control when a job is ready to be purged from the system; that is, after the job has been ended and all the SYSOUT output that pertains to the job has been processed.

This parameter defaults to YES, which specifies that the IEFUJP exit is to be taken when a job is purged.

Modification: \$T JOBCLASS operator command or cold start.

IEFUSO=Yes|No

IEFUSO=NO specifies that the IEFUSO installation exit is not to be taken when the SYSOUT limit is reached for a job in this job class. The SYSOUT limit, which is specified by the OUTLIM parameter on the DD statement, defines the maximum number of physical records to be written to the associated SYSOUT data set. When the OUTLIM value is exceeded, JES2 normally calls the IEFUSO SMF exit routine either to increase the SYSOUT limit or to end the job. When NO is specified and OUTLIM is exceeded, JES2 abnormally ends the job.

This parameter defaults to YES, which specifies that the IEFUSO installation exit is to be taken when the SYSOUT limit is reached for a job in this job class.

Modification: \$T JOBCLASS operator command or cold start.

JESCANCEL=ALLOWED|RESTRICTed

Specifies whether a JES CANCEL issued while a job is in execution is allowed or restricted. JES CANCEL includes the \$C and the \$C,P commands, the CANCEL function of the job modify SSI 85, and the CANCEL TSO command (SSI 2).

Note: The TSO CANCEL command (SSI 2) cannot be used to cancel an active STC or TSU regardless of the setting of this operand.

Note: JESCANCEL=RESTRICTED does not protect the job from being canceled as part of a job group cancel (\$CG cancel) or a restart job (\$EJ,C) command.

Modification: \$T JOBCLASS operator command or cold start.

JESLOG=

Specifies for the indicated jobclass that each job's JESLOG data (JESMSG LG and JESYSMSG data sets) is to be spun at a certain time interval, suppressed from being recorded, or not spun at all.

Note: Specifying JESLOG=SPIN causes a job in this class to use at least 2 additional track groups of SPOOL space for the two JESLOG data sets (JESMSG LG or JESYSMSG). If this job class normally has many jobs that use a minimal amount of SPOOL space, then an increase of 2 track groups could significantly increase SPOOL utilization. Consider these additional SPOOL requirements when deciding whether to use JESLOG=SPIN.

SPIN

Jobs running in this job class are 'spinnable'. \$TJnnnn,SPIN can be used to immediately spin the JESMSG LG and JESYSMSG data sets.

(SPIN,+hh:mm)

Indicates to spin JESLOG every hh:mm time interval.

where:

- hh is hours and has a range of 0 through 23
- mm is minutes and has a range of 00 through 59

Note: You must specify a minimum of 10 minutes or JES2 issues an error message. Also, for time intervals of less than one hour, you must specify the following format: JESLOG=(SPIN, +00:mm).

(SPIN, hh:mm)

Indicates to spin JESLOG at hh:mm every 24 hours.

(SPIN, nnn)

Indicates to spin JESLOG whenever either JESMSG LG or JESYSMSG has nnn lines. nnn is the number (1–999) of lines in the data set.

Note:

You must specify a minimum of 500 lines or JES2 issues an error message.

(SPIN, nnnK)

Indicates to spin JESLOG whenever either JESMSG LG or JESYSMSG has "nnnK" lines, where "K" indicates thousands of lines.

(SPIN, nnnM)

Indicates to spin JESLOG whenever either JESMSG LG or JESYSMSG has "nnnM" lines, where "M" indicates millions of lines.

SUPPRESS

Indicates that JES2 suppresses writing to the JESLOG data sets during the execution of jobs defined for this job class. JES2 only writes data to the JESLOG data sets during each job's input service and post-execution processing phases.

NOSPIN

Indicates that JESLOG data is not spun, but is not suppressed. NOSPIN is the default.

Modification: \$T JOBCLASS command or cold start.

JOBRC=MAXRC|LASTRC

Specifies the method JES2 uses to determine the return code for jobs submitted in this class. Specify MAXRC to use the highest return code of any executed step as the job return code. Specify LASTRC to use the return code of the last executed step as the job return code. The default value is MAXRC.

Modification: \$T JOBCLASS operator command or cold start

JOURNAL=Yes|No

Specifies whether (Yes) or not (No) job-related information is to be saved in a job journal.

Job journaling limits the scope of RESTART=YES. If the JOURNAL=Yes parameter is specified:

- JES2 restarts interrupted jobs from the beginning only if the MVS system is unable to restart the job from a step or checkpoint.
- RESTART=NO has no effect; all jobs are requeued for execution.

(Specifying RD=R|RNC on the JCL JOB statement has the same effect).

If the jobs are not journaled (JOURNAL=No), JES2 always attempts to restart interrupted jobs in this class from the beginning.

JOURNAL=No specifies that information for the job journal is not to be processed for a job in this job class unless RD=R or RD=RNC is specified on the JOB statement for a job or on the EXEC statements for the job.

Note: To restart a job automatically through checkpoint/restart or step restart, information about the job must be recorded in the job journal. To restart a job using the automatic restart manager, the job journal is not needed (the automatic restart manager does not use the job journal).

The default of this parameter is Yes, which specifies that information for the job journal is to be processed for this job class.

Note: This parameter is not allowed on **JOBCLASS(STC)** and **JOBCLASS(TSU)** initialization statements.

Modification: \$T JOBCLASS operator command or cold start.

LOG=Yes|No

LOG=NO specifies that the JES2 job log is not to be printed for this job class. The JES2 job log contains the user's console messages and replies to WTORs issued during the processing of the job. When No is specified, JES2 statistics information (normally printed with the job) is also suppressed.

This parameter defaults to Yes, which specifies that the job log is to be printed for this job class. Even when LOG=Yes is specified, the job log may be suppressed on an individual job basis through a parameter in the accounting field of the JOB card or by a parameter on a /*JOBPARM control card.

Modification: \$T JOBCLASS operator command or cold start

MODE=JES|WLM

Indicates whether jobs in this class are to be run under JES-mode or WLM-mode initiators. See [z/OS JES2 Initialization and Tuning Guide](#) for more information.

Note: This parameter is not allowed on **JOBCLASS(STC)** and **JOBCLASS(TSU)** initialization statements.

Modification: \$T JOBCLASS operator command or cold start

MSGCLASS=msgclass

Specifies a default message class for started tasks or time-sharing users.

Note: This parameter is only allowed on JOBCLASS(STC) and JOBCLASS(TSU) initialization statements.

Modification: \$T JOBCLASS operator command or cold start

MSGLEVEL=(n,m)|(0,1)

Specifies a message level value (n) for use when the MSGLEVEL parameter is not specified on a JOB statement. If a MSGLEVEL parameter is not specified, JCL and allocation/termination messages are recorded in the system message data set according to the value specified in this parameter.

The character “n” specifies the kinds of JCL listed, as follows:

0

JOB statement only

1

Input statements, cataloged procedure statements, and symbolic parameter substitution values

2

Input statements only, including in-stream procedures.

The character “m” specifies the kinds of allocation/termination messages listed, as follows:

0

No messages are to be listed, except for an abnormal termination, in which case allocation/termination messages are listed.

1

Allocation/termination messages are listed.

Modification: \$T JOBCLASS operator command or cold start

NAME=ccccccc

Specifies the jobclass to be used for modification.

OUTDisp=(normal) [,abnormal])

Specifies the default output disposition for JES data sets created for jobs in this class, depending on whether or not the job abended.

normal

Specifies the output disposition if the job does not abend.

abnormal

Specifies the output disposition if the job abends.

Valid output dispositions are:

Hold

Hold the output. JES2 does not process the output until you either change the disposition to WRITE or KEEP, or release the output. When the output is released, the disposition changes to WRITE.

Note: This specification is honored when the output reaches the destination node.

Keep

Process the output and then keep a copy of it on spool. After processing, the disposition of this output becomes LEAVE.

Leave

JES2 does not process the output until you change the disposition to WRITE or KEEP, or release the output. When the output is released, the disposition changes to KEEP.

Purge

Purge the output immediately.

Write

Process the output then purge it.

Only code OUTDISP= on JOBCLASS when you require that system data sets have a specific output disposition regardless of their message class (MSGCLASS=) specification. If you have no such requirement, either code OUTDISP=(), OUTDISP=(,) , or leave it off the JOBCLASS statement completely.

If you do not code OUTDISP=, JES2 assigns the value on the OUTCLASS statement for JES2 member data sets in this class. See [z/OS JES2 Initialization and Tuning Guide](#) for more information about specifying output disposition and how JES2 determines output disposition defaults.

Modification: \$T JOBCLASS operator command or cold start

OUTPUT=Yes|No

OUTPUT=No specifies that no SYSOUT data is to be written for jobs executed in this job class.

Note: Specification of the No option prevents the TSO/E TRANSMIT command from functioning. For further discussion of the relationship between JES2 and the TSO/E interactive data transmission facility, see the description of Exit 40 in [z/OS JES2 Installation Exits](#).

This parameter defaults to YES, which specifies that SYSOUT data is to be written for jobs that are executed in this job class.

Modification: \$T JOBCLASS operator command or cold start

PERFORM=nnn|000

Specifies the default performance-group number (0-999) for this job class. This number is used as the performance-group number on the JCL EXEC statement when a performance-group number is not specified on the JCL JOB or EXEC statement for a job of this job class.

Note: The performance-group value specified on the EXEC card (step level) has no effect if running in WLM goal mode.

The parameter default is 000, which indicates that no performance-group processing is performed by JES2. A default value of 1 is assigned for all steps in a job.

Modification: \$T JOBCLASS operator command or cold start

PGMRNAME=Yes|No

Specifies whether a programmer name is required (Yes) or not required (No) on a JCL JOB statement.

Note: This parameter is not allowed on **JOBCLASS(STC)** and **JOBCLASS(TSU)** initialization statements.

Modification: \$T JOBCLASS operator command or cold start

PROCLIB=nn|jccccccc|00

Specifies the default 2-8 character procedure library name (jccccccc) or procedure library number (0-99) which is to be used for this job class. It allows you to specify procedure libraries for different job classes. In the JES2 procedure, one DD statement must be named PROC00. If you specify additional procedure libraries (jccccccc or 01-99), then you might associate these libraries to a job class by replacing the jccccccc or nn of this parameter with the appropriate procedure library name or number. All cataloged procedure libraries to be used by jobs, time-sharing users, or system tasks must be defined in the JES2 procedure.

Note: Setting a procedure library number nn has the same effect as setting a procedure library name of PROCnn. Setting PROCLIB=nn or PROCnn will display as PROCLIB=nn.

Modification: \$T JOBCLASS operator command or cold start

PROMO_RATE=0| nnn

Specifies how many positions a job can be moved up the execution queue in one STARTBY aging cycle (1 minute). The default value PROMO_RATE=0 means that the STARTBY function is disabled for the job class.

Modification: \$T JOBCLASS operator command or cold start.

QHELD=Yes|No

Specifies whether (Yes) or not (No) jobs in this class are not selected for execution (meaning they are held) until the class is released from held status by operator command.

Note: This parameter is not allowed on **JOBCLASS(STC)** and **JOBCLASS(TSU)** initialization statements.

Modification: \$T JOBCLASS operator command

REGION=nnnnx|1M

Specifies the default for the region size assigned to each job step. The “nnnn” indicates the number of units that make up the default region size; the “x” indicates the unit of measure (either 'K' for Kilobytes or 'M' for Megabytes).

- For nnnnK, the maximum allowable value is 9999K.
- For nnnnM, the maximum allowable value is 2047M.

The region size (0-2047M) is assigned when no region size is specified in the JOB and EXEC statements and the job step is to be run with ADDRSPC=VIRT. (See [z/OS MVS JCL Reference](#) for further details on specifying the REGION parameter on the JOB and EXEC statements.)

Note: For STC and TSU the default is 0K.

Modification: \$T JOBCLASS operator command or cold start

RESOURCE(restype)=(LIMIT=nn|DEFAULT,ACTION=NONE|WAIT|FAIL|DEFAULT)

Specifies resource limits parameters for the jobs of this job class for resource type **restype**.

The supported values for **restype** are:

TG

SPOOL space (Track Groups).

JOE

JES2 output groups (Job Output Elements).

LIMIT

keyword defines resource usage limit for jobs of this job class as percentage of total available. Valid values for **LIMIT** keyword are:

nn

percentage value (1-100).

DEFAULT

use system default.

System default for resource type TG is 75% for installations with less than 10000 TGs of SPOOL space and 25% otherwise.

System default for resource type JOE is 75% for installations with less than 600 JOEs defined in JES2 configuration and 25% otherwise (see JOENUM keyword of OUTDEF initialization statement).

ACTION

keyword defines the action JES2 takes when job of this job class exceeds its limit for the respective resource type:

NONE

JES2 issues a message and continues processing.

WAIT

JES2 suspends allocation of resources of this type to the job until more resources of this type become available to the job.

FAIL

JES2 fails resource allocation request.

DEFAULT

use system default. System default is WAIT.

For more details about the JES2 resource limit function see [JES2 Resource limit management in z/OS JES2 Initialization and Tuning Guide](#).

RESTART=Yes|No

Specifies whether (Yes) or not (No) JES2 is to requeue for execution any job of this job class that had been executing before the IPL of the system was repeated and a JES2 warm start was performed. The job is restarted from the beginning, unless the scheduler can restart it from a step or checkpoint.

Job journaling limits the scope of RESTART=Yes. If the JOURNAL=Yes parameter is specified:

- JES2 restarts interrupted jobs from the beginning only if the MVS system is unable to restart the job from a step or checkpoint.
- RESTART=No has no effect; all jobs are requeued for execution.

(Specifying RD=R|RNC on the JCL JOB statement has the same effect).

If RESTART=Yes and the jobs are not journaled (JOURNAL=No), JES2 always attempts to restart interrupted jobs in this class from the beginning.

Note: This parameter is not allowed on **JOBCLASS(STC)** and **JOBCLASS(TSU)** initialization statements.

Modification: \$T JOBCLASS operator command or cold start

Note:

1. This parameter pertains to restarts that do not involve jobs registered with the MVS automatic restart manager. RESTART is ignored if the job is registered with the automatic restart manager.
2. Specifying RESTART=Y or RESTART=N on the /*JOBPARM control statement for a particular job overrides this job class RESTART parameter.
3. RESTART=No only applies to restarts after a system failure.

SCAN=Yes|No

SCAN=YES specifies that jobs in this job class are to be queued for output processing immediately after JCL conversion, as though TYPRUN=SCAN was specified on the JOB statement for these jobs.

This parameter defaults to NO, which specifies that jobs in this job class are to be queued as usual. SCAN=NO is ignored if the TYPRUN=SCAN parameter is specified on the JOB statement for a job.

Note: This parameter is not allowed on **JOBCLASS(STC)** and **JOBCLASS(TSU)** initialization statements.

Modification: \$T JOBCLASS operator command or cold start

SCHENV=xxxxx

Specifies a 1 to 16 character default WLM scheduling environment name to be used for jobs converted in this job class. SCHENV specified on a JOB card takes precedence over the value specified here. See [z/OS MVS JCL Reference](#) for the rules regarding SCHENV names. The SCHENV will be rejected if it is not defined to WLM.

Modification: \$T JOBCLASS operator command or cold start

SWA= Above|Below

SWA=Above specifies that all eligible schedule work area (SWA) control blocks created for jobs in this job class are placed above 16 megabytes in virtual storage.

This parameter defaults to Below, which specifies that all SWA control blocks for jobs in this job class resides below 16 megabytes in virtual storage.

Modification: \$T JOBCLASS operator command or cold start

SYSSYM[= ALLOW|DISALLOW]

Specifies whether system symbols are substituted in batch jobs that are submitted in this JOBCLASS. Symbols are substituted when the job is processed by the z/OS converter using the system symbols that are set on the system where the conversion occurs.

Note: You can choose the system that converts a job using SYSAFF on the JOB or JOBPARM JCL/JECL card or SYSTEM on the JOB card. If CNVT_SCHENV= is set to HONOR on the JOBDEF statement, then you can also choose the system that converts a job by associating a system with the job scheduling environment.

Modification: \$T JOBCLASS operator command or cold start

TIME=(mmmmmm,ss) (30,0)

Specifies the default for the maximum processor time that each job step may run. The “mmmmmm” indicates minutes (0-357912); the “ss” indicates seconds (0-59). The value specified is subject to the limits described for the TIME parameter in [z/OS MVS JCL Reference](#).

This default TIME= specification is used when no TIME parameter is specified on the JCL EXEC statement. (See [z/OS MVS JCL Reference](#) for further details on specifying the TIME parameter on the EXEC statement. See notes for \$T job C=class in [z/OS JES2 Commands](#) for further details concerning the results of changing the job class.)

Modification: \$T JOBCLASS operator command or cold start

Note: This parameter only defaults the TIME for the EXEC statement; not for the JOB statement.

TYPE6=Yes|No

TYPE6=No specifies that JES2 is not to produce type 6 SMF records for jobs in this job class. Type 6 SMF records are written for each group of job-related data sets and each spin data set (available for printing) that is processed. Type 6 records are described in [z/OS MVS System Management Facilities \(SMF\)](#).

This parameter defaults to Yes, which specifies that JES2 is to produce type 6 SMF records for this job class. When type 6 records are to be produced, the BUFNUM= parameter on the SMFDEF statement must specify two or more SMF buffers.

Modification: \$T JOBCLASS operator command or cold start

Note: Suppressing SMF information may not be consistent with your installation's security policy.

TYPE26=Yes|No

TYPE26=No specifies that JES2 is not to produce type 26 (job summary) SMF records for jobs in this job class. A full explanation of type 26 records is provided in [z/OS MVS System Management Facilities \(SMF\)](#).

This parameter defaults to Yes, which specifies that JES2 is to produce type 26 SMF records for jobs in this job class. When type 26 records are to be produced, the BUFNUM= parameter on the SMFDEF statement must specify two or more SMF buffers.

Modification: \$T JOBCLASS operator command or cold start

Note: Suppressing SMF information may not be consistent with your installation's security policy.

XBM= procname

Specifies the procedure name JES2 uses as the target of an EXEC statement. The procedure names a program that processes the input submitted to this job class. Specifying this parameter reserves this job class for the Execution Batch Monitoring (XBM) facility. See *z/OS JES2 Initialization and Tuning Guide* for details on using this facility.

If you do not specify this parameter, or nullify the parameter, JES2 does not use the XBM facility and processes jobs in this class normally.

Note: This parameter is not allowed on **JOBCLASS(STC)** and **JOBCLASS(TSU)** initialization statements.

Modification: \$T JOBCLASS command or cold start

XEQcount=MAXimum=4,294,967,295

Specifies the maximum number of jobs that can execute concurrently in the class. The limit is the total number of jobs executing in the MAS. For example, a limit of 5 means there can be 3 jobs running on one member and 2 jobs running on another member.

Modification: \$T JOBCLASS operator command or cold start

Examples

JOBCLASS(class) REGION=1M

Sets the REGION for job class A to 1M.

JOBCLASS(?) REGION=1M

Sets the region for job classes A, B, C, D, E, F, G, H, I, J, K, L, M, N, O, P, Q, R, S, T, U, V, W, X, Y, Z, 0, 1, 2, 3, 4, 5, 6, 7, 8, and 9 to 1M.

JOBCLASS (*) REGION=1M

Sets the region for job classes A, B, C, D, E, F, G, H, I, J, K, L, M, N, O, P, Q, R, S, STC, T, TSU, U, V, W, X, Y, Z, 0, 1, 2, 3, 4, 5, 6, 7, 8, and 9 to 1M.

JOBCLASS(A,E,I,O,U) MODE=WLM

Defines job classes A, E, I, O, and U as WLM mode job classes.


JOBCLASS(STC) JESCANCEL=RESTRICTED

Prevents the use of the \$CS and \$CS,P command against started tasks (STCs).

JOBDEF - Job Definition

The JOBDEF statement defines the characteristics that are assigned to jobs that enter the JES2 member.

Format description for JOBDEF



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter description for JOBDEF

ACCTFLD=IGNORE|REQUIRED|OPTIONAL

Specifies whether the JES2 form of the accounting information (the job accounting number and room number) is required (REQUIRED), ignored by JES2 if present (IGNORE), or is not required but used by JES2 if present (OPTIONAL) on the JCL JOB statement for this job.

If ACCTFLD=REQUIRED is coded, JES2 cancels your job when either of the accounting field parameters is missing and issues message \$HASP110 jobid jobname ILLEGAL JOB CARD.

Modification: \$T JOBDEF operator command.

BAD_JOBNAME_CHAR=c|?

Specifies the character to use in place of invalid characters in a jobname. This translation is used for JES2 commands and displays RACF entity names too. Valid values are: A-Z,0-9, \$, #, @, /, +, :, ;, ?, _, -, !

Modification: \$T JOBDEF operator command or JES2 cold start

CISUB_PER_AS=nn|5

Specifies the *nn* number of converter/interpreter subtasks (1-25) that are run in each of the jesxCIXx address spaces when INTERPRET=JES is specified. Valid values are 1-25 (25 being the maximum number of converter PCEs that can be specified on PCEDEF).

Modification: \$T JOBDEF operator command

CNVT_ENQ=WAIT|FAIL

Specifies how the system should process jobs that request JCLLIB data sets that are already enqueued at job conversion time.

WAIT

Indicates that system allows the job to wait for the enqueued data set.

FAIL

Indicates that the system fails (with a JCL error) a job that requests an unavailable JCLLIB data set.

Modification: \$T JOBDEF operator command or cold start. Note that this parameter cannot be modified through a hot start, quick start, or single-member warm start, such that the parameter value in effect before the termination is used.

CNVT_SCHENV=HONOR|IGNORE

Specifies whether the availability of a scheduling environment that is associated with a job controls which member a job converts on. If CNVT_SCHENV=HONOR is specified, then a job can only convert on a system where the scheduling environment associated with the job is available.

Modification: \$T JOBDEF operator command. This parameter cannot be modified by a hot start, quick start, or single-member warm start.

DEF_CLASS=class|A

Specifies a default class that JES2 uses if a non-valid class is discovered during processing. The specified class must be a defined and active batch job class. The specified class cannot be set to ACTIVE=NO, and cannot be deleted. The following examples show when the default class would be used:

- When a job is submitted with a CLASS= value that is not valid. The job is failed, but this class is associated with the job for later processing.
- When a job class is deleted that is associated with the INTRDR statement as CLASS=. The INTRDR CLASS value is set to this value.
- During initialization processing, when the CLASS= value that is specified for a reader (INTRDR, local or remote) is not valid and the operator continues initialization.

The default is A.

Modification: \$T JOBDEF operator command or a JES2 all-member warm start.

Scope: MAS-wide

DUPL_JOB=NODELAY|DELAY

Specifies whether JES2 is allowed to concurrently execute batch jobs with the same name in the same MAS.

DELAY

Do not allow JES2 to execute batch jobs with the same name in the same MAS at the same time.

NODELAY

Allow JES2 to execute batch jobs with the same name in the same MAS at the same time.

Modification: \$T JOBDEF operator command or JES2 cold start.

HTTP_NOTIFY={ENABLED|DISABLED}

Specifies whether JES2 should attempt delivery of job notification messages via HTTP POST. The job notifications are requested via interface described in [Requesting job notification in z/OS JES Application Programming](#).

When this option is set to DISABLED (default), JES2 only sends job notification via ENF 78. When it is set to ENABLED, JES2 also attempts to deliver notification via HTTP POST to the URL provided with the job notification request. Notification messages are delivered using [JES2 Email Delivery Services in z/OS JES2 Initialization and Tuning Guide](#).

Modification: \$T JOBDEF operator command.

Scope: MAS-wide.

INTERPRET=INIT|JES

Specifies when JES2 calls the MVS interpreter to process a job.

INIT

Specifies to call the interpreter when the job is selected for execution by an initiator. Invoking the interpreter in the initiator is the traditional JES2 processing method.

JES

Specifies for JES2 to call the interpreter at the end of conversion processing. The following functions are available if processing is done under JES (after conversion):

- Earlier detection of JCL errors that are detected by the MVS interpreter. This allows errors to be detected even if the job never executes for TYPRUN=.
- Processing of JESDS OUTPUT statements to control data set attributes, even if the job never executes.

Note: Specifying INTERPRET=JES causes EXIT 60 to be driven instead of exit 6. If you use exit 6, you might need to also provide similar function in exit 60 before setting interpret=JES.

Modification: \$T JOBDEF operator command.

JNUMWARN=nnn|80

Specifies the percentage (1–99) of assignable job numbers (specified through the RANGE= parameter) that have been used for jobs submitted at the local node at which the operator is to be alerted with message \$HASP050 JES2 RESOURCE SHORTAGE.

Modification: \$T JOBDEF operator command. Note that this parameter cannot be modified through a hot start, quick start, or single-member warm start.

JOBNUM=nnnnnn|1000

Specifies the maximum number (must be no greater than 1,000,000) of jobs that can be in the JES2 job queue at any given time. This value includes all TSU, STC jobs, and batch jobs.

Performance Consideration: Specify JOBNUM= large enough to accommodate all jobs (including batch jobs, started tasks, and TSO/E logons) in the system at all phases of processing. Be careful not to specify a value that is too small.

If you use the \$T JOBDEF command to increase JOBNUM=, only do so when you can allow your system to experience temporary performance degradation while all JES2 systems read the checkpoint data set.

Note: Use this parameter to increase the limit for the JNUM resource that is reported on the HASP050 message.

Modification: \$T JOBDEF operator command to increase or decrease the number of jobs.

JOBWARN=nnn|80

Specifies the percent (1–99) usage threshold of available job queue elements (JQEs) at which the operator is to be alerted with message \$HASP050 JES2 RESOURCE SHORTAGE. If you specify 0, no alert is given.

Modification: \$T JOBDEF operator command. Note that this parameter cannot be modified through a hot start, quick start, or single-member warm start.

NFY_SUBJECT=string

Specifies the optional character string that is used by JES2 as a subject line in email messages that are sent as a result of processing the NOTIFY JCL statement. Subject line can be up to 128 characters. Enclose string in single quotation marks if text includes blanks or special characters. Adding quotation marks also prevents capitalization of alphabetic characters.

Default: If this parameter is not specified, JES2 provides the default subject line of: z/OS job event notification.

Scope: Single Member.

LOGMSG=ASIS|FOLD

Specifies whether the messages issued by JES2 and written at job JCL converter time are mixed-case (ASIS) or uppercase (FOLD). The default is ASIS.

Modification: \$T JOBDEF operator command or JES2 start.

PRTYHIGH=nn|10

Specifies the upper priority limit (0-15) to be associated with the JES2 job priority-aging feature. A job is not priority-aged if its priority is (or becomes) greater than or equal to the value specified in this parameter. Jobs on the \$HARDCPY queue are not priority-aged.

Modification: \$T JOBDEF operator command. Note that this parameter cannot be modified through a hot start, quick start, or single-member warm start.

PRTYJECL=YES|NO

Specifies whether the JES2 /*PRIORITY control statement is to be supported (YES) or ignored (NO).

Modification: \$T JOBDEF operator command.

PRTYJOB=YES|NO

Specifies whether the priority specified (PRTY= keyword) on the JCL JOB statement is supported (YES) or ignored (NO).

Modification: \$T JOBDEF operator command.

PRTYLOW=nn|5

Specifies the lower priority limit (0-15) to be associated with the JES2 job priority-aging feature. A job is not priority-aged unless its priority is initially equal to or greater than this value. Jobs on the \$HARDCPY queue are not priority-aged. (See the PRTYRATE= and PRTYHIGH= parameters on this initialization statement for additional information.)

Modification: \$T JOBDEF operator command. Note that this parameter cannot be modified through a hot start, quick start, or single-member warm start.

PRTYRATE=nnnn|0

Specifies the number (0-1440) of time periods into which a 24-hour day is to be divided for use in increasing a job's priority by the JES2 priority-aging feature. For example, if 3 is specified, a job's

priority is increased by one for every 8 hours it remains in the system. However, a job's priority not incremented unless it is at least equal to the value specified in the PRTYLOW= parameter; nor is a job's priority be increased above the value specified in the PRTYHIGH= parameter. If 0 is specified, the values specified in the PRTYLOW= and PRTYHIGH= parameters are ignored. See [z/OS JES2 Initialization and Tuning Guide](#) for a discussion of this processing.

If a job's priority is specified on a `/*PRIORITY` control statement or through the `PRTY` parameters on the `JOB` card, the job is priority-aged if its priority is eligible. See the `JOBPRTY` statement (`JOBPRTY=` parameter) and `OUTPRTY` statement (`RECORD=`, `PAGE=`, and `PRIORITY=` parameters) in this chapter for additional information.) Jobs in WLM-mode job classes are not priority aged.

Modification: \$T JOBDEF operator command. Note that this parameter cannot be modified through a hot start, quick start, or single-member warm start.

RANGE=nnnnnn[,mmmmm]|1,9999

Specifies the range of numbers (1 through 999999) which JES2 assigns as JOBIDs to jobs which originated on the local node.

The integer n specifies the lowest number (1 through 999999) which is assigned as a JES2 job identifier for jobs originating locally.

The integer m specifies the highest number (n+10 through 999999) which is assigned as a JES2 job identifier to jobs originating locally. Note that setting the upper limit above 99,999 causes the JOBID format to change from CCCNNNNN to CONNNNNN where CCC is either JOB, STC, or TSU, and C is J, S, or T. NNNNN or NNNNNN is a number.

Note: Use this parameter to increase the limit for the JNUM resource that is reported on the HASP050 message.

Modification: \$T JOBDEF operator command or cold start. If you modify this parameter and then restart JES2 with a warm or hot start, the parameter value in effect before the termination is used.

RASSIGN=No|Yes

Specifies whether job numbers outside of the RANGE definition can be assigned to jobs received through NJE or spool reload. YES= Jobs with original job numbers outside JOBDEF RANGE retain their original job number, if possible. NO= Jobs with original job numbers outside JOBDEF RANGE are always assigned a new job number within the range.


SUP_EVENTLOG_SMF=No|Yes

Indicates if the writing of SMF records to the EVENTLOG data set should be suppressed. The default is No.

JOBPTY(n) - Job Priority

The JOBPTY(n) statement defines the relationship between priorities for execution-time jobs and the time required to execute those jobs. Specify n as an integer (1-9).

Format Description for JOBPRTY(n)



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for JOBPRTY(n)

PRIORITY=nn

Specifies the job-scheduling priority (0-15) relationship with execution times, as specified in a corresponding TIME= parameter on this statement.

If this parameter is not specified, the following values are used as default values:

JOBPRTY(n)	PRIORITY=
(1)	9
(2)	8
(3)	7
(4)	6
(5)	5
(6)	4
(7)	3
(8)	2
(9)	1

Modification: \$T JOBPRTY(n) operator command.

TIME=nnnnnn

Specifies execution times (1-279620), in minutes, that are to be associated with job-scheduling priorities, as specified in a corresponding PRIORITY parameter.

If a /*PRIORITY control statement is specified for a job or if PRTY= is specified on the JOB statement, these values are not used. See the PRIORITY= parameter on this initialization statement for additional information.

If these parameters are not specified, the following are used as defaults:

JOBPRTY(n)	PRIORITY=	TIME=
(1)	9	2
(2)	8	5
(3)	7	15
(4)	6	279620
.	.	.
.	.	.
.	.	.
(9)	1	279620

Modification: \$T JOBPRTY(n) operator command.


L(nnnnn).JT(n) - Job Transmitter

The L(nnnnn).JT(n) statement specifies work selection characteristics for a job transmitter on one teleprocessing line or logical line (for SNA NJE terminals) to be used during network job entry. The work selection characteristics include size limits, by number of lines and pages, for data sets that the transmitter will accept. Use these limits to customize transmitter streams to specific workloads, such as large files or smaller message traffic, depending on the needs of the system. Identify the teleprocessing line by L(nnnnn), where nnnnn can be 1-65535. Identify the Job transmitter by .JT(n), where n can be 1-7.

Note: If a job transmitter number (n) is higher than the value of the JTNUM= parameter on the NJEDEF statement, or higher than an overriding STNUM= value on a LINE statement for this line, the transmitter is not created. When this statement is coded with a valid transmitter number, a full set of job transmitters and receivers is created for the line as specified on JRNUM=, JTNUM=, SRNUM=, and STNUM= parameters of the NJEDEF or LINE statements.

After you define the job transmitters, you can use the subscript on this statement name to modify transmitters, that is, individual lines (nnnnn), a range of lines in either ascending (n-m) or descending (m-n) order, or a generic range in ascending (n-*), descending (*-n) order, or an asterisk (*) to indicate all lines. The valid subscript range for the LINE statement is now 1-65535.

Format Description for L(nnnnn).JT(n)



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for L(nnnnn).JT(n)

LIMit=m|m-n|m-*

Specifies the limits (in records) for data sets that the transmitter will select for line-mode transmissions. This number applies to the total lines of all non-spun output in the job or to individual spun SYSOUT data sets (or data set fragments) in a job.

For both variables m and n , you can specify a range of values 0-4294967295. m and n can be equal. If they are not equal, n must be larger than m .

If you code only m , that value becomes both the lower and upper limit. If m^* is specified, the upper limit is set to the default value of 4294967295.

Default: If you omit this parameter, JES2 uses the defaults $m=0$ and $n=4294967295$.

Modification: \$TL(nnn).JT(n) command.

WS=(criteria,.../criteria,...)

Specifies the work selection criteria for this device. Using any combination of installation- and JES2-defined criteria, you can specify up to 18 criteria in the WS= list. JES2 defines LIM (page and record limit only); any other criterion is installation defined through use of the \$WSTAB macro. (See *z/OS JES2 Macros* for an explanation of using the \$WSTAB macro.) Multiple entries must be separated by commas and the list (even a list of one criterion) must be enclosed in parentheses. If a criterion is specified in the list, work selection is based on the current setting of the corresponding parameter. If a criterion is not specified in the list, the criterion is not considered during work selection.

The general rules for specifying a SYSOUT transmitter work selection list are:

- You can use one slash (/) before or after one of the criterion to further specify work selection. Criteria placed before the slash must be matched exactly if the work is to be selected. Criteria placed after the slash do not have to match exactly.
- The order of those criteria specified after the slash indicates the priority (highest to lowest, in left to right order) in which JES2 attempts to match them.
- If the data being considered for transmission was received from a node that does not provide a page count for its files, then JES2 sets the page count to zero and transmits the data only if a zero page count is within the limits. For more information, see the sending node's reference documentation.
- In general, the smaller the work selection list the less the placement of certain criteria within the list affects the work selection.

Default: / (no work selection criteria)

Modification: \$TL(nnn).JT(n) command.


L(nnnnn).ST(n) - SYSOUT Job Transmitter

The L(nnnnn).ST(n) statement specifies work selection characteristics for a SYSOUT transmitter on one teleprocessing line or logical line (for SNA NJE terminals) to be used during network job entry. The work selection characteristics include size limits, by number of lines and pages, for SYSOUT data sets that the transmitter will accept. Use these limits to customize transmitter streams to specific workloads, such as large files or smaller message traffic, depending on the needs of the system. Identify the teleprocessing line by L(nnnnn), where nnnnn can be 1-65535. If you specify * as an ending subscript range, possible performance degradation can result during JES2 initialization. Identify the SYSOUT transmitter by .ST(n), where n can be 1-7.

Note: If a SYSOUT transmitter number (n) is higher than the value of the STNUM= parameter on the NJEDEF statement, or higher than an overriding STNUM= value on a LINE statement for this line, the SYSOUT transmitter is not created. When this statement is coded with a valid transmitter number, a full set of job and SYSOUT transmitters and receivers is created for the line as specified on JRNUM=, JTNUM=, SRNUM=, and STNUM= parameters of the NJEDEF or LINE statements.

After you define the SYSOUT job transmitters, you can use the subscript on this statement name to modify SYSOUT transmitters, that is, individual lines (nnnnn), a range of lines in either ascending (n-m) or descending (m-n) order, or a generic range in ascending (n-*), descending (*-n) order, or an asterisk (*) to indicate all lines. The valid subscript range for the LINE statement is now 1-65535.

Format Description for L(nnnnn).ST(n)



Notes:

- ¹ Omit the comma between initialization statement and first keyword
- ² OUTDisp can be coded up to 4 times

Parameter Description for L(nnnnn).ST(n)

LIMit=*m*|*m-n*|*m*-*

Specifies the limits (in records) for SYSOUT data sets that the SYSOUT transmitter will select for line-mode transmissions. This number applies to the total lines of all non-spun output in the job or to individual spun SYSOUT data sets (or data set fragments) in a job.

For both variables *m* and *n*, you can specify a range of values 0-4294967295. *m* and *n* can be equal. If they are not equal, *n* must be larger than *m*.

If you code only *m*, that value becomes both the lower and upper limit. If *m*-* is specified, the upper limit is set to the default value of 4294967295.

Default: If you omit this parameter, JES2 uses the defaults *m*=0 and *n*=4294967295.

Modification: \$T L(nnnnn).ST(n) operator command.

OUTDisp=(disposition[...disposition])

Specifies the disposition(s) that the output must have in order to be eligible for processing by this offload transmitter. The operator can specify one to four of the following valid dispositions:

HOLD|H

Hold the output. JES2 does not process the output until you either change the disposition to WRITE or KEEP, or release the output. When the output is released, the disposition changes to WRITE.

Note: This specification is honored when the output reaches the destination node.

KEEP|K

JES2 processes the output. After processing, the disposition of this output becomes LEAVE. A copy will NOT be kept on spool on the source node after transmission, or offload process. Output disposition is only honored at final destination.

LEAVE|L

JES2 does not process the output until you change the disposition to WRITE or KEEP, or release the output. When the output is released, the disposition changes to KEEP. A copy will NOT be kept on spool on the source node after transmission, or offload process. Output disposition is only honored at final destination.

WRITE|W

JES2 processes the output then purges it.

See [z/OS JES2 Initialization and Tuning Guide](#) for more information about specifying output disposition and how JES2 determines output disposition defaults.

Default: Only output with dispositions WRITE and KEEP are selected by this offload transmitter if you do not specify values for OUTDisp=.

Modification: \$T L(n).ST operator command

PLIM=*m*|*m-n*|*m*-*

Specifies the limits (in pages) set by this device for SYSOUT data sets that the SYSOUT transmitter will select for page-mode transmissions. This number applies to the total pages of all non-spun output in the job or to individual spun SYSOUT data sets in a job.

For both variables *m* and *n*, you can specify a range of values 0-4294967295. *m* and *n* can be equal. If they are not equal, *n* must be larger than *m*.

If you code only *m*, that value becomes both the lower and upper limit. If *m*-* is specified, the upper limit is set to the default value of 4294967295.

Default: If you omit this parameter, JES2 uses the defaults *m*=0 and *n*=4294967295.

Modification: \$T L(nnnnn).ST(n) operator command.

WS=(criterion,.../criterion,...)

Specifies the work selection criteria for this device. Using any combination of installation- and JES2-defined criteria, you can specify up to 18 criteria in the WS= list. JES2 defines LIM (page and record

limit only); any other criterion is installation defined through use of the \$WSTAB macro. (See *z/OS JES2 Macros* for an explanation of using the \$WSTAB macro.) Multiple entries must be separated by commas and the list (even a list of one criterion) must be enclosed in parentheses. If a criterion is specified in the list, work selection is based on the current setting of the corresponding parameter. If a criterion is not specified in the list, the criterion is not considered during work selection.

The general rules for specifying a SYSOUT transmitter work selection list are:

- You can use one slash (/) before or after one of the criterion to further specify work selection. Criteria placed before the slash must be matched exactly if the work is to be selected. Criteria placed after the slash do not have to match exactly.
- The order of those criteria specified after the slash indicates the priority (highest to lowest, in left to right order) in which JES2 attempts to match them.
- If the data being considered for transmission was received from a node that does not provide a page count for its files, then JES2 sets the page count to zero and transmits the data only if a zero page count is within the limits. For more information, see the sending node's reference documentation.
- In general, the smaller the work selection list the less the placement of certain criteria within the list affects the work selection.

Default: / (no work selection criteria)

Modification: \$T L(nnnnn).ST(n) operator command.

LINE(nnnnn) - NJE/RJE BSC Lines


The LINE(nnnnn) statement specifies the characteristics of one teleprocessing line to be used during remote or network job entry (for BSC NJE and RJE terminals). Define each teleprocessing line by a LINE(nnnnn) statement with a unique value (1-65535).

Use the subscript on this statement name to specify individual lines (nnnnn), a range of lines in either ascending (n-m) or descending (m-n) order, or a generic range in ascending (n-*), descending (*-n) order, or an asterisk (*) to indicate all lines. The valid subscript range for the LINE statement is now 1–65535.


There are four parameters that you use to define the number of transmitters and receivers for a line. They are: JRNUM=, JTNUM=, SRNUM=, and STNUM=, and are collectively referred to as xxNUM= parameters. If all the xxNUM= parameters are specified as DEFAULT, no devices are dedicated to this line unless a device is specified on either an L(nnnnn).ST(n) statement or an L(nnnnn).JT(n) statement for this line. In that case, a full set of transmitter and receiver devices is dedicated as specified on the NJEDEF xxNUM= parameters. If any of the xxNUM= parameters are set to a value other than DEFAULT, a full set of transmitters and receivers is dedicated to the line, with default values taken from NJEDEF.

- If a set of transmitters and receivers are dedicated to the line, the line may not be used for RJE.
- If transmitters/receivers are not dedicated to the line, it may still be used for NJE.
- A default set of transmitters and receivers is assigned when the NJE link is started, and detached when the NJE link is ended.


Format Description for LINE(nnnnn) - BSC




Modification keywords



Selection limiting keywords





Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for LINE(nnnnn) - BSC

AUTODISC=Yes|No

Specifies whether (Yes) or not (No) this line is to be disconnected automatically from a terminal when the local modem disconnects.

Note: If you use AUTODISC=Yes for a leased, dedicated line, you can cause serious performance impact without receiving the \$HASPO94 I/O ERROR message. This may also occur if a modem is disconnected or powered-off during a session or a line started with a modem disconnected or powered off.

Modification: \$T LINE(nnnnn) operator command.

CODE=A|B

Specifies the code for this line.

A

Specifies code A for this line; code A refers to the first code in a BSC adapter that has the dual code feature.

B

Specifies code B for this line. Code B refers to the second code in a BSC adapter that has the dual code features. If the dual code feature is not present, B should not be specified. See *2701 Data Adapter Component Description* for information about BSC CCWs and sense codes.

Modification: \$T LINE(nnnnn) operator command.

COMPRESS= Yes|No

For RJE workstations only, specifies whether (Yes) or not (No) BSC hardware terminals attached to this line can utilize data compression. If you specify NO, it overrides the specification of the COMPRESS= parameter on the RJE workstation (RMT(nnnnn)) initialization statement for any workstation that might use this line and any remote device statement. Compression compatibility is standard for BSC multileaving workstations.

If you specify COMPRESS=Yes, the specification of the COMPRESS= parameter on the RMT(nnnnn) and the COMP parameter on the remote device (Rnnnnn.xxx) statements is allowed to take effect. IF RMT(nnnnn) specifies COMPRESS=No, or Rnnnnn.xxx specifies NOCOMP, no compression will take place.

This parameter defaults to Yes, which specifies that the line allows data compression.

Modification: \$T LINE(nnnnn) operator command.

CONNECT= (Yes|No|DEFAULT,interval)

Specifies whether an NJE connection should be automatically attempted for this line. If DEFAULT is specified, processing defers to the CONNECT=(YES|NO) value that is specified on the associated NODE statement. The *interval* is the approximate time (in minutes) between attempted connections. The valid range for *interval* is 0 to 1440. A value of 0 indicates that the default interval (from NJEDEF CONNECT=) should be used. The default CONNECT value is DEFAULT, and the default *interval* is 0.

Discon={NOI|INTERRUPT|Q|QUIESCE}

Specifies whether the line is to be disconnected immediately (I) or after it completes its current activity (Q).

I or INTERRUPT

A sign-off record is sent to the attached multi-leaving remote workstation or to the connected NJE node.

Q or QUIESCE

The disconnection occurs as though the remote operator or NJE node had signed off. This is for active lines only.

Note: You can change this parameter only if the specified line is **not** currently drained.

DUPLEX=HALF|FULL

Specifies whether this is a full-duplex (FULL) or half-duplex (HALF) line.

Modification: \$T LINE(nnnnn) operator command.

INTERFAC=A|B

A specifies interface A for this line; interface A refers to the first interface in a BSC adapter that has the dual-communications interface feature.

B specifies interface B for this line; interface B refers to the second interface in a BSC adapter that has the dual-communications interface feature. If the adapter for this line does not have the dual-communications interface feature, B should not be specified.

Modification: \$T LINE(nnnnn) operator command.

JRNUM=n|DEFAULT

Specifies the number (0-7) of network job receivers to be associated with this NJE line. The value of n is an integer that specifies the maximum number of input job streams allowed to be concurrently active on this line. This specification should match the value of JTNUM= for this line on other nodes with which this node is to communicate directly. The sum of the values of JRNUM= and SRNUM= for this line must not exceed 8, or the statement is ignored.

This value overrides the default global value set by the JRNUM= parameter of the NJEDEF statement. If this value is omitted or set to DEFAULT, the value is taken from the JRNUM= parameter of NJEDEF. If you omit or use the DEFAULT where the sum of JRNUM= and SRNUM= exceeds 8, JRNUM= is reduced so that the sum equals 8.

Default: Value of the JRNUM parameter of NJEDEF.

Modification: Operator command.

JTNUM=n|DEFAULT

Specifies the number (0-7) of network job transmitters to be associated with this NJE line. The value of n is an integer that specifies the maximum number of output job streams allowed to be concurrently active on this line. You should not change this value unless it is known that a particular user has jobs with extremely large amounts of input to be transmitted and other short jobs that must be transmitted concurrently. If there are not enough receivers on the receiving node to receive jobs over the line, excess transmitters drain automatically. The sum of the values JTNUM and STNUM for this line must not exceed 8, or the statement is ignored.

This value overrides the default global value set by the JTNUM= parameter of the NJEDEF statement. If this value is omitted or set to DEFAULT, the value is taken from the JTNUM= parameter of NJEDEF. If you omit or use the DEFAULT where the sum of JTNUM and STNUM exceeds 8, JTNUM= is reduced so that the sum equals 8.

Default: Value of the JTNUM= parameter of NJEDEF.

Modification: Operator command.

LINECHR=USASCII|EBCDIC

USASCII specifies that the BSC adapter is configured for ASCII line-control characters. When USASCII is specified, this line must be used with 2770, 2780, or 3780 USASCII terminals. EBCDIC specifies that the BSC adapter is configured for EBCDIC line-control characters.

Modification: \$T LINE(nnnnn) operator command.

LOG=Yes|No

Specifies whether (Yes) or not (No) JES2 is to monitor this line for channel-end completions or SNA events. If you specify LOG=Yes, JES2 issues \$HASP094 message for every transmission across this BSC line. You should specify LOG=No if your installation performs extensive networking activity.

Modification: \$T LINE(nnnnn) operator command.

NODE=node

Specifies the NJE node name associated with this node. This value determines which node to connect to when a \$SN,LINE=xxx command is issued or the line is automatically connected.

Password=xxxxxxx

Specifies a 1- to 8-character security password JES2 is to use to prevent unauthorized terminal users from using this line. You can use this password in the connection request from RJE workstations.

If you do not specify a password, one does not exist.

Modification: \$T LINE(nnnnn) operator command.

REST=nnnnn|0

Specifies an integer between 0 and 2000 which represents the resistance rating of the line as viewed by the installation management and coordinated with other installations. Resistance is an arbitrary value set to indicate a specific line's ability or inability to route work that has "normal" workload requirements and line speed. See [z/OS JES2 Initialization and Tuning Guide](#) for details concerning resistance selection.

Modification: \$T LINE(nnnnn) operator command.

RESTART= (Yes|No,*interval*)

Specifies whether (Yes) or not (No) this line will be restarted if it is drained. The *interval* is the approximate time (in minutes) between attempted restarts. The valid range for *interval* is 0 to 1440. A value of 0 indicates that the default interval (from NJEDEF CONNECT=) should be used. The default RESTART value is No, and the default *interval* value is 0.

SPEED=HIGH|LOW

Specifies whether this is a high-speed (greater than 9600 bits per second) or low-speed line.

Note: This parameter is only applicable to 360/20 submodels 2 and 4.

Modification: \$T LINE(nnnnn) operator command.

SRNUM=n|DEFAULT

Specifies the number (0-7) of network SYSOUT receivers to be associated with this NJE line. The value of n is an integer which specifies the maximum number of SYSOUT receiver streams allowed to be concurrently active on this line. This specification should match the value of STNUM= for this line on the other nodes with which this member is to communicate directly. The sum of the values JRUNUM= and SRNUM= for this line must not exceed 8, or the statement is ignored. This value overrides the default global value set by the SRNUM= parameter of the NJEDEF statement. If this value is omitted or set to DEFAULT, the value is taken from the SRNUM= parameter of NJEDEF. If you omit or use the DEFAULT where the sum of SRNUM= and JRUNUM= exceeds 8, SRNUM= is reduced so that the sum equals 8.

Default: Value of the SRNUM= parameter of NJEDEF.

Modification: Operator command.

START=Yes|No

Specifies whether (Yes) or not (No) this line, if it is ready, will be started automatically when JES2 starts processing. The default START value is No.

STNUM=n|DEFAULT

Specifies the number (0-7) of network SYSOUT transmitters which will be associated with this NJE line. The value of n is an integer which specifies the maximum number of SYSOUT transmitter streams allowed to be concurrently active on this line. If there are not enough receivers on the receiving node to receive SYSOUT data over the line, excess transmitters drain automatically. The sum of the values JTNUM= and STNUM= for this line must not exceed 8, or the statement is ignored.

This value overrides the default global value set by the STNUM= parameter of the NJEDEF statement. If this value is omitted or set to DEFAULT, the value is taken from the STNUM= parameter of NJEDEF. If you omit or use the DEFAULT where the sum of STNUM= and JTNUM= exceeds 8, STNUM value is reduced so that the sum equals 8.

Default: Value of the STNUM= parameter of NJEDEF.

Modification: Operator command.

TRaceio=Yes|No

Specifies whether (Yes) or not (No) trace ID 4 will trace channel-end completions for BSC lines on VTAM lines and JES2/VTAM interface events, and trace IDs 21 through 24 will trace network control connect (NCC) records.

Modification: \$T LINE(nnnnn) operator command.

TRANSPAR=Yes|No

Specifies whether (Yes) or not (No) the text transparency feature of the BSC adapter is present on this line. The text transparency feature allow JES2 to send all 256 characters in a data stream without the data being interpreted as control characters. You must specify Yes for NJE lines.

TRANSPAR=No is valid only for EP links generated to operate as a D/T2701 without the transparency feature. For device types which require the transparency feature, such as 2703 and CTC, specifying TRANSPAR=NO will have no effect and TRANSPAR=YES will be forced at initialization.

Modification: \$T LINE(nnnnn) operator command.

UNIT=hhhh | /hhhh

UNIT can be specified as one of the following:

- A 3- or 4-digit hexadecimal device number. Device numbers can be specified in any of the following formats:

```
UNIT=hhh
UNIT=hhhh
UNIT=/hhh
UNIT=/hhhh
```

where hhh and hhhh represent the device numbers.

A slash (/) can optionally precede the device number (for compatibility with other initialization statements that require a slash to denote a 4-digit device number).

- For RJE BSC lines, specify the device number as the same address that you specified for the subchannel address defined for the communication controller.
- NJE protocols support an ESCON Basic Mode CTC (defined to the hardware configuration dialog as BCTC) and a 3088 CTC but do not support an ESCON CTC (defined to the hardware as SCTC).

The same unit address may be specified for more than one line to allow use of different interfaces or codes available in a single BSC adapter. JES2 will allow only one of these lines to be started by the operator at any one time.

If UNIT= is specified, a BSC adapter that was previously offline during JES2 initialization will remain accessible.

You can specify line availability in the following three ways:

1. Make the line available to any RJE workstation (dial up)
2. Make the line available to two or more RJE workstations that must contend for use of the line
3. Make the line available only to a single RJE workstation

The relationship between lines and RJE workstations is controlled by the LINE(nnnnn) and RMT(nnnnn) initialization statements.

If non-SNA NJE lines are attached to a 3705, the 3705 must have been generated to emulate a 2701 or a 2703. During system installation, use hardware configuration definition (HCD) to define the attached NJE lines as follows:

- On the 'Primary Task Selection' panel, select '1. Define, modify, or view configuration'. On the resulting panel, select '5. I/O devices'
- On the 'Add Device' panel, specify the device type as BSC1.
- On the 'Define Parameter / Feature' panel, specify the TCU parameter as 2701

See [z/OS HCD User's Guide](#) for a complete list of the steps involved in defining a device.

If not specified, JES2 does not assign an available BSC line; instead, a BSC line can be dynamically assigned using a \$T LINE(nnnnn) command.

Modification: \$T LINE operator command.


LINE(nnnnn) - NJE/RJE SNA Lines


The LINE(nnnnn) statement specifies the characteristics of one teleprocessing line or logical line (for SNA RJE terminals) to be used during remote or network job entry. Define each teleprocessing line by a LINE(nnnnn) statement with a unique value (1-65535).

Use the subscript on this statement name to specify individual lines (nnnnn), a range of lines in either ascending (n-m) or descending (m-n) order, or a generic range in ascending (n-*), descending (*-n) order, or an asterisk (*) to indicate all lines. The valid subscript range for the LINE statement is now 1-65535.


Note:


1. Do not specify a password for SNA lines used in NJE host-to-host sessions.
2. There are four parameters that you use to define the number of transmitters and receivers for a line. They are: JRNUM=, JTNUM=, SRNUM=, and STNUM=, and are collectively referred to as xxNUM= parameters. If all the xxNUM= parameters are specified as DEFAULT, no devices are dedicated to this line unless a device is specified on an L(nnnnn) statement for this line. In that case, a full set of transmitter and receiver devices is dedicated as specified on the NJEDEF xxNUM= parameters. If any of the xxNUM= parameters are set to a value other than DEFAULT, a full set of transmitters and receivers is dedicated to the line, with default values taken from NJEDEF.
 - If a set of transmitters and receivers are dedicated to the line, you cannot use the line RJE.
 - If transmitters or receivers are not dedicated to the line, you can still use the line for NJE.
 - A default set of transmitters and receivers is assigned when the NJE link is started, and detached when the NJE link is ended.

Format Description for LINE(nnnnn) - SNA**Modification keywords**



Selection limiting keywords





Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for LINE(nnnnn) - SNA

COMPRESS= Yes|No

For RJE workstations only, specifies whether (Yes) or not (No) hardware terminals attached to this line can utilize data compression. If you specify No, it overrides the specification of the COMPRESS= parameter on the RJE workstation (RMT(nnnnn)) initialization statement for any RJE workstation that might use this line and any remote device statement.

If you specify COMPRESS=Yes, the specification of the COMPRESS= parameter on the RMT(nnnnn) and the COMP parameter on the remote device (Rnnnnn.xxx) statements is allowed to take effect. IF RMT(nnnnn) specifies COMPRESS=oO, or Rnnnnn.xxx specifies NOCOMP, no compression will take place.

This parameter defaults to Yes, which specifies that the line allows data compression.

Modification: \$T LINE(nnnnn) operator command.

CONNECT= (Yes|No|DEFAULT, *interval*)

Specifies whether an NJE connection should be automatically attempted for this line. If DEFAULT is specified, processing defers to the CONNECT=(YES|NO) value that is specified on the associated NODE statement. The *interval* is the approximate time (in minutes) between attempted connections. The valid range for *interval* is 0 to 1440. A value of 0 indicates that the default interval (from NJEDEF CONNECT=) should be used. The default CONNECT value is DEFAULT, and the default interval is 0.

Discon={NoI|INTERRUPT|Q|QUIESCE}

Specifies whether the line is to be disconnected immediately (I) or after it completes its current activity (Q).

I or INTERRUPT

A sign-off record is sent to the attached multi-leaving remote workstation or to the connected NJE node.

Q or QUIESCE

The disconnection occurs as though the remote operator or NJE node had signed off. This is for active lines only.

Note: You may change this parameter only if the specified line is **not** currently drained.

JRNUM=n|DEFAULT

Specifies the number (0-7) of network job receivers to be associated with this NJE line. The value of n is an integer that specifies the maximum number of input job streams allowed to be concurrently active on this line. This specification should match the value of JTNUM for this line on other nodes with which this node is to communicate directly. The sum of the values of JRNUM and SRNUM for this line must not exceed 8, or the statement is ignored.

This value overrides the default global value set by the JRNUM= parameter of the NJEDEF statement. If this value is omitted or set to DEFAULT, the value is taken from the JRNUM= parameter of NJEDEF. If you omit or use the DEFAULT where the sum of JRNUM= and SRNUM= exceeds 8, JRNUM= is reduced so that the sum equals 8.

Default: Value of the JRNUM= parameter of NJEDEF.

Modification: \$T LINE(nnnnn) operator command.

JTNUM=n|DEFAULT

Specifies the number (0-7) of network job transmitters to be associated with this NJE line. The value of n is an integer that specifies the maximum number of output job streams allowed to be concurrently active on this line. This value should remain unchanged unless it is known that a particular user has some jobs with extremely large amounts of input to be transmitted and other short jobs that must be transmitted concurrently. If there are not enough receivers on the receiving node to receive jobs over the line, excess transmitters drain automatically. The sum of the values JTNUM= and STNUM= for this line must not exceed 8, or the statement is ignored.

This value overrides the default global value set by the JTNUM= parameter of the NJEDEF statement. If this value is omitted or set to DEFAULT, the value is taken from the JTNUM= parameter of NJEDEF. If you omit or use the DEFAULT where the sum of JTNUM= and STNUM= exceeds 8, JTNUM= is reduced so that the sum equals 8.

Default: Value of the JTNUM= parameter of NJEDEF.

Modification: \$T LINE(nnnnn) operator command.

LOG=Yes|No

Specifies whether (Yes) or not (No) JES2 is to monitor this line for channel-end completions or SNA events. If you specify LOG=Yes, JES2 issues \$HASP094 message for every transmission across this SNA line. You should specify LOG=No if your installation performs extensive networking activity.

Modification: \$T LINE(nnnnn) operator command.

NODE=node

Specifies the NJE node name associated with this node. This value determines which node to connect to when a \$SN,LINE=xxx command is issued or the line is automatically connected.

Password=xxxxxxx

Specifies a 1- to 8-character security password JES2 is to use to prevent unauthorized terminal users from using this line. This password can be used in the connection request from RJE workstations. You cannot specify a password for SNA lines used in NJE host-to-host sessions.

Note: If you specify a password for an SNA line, it is meaningful only if that line is a dedicated line.

If you do not specify a password, none exists.

Modification: \$T LINE(nnnnn) operator command.

REST=nnnn|0

Specifies an integer between 0 and 2000 which represents the resistance rating of the line as viewed by the installation management and coordinated with other installations. Resistance is an arbitrary value set to indicate a specific line's ability or inability to route work that has "normal" workload requirements and line speed.

Note that this parameter defaults to the REST= value specified on the APPL(jxxxxxxx) or the NODE(xxxxxxxx) initialization statement. See [z/OS JES2 Initialization and Tuning Guide](#) for details concerning resistance selection.

Modification: \$T LINE(nnnnn) operator command.

RESTART= (Yes|No, *interval*)

Specifies whether (Yes) or not (No) this line will be restarted if it is drained. The *interval* is the approximate time (in minutes) between attempted restarts. The valid range for *interval* is 0-1440. A value of 0 indicates that the default interval (from NJEDEF CONNECT=) should be used. The default RESTART value is No, and the default interval value is 0.

SRNUM=n|DEFAULT

Specifies the number (0-7) of network SYSOUT receivers to be associated with this NJE line. The value of n is an integer which specifies the maximum number of SYSOUT receiver streams allowed to be concurrently active on this line. This specification should match the value of STNUM= for this line on the other nodes with which this member is to communicate directly. The sum of the values JRNUM= and SRNUM= for this line must not exceed 8, or the statement is ignored.

This value overrides the default global value set by the SRNUM= parameter on the NJEDEF statement. If this value is omitted or set to DEFAULT, the value is taken from the SRNUM= parameter of NJEDEF. If you omit or use the DEFAULT where the sum of SRNUM= and JRNUM= exceeds 8, SRNUM= is reduced so that the sum equals 8.

Default: Value of the SRNUM= parameter of NJEDEF.

Modification: \$T LINE(nnnnn) operator command.

START=Yes|No

Specifies whether (Yes) or not (No) this line, if it is ready, will be started automatically when JES2 starts processing. The default START value is No.

STNUM=n|DEFAULT

Specifies the number (0-7) of network SYSOUT transmitters which will be associated with this NJE line. The value of n is an integer which specifies the maximum number of SYSOUT transmitter streams allowed to be concurrently active on this line. If there are not enough receivers on the receiving node to receive SYSOUT data over the line, excess transmitters drain automatically. The sum of the values JTNUM= and STNUM= for this line must not exceed 8, or the statement is ignored.

This value overrides the default global value set by the STNUM= parameter of the NJEDEF statement. If this value is omitted or set to DEFAULT, the value is taken from the STNUM= parameter of NJEDEF. If you omit or use the DEFAULT where the sum of STNUM= and JTNUM= exceeds 8, STNUM= is reduced so that the sum equals 8.

Default: Value of the STNUM= parameter of NJEDEF.

Modification: \$T LINE(nnnnn) operator command.

TRaceio=Yes|No

Specifies whether (Yes) or not (No) trace ID 5 will trace I/O associated with SNA lines on VTAM lines and JES2/VTAM interface events, and trace IDs 21 through 24 will trace network control connect (NCC) records.

Modification: \$T LINE(nnnnn) operator command.

UNIT=SNA

Specify UNIT=SNA to obtain a logical line. You can specify the line availability in the following three ways:

1. Make the line available to any RJE workstation (dial up)
2. Make the line available to two or more RJE workstations that must contend for use of the line
3. Make the line available only to a single RJE workstation

The relationship between lines and RJE workstations is controlled by the LINE(nnnnn) and RMT(nnnnn) initialization statements. For example, to define a SNA line that is to be available to any RJE workstation, specify only UNIT=SNA on the LINE(nnnnn) statement and do not specify LINE=nnnnn on the RMT(nnnnn) statement.

You must specify this parameter as SNA.

Modification: \$T LINE operator command.

LINE(nnnnn) - NJE TCP/IP lines



The LINE(nnnnn) statement specifies the characteristics of one teleprocessing line or logical line to be used during remote or network job entry. Define each teleprocessing line by a LINE(nnnnn) statement with a unique value (1-65535).

Use the subscript on this statement name to specify individual lines (nnnnn), a range of lines in either ascending (n-m) or descending (m-n) order, or a generic range in ascending (n-*), descending (*-n) order, or an asterisk (*) to indicate all lines. The valid subscript range for the LINE statement is now 1–65535.







Note:

1. Do not specify a password for TCP/IP lines used in NJE host-to-host sessions.
2. There are four parameters that you use to define the number of transmitters and receivers for a line. They are: JRNUM=, JTNUM=, SRNUM=, and STNUM=, and are collectively referred to as xxNUM= parameters. If all the xxNUM= parameters are specified as DEFAULT, no devices are dedicated to this line unless a device is specified on an L(nnnnn) statement for this line. In that case, a full set of transmitter and receiver devices is dedicated as specified on the NJEDEF xxNUM= parameters. If any of the xxNUM= parameters are set to a value other than DEFAULT, a full set of transmitters and receivers is dedicated to the line, with default values taken from NJEDEF.
 - If a set of transmitters and receivers are dedicated to the line, you cannot use the line for RJE.
 - If transmitters or receivers are not dedicated to the line, you can still use the line for NJE.
 - A default set of transmitters and receivers is assigned when the NJE link is started, and detached when the NJE link is ended.


Format Description for LINE(nnnnn) - TCP/IP



Modification keywords



Selection limiting keywords



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for LINE(nnnnn) - TCP/IP

CONNECT=(Yes|No|DEFAULT,interval)

Specifies whether an NJE connection should be automatically attempted for this line. If **DEFAULT** is specified, processing defers to the **CONNECT=(YES|NO)** value that is specified on the associated **NODE** statement. The *interval* is the approximate time (in minutes) between attempted restarts. The valid range for *interval* is 0 to 1440. A value of 0 indicates that the default interval (from NJEDEF **CONNECT=**) should be used. The default **CONNECT** value is **DEFAULT**, and the default *interval* is 0.

JRNUM=n|DEFAULT

Specifies the number (0-7) of network job receivers to be associated with this NJE line. The value of *n* is an integer that specifies the maximum number of input job streams allowed to be concurrently active on this line. This specification should match the value of **JTNUM** for this line on other nodes with which this node is to communicate directly. The sum of the values of **JRNUM** and **SRNUM** for this line must not exceed 8, or the statement is ignored.

This value overrides the default global value set by the **JRNUM=** parameter of the **NJEDEF** statement. If this value is omitted or set to **DEFAULT**, JES2 takes the value from the **JRNUM=** parameter of **NJEDEF**. If you omit the value or use the default value where the sum of the values of **JRNUM** and **SRNUM** exceeds 8, **JRNUM=** is reduced so that the sum equals 8.

Default: Value of the **JRNUM=** parameter of **NJEDEF**.

Modification: Hot start.

JTNUM=n|DEFAULT

Specifies the number (0-7) of network job transmitters to be associated with this NJE line. The value of *n* is an integer that specifies the maximum number of output job streams allowed to be concurrently active on this line. You should not change this value unless it is known that a particular user has jobs with extremely large amounts of input to be transmitted and other short jobs that must be transmitted concurrently. If there are not enough receivers on the receiving node to receive jobs over the line, excess transmitters drain automatically. The sum of the values **JTNUM=** and **STNUM=** for this line must not exceed 8, or the statement is ignored.

This value overrides the default global value set by the JTNUM= parameter of the NJEDEF statement. If this value is omitted or set to DEFAULT, the value is taken from the JTNUM= parameter of NJEDEF. If you omit or use the DEFAULT value, where the sum of the values of JRNUM and SRNUM exceeds 8, JTNUM= is reduced so that the sum equals 8.

Default: Value of the JTNUM= parameter of NJEDEF.

Modification: Hot start.

NODE=node

Specifies the NJE node name associated with this node. This value determines which node to connect to when a \$SN,LINE=xxx command is issued or the line is automatically connected.

Password=xxxxxxx

Specifies a 1- to 8- character security password JES2 is to use to prevent unauthorized terminal users from using this line. This password can be used in the connection request from RJE workstations. Do not specify a password for TCP/IP lines used in NJE host-to-host sessions.

Note: If you specify a password for a TCP/IP line, it is meaningful only if that line is a dedicated line.

If you do not specify a password, none exists.

Modification: \$T LINE(nnnnn) operator command.

REST=nnnn|0

Specifies an integer between 0 and 2000 which represents the resistance rating of the line as viewed by the installation management and coordinated with other installations. Resistance is an arbitrary value set to indicate a specific line's ability or inability to route work that has "normal" workload requirements and line speed.

Note that this parameter defaults to the REST= value specified on the SOCKET(jxxxxxx) or the NODE(xxxxxxx) initialization statement. See [z/OS JES2 Initialization and Tuning Guide](#) for details concerning resistance selection.

Modification: \$T LINE(nnnnn) operator command.

RESTART= (Yes|No,interval)

Specifies whether (Yes) or not (No) this line will be restarted if it is drained. The *interval* is the approximate time (in minutes) between attempted restarts. The valid range for *interval* is 0 to 1440. A value of 0 indicates that the default interval (from NJEDEF CONNECT=) should be used. The default RESTART value is No, and the default *interval* value is 0.

SRNUM=n|DEFAULT

Specifies the number (0-7) of network SYSOUT receivers to be associated with this NJE line. The value of n is an integer which specifies the maximum number of SYSOUT receiver streams allowed to be concurrently active on this line. This specification should match the value of STNUM= for this line on the other nodes with which this member is to communicate directly. The sum of the values JRNUM= and SRNUM= for this line must not exceed 8, or the statement is ignored.

This value overrides the default global value set by the SRNUM= parameter on the NJEDEF statement. If this value is omitted or set to DEFAULT, the value is taken from the SRNUM= parameter of NJEDEF. If you omit or use the DEFAULT where the sum of SRNUM= and JRNUM= exceeds 8, SRNUM= is reduced so that the sum equals 8.

Default: Value of the SRNUM= parameter of NJEDEF.

Modification: Hot start.

START=Yes|No

Specifies whether (Yes) or not (No) this line, if it is ready, will be started automatically when JES2 starts processing. The default START value is No.

STNUM=n|DEFAULT

Specifies the number (0-7) of network SYSOUT transmitters which will be associated with this NJE line. The value of n is an integer which specifies the maximum number of SYSOUT transmitter streams allowed to be concurrently active on this line. If there are not enough receivers on the receiving node

to receive SYSOUT data over the line, excess transmitters drain automatically. The sum of the values JTNUM= and STNUM= for this line must not exceed 8, or the statement is ignored.

This value overrides the default global value set by the STNUM= parameter of the NJEDEF statement. If this value is omitted or set to DEFAULT, the value is taken from the STNUM= parameter of NJEDEF. If you omit or use the DEFAULT where the sum of STNUM= and JTNUM= exceeds 8, STNUM= is reduced so that the sum equals 8.

Default: Value of the STNUM= parameter of NJEDEF.

Modification: Hot start.

UNIT=TCP|TCPIP|TCP/IP

Specify UNIT=TCP to define a logical line. TCP/IP lines may only be used for NJE communication.

TRaceio={YES|NO|JES=YES|NO|COMMON=YES|NO|VERBOSE=YES|NO}

Specifies whether tracing is to be active, and which types of traces are to be activated for the TCP/IP line.

YES

Indicates all types of tracing are to be done.

NO

Indicates no tracing is to be done.

JES=YES|NO

Indicates whether data and control records passed between JES2 and TCP/IP are to be traced for this line.

COMMON=YES|NO

Indicates whether TCP/IP and other services called by IAZNJTCP are to be traced.


VERBOSE=YES|NO

Indicates whether diagnostic messages are to be issued to the master console and SYSLOG.

LOADmod(jxxxxxxx) - Load Installation Exit Routine Modules

The LOADmod(jxxxxxxx) statement causes a load module of one or more installation exit routines to be loaded. JES2 will verify that the module has standard JES2 module structure. Use the subscript to specify a 1- to 8-character name of the module to be loaded. When loading the module, the system uses the RMODE and page alignment attributes assigned by the linkage editor.

Format Description for LOADmod(jxxxxxxx)



Parameter Description for LOADmod(jxxxxxxx)

STORage=PVT|CSA|LPA|PRIVATE

Specifies whether this load module is to be loaded into the user's private area (PVT), common storage (CSA), or if the module is to be found in the link pack area (LPA). See [z/OS JES2 Initialization and Tuning Guide](#) for more details. For details on how JES2 uses this statement to determine which load module (if more than one) to use, see [z/OS JES2 Installation Exits](#).


Modification: Single-member warm start.

LOGON(nnn) - Identification of JES2 to VTAM


The LOGON(nnn) statement identifies JES2 as an application program to VTAM.

Automatic logon is available to SNA RJE workstations.

Format Description for LOGON(nnn)



Selection limiting keywords



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for LOGON(nnn)

nnn

Specifies the number applications.

APPLID=avvvvvvv|JES2

Specifies the 1- to 8-character name that your installation assigned to JES2. This name is passed to VTAM, and it must match the name defined to VTAM. (See [z/OS Communications Server: SNA Resource Definition Reference](#) for more information about VTAM definition.)

Although the default name, JES2, will be supplied in the absence of this specification, it must be stressed that in the JES2 networking environment each job entry subsystem must have a unique name by which it is defined to VTAM. For NJE, this name must correspond to an application name appearing in one of the application table (APT) entries defined for the local node (OWNNODE parameter on the NJEDEF statement). Application table entries are created using information provided on the APPLID(avvvvvvv) initialization statement or, by default, using information from the NODE(xxxxxxxx) initialization statement.

Modification: \$T LOGON(n) operator command.

LOG=Yes|No

Specifies whether or not JES will monitor the VTAM interface and record all SNA events.

If you specify LOG=YES, JES2 issues a \$HASP094 message for every transmission on the LOGON APPLID. You should specify LOG=NO if your installation performs extensive networking activity.

This parameter does not have a default.

Modification: \$T LOGON(n) operator command.

Password=xxxxxxx

Specifies a 1- to 8-character security password that is presented to VTAM. (Passwords with fewer than 8 characters are padded with blanks.) This password must have been associated with the APPLID= parameter on this statement at VTAM system definition.

If you do not specify a password, none exists.

Modification: \$T LOGON(n) operator command.

RESTART= (Yes|No, *interval*)

Specifies whether this logon will be restarted if it is drained. The *interval* is the approximate time (in minutes) between attempted restarts. The valid range for *interval* is 0 to 1440. A value of 0 indicates that the default interval (from NJEDEF CONNECT=) should be used. The default RESTART value is No, and the default *interval* value is 0.

START=Yes|No

Specifies whether (Yes) or not (No) this logon will be started automatically when JES2 starts processing. The default START value is No.

TRaceio=Yes|No

Specifies whether (Yes) or not (No) JES2 will trace channel-end completions for logons. This is done with trace ID 5.


Modification: \$T LOGON(n) operator command.

MASDEF - Multi-Access Spool Definition

The MASDEF statement defines the JES2 multi-access spool configuration.

Attention: Because the SHARED= parameter on this statement defaults to CHECK (that is, your spool and checkpoint devices are shared), you **must** add this statement with SHARED=NOCHECK to your initialization data set if you are operating a single-member environment.

Format Description for MASDEF



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter description for MASDEF

AUTOEMEM=ON|OFF

Specifies whether (ON) or not (OFF) this JES2 MAS member wants to have its work restarted if this member fails. If a MAS member has specified AUTOEMEM=ON and the MVS system where the member resides fails, its jobs are warm started if another active member has specified RESTART=YES on its MASDEF statement.

Note: If you specify AUTOEMEM=ON, but no other MAS member has RESTART=YES, and the MVS system on which this member resides fails, then the active work on this member does not restart.

However, if the job is registered with the automatic restart manager, the automatic restart manager restarts jobs regardless of the settings of the AUTOEMEM= and RESTART= parameters.

Modification: \$T MASDEF operator command.

CKPTLOCK=INFORM|ACTION

CKPTLOCK=INFORM causes JES2 not to issue message \$HASP479 during a cold or warm start of JES2 if the following conditions exist:

- The checkpoint lock cannot be obtained.
- The member ID of the member that holds the lock is the same as the one being started.

Instead, JES2 issues message \$HASP459 to indicate that the member bypassed confirmation of the lock release.

If you specify CKPTLOCK=ACTION, JES2 issues the message \$HASP479 in all cases.

Modification: \$T MASDEF command during initialization only.

CYCLEMGT=MANUAL|AUTO

Specifies how access of individual members to the checkpoint data is controlled.

With CYCLEMGT=MANUAL, JES2 uses HOLD and DORMANCY parameters that are provided on the MASDEF initialization statement or \$TMASDEF command.

With CYCLEMGT=AUTO, JES2 automatically manages HOLD and DORMANCY on all active members based on the current workload in MAS.

With CYCLEMGT=AUTO, HOLD and DORMANCY are under control of JES2 and cannot be changed by using the \$TMASDEF command.

With CYCLEMGT=AUTO, it applies when CKPT is located in DASD or on a CF structure and is always available.

Modification: \$T MASDEF operator command.

DORMANCY=(mmmm,nnnn)|(100,500)

Use the first positional operand (mmmm) to specify, in hundredths of a second (0-3000), the minimum time a member of a multi-access spool configuration must wait after control is released of the checkpoint data set (that is, shared queues) before again attempting to gain control of them. This parameter is used to prevent one member of a multi-access spool configuration from monopolizing control of the checkpoint data set.

Use the second positional operand (nnnn) to specify, in hundredths of a second (100-6000), the maximum time a member of a multi-access spool configuration can refrain from attempting to gain control of the checkpoint data set.

When processors are active in JES2, this parameter has little meaning because control of the checkpoint data set is frequently requested. However, when JES2 is idle, this parameter helps ensure that JES2 periodically looks at the shared queues for eligible work that another member of the configuration may have placed there.

Note:

1. If the value specified for nnnn is too small, excessive system time could be expended in unnecessary attempts to reacquire the checkpoint data set. However, if the value specified is too large, the start of certain functions and the responses to certain display commands can be delayed.
2. See *z/OS JES2 Initialization and Tuning Guide* for a discussion of the relationship between DORMANCY= and HOLD=, and recommended configuration-dependent initial values.
3. When CYCLEMGT=AUTO, value of DORMANCY keyword takes effect when \$T MASDEF operator command is used to change from CYCLEMGT=AUTO to CYCLEMGT=MANUAL.

ESUBSYS=emergency_subsystem_name

Specify the 1 to 4 character subsystem name to be used for the emergency subsystem. If the name is not defined, its definition is added at JES2 initialization. If it is a defined name and it is in active use, message HASP430 is issued and JES2 fails to initialize.

If an emergency subsystem name is not provided, a default of HASP is used. If HASP is not defined, its definition is added at JES2 initialization. If the name is in active use, a new default of HASA is used. If HASA is in use, a new default of HASB is used. If HASB is in use, a new default of HASC is used, and so on.

HOLD=nnnnnnnn|99999999

Specifies, in hundredths of a second (0-99999999), the minimum length of time a member of a multi-access spool configuration must maintain control of the checkpoint data set after gaining control of them.

This parameter is provided to minimize the contention that could occur with the checkpoint data set in an environment in which all members of the configuration specify HOLD=0.

Note:

1. If you have more than one member in the MAS, you MUST specify a value for this parameter.
2. Setting this parameter to a high value tends to limit access of other members of the configuration to the shared queues.
3. See *z/OS JES2 Initialization and Tuning Guide* for a discussion of the relationship between DORMANCY= and HOLD=, and recommended configuration-dependent initial values.
4. When CYCLEMGT=AUTO, value of HOLD keyword takes effect when \$T MASDEF operator command is used to change from CYCLEMGT=AUTO to CYCLEMGT=MANUAL.

Performance Considerations: If you specify MODE=DUAL on CKPTDEF, also specifying HOLD=99999999 on the MASDEF statement causes performance degradation. If you must use HOLD=99999999 on MASDEF, be certain to also specify MODE=DUPLEX on CKPTDEF.

Modification: \$T MASDEF operator command.

LOCKOUT=nnnnn|1000

Specifies, in hundredths of a second, the time interval (500-15000) from the first-denied request for access to the shared queues of a member of a multi-access spool configuration to the time that the configuration assumes the member controlling the queues is down. When this situation occurs, JES2 issues either the \$HASP263 WAITING FOR ACCESS TO JES2 CHECKPOINT VOLUME or \$HASP263 WAITING FOR ACCESS TO JES2 CHECKPOINT. LOCK HELD BY MEMBER *member* message, indicating a lock-out situation, and resets the timer interval to the LOCKOUT value.

Modification: \$T MASDEF operator command.

OWNMEMB=xxxx

Specifies the member identifier of this member, where xxxx is the 1-4 character alphanumeric name to be used in place of that provided by System Management Facility (SMF). This parameter may be required to warm start JES2 on a system with a different SMF-defined system ID or to warm start JES2 on the same system that follows an IPL with different SMF specifications. The member identifier for OWNMEMB defaults to the generated system SMF ID.

Note: When naming a member, avoid 1- or 2-digit numbers such as '6' and '23'. This can cause confusion when the name is used in commands or displayed in messages. Consider the following initialization statements and series of commands:

```
MEMBER(3) NAME=6
MEMBER(6) NAME=SYSA
```

If you enter:

```
$E MEMBER(3)
```

JES2 resets the third member (NAME=6).

If you enter:

```
$E MEMBER(SYSA)
```

JES2 resets the sixth member (NAME=SYSA).

However, if you enter:

```
$E MEMBER(6)
```

it might not be obvious that JES2 resets the third member (MEMBER(3) NAME=6), not MEMBER(6) NAME=SYSA.

Therefore, if you must use 1- or 2-digit names, to reduce any possibly of confusion, pad the number on the left with 0s. The example before this becomes:

```
MEMBER(3) NAME=0006
MEMBER(6) NAME=SYSA
```

Now, \$E MEMBER(6) resets the sixth member (MEMBER(6) NAME=SYSA), and \$E MEMBER(0006) resets the third member (MEMBER(3) NAME=0006).

Modification: Single-member warm start

RESTART=Yes|No

Specifies whether (Yes) or not (No) a JES2 MAS member can make the jobs on a failed member eligible for restart.

Note:

1. If the job is registered with the automatic restart manager, the automatic restart manager restarts jobs regardless of the settings of the AUTOEMEM= and RESTART= parameters.
2. If a JES2 member has been identified as the target of an automatic reconfiguration facility takeover, specify RESTART=NO. For more information about the Processor Resource/Systems Manager (PR/SM) environment to which this applies, see [z/OS MVS Setting Up a Sysplex](#).

Modification: \$T MASDEF operator command.

SHARED=CHECK|NOCHECK

Specifies whether the DASD used in your configuration for the spool and checkpoint devices is shared (CHECK) or nonshared (NOCHECK).

Note: Specify CHECK in a multi-access spool environment and you must specify NOCHECK in a single-member environment. The following are exceptions to this rule:

- Use this parameter specifically to test your multi-access spool complex when in a poly-JES environment; shared DASD is not required.
- If the shared pack is damaged, the installation can use a nonshared pack to open one JES2 member.

Modification: \$T MASDEF operator command, cold start, or warm start.

SYNCTOL=nnn|120

Specifies, in seconds (0-300), the time interval that must elapse before one JES2 member in a multi-access spool configuration is assumed to be not operating.

Actions such as cold start, warm start, or \$E MEMBER operator commands are rejected unless the timestamps of the affected members in the shared checkpoint record are greater than the current time minus this parameter value.

Note: JES2 processing uses the SYNCTOL= keyword value to identify when members of differing sysplexes are using the same checkpoint. JES2, in this way, can identify this exceptional condition and take appropriate action. Generally, all members in a sysplex use a unique checkpoint, and any given checkpoint is not typically shared among sysplexes.

Modification: \$T MASDEF operator command.

Each MAS in a sysplex is required to use a unique XCF groupname. The groupname must be a 1- to 8-alphanumeric or special character (\$ # @) name that follows all XCF naming conventions. To avoid the names that IBM uses for its XCF groups, do not begin group names with the letters A through I or the character string SYS. Also, do not use the name UNDESIG, which is reserved for use by the system programmer in your installation.

The default is the local node name as defined on the NAME= parameter of the local. NODE(xxxxxxx) initialization statement. IBM suggests that you use the default unless it conflicts with an existing XCF group name.

If you set the XCFGRPNM to the SYSPLEX value, ensure that no other functions are also registering to that same name or else you risk receiving \$HASP792 at JES2 startup stating that some members were found active but are not part of the SYSPLEX.

Modification: All-member warm start.

ENFScope=JESplex/SYSplex

ENFScope=SYSplex/JESplex specifies whether ENF signals 58, 70, and 78 should be broadcast to all systems in the SYSplex (ENFScope=SYSplex) or just to all systems in the JESplex (ENFScope=JESplex). JESplex refers to systems in the Multi-Access Spool (MAS). The default is ENFScope=SYSplex.

Note: This setting is a MAS-wide specification. Setting a value on one member sets it on all members.


Modification: \$T MASDEF operator command or cold start.

MEMBer(nn) - Define Members of a Multi-Access Spool Configuration

The MEMBER statement defines each member in a multi-access spool (MAS) configuration.

See *z/OS JES2 Initialization and Tuning Guide* for additional information about using the MEMBER statement when initializing the multi-access spool configuration.


Format Description for MEMBER



Modification keywords

Diagram illustrating a variable declaration: `.NAME=xxxx`

Selection limiting keywords



Notes:

- ¹ Omit the comma between initialization statement and first keyword

Parameter Description for MEMBer

member

Specifies the member name to be defined in the multi-access spool (MAS) environment.

nn

Specifies a number from 1 to 32.

NAME=xxxx

Specifies the 1- to 4-character member name. Specify only the following characters: A-Z, 0-9, \$, #, and @. Each member must have a unique name.

Note:

1. When naming a member, avoid 1- or 2-digit numbers such as '6' and '23'. This can cause confusion when the name is used in commands or displayed in messages. JES2 first interprets the *n* in \$E MEMBer(*n*) as the member name (NAME= on this initialization statement). Only, if there is no matching NAME= specification, will JES2 interpret the *n* to be the subscript (MEMBer(subscript)) of this initialization statement. Consider the following initialization statements and series of commands:

```
MEMBer(3) NAME=6
MEMBer(6) NAME=SYSA
```

If you enter:

```
$E MEMBer(3)
```

JES2 resets the third member (NAME=6).

If you enter:

```
$E MEMBer(SYSA)
```

JES2 resets the sixth member (NAME=SYSA).

However, if you enter:

```
$E MEMBer(6)
```

it might not be obvious that JES2 resets the third member (MEMBer(3) NAME=6), not MEMBer(6) NAME=SYSA.

Therefore, if you must use 1- or 2-digit names, to reduce any possibly of confusion, pad the number on the left with 0s. The above example becomes:

```
MEMBer(3) NAME=0006
MEMBer(6) NAME=SYSA
```

Now \$E MEMBer(6) resets the sixth member (MEMBer(6) NAME=SYSA), and \$E MEMBer(0006) resets the third member (MEMBer(3) NAME=0006).

2. Do not set the first three characters of a member name to ANY, ALL, or IND. These specifications have other meanings reserved for use on the /*JOBPARM control statement.

3. To avoid confusion, you may not want to use '\$' in the member name. The member name is part of the XCF group name specified as *nodename\$membername*.

Modification: Single-member warm start to define the name of the starting member. Hot start to define the name of any member that is not active.

NAME - Naming the Module to Change Through the JES2 Patching Facility

The NAME initialization statement is one of several statements used by the JES2 patching facility. For the other statements, see [“REP - Replacing Code Through the JES2 Patching Facility”](#) on page 379 and [“VERify - Verifying Code Through the JES2 Patching Facility”](#) on page 432. When specifying replacement data, this statement is optional unless JES2 issues a \$HASP467 message indicating that data cannot be replaced at the storage location specified. If JES2 issues a \$HASP467 diagnostic message, you must use the NAME statement before specifying the VER and REP statements.

The JES2 patching facility allows you to specify replacement data (patches) for the following:


- Any module in JES2 (HASJES20 or an installation exit load module)
- Any absolute storage address from the address space where JES2 is loaded.
- On a hot start, any address in a data space created by JES2 (that is, owned by JES2AUX)
- On any warm start, any address in the JES2 checkpoint data set.

The JES2 patching facility applies temporary patches to the in-storage copy of JES2 modules. You place patching facility statements in the JES2 initialization stream; these patches are applied when you initialize JES2. Because some of the initialization code has already been executed before the patch facility initialization statements are processed, patches made to those portions of the code are ineffective; those portions of code **do not** execute again until you restart JES2. Most patches are applied immediately as the statements are processed. However, checkpoint updates are deferred until the checkpoint record is read. Non-checkpoint patches are not saved across a warm start. In addition, you should be aware that the JES2 patching facility does **not** support:

- Patching a module or data area residing in read-only storage. For example, you cannot use the facility to modify modules in PLPA or PSA.
- Patching a HASPFSSM load module that has been loaded into a functional subsystem address space. Use AMASPZAP (the service aid program that modifies both instructions and data) to patch the HASPFSSM load module.
- Altering the JES2 dump formatting exit modules (HASMxxxx).
- Using a patch across a restart of JES2. Because these patches are valid only until a load module is reloaded, they must be reapplied every time JES2 is started.

The JES2 patching facility statements in the JES2 initialization data set can be specified in either the JES2 patching format or in the AMASPZAP format. All patches in the JES2 patching form should precede any AMASPZAP patches. If you supply the NAME statement or first format type of the AMASPZAP patch, JES2 resets prior verification errors. For more information on AMASPZAP patches, see "SPZAP" in [z/OS MVS Diagnosis: Tools and Service Aids](#).

Format Description for NAME



Notes:

¹ Omit the comma between initialization statement and first keyword or variable

Parameter Description for NAME

NAME

Specifies the module as a keyword that must be coded.

member

Specifies the member name on the AMASPZAP control statement. JES2 processing ignores this field on an AMASPZAP patch statement, but you must specify it to provide compatibility with the AMASPZAP control statements.

csect|dspname|CKPTname|*

Specifies the control section (or control block), dataspace name, or checkpoint CTENT in which the data to be modified or verified resides.

If an asterisk (*) is coded, JES2 uses the CSECT in effect on a previous JES2 patch statement. [Table 99 on page 433](#) contain a list of the possible patch names which can be coded and area to which these names refer. If the CSECT is listed in [Table 99 on page 433](#), you can specify the last four characters of the CSECT name.

If an installation exit CSECT is referenced, the JES2 patching facility requires the entire module name, except for the reserved names HASPXJ00-HASPXJ31. If you do not link it the installation exit routines HASPXJ00 - HASPXJ31 with the HASJES20 load module, you must specify the full 8-character CSECT name.

Furthermore, do not name an exit with the same three or four characters (xxxx) as used for a JES2 module. For example, an installation-defined exit named CKPT or TABS (that is, HASPCKPT or HASPTABS, with the HASP characters removed) would modify the IBM-supplied HASPCKPT or HASPTABS module.

While this field is optional on the AMASPZAP control statement, it is required on the AMASPZAP patch statement. For further information on AMASPZAP, see [“REP - Replacing Code Through the JES2 Patching Facility” on page 379](#) and [“VERify - Verifying Code Through the JES2 Patching Facility” on page 432](#)


NETACCT - Define Network/JES2 Account Number Correspondence

The NETACCT statement specifies the correspondence between a JES2 (local) account number (or range of account numbers) and the network account number (or range of account numbers). In its simplest form, the statement defines a direct correspondence between a single JES2 account number and a single network account number. A collection of NETACCT statements is used to define lookup tables for conversion between JES2 account numbers and corresponding network account numbers.


Each NETACCT statement can cause an entry to be made in two lookup tables: a JES2-to-network conversion lookup table and a network-to-JES2 lookup table. The JES2-to-network table is used by JES2 input service to obtain network account numbers for jobs which specify JES2 account numbers but do not specify a network account number through a /*NETACCT control statement. The network-to-JES2 table is used by the JES2 NJE job receiver and the JES2 NJE SYSOUT receiver to obtain local JES2 account numbers for jobs and SYSOUT data received from other nodes.

When specifying multiple NETACCT initialization statements, ensure that the ranges specified on each statement do not overlap. For example, if the first NETACCT statement specifies a range from A11 to B33 and the next NETACCT initialization statement specifies numbers from A27 to B0, JES2 does not provide a JES2 account number for jobs with network account numbers from A11 to A26 and B1 to B33. The conversion of JES2 account numbers to network account numbers is unaffected. For more information on specifying JES2 and network account numbers, see [z/OS JES2 Initialization and Tuning Guide](#).


Format Description for NETACCT



Modification keywords



Selection limiting keywords



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for NETACCT

JACCT=xxxx

Specifies the 1- to 4-character name that defines a job account number. If this parameter is used in conjunction with the JTHRU= parameter, it defines the lower limit of the defined range.

This parameter must be specified.

Modification: Single-system warm start.

JTHRU=xxxx

Specifies the 1- to 4-character upper limit of the range of job account numbers.

If the JTHRU= parameter is specified on this statement, it causes a range of JES2 account numbers to correspond to a single network account number in the JES2-to-network lookup table. Also, only two entries are created in the appropriate lookup tables (one for either limit of the range), regardless of range size. Ranges of this type may be used to cause the JES2 account numbers for an entire department, for example, to be converted to a single network account number for charging outside the local node.

This parameter defaults to the name specified on the JACCT= parameter.

This parameter is ignored if TYPE=NET.

Modification: Single-system warm start.

NACCT=xxxxxxxx

Specifies the 1- to 8-character name that defines a network account number. If this parameter is used in conjunction with the NTHRU= parameter, it defines the lower limit of the range specified.

This parameter must be specified.

Modification: Single-system warm start.

NTHRU=xxxxxxxx

Specifies the 1- to 8-character upper limit of the range of network account numbers.

If the NTHRU= parameter is specified on this statement, it causes a range of network account numbers to correspond to a single JES2 account number in the network-to-JES2 lookup table. Also, only two entries are created in the appropriate lookup tables (one for either limit of the range), regardless of range size. Ranges of this type may be used to cause all of the network account numbers in use at some distant location to be converted to a single JES2 account number for local charging.

This parameter defaults to the name specified on the NACCT= parameter.

This parameter is ignored if TYPE=JES2.

Modification: Single-system warm start.

TYPE=JES2|NET|BOTH

Specifies the type of account number defined by this statement.

JES2

This statement defines a JES2 account number.

NET

This statement defines a network account number.

BOTH

This statement defines both a JES2 and network account number. Duplicate entries will be made in both lookup tables.

If the NETACCT statement specifies two ranges (that is, both JTHRU= and NTHRU= are specified) then the JES2 account range will be converted to the low end of the network account number range. Also, the network account number range will be converted to the low end of the JES2 account number range. Because of these conversions, it may be desirable to define ranges of this type with two separate NETACCT statements; one statement specifying the JES2 range (TYPE=JES2) and the other specifying the network range (TYPE=NET).

If the TYPE= parameter is not specified on the NETACCT statement or is specified as TYPE=BOTH, then duplicate entries will be made in both lookup tables. For example, assume the following specification:

```
NETACCT JACCT=1234,NACCT=NET001A
```

In this case, if a job enters the local node with JES2 account number “1234” and does not specify a network account number through a /*NETACCT statement, it will be assigned network account number “NET001A” by JES2 input service. Conversely, if a job (or SYSOUT) is received from another node which specifies network account number “NET001A” in its NJE job header, it will be assigned the local JES2 account number “1234”.

The entries may also be assigned on two different NETACCT statements as follows:

```
NETACCT  JACCT=1234,NACCT=NET001A,TYPE=JES2
NETACCT  JACCT=9999,NACCT=NET001A,TYPE=NET
```

In this example, a job entering the local node and specifying JES2 account number “1234” will be assigned network account number “NET001A” as in the previous example, but a job received from the network specifying network account number “NET001A” will be assigned JES2 account number “9999” for local processing. For this example, if a job enters the local node specifying JES2 account number “9999”, it will not be assigned network account number “NET001A” because there is no entry for JES2 account number “9999” in the JES2-to-network lookup table. Therefore, no network account number will be assigned, rather it will remain as binary zeros.


This parameter has no default.

Modification: Single-system warm start.


NETSERV(nnn) - Define NJE over TCP/IP server address space

The NETSERV statement defines a network server that is to be used for NJE TCP/IP communication.


Format Description for NETSERV(nnn)



Modification keywords



Selection limiting keywords



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for NETSERV(1-nnn)

RESTART= (Yes|No,interval)

Specifies whether this netsrv is restarted if it is drained. The *interval* is the time (in minutes) between attempted restarts. The valid range for *interval* is 0 to 1440. A value of 0 indicates that the default interval (from NJEDEF CONNECT=) is used. The default RESTART value is No, and the default *interval* value is 0.

SOCKET=xxxxxxx

Specifies the name of a local socket upon which the NETSRV should listen.

Modification: \$TNETSRV command.

START=Yes|No

Specifies whether (Yes) or not (No) this server should be started automatically. The default START value is No.

TTraceio=Yes|No|JES=YES/NO|COMMON=YES/NO|VERBOSE=YES/NO

Specifies whether (YES) or not (NO) tracing is to be active, and if YES, which types of traces are to be activated for the server.

YES

Indicates all types of tracing are to be done.

NO

Indicates no tracing is to be done.

JES=YES|NO

Indicates whether data and control records passed between JES and TCP/IP are to be traced for this server.

COMMON=YES|NO

Indicates whether TCP/IP and other services called by IAZNJTCP are to be traced.

VERBOSE=YES|NO

Indicates whether diagnostic messages are to be issued to the master console and SYSLOG.

Modification: \$T NETSRV command.

STACK=xxxxxxx

Specifies the name of a TCP/IP stack to be used by this server when the Common INET (CINET) configuration is being used. If not specified, all stacks on the local machine is used. When only an INET configuration is being used, a specification of a stack name is ignored.

Modification: \$T NETSRV command.

SECURE=OPTIONAL|REQUIRED|USE_SOCKET

Indicates whether the NETSERV should accept only connection requests with a secure protocol in use such as TLS/SSL. When SECURE=REQUIRED is specified, the NETSERV rejects all connection requests that do not specify a secure protocol is to be used for the connection. When SECURE=OPTIONAL is specified, the NETSERV allows connections with or without a secure protocol in use.


The default, USE_SOCKET, inherits the SECURE setting from the SOCKET statement associated with the NETSERV. If the SOCKET says SECURE=YES, then processing is the same as specifying SECURE=REQUIRED on the NETSERV.

To specify that the NETSERV should use NJENET-SSL (2252) as the PORT it is listening on and the default port for outgoing connections, but not require all connections to use TLS/SSL, you must specify SOCKET SECURE=YES on the socket that is associated with the NETSERV and set the NETSERV to SECURE=OPTIONAL.

NJEDF - Network Job Entry Definition

The NJEDF statement defines the network job entry characteristics of this JES2 node.

Format Description for NJEDEF



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for NJEDF

CONNECT=(YES|NO,*interval*)

Specifies whether NJE connections for APPL, LINE, or SOCKET statements that specify or defer to CONNECT=YES should automatically be initiated or restarted. The *interval* is the time (in minutes) between attempted connections. The valid range for *interval* is 1-1440; the default value is 10. The default CONNECT value is YES.

DELAY=nnn|120

Specifies the maximum length of time, in approximate seconds (10-999), that a message or command is delayed in any stage of transmission between MAS members in a node before the member is to assume that possible lockout situations have occurred. The member discards messages or restart communication lines in attempts to clear the congestion and remove the lockout situation.

Modification: \$T NJEDF operator command.

HDRBUF=(LIMIT=nnnn,WARN=nnn)

Specifies the amount of storage (cell buffers) used by NJE headers and trailers at a particular installation.

LIMIT=nnnn

Specifies the number of NJE header and trailer cell buffers (10-9999) allocated by this installation for both jobs and SYSOUT transmitted from another node.

If you do not specify a value for the LIMIT= parameter, JES2 processing provides a default based on the following algorithm:

$$(\text{number of NJE lines}) \times 2 + ((\text{number of offload devices}) + 2)$$

JES2 determines the number of NJE lines at an installation through the LINENUM= parameter on this initialization statement and the number of lines defined on a packet of predefined transmitters and receivers based on the L(nnnn).ST(m) initialization statement, the L(nnnn).JT(n) initialization statement, or the L(nnnn).ST(n) initialization statement. JES2 determines the number of offload devices defined through the number of OFFLOAD(n) initialization statements defined. For more information about how to adjust this parameter for particular installation needs, see [z/OS JES2 Initialization and Tuning Guide](#).

If the result of the algorithm is less than 10, JES2 allocates 10 cells.

Note: Use this parameter to increase the limit for the JNUM resource that is reported on the HASP050 message.

WARN=nnn|80

Specifies the percentage (0-100) of NJE header and trailer cells that have been used by this JES2 member when it issues the \$HASP050 warning message.

If you specify WARN=0, JES2 does not issue the \$HASP050 message.

Modification: \$T NJEDF operator command.

JRNUM=n|1

Specifies the number (0-7) of network job receivers to be associated with each NJE line. The value of n is an integer that specifies the maximum number of input job streams allowed to be concurrently active on a given line. This specification should match the value of JTNUM= on other members with which this member is to communicate directly.

Modification: Hot start.

JTNUM=n|1

Specifies the number (0-7) of network job transmitters to be associated with each NJE line. The value of n is an integer that specifies the maximum number of output job streams allowed to be concurrently active on a given line. This value should remain unchanged unless it is known that a particular user has some jobs with extremely large amounts of input to be transmitted and other short jobs that must be transmitted concurrently. If there are not enough receivers on the receiving node to

receive jobs over the line, excess transmitters drain automatically. The sum of the values JTNUM= and STNUM= must not exceed 8.

Modification: Hot start.

LINEUM=nnnnn|0

Specifies the number of lines (0-65535), including CTC adapters, to be used by this JES2 member for NJE communications. The value of nnnn is an integer between 0 and the number of lines defined by unique LINEnnnn initialization statements.

This value does not include the number of NJE lines that have transmitters and receivers specifically defined by the JRNUM=, JTNUM=, SRNUM=, or STNUM= parameters of the LINE statements, or by the L(nnnn).ST(m) statement, the L(nnnn).JT(n) initialization statement, or the L(nnnn).ST(n) initialization statement.

Modification: Hot start.

MAILMSG=Yes|No

Specifies whether (YES) or not (NO) JES2 issues the \$HASP549 mail notification message automatically to notify a user ID that a transmitted file has arrived from another node or a spool reload procedure.

If Exit 40 sets a response value of X040FRNT or X040RRNT, this parameter is ignored. For more information on Exit 40, see *z/OS JES2 Installation Exits*.

If you specify MAILMSG=Yes, and the target user ID is not logged on, the \$HASP549 message is discarded. However, JES2 adds the \$HASP549 message to the shared SYS1.BROADCAST or userid.BROADCAST data set when the target user ID is logged off.

Modification: \$T NJEDEF operator command.

MAXHOP=nnnnn|0

Specifies the maximum number of nodes (0-65535) through which a job can travel before it is placed in hold. To determine the proper value for your installation, you should specify a value that is twice the longest path in your network plus 2. Specifying MAXHOP=0 or MAXHOP=65535 causes JES2 to assign no limit.

Modification: \$T NJEDEF operator command.

NODENUM=nnnnn|1

Specifies the maximum number (1-32767) of nodes in the NJE network to which this member belongs or a value greater than or equal to the highest numbered node in your system. For example, if your system contains three nodes numbered 1, 2, and 3, set NODENUM=3 (or greater). However, if your system contains three nodes numbered 1, 10, and 20, set NODENUM=20 (or greater).

Modification: The number of nodes can be increased on any start other than a hot start, or through operation command. Cold start is required to decrease the value.

OWNNODE=nnnnn|1

Specifies the number (1-32767) of this node, where nnnn is an integer between 1 and the value specified in the NODENUM= parameter. In an NJE network environment, node names must be unique to be able to connect to other nodes. Therefore, the NJEDEF OWNNODE value must be coordinated with other node names (in network) and point to a node number that has a unique node name. Each JES2 member of the same multi-access spool configuration must have the same value for OWNNODE=.

Modification: Cold start.

PATH=n|1

Specifies the maximum number (1-8) of paths from the local subsystem to a given non-adjacent node that must be maintained simultaneously. The integer value should be set to the maximum number of connection devices the local subsystem has for sending work to a given non-adjacent node. If, at any given time, a node uses only one path to transmit data to another node, the value should be left at 1.

Modification: Single member warm start.

PRECHECK=YES|NO

Indicates whether NJE jobs that are marked dubious (due to the VFYPATH or VERIFY_SUBNET specification) must pass additional verification processing before being allowed to run on the local node. The pre-check ensures that the job can pass verification without any submitter information being passed to the security product. Specifying PRECHECK=YES can result in security failures for jobs from nodes indicated as trusted in RACF (if the job is marked as dubious). These same jobs may pass verification when PRECHECK=NO is specified. This setting has no effect on jobs that are not marked dubious.

RESTMAX=nnnnnnn|79992000

Specifies the maximum tolerable resistance (0 to 79992000) of a connection. If the resistance of a path is greater than the value specified in RESTMAX=, the path is ignored.

If the path to a given node passes through an undesirably large number of members, the value of RESTMAX= may be set so that JES2 ignores the paths which are too long for practical use. Low values would be used when a member should wait for better connections before attempting to communicate with nodes connected through inefficient paths. (For more information, see [z/OS JES2 Initialization and Tuning Guide](#).)

When RESTMAX=0, the direct path to any adjacent node is considered usable regardless of the resistance to that node. Nodes beyond the adjacent node are only considered reachable if the total resistance to them is zero or they are in the same subnet as an adjacent node. RESTMAX=0 can be used to ensure that data is only sent directly to an adjacent node and never to an intermediate node for forwarding to the destination node.

Note: This parameter applies to both adjacent and non-adjacent nodes.

Modification: \$T NJEDEF operator command.

RESTNODE=nnnn|100

Specifies the resistance (1-2000) of the node to the flow of jobs through the network. High values of RESTNODE= tends to make other JES2 members choose other paths rather than come through this member's node (see [z/OS JES2 Initialization and Tuning Guide](#) for more information).

Modification: \$T NJEDEF operator command.

RESTTOL=nnnn|0

Specifies the maximum difference in resistance (0-8000) allowed between the best possible path and an acceptable alternate path. This value has no meaning unless the value specified in the PATH= parameter is greater than 1.

If the value of RESTTOL= is greater than or equal to the minimum resistance between any two nodes within the network, jobs and messages may be transmitted throughout the network in an erratic fashion. (For more information, see [z/OS JES2 Initialization and Tuning Guide](#).)

Modification: \$T NJEDEF operator command.

SRNUM=n|1

Specifies the number (0-7) of network SYSOUT receivers to be associated with each NJE line. The value of n is an integer which specifies the maximum number of SYSOUT receiver streams allowed to be concurrently active on a given line. This specification should match the value of STNUM on the other members with which this member is to communicate directly. The sum of the values JRNUM= and SRNUM= must not exceed 8.

Modification: Hot start.

STNUM=n|1

Specifies the number (0-7) of network SYSOUT transmitters that are associated with each NJE line. The value of n is an integer that specifies the maximum number of SYSOUT transmitter streams allowed to be concurrently active on a given line. This value should remain unchanged unless it is known that a particular user has some extremely large data sets to be transmitted, and other short data sets that must be transmitted concurrently. If there are not enough receivers on the receiving node to receive SYSOUT data over the line, excess transmitters drain automatically.

Modification: Hot start.

TIMEtol=nnnn|1440

Specifies the approximate time difference (0 - 1500 minutes) allowed between the TOD clock of this node and any adjacent node. For example, if you specify TIMETOL=60 and an adjacent node attempts a signon to this node with a clock that differs from this clock by 60 minutes or less, the signon is successful. If the adjacent node's clock differs from this clock by significantly more than 60 minutes, the signon fails.

Supply a TIMEtol= value (or accept the default value) so that JES2 can determine whether to accept status information about any node in the network or permit a signon.

During JES2 processing, if a record is received with a future time stamp, but the time does not differ from the TOD clock value by more than the TIMETOL=value, JES2 accepts the record. If the time stamp is in the future by an amount that is significantly greater than the TIMETOL= value, JES2 rejects the record. For network topology records, rejection results in the record being ignored (with error message \$HASP500). For network sign on records, the signon to the adjacent node fails.

Modification: \$T NJEDEF operator command.

VERIFY_SUBNET=YES|NO

Specifies whether subnet path verification is done for jobs and commands arriving by way of NJE. Verification ensures that jobs and commands that claim to originate from a node within the local subnet (subnet that the local node is in) and indicate to run on a node in the local subnet arrive from an adjacent node that is also within the local subnet. Jobs that do not match this criteria are marked dubious and are subject to a validation precheck (based on the NJEDEF PRECHECK setting). Commands that do not match this criteria are rejected. This setting has no effect if the local node is not within a subnet (NODE(xx) SUBNET= is blank for the local node) and for jobs and commands that indicate they are from a node that is not in the local subnet.

NODE(xxxxxxxx) - Define a Network Node to JES2


The NODE(xxxxxxxx) statement defines each node or a range of nodes. The subscript (nnnn) can specify:

- A specific node with a numeric identifier (1-32767), as specified by the NODENUM= parameter on the NJEDEF statement), for example, NODE(105).
- A range of nodes with a generic numeric identifier in the form NODE(x-*), for example, NODE(105-*).
- A specific node with a symbolic identifier in the form xxxxxxxx, for example, NODE(POKIPSY1). This must be related to a NAME= parameter on a previous NODE(xxxxxxxx) statement.
- A range of nodes with a generic symbolic identifier in the form jx*, for example, NODE(POK*).
- All nodes in the form NODE(*). This defines all nodes from 1 to the NODENUM= specification on the NJEDEF initialization statement. Using the form NODE(*) causes JES2 to scan for 32767 nodes, regardless of the number previously defined. Using this option does not create definitions of additional nodes (that is, above the NODENUM= specification on the NJEDEF initialization statement), but can significantly increase the processing time that JES2 takes to process this initialization statement.


Note:


1. If the node being defined is the same as that specified by the OWNNODE= parameter on the NJEDEF statement (the NODE(xxxxxxxx) statement is for the node that is being initialized, not for another node), the only useful specifications are the NAME= and PASSWORD= parameters. When one member signs on to another, the name and password(s) are used in the signon sequence such that the other member can verify the acceptability of the member signing on.
2. Before defining a node name that starts with a numeric character, ensure that all nodes in your network support node names that start with numeric characters, that is, the nodes are at JES2 SP5.1 or higher.

Format Description for NODE(xxxxxxxx)





Modification keywords





Selection limiting keywords





Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for NODE(xxxxxxxx)

AUTH=

Specifies the level of command authority for this node in relation to another node.

Note: This parameter has no effect when the associated resource class and profile in RACF 1.9 or higher are active. For more information about JES2 security, see [z/OS JES2 Initialization and Tuning Guide](#).

NET=

Specifies the node's network authority.

Yes

Specifies that the node has the command authority of locally attached consoles.

No

Specifies that this node can only enter commands that affect devices (assuming DEVICE=Yes) and jobs (assuming JOBS=Yes). If all AUTH subparameters are No, the node being defined can enter only display commands to this member (the defining node).

Device=

Specifies this node's authority over devices on this member.

Yes

Specifies that the node has command authority to affect devices on this member.

No

Specifies that the node cannot enter commands that affect devices on this member.

Job=

Specifies this node's authority over jobs on this member.

Yes

Specifies that the node can enter commands that affect jobs.

No

Specifies that the node cannot enter commands that affect jobs on this member.

System=

Specifies this node's authority over all members at the node being defined. If NET=No, this parameter has no effect.

Yes

Specifies that the node can enter commands that affect system functions on these members.

No

Specifies that the node cannot enter commands that affect system functions.

Modification: \$T NODE(xxxxxxxx) operator command.

COMPACT= nn|0

Specifies the number (nn) of the compaction table to be used for outbound compaction in communicating with this node. The compaction table number must be in the range of 0 to 99, where 0 denotes no compaction.

The value specified here is used as a default if no value for COMPACT is specified on the APPL(jxxxxxx) initialization statement for an SNA NJE networking node.

This parameter defaults to 0, indicating no compaction.

Modification: \$T NODE(xxxxxxxx) operator command.

CONNECT= (YES|NO, interval)

Specifies whether NJE connections, which specify CONNECT=DEFAULT on the APPL, LINE, or SOCKET statements associated with this node, are automatically attempted. The *interval* is the approximate time (in minutes) between attempted connections. The valid range for *interval* is 0-1440; the default value is 0. A value of 0 indicates that the default interval (from NJEDEF CONNECT=) is used. The default CONNECT value is NO.

Note: This parameter starts all connections that point to the node, through LINE NODE=, APPL NODE=, or SOCKET NODE=, plus the line that NODE(n) LINE= points to if any.

DIRECT=YES|NO

Specifies whether the node must be directly attached:

YES

Indicates that only direct connections to this node is considered when computing path information.

NO

Indicates that the node can be reached either through direct or indirect paths. For example, store-and forward.

DIRECT has MAS scope. The values can be changed on any start other than a hot start, and affects all MAS members regardless of whether the node is active or inactive.

ENDNODE=Yes|No

Specifies whether (Yes) or not (No) the node is to be eligible for use in store-and-forward operations. This parameter has MAS scope.

Yes

Local node: If you are defining your node (the local node) and you do not want the node to be eligible for use in store-and-forward operations, code ENDNODE=Yes. This ensures that path manager connect records are not sent from your node to adjacent nodes.

Where possible, IBM suggests that other nodes also specify ENDNODE=Yes on their initialization statements for your node. If all nodes in the network define your node as an end node, the possibility of your node being used for store-and-forward operations is reduced.

Non-local node: If you are defining a remote node and the installation personnel at that node have defined the node as an end node, code ENDNODE=Yes.

No

Local node: If you are defining your node (the local node) and the node is to be eligible for use in store-and-forward operations, code ENDNODE=No or omit the parameter.

If you specify ENDNODE=No for this node, IBM suggests that other nodes specify ENDNODE=No on their initialization statements for your node.



Attention: If your node provides the only gateway into a subnet, IBM suggests that you define your node as eligible for store-and-forward operations. To do otherwise prevents other nodes from communicating with the subnet.

Non-Local node: If you are defining a remote node and the installation personnel at that node have defined the node as eligible for store-and-forward operations, code ENDNODE=NO or omit the parameter.

Modification: To modify the ENDNODE= specification for the local node, you must perform a hot start. To modify the ENDNODE= specification for other nodes, use the \$T NODE(xxxxxxxx) operator command. The values can be changed on any start other than a hot start, and affects all MAS members regardless of whether the node is active or inactive.

HOLD=JOBS|NONE

HOLD=JOBS specifies that the node, as specified as OWNNODE on the NJEDEF statement holds jobs that are received from the specified node(s). HOLD=NONE specifies received jobs are not held.

Modification: \$T NODE(xxxxxxxx) operator command.

JES3_LOCAL_CHK= or LOCAL_CHK= Yes|No

Specifies whether (Yes) or not (No) batch jobs that contain the JES3 /*ROUTE XEQ with a destination of the node defined by this statement, should have the first JOB card verified on the submitting node (Yes) or not (No). This statement, combined with PENCRIPT=, function in the same way as the JES3 PWCNTL= keyword on the NJERMT statement. This parameter has MAS scope. The following table list the JES2 settings to use to match the JES3 PWCNTL specifications:

PWCNTL= specification	JES3_LOCAL_CHK=	PENCRYPT=
LOCALCHK	YES	n/a
SENDCLR	NO	NO
SENDENC	NO	YES

Modification: \$T NODE(xxxxxxxx) operator command. The values can be changed on any start other than a hot start, and affects all MAS members regardless of whether the node is active or in-active.

LINE=nnnn

Specifies a line to be dedicated to the NJE session associated with this node. Range is 0-65535.

Note: If there are multiple SNA paths to this node, use the LINE= parameter on the APPL initialization statement; if there are multiple TCP/IP paths to this node, use the LINE=parameter on the SOCKET initialization statement.

Default: 0 (No line is dedicated.)

Modification: \$T NODE(xxxxxxxx) operator command, if the node is not active.

LOGMODE=avvvvvvv

Specifies the logon mode table entry name for this application. This name determines which entry in the VTAM application logon mode table is to be used to provide a set of session parameters for the application program if the program participates as the secondary end of a session. This parameter is valid only for NJE applications. The name specified should follow the VTAM naming conventions for a logon mode table entry name. See [z/OS Communications Server: SNA Programming](#) for more information about the logon mode table.

The default values of the name are blanks, and VTAM defaults are used for the session parameters.

Modification: \$T NODE(xxxxxxxx) operator command, if the node is not active.

LOGON=nn

Specifies the number of the logon DCT to be used in communication with this node.

NAME=xxxxxxxx

Specifies the 1- to 8-character name that symbolically defines the node. A DESTID statement defining this name is not required.

Restrictions:If the XCFGRPNM parameter is not coded on the MASDEF statement, the node name should follow the XCF naming conventions. To avoid using the names IBM uses for its XCF groups, do not begin names with the letters A through I or the character string SYS. Also, do not use the name UNDESIG, which is reserved for use by the system programmer in your installation.

Note:

1. When using the spool offload facility, be certain that the node name of the offloaded member is known to the reloading member. If these names do not match, unpredictable routing of jobs and SYSOUT can occur on the reloading member. Any unresolved routing results in SYSOUT or jobs executing and printing locally.
2. If a non-numeric subscript is specified for NODE, that is NODE(xxxxxxxx) or NODE(xx*), the subscript must match the specification on this parameter.
3. You should not use RMTnnnn, RMnnnn and Rnnnn as symbolic names.
4. Before defining a node name that starts with a numeric character, ensure that all nodes in your network support node names that start with numeric values.
5. When naming a node, avoid 1- to 4-digit number such as '3' and '234'. This can cause confusion when the name is used in commands or displayed in messages. Consider the following initialization statements and series of commands:

```
NODE(3)    NAME=246
NODE(246)  NAME=POKIPSY
```

If you enter:

```
$T NODE(3)
```

JES2 modifies the third node (NAME=246).

If you enter:

```
$T NODE(POKIPSY)
```

JES2 modifies the 246th node (NAME=POKIPSY).

However, if you enter:

```
$T NODE(246)
```

it might not be obvious that JES2 modifies the third node (NODE(3) NAME=246), not NODE(246) NAME=POKIPSY.

Therefore, if you must use 1- to 4-digit names, to reduce any possibly of confusion, pad the number on the left with 0s. The above example becomes:

```
NODE(3)    NAME=00000246
NODE(246)  NAME=POKIPSY
```

Now \$T NODE(246) modifies the 246th node (NODE(246) NAME=POKIPSY), and \$T NODE(00000246) modifies the third node (NODE(3) NAME=00000246).

This parameter has MAS scope.

The default value of this parameter is Nnnnn where nnnn is the node number.

Modification: \$T NODE(nnnn) operator command. If you modify this parameter value and then restart JES2 with a hot start, the parameter value in effect before termination is used. This specification cannot be changed if the NODE(xxxxxxxx) or NODE(xx*) form of the NODE statement is to be used. The values can be changed on any start other than a hot start, and affect all MAS members regardless of whether the node is active or inactive.

NETSRV=nnn

Specifies the device number of the NETSRV that is to be used to establish a TCP/IP NJE connection to this node.

Default 0 (no NETSRV is to be dedicated).

Modification: Operator command.

Password=([SEND=word1,]VERify=word2) | word

Specifies passwords for verification each time one node signs on to another. There are two ways of specifying the parameter:

- Password = ([SEND=word1,]VERify=word2) allows you to specify unique passwords to be used between nodes that communicate with each other in the network. This method provides enhanced security for the transmission of information between nodes, and is the preferable way of specifying Password=.
- Password=word allows a node to send a common password to all nodes with which it might communicate. Although it is recommended that you define all nodes using Password=(SEND=word1,VERify=word2), the Password=word method provides compatibility with previous releases of JES2.

Detailed descriptions for both methods follow.

Password=([SEND=word1,]VERify=word2)

Use Password=(SEND=word1,VERify=word2) to specify unique passwords between nodes in the network.

SEND=word1

Specifies a unique 1- to 8-character password that is sent to the node by OWNNODE when it is signing on to the node, to verify that OWNNODE is the correct node.

VERify=word2

Specifies the 1- to 8-character password that OWNNODE expects back from the node.

Password=word

Specifies a 1- to 8-character password that is to be used when the node is signing on to any other node.

Note:

1. If all nodes in your network use the Password=(SEND=word1,VERify=word2) method of password verification, it is unnecessary to include this Password= parameter on the NODE(xxxxxxxx) initialization statement for OWNNODE in this initialization stream. However, if some nodes use the Password=(SEND=word1,VERify=word2) specification and others use the Password=word specification, you must include a PASSWORD=(VERify=word2) specification for the OWNNODE.
2. Using Password=word is similar to specifying Password=(VERify=word2) for OWNNODE. The result is that OWNNODE sends the same password to all nodes to which it may sign on.
3. If both Password specifications are omitted, no password verification of the node is performed unless the operator sets a password through the JES2 \$T N command.
4. To prevent disclosing the passwords, protect the data set containing the initialization statements. If RACF 1.9 or higher is used, protection can be provided by specifying UACC=NONE for the data set.
5. Be certain to record the passwords in effect because no facility exists to display the current value.

This parameter has no default.

Modification: \$T NODE(xxxxxxxx) operator command.

PATHMGR=Yes | No

Specifies whether (Yes) or not (No) connection records should be sent to the directly adjacent node defined by this statement. You must specify PATHMGR=No when connecting to adjacent non-JES2 nodes. A CONNECT statement is not necessary for connecting to adjacent non-JES2 nodes. This parameter has MAS scope.

Modification: \$T NODE(xxxxxxxx) operator command, if the node is not active. The values can be changed on any start other than a hot start, and affects all MAS members regardless of whether the node is active or inactive.

PENCRYPT=Yes|No

Specifies whether (Yes) or not (No) this node supports password encryption.

If PENCRYPT=Yes, JES2 encrypts the password for any job that is sent across the network to this node. The encryption scheme JES2 uses is the data encryption system (DES) that exists in RACF. If the destination node's security product cannot interpret passwords using this scheme, the job(s) fails.

If PENCRYPT=No, JES2 does not encrypt the password for jobs that are sent across the network to this node.

This parameter has MAS scope.

Modification: \$T NODE(xxxxxxxx) operator command. The values can be changed on any start other than a hot start, and affects all MAS members regardless of whether the node is active or inactive.

PRIVATE=Yes | No

Specifies whether the information about the connection between the local node and the directly adjacent node that is defined by this statement is to be kept private; that is, the information is only known to this node and the directly adjacent node. Yes specifies that the information is not to be sent

to other nodes, No specifies that the information is sent to other nodes. The information about the connection is always sent to other members of this MAS. This parameter is ignored if the node is not a directly adjacent node. This parameter has MAS scope.

Modification: \$T NODE(xxxxxxxx) operator command, if the node is not active. The values can be changed on any start other than a hot start, and affects all MAS members regardless of whether the node is active or inactive.

RECeive=JOBS|SYSOUT|NONE|BOTH

Specifies what the node, as specified as OWNNODE= on the NJEDEF statement, receives from the specified adjacent node.

JOBS

Indicates that OWNNODE can only receive JOBS from the specified node(s).

SYSOUT

Indicates that OWNNODE can only receive SYSOUT from the specified node(s).

NONE

Indicates that OWNNODE accepts no data (JOBS or SYSOUT) from the specified node(s).

BOTH

Indicates that OWNNODE accepts both JOBS and SYSOUT from the specified node(s).

For example, NODE(5) REC=BOTH allows OWNNODE to accept both JOBS and SYSOUT from NODE5.

Modification: \$T NODE(xxxxxxxx) operator command.

REST=nnnn|@

Specifies an integer (0-2000) that represents the resistance rating of the connection as viewed by the installation manager and coordinated with other installations. If the node is specified as PATHMGR=NO, and no CONNECT statement is specified for this node, this value is the total resistance of the direct connection to this node plus the resistance of the node. See *z/OS JES2 Initialization and Tuning Guide* for details concerning resistance selection. The value specified here is used as a default if no APPL is defined for a SNA NJE networking node (that is, the APPL is dynamically defined). For BSC, node REST= is not used. LINE resistance is used instead. For BSC, this value is specified on the REST= parameter of the LINEnnnn statement.

Modification: \$T NODE(xxxxxxxx) operator command.

SENTREST=ACCEPT|IGNORE

The total resistance of a connection is composed of the partial resistance of the local node *plus* the partial resistance of the node to which you are making a connection.

When a connection is established between the local node and another node (that is, the node you specify on this NODE(xxxxxxxx) statement), SENTREST=ACCEPT specifies that the partial resistance sent to the local node during signon processing is to be added to the partial resistance calculated by the local node to determine the total resistance of the connection. SENTREST=IGNORE specifies that only the partial resistance calculated at the local node is to be used to calculate the total resistance of the connection. The partial resistance sent by the other node is ignored. This keyword only applies if PATHMGR=NO.

This keyword is useful when the node to which the connection is being made cannot control the resistance being sent during signon processing.

Modification: \$T NODE(xxxxxxxx) operator command.

SIGNON=SECURE | COMPAT

Specifies the type of signon security to be used when NJE connections to this node are established:

COMPAT

Specifies that node and line passwords, where applicable, are to be exchanged and verified by the NJE signon process.

SECURE

Specifies that encrypted session keys are to be exchanged rather than node and line passwords.

Modification: \$TNODE(nnn) operator command.

Note: For nodes connected through BSC, the N= parameter MUST be specified on the \$SN command for a secure signon to be processed.

SUBnet=xxxxxxx

Specifies the name of the subnet in which this node belongs. Connection records between two nodes in the same subnet are not passed between nodes outside that subnet.

This parameter has no default. It has MAS scope.

Modification: \$T NODE(xxxxxxx) operator command. The values can be changed on any start other than a hot start, and affects all MAS members regardless of whether the node is active or inactive.

TRace= Yes | No

Specifies whether network connect control (NCC) records to and from the direct connection to the specified member of this node should be traced (trace IDs 21 through 24).

Modification: \$T NODE(xxxxxxx) operator command.

TRANsmit=JOBS|SYSOUT|NONE|BOTH

Specifies what the node, as specified as OWNNODE= on the NJEDEF statement, transmits to the specified adjacent node.

JOBS

Indicates that OWNNODE can only transmit JOBS to the specified node(s).

SYSOUT

Indicates that OWNNODE can only transmit SYSOUT to the specified node(s).

NONE

Indicates that OWNNODE transmits no data (JOBS or SYSOUT) to the specified node(s).

BOTH

Indicates that OWNNODE transmits both JOBS and SYSOUT to the specified node(s).

For example, NODE(5) TRA=BOTH allows OWNNODE to transmit both JOBS and SYSOUT to NODE5.

Modification: \$T NODE(xxxxxxx) operator command.

VFYPATH=YES|NO


Specifies whether path verification processing is done for jobs and commands that indicate they originated at this node. This keyword only applies if the node is the origin node. Jobs that do not pass path verification are marked dubious and are subject to a validation precheck (based on the NJEDEF PRECHECK setting). Commands that do not pass path verification are rejected. Verification is based on the adjacent node from which the job or the command arrived, the node the job or the command claims to originate from, the intended execution node, and the VFYPATH setting of NODE statement defining the originating node of the job or the command.

OFF(n).JR - Offload Job Receiver


The OFF(n).JR initialization statement describes the offload job receiver associated with an individual offload device. An offload job receiver is a logical device that controls the loading of pre-execution jobs from an offload data set.

Specifying n from 1 to 8 associates this offload job receiver with a specific offload device as described by a corresponding OFFLOAD(n) initialization statement. The OFFLOAD(n) initialization statement defines the offload data set.


Format Description for OFF(n).JR



Modification keywords



Selection limiting keywords



Notes:

- ¹ Omit the comma between initialization statement and first keyword
- ² SYSaff can be coded up to 32 times

Parameter Description for OFF(n).JR

CReator=ccccccc

Specifies the 1- to 8-character userid whose job(s) are to be loaded from the offload data set. Wildcard specifications are allowed on this parameter. If you allow this parameter to default, JES2 can load jobs for all userids.

Modification: \$T OFF(n).JR operator command.

Class=classlist[(class,class)

Specifies the classes which are associated with the initiator. Classes associated with the initiator but ineligible to select work are not displayed in the list (but are matched on a filter).

The *classlist* variable specifies a list of single character job classes A-Z and 0-9: for example, 'ABCDEF'. A maximum of 36 classes can be specified.

The *class* variable specifies a comma-separated list of job classes or job class groups (each 1-8 characters in length). A maximum of eight items can be specified in the list: for example, (CLASS1,CLASS2,CLASS3).

Wildcards can also be specified: see [“Subscript ranges”](#) on page 2 for details.

Modification: \$T I[nnnn] operator command.

Hold=Yes|No

Specifies whether jobs in HOLD status can be loaded. If you allow this parameter to default and HOLD is not in the work selection list, JES2 can select all jobs, whether held or not, for loading. If you allow this parameter to default and HOLD is in the work selection list, no jobs can be loaded.

Yes

Indicates that only jobs that are in HOLD status can be loaded.

No

Indicates that only jobs that are not in HOLD status can be loaded.

Modification: \$T OFF(n).JR operator command.

JOBname=jcccccc

Specifies the 1- to 8-character job name of the job(s) to be loaded from the offload data set. Wildcard specifications are allowed on this parameter. If you allow this parameter to default, JES2 can select all jobs regardless of jobname, for loading.

Modification: \$T OFF(n).JR operator command.

MOD=

Specifies those characteristics of the pre-execution jobs that are to be automatically modified when these jobs are loaded from the offload data set. Use commas to separate individual modification characteristics and enclose the list in parenthesis if more than one is specified.

CLass=c1[...cn]

Specifies the execution class for all pre-execution jobs loaded by this device.

If you do not select a class, CLass will not be modified.

Hold=Yes|No

Specifies whether jobs are held for conversion after reloading.

If you do not specify this parameter, Hold will not be modified.

Routeode=rtcode

Specifies the destination from which jobs loaded by this device are run.

ANYLOCAL | LOCAL

Indicates that the jobs are to be run at the local node.

destid

Specifies the name of a node, or an alias for the name of a node, where the jobs are to be run.

Note: If destid is used, it must be previously defined on a DESTID statement in the initialization stream.

Nnnnn | nodename

Indicates that the jobs are to be run at the specified node. The node can be specified using the binary node identifier (nnnn), or the EBCDIC nodename.

Default: null (Routeode will not be modified)

Modification: Operator command.

SYSaff=sidn

Specifies the member affinity (sysid) for all pre-execution jobs loaded by this device.

If you do not select a value, member affinity will not be modified.

NOTify=Yes|No

Specifies whether a notification message is sent to the TSO/E userid specified on either the JOB statement or the /*NOTIFY control statement.

Yes

Indicates that a notification message is sent when a pre-execution job is loaded from the offload data set.

No

Indicates that a notification message is not sent when a pre-execution job is loaded from the offload data set.

Modification: \$T OFF(n).JR operator command.

RANGE=Jnnnnn[-nnnnn]||J1-2147483647

Specifies the job ID range of those jobs that can be loaded from the offload data set. If you code this parameter, you can specify one or two values:

- If you specify one value, that value becomes both the low and the high end of the range.
- If you specify two values, the first value is the low end of the range and the second value the high end. The two values can be equal. If they are not equal, the second value must be larger than the first value.

Modification: \$T OFF(n).JR operator command.

Route~~c~~de=rtcode

Specifies the execution node selection criteria for jobs to be loaded. Use commas to separate individual route codes and enclose the list in parenthesis if more than one route code is specified. Valid values for *rtcode* are:

ANYLOCAL | LOCAL

Indicates that only jobs routed to the local node for execution can be selected.

destid

Indicates that only jobs routed to the specified destid for execution can be selected. The destid can be the name of a node, or an alias for the name of a node.

Nnnnn | nodename

Indicates that only jobs routed to the specified node for execution can be selected. The node can be specified using the binary node identifier (nnnn) or the EBCDIC nodename.

Modification: \$T OFF(n).JR operator command.

SCHenv=schenv

Specifies the 1 to 16 byte scheduling environment. Only those jobs with this SCHenv will be selected.

Modification: \$T OFF(n).JR operator command.

SRVclass=srvclass

Specifies the 1 to 8 byte service class name. Only those jobs with this service class will be selected.

Modification: \$T OFF(n).JR operator command.

START=Yes|No

Specifies the initial status of this receiver when its corresponding offload device is started for a receive operation, that is, when a \$S OFFLOAD(n),TYPE=RECEIVE command is issued.

Yes

Indicates that this receiver is started when a corresponding \$S OFFLOAD(n) command is issued.

No

Indicates that this receiver is not started when a corresponding \$\$ OFFLOAD(n) command is issued. This receiver can later be started individually by issuing the \$\$ OFF(n).JR command and stopped as required by issuing the \$P OFF(n).JR command.

Modification: \$\$ OFF(n).JR operator command or \$P OFF(n).JR operator command.

SYSaff=sid1[,...sid32]|ANY

Specifies the member affinity for jobs that are selected for loading. Use commas to separate individual members and enclose the list in parenthesis if more than one member ID is specified.

sidn

Indicates the specific member ID. As many as 32 IDs can be indicated.

ANY

Indicates that the offload receiver can reload a job with any member affinity.

Modification: \$T OFF(n).JR operator command.

WS=(Class/)

Specifies the job selection criteria for this device. If a criterion is specified in the work selection list, job selection is based on the corresponding parameter specification on this initialization statement. If the job selection criterion is not listed here, the criterion is not considered during work selection.

Note:

1. A slash is required in this work selection list; all specifications are required to match and must be listed before a slash. Any criteria listed after the slash will be rejected by JES2.
2. As with other work selection lists, priority for a criterion which specifies multiple values (as do Class and Routeode) is in left to right priority order.

Class

Specifies that a match must be found for one of the job classes currently set for this device. If several classes are specified, the order of the class list is in left to right priority order.

Creator

Specifies that the current creator must match the creator specified for this device.

Hold

Specifies that the current hold specification is considered as a selection criterion.

JOBname

Specifies that the current job name must match the job name specified for this device.

RANGE

Specifies that the current job number must be within the range specified for this device.

Routeode

Specifies that one of the current route codes must match. If several route codes are specified, the order of the list is in right to left priority order.

SYSaff

Specifies that the job's member affinity must match one of the member affinities currently set for this device.

If you do not specify a value, the default value is WS=(Class/).

Note: Embedded comments are not allowed within the WS= parameter specification.


Modification: \$T OFF(n).JR operator command.

OFF(n).JT - Offload Job Transmitter


The OFF(n).JT initialization statement describes the offload job transmitter associated with an individual offload device. An offload job transmitter is a logical device that controls the dumping of pre-execution jobs to an offload data set.

Specifying n from 1 to 8 associates this offload job transmitter with a specific offload device as described by a corresponding OFFLOAD(n) initialization statement. The OFFLOAD(n) initialization statement defines the offload data set.


Format Description for OFF(n).JT



Modification keywords



Selection limiting keywords



Notes:

¹ Omit the comma between initialization statement and first keyword

² SYSaff can be coded up to 32 times

Parameter Description for OFF(n).JT

CREATOR=ccccccc

Specifies the 1- to 8-character userid whose job(s) are to be selected by this job transmitter. Wildcard specifications are allowed on this parameter. If you allow this parameter to default, JES2 can select jobs for all userids.

Modification: \$T OFF(n).JT operator command.

Class=classlist[(class,class)]

Specifies the classes which are associated with the initiator. Classes associated with the initiator but ineligible to select work are not displayed in the list (but are matched on a filter).

The *classlist* variable specifies a list of single character job classes A-Z and 0-9: for example, 'ABCDEF'. A maximum of 36 classes can be specified.

The *class* variable specifies a comma-separated list of job classes or job class groups (each 1-8 characters in length). A maximum of eight items can be specified in the list: for example, (CLASS1,CLASS2,CLASS3).

Wildcards can also be specified: see [“Subscript ranges”](#) on page 2 for details.

Modification: \$T I[nnnn] operator command.

DISP=HOLD|KEEP|DELETE

Specifies the disposition of all jobs that are selected for transmitting to the offload data set as follows:

KEEP

Indicates that selected job(s) will not change status after being transmitted to the offload data set.

HOLD

Indicates that selected job(s) are put into HOLD status after being transmitted to the offload data set.

DELETE

Indicates that the selected job(s) are purged after being transmitted to the offload data set.

Modification: \$T OFF(n).JT operator command.

Hold=Yes|No

Specifies whether jobs in HOLD status (that is, jobs that have been held by specifying a \$H J command, TYPRUN=HOLD, or JCL HOLD) can be transmitted. Jobs that have been previously held (in a held class) do not apply to this parameter; such jobs are not considered here.

If you allow this parameter to default and HOLD is not in the work selection list, JES2 can select all jobs, whether held or not, for transmission. If you allow this parameter to default and HOLD is in the work selection list, no jobs can be transmitted.

Yes

Indicates that only jobs that are in HOLD status can be selected.

No

Indicates that only jobs that are not in HOLD status can be selected.

Modification: \$T OFF(n).JT operator command.

JOBname=jccccc

Specifies the 1- to 8-character job name of the job(s) to be transmitted to the offload data set. Wildcard specifications are allowed on this parameter. If you allow this parameter to default, JES2 can select all jobs, regardless of jobname, for transmission.

Modification: \$T OFF(n).JT operator command.

LIMit=m|m-n|m-*

Specifies the limits (in records) set by this device for the amount of input records in a job.

For both variables *m* and *n*, you can specify a range of values 0-4294967295. *m* and *n* can be equal. If they are not equal, *n* must be larger than *m*.

If you code only *m*, that value becomes both the lower and upper limit. If *m-** is specified, the upper limit is set to the default value of 4294967295.

Default: If you omit this parameter, JES2 uses the defaults *m*=0 and *n*=4294967295.

Modification: \$T OFF(n).JT(n) command.

NOTify=Yes|No

Specifies whether a notification message is sent to the TSO/E userid specified on either the JOB statement or the /*NOTIFY control statement.

Yes

Indicates that a notification message is sent when a pre-execution job is transmitted to the offload data set.

No

Indicates that a notification message is not sent when a pre-execution job is transmitted to the offload data set.

Modification: \$T OFF(n).JT operator command.

RANGE=Jnnnnn[-nnnnn][J1-999999]

Specifies the job ID range of those jobs that can be transmitted to the offload data set. If you code this parameter, you can specify one or two values:

- If you specify one value, that value becomes both the low and the high end of the range.
- If you specify two values, the first value is the low end of the range and the second value the high end. The two values can be equal. If they are not equal, the second value must be larger than the first value.

Modification: \$T OFF(n).JT operator command.

Routecde=rtcode

Specifies the execution node selection criteria for jobs to be transmitted. Use commas to separate individual route codes and enclose the list in parentheses if more than one route code is specified. If you allow this parameter to default, JES2 can select all jobs, regardless of execution node, for transmission. Valid values for rtcode are:

ANYLOCAL | LOCAL

Indicates that only jobs on the local node can be selected.

destid

Specifies the name of a node, or an alias for the name of a node, from which jobs can be selected.

Note: If destid is used, it must be previously defined on a DESTID statement in the initialization stream.

Nnnnn | nodename

Indicates that only jobs which are to run on the specifically indicated node(s) can be selected. The nodes can be specified using the binary node identifier (nnnn) or the EBCDIC nodename.

Modification: \$T OFF(n).JT operator command.

START=Yes|No

Specifies the initial status of this transmitter when its corresponding offload device is started for a transmit operation, that is when a \$\$ OFFLOAD(n),TYPE=TRANSMIT command is issued.

Yes

Indicates that this transmitter is started when a corresponding \$\$ OFFLOAD(n) command is issued.

No

Indicates that this transmitter is not started when a corresponding \$\$ OFFLOAD(n) command is issued. This transmitter can later be started individually by issuing the \$T OFF(n).JT command and stopped, as required, by issuing the \$P OFF(n).JT command.

Modification: \$\$ OFF(n).JT operator command or \$T OFF(n).JT operator command.

SYSaff=

Specifies the member affinity for jobs that are selected for offloading. Use commas to separate individual members and enclose the list in parenthesis if more than one member ID is specified.

sidn

Indicates the specific member ID. As many as 32 IDs can be indicated.

ANY

Indicates that the offload job transmitter can transmit a job with any member affinity.

If you do not specify a value, the default value of this parameter is SYSaff=().

Modification: \$T OFF(n).JT operator command.

Volume=(v1[,v2][,v3][,v4])

Specifies the 5- or 6-character volume serial of a volume containing a spool data set. Only jobs using tracks on this volume(s) can be selected for dumping. As many as four volumes can be specified. Use

commas to separate individual volume IDs and enclose the list in parenthesis if more than one ID is specified.

If you do not specify a value, the default value of this parameter is Volume=().

Modification: \$T OFF(n).JT operator command.

WS=(Class/)

Specifies the job selection criteria for this device. If a criterion is specified in the work selection list, job selection is based on the corresponding parameter specification on this initialization statement. If the job selection criterion is not listed here, the criterion is not considered during work selection.

A slash can be used within the work selection list to further specify work selection. The use of a slash has the following general meaning: 1) those criterion listings several specifications is prioritized in a left to right priority order when placed to the left of the slash; 2) the placement of a criterion to the left of the slash indicates a required exact match of work selection and job criteria; and 3) placement of a criterion to the right of the slash indicates a preferred (but not required match) of work selection and job criteria. Exceptions to these rules are noted in the following descriptions.

Class

Specifies that a match must be found for one of the job classes currently set for this device. If specified to the left of the slash, the order of the class list is in left to right priority order. If specified to the right of the slash, an exact match is still required, but the list has no priority order.

Creator

Specifies that the current creator is preferred. If specified to the left of the slash, an exact match is required.

Hold

Specifies that the current hold specification is considered as a selection criterion. If specified to the left of the slash, an exact match is required.

JOBname

Specifies that the current job name is preferred. If specified to the left of the slash, an exact match is required.

Priority

Specifies that job priority is considered. The higher the priority value, the higher priority this criterion receives. The priority specification receives greater importance relative to its left to right placement in the criteria string.

RANGE

Specifies that the current job range is preferred. If specified to the left of the slash, an exact match is required.

Route code

Specifies that one of the current route codes must match. If specified to the left of the slash, an exact match is required and priority order is indicated from left to right. If specified to the right of the slash, an exact match is still required; however, no priority order is indicated.

SYSaff

Specifies that the current member affinity specification is preferred. If specified to the left of the slash, an exact match is required.

Volume

Specifies that one of the currently specified volumes must match. If specified to the left of the slash, an exact match is required and priority order is indicated from left to right. If specified to the right of the slash, an exact match is still required; however, no priority order is indicated.

If you do not specify a value, the default value of this parameter is WS=(Class/).

Note: Embedded comments are not allowed within the WS= parameter specification.


Modification: \$T OFF(n).JT operator command.

OFF(n).SR - Offload SYSOUT Receiver


The OFF(n).SR initialization statement describes the offload SYSOUT receiver associated with an individual offload device. An offload SYSOUT receiver is a logical device that controls the loading of output from an offload data set.


Specifying *n* from 1 to 8 associates this offload SYSOUT receiver with a specific offload device as described by a corresponding OFFLOAD(*n*) initialization statement. The OFFLOAD(*n*) initialization statement defines the offload data set.


Format Description for OFF(n).SR



Modification keywords












Notes:


- ¹ Omit the comma between initialization statement and first keyword
- ² Forms can be coded up to 8 times
- ³ OUTDisp can be coded up to 4 times
- ⁴ PRMode can be coded up to 8 times

Selection limiting keywords





HOLD



Notes:

¹ *form* can be coded up to 8 times

Parameter Description for OFF(n).SR

Burst=Yes|No

Specifies the burst specification for which output is selected.

If you allow this parameter to default, JES2 can select all output, regardless of burst specification, for loading.

Yes

Indicates that the printed output is to be burst into separate sheets.

No

Indicates that the printed output is not to be burst into separate sheets.

Modification: \$T OFF(n).SR operator command.

CReator=cccccccc

Specifies the 1- to 8-character userid whose output is to be loaded from the offload data set. Wildcard specifications are allowed on this parameter. If you allow this parameter to default, JES2 can load jobs for all userids.

Modification: \$T OFF(n).SR operator command.

FCB|C=xxxx

Specifies the 1- to 4-character name forms control image buffer or carriage control tape.

If you allow this parameter to default, JES2 can select all output, regardless of its FCB, for loading.

Modification: \$T OFF(n).SR operator command.

FLash|O=xxxx

Specifies a 1- to 4-character flash name for output loaded from the offload data set.

If you allow this parameter to default, JES2 can select all output, regardless of the flash specification, for loading.

Modification: \$T OFF(n).SR operator command.

Forms=xxxxxxxx,...,xxxxxxxx

Specifies the 1- to 8- character forms specification for which output is selected. Wildcard specifications are allowed on this parameter.

If you allow this parameter to default, JES2 can select all output, regardless of the forms specification, for loading.

Modification: \$T OFF(n).SR operator command.

Hold=Yes|No

Specifies whether output for held jobs are to be reloaded.

If you allow this parameter to default and HOLD is not in the work selection list, JES2 can select all output, whether held or not, for reloading. If you allow this parameter to default and HOLD is in the work selection list, no output can be reloaded.

Yes

Specifies that output from held jobs can be selected by this device.

No

Specifies that output from held jobs cannot be selected by this device.

Modification: \$T OFF(n).SR operator command.

JOBname=jcccccc

Specifies the 1- to 8-character job name of the job(s) to be loaded from the offload data set. Wildcard specifications are allowed on this parameter.

If you allow this parameter to default, JES2 can select all output, regardless of its jobname, for loading.

Modification: \$T OFF(n).SR operator command.

MOD=

Specifies those characteristics of the post-execution jobs that are to be automatically modified when post-execution jobs are loaded from the offload data set. Use commas to separate individual modification characteristics and enclose the list in parenthesis if more than one is specified.

Burst=Yes|No

Specifies whether job output from this device is to be burst (page-separated).

FCB=xxxx

Specifies a valid forms control buffer image or carriage control tape for output loaded from the offload data set.

FLash|O=xxxx

Specifies a valid flash name for output loaded from the offload data set.

Forms=xxxxxxxx,...,xxxxxxxx

Specifies a valid forms name for output loaded from the offload data set.

Hold=Yes|No

Specifies whether all jobs are held after loading.

Yes

Specifies that all jobs are held before output processing.

No

Specifies that all jobs are released before output processing.

OUTDisp=disposition

Specifies that output selected by this offload SYSOUT receiver should have its disposition changed to this value. You can specify one of the following valid dispositions:

HOLD|H

Hold the output. JES2 does not process the output until you either change the disposition to WRITE or KEEP, or release the output. When the output is released, the disposition changes to WRITE.

Note: This specification is honored when the output reaches the destination node.

KEEP|K

Process the output, then keep a copy of it on spool. After processing, the disposition of this output becomes LEAVE.

LEAVE|L

JES2 does not process the output until you change the disposition to WRITE or KEEP, or release the output. When the output is released, the disposition changes to KEEP.

WRITE|W

Process the output then purge it.

This modification defaults to the current disposition.

PRMode=vvvvvvvv

Specifies a valid processing mode for output loaded from the offload data set.

Queue=c1[...cn]

Specifies a valid output class (A-Z, 0-9) for all output loaded from the offload data set. A maximum of 15 classes can be specified on this parameter. If you need to exceed the limit of 15 classes, specify Queue=, (that is, null) and do not code Queue in the WS= list on this statement; this allows **all** defined classes to be reloaded.

Routecde=rtcode

Specifies a destination for all output loaded from the offload data set.

UCS|T=xxxx

Specifies a valid print train or character arrangement table for all output loaded from the offload data set.

Writer=xxxxxxxx

Specifies an external writer name for output loaded from the offload data set.

NOTify=Yes|No

Specifies whether a notification message is sent to the userid specified on either the JOB statement or the /*NOTIFY control statement.

Yes

Indicates that a notification message is sent when a post-execution job is offloaded to the offload data set.

No

Indicates that a notification message is not sent when a post-execution job is offloaded to the offload data set.

Modification: \$T OFF(n).SR operator command.

OUTDisp=(disposition[,...disposition])

Specifies the disposition(s) that the output must have in order to be eligible for processing by this offload receiver. The operator can specify one to four of the following valid dispositions:

HOLD|H

Hold the output. JES2 does not process the output until you either change the disposition to WRITE or KEEP, or release the output. When the output is released, the disposition changes to WRITE.

KEEP|K

Process the output, then keep a copy of it on spool. After processing, the disposition of this output becomes LEAVE.

LEAVE|L

JES2 does not process the output until you change the disposition to WRITE or KEEP, or release the output. When the output is released, the disposition changes to KEEP.

WRITE|W

Process the output then purge it. If there is a piece of output with an OUTDISP of WRITE, the offloader will select it.

See *z/OS JES2 Initialization and Tuning Guide* for more information about specifying output disposition and how JES2 determines output disposition defaults.

Default: The offload receiver will select on WRITE, HOLD, KEEP, and LEAVE.

Modification: \$T OFF(n).SR operator command

PRMode=(vvvvvvvv[,vvvvvvvv...])

Specifies the processing mode for which output can be selected. Use commas to separate individual processing modes and enclose the list in parenthesis if more than one processing mode is specified. Wildcard specifications are allowed on this parameter.

If you allow this parameter to default, JES2 can select all output, regardless of its processing mode, for loading.

Modification: \$T OFF(n).SR operator command.

Queue=c1[...cn]

Specifies the class(es) for which output can be selected. As many as 15 classes can be specified.

If you allow this parameter to default, JES2 can select all output, regardless of its class, for loading.

Modification: \$T OFF(n).SR operator command.

RANGE={J|S|T} nnnnnn[-nnnnnn]|J1-2147483647

Specifies the range (1-2147483647) of IDs for jobs (J), started tasks (S), or TSUs (T) of those jobs that can be loaded from the offload data set. If you code this parameter, you can specify one or two values:

- If you specify one value, that value becomes both the low and the high end of the range.
- If you specify two values, the first value is the low end of the range and the second value the high end. The two values can be equal. If they are not equal, the second value must be larger than the first value.

Modification: \$T OFF(n).SR operator command.

Route`cd`=`rtcode`

Specifies a destination for a piece of output. Its meaning depends on whether it is used as a subparameter of MOD= or not:

- If it is **not** used as a subparameter of MOD=, Route`cd`= means that output sent to the specified destination(s) can be selected.
- If Route`cd`= is used as a subparameter of the MOD= parameter, it specifies the destination(s) to which you want this output to go.

The maximum size of a route code is 18 characters. Use parentheses if more than one route code is specified. You can specify a route code in any of the forms listed. Note that a slash, a colon, or a matched set of parentheses can be used instead of a period anywhere a period appears as a separator in a route code. For example, you could specify node.remote, node:remote, node/remote, or node(remote) for an explicit route code. Wildcard specifications are allowed on this parameter for userids only.

```
node
NnnnnnRmmmmm
Ummmmm
destid
node.remote
node.user
node.Ummmmm
node.destid
remote
user
node.*
*
```

Note: If destid is used, it must be previously defined on a DESTID statement in the initialization stream. Explanations of the different forms of specifying route codes follow.

LOCAL | ANYLOCAL

Indicates routing to the local node.

Nnnnnn

Indicates routing to the node specified by its binary node identifier. The value specified for nnnnn can range from 1 to 32767.

destid

Indicates routing to the specified node(s). You can specify the name of a node, or an alias for the name of a node, for destid.

nodename

Indicates routing to the node specified by its EBCDIC node name.

NnnnnnRmmmmm

Indicates routing to the remote Rmmmmm at the node Nnnnnn. If the node is the local node, Nnnnnn may be omitted. Values specified for both nnnnn and mmmmm can range from 1 to 32767.

Note: NnnnnnRmmmmm is restricted to a maximum of eight characters. Therefore, the combined number of digits *nnnnn* plus *mmmmm* cannot exceed six. Valid combinations are NnnnnnRmm, NnnnRmmm, NnnRmmmm.

Ummmmm

Indicates special local routing. The special routing numbers range from 1 to 32767.

destid

Indicates routing to the specified node(s). If destid is specified alone, it refers to both the node and the remote.

node.remote

Indicates routing to a remote at the specified node.

node.user

Indicates routing to a user at the specified node.

node.Ummmmm

Indicates special local routing at the specified node. The special routing numbers range from 1 to 32767.

node.destid

Indicates a destination at the specified node. The destid refers to both the node and the remote. The node specified in the destid must be the same as the node portion of the route code.

remote

Indicates routing to a remote. Remote can be specified in any of the following ways:

Rmmmmm

Indicates routing to the specified remote. Rmmmmm can also be specified as RMmmmmm or RMTmmmmm. The value specified for mmmmm can range from 1 to 32767.

destid

Indicates routing to a destid referring to a remote.

user

Indicates routing to a specified userid.

If Routecde= is not used as a subparameter of MOD=, a generic userid can be specified. A generic userid is a userid that ends in an asterisk (*), and refers to all userids that begin with any characters preceding the *. Note that the * can only be specified in the last position of the userid.

A userid at the local node must be in the form of a valid TSO/E userid. (It must begin with an alphabetic (A-Z) or a special character (@ # or \$) and the remaining characters can be alphabetic, numeric, or special characters.) Userids at non-local nodes may contain any characters except separators (a period, a colon, a slash, or a set of parentheses), delimiters (a comma, or a blank), or an asterisk (*).

node.*

If Routecde= is not used as a subparameter of MOD=, node.* indicates that all output destined for the specified node is selected, regardless of the userid or remote specified. If Routecde= is used as a subparameter of MOD=, node.* indicates that the node name is to be modified to the specified node name, but the remote node will remain the same.

If Routecde= is not used as a subparameter of MOD=, * indicates that all output specified for the local node is selected, regardless of the userid or remote specified. If Routecde is used as a subparameter of MOD=, * indicates that the node number will be changed to the local node. However, the remote number originally specified will remain the same.

Modification: \$T OFF(n).SR operator command.

START=Yes|No

Specifies the initial status of this receiver when its corresponding offload device is started for a receive operation, that is when a \$\$ OFFLOAD(n),TYPE=RECEIVE command is issued.

Yes

Indicates that this receiver is started when a corresponding \$\$ OFFLOAD(n) command is issued.

No

Indicates that this receiver is not started when a corresponding \$\$ OFFLOAD(n) command is issued. This receiver can later be started individually by issuing the \$\$ OFF(n).SR command and stopped, as required, by issuing the \$P OFF(n).SR command.

Modification: \$\$ OFF(n).SR operator command or \$T OFF(n).SR operator command.

UCS|T=xxxx

Specifies the 1- to 4-character print train (universal character set) for output to be dumped.

If you allow this parameter to default, JES2 can select all output, regardless of its UCS, for loading.

Modification: \$T OFF(n).SR operator command.

Writer=xxxxxxxx

Specifies the 1- to 8-character writer name for which output can be selected. Wildcard specifications are allowed on this parameter.

If you allow this parameter to default, JES2 can select all output, regardless of its writer, for loading.

Modification: \$T OFF(n).SR operator command.

WS=(Queue,OUTDisp)

Specifies the selection criteria for this device. If a criterion is specified in the work selection list, output selection is based on the corresponding parameter specification on this initialization statement. If the selection criterion is not listed here, the criterion is not considered during work selection.

Note:

1. A slash is not required in this work selection list; all specifications are required to match and are assumed to be listed before a slash. You can code a slash if criteria are listed before it or use WS=(/) to specify a null work selection list.
2. As with other work selection lists, priority for a criterion which specifies multiple values (as do Queue, PRMode, and RouteCde) is in left to right priority order.

Burst

Specifies that the current burst specification is required.

CREATOR

Specifies that the creator is preferred.

FCB|C

Specifies that the current FCB specification is required. "C" can be used rather than FCB; however, its use is not recommended.

Flash|O

Specifies that the current flash specification is preferred. "O" can be used rather than FL or FLASH; however, its use is not recommended.

Forms

Specifies that the current forms specification is preferred.

Hold

Specifies that the current hold specification is considered as a selection criterion.

JOBname

Specifies that the current job name must match the job name specified for this device.

OUTDisp

Specifies that the disposition of the output must match the disposition specified on the OUTDisp= parameter in order for the output to be selected by this SYSOUT receiver.

PRMode|PMD

Specifies that the current data set processing mode must match.

Queue

Specifies that the data set's output class must match one of the current output classes set for this device.

RANGE

Specifies that the current job number must be within the range specified for this device.

Route code

Specifies that the data set's route code must match one of the currently set route codes. If specified, an exact match is required and priority order is indicated from left to right.

UCS|T

Specifies that the data set's UCS specification must match the UCS set for this device.

Writer

Specifies that the writer name of the output data set must match the writer name currently set for this device.

Note: Embedded comments are not allowed within the WS= parameter specification.

Modification: \$T OFF(n).SR operator command.

Examples for OFF(n).SR

OUTDISP=WRITE, WS=(OUTD/), DISP=DELETE


The offloader will select output with any OUTDISP and delete it after the offloader has completed.


OFF(n).ST - Offload SYSOUT Transmitter

The OFF(n).ST initialization statement describes the offload SYSOUT transmitter associated with an individual offload device. An offload SYSOUT transmitter is a logical device that controls the offloading of output to an offload data set.

Specifying n from 1 to 8 associates this offload SYSOUT transmitter with a specific offload device as described by a corresponding OFFLOAD(n) initialization statement. The OFFLOAD(n) initialization statement defines the offload data set.

Format Description for OFF(n).ST







Notes:

- ¹ Form can be coded up to 8 times
- ² OUTDisp can be coded up to 4 times
- ³ PRMode can be coded up to 8 times

Selection limiting keywords





Notes:

¹ *form* can be coded up to 8 times

Parameter Description for OFF(n).ST

Burst=Yes|No

Specifies the burst specification for which output is selected.

If you allow this parameter to default, JES2 can select all output, regardless of its burst specification, for transmission.

Yes

Indicates that the printed output is to be burst into separate sheets.

No

Indicates that the printed output is not to be burst into separate sheets.

Modification: \$T OFF(n).ST operator command.

CReator=ccccccc

Specifies the 1- to 8-character userid whose output is to be offloaded to the offload data set. Wildcard specifications are allowed on this parameter. If you allow this parameter to default, JES2 can select all output, regardless of its userid, for transmission.

Modification: \$T OFF(n).ST operator command.

DISP=KEEP|HOLD|DELETE

Specifies the disposition of all output that is selected for offload to the offload data set as follows:

KEEP

Indicates that selected output will not change status after offloading to the offload data set.

HOLD

Indicates that selected held output remains held after offloading to the offload data set, or HOLD indicates that selected non-held output is marked as non-selectable after offloading to the offload data set. The operator must issue a \$T O command to release jobs specified here as "HOLD".

Note: Marking this output as non-selectable is not the same as putting a job in HOLD status.

DELETE

Indicates that the selected output groups are deleted after offloading to the offload data set.

Modification: \$T OFF(n).ST operator command.

FCB|C=xxxx

Specifies the 1- to 4-character name forms control image buffer or carriage control tape.

If you allow this parameter to default, JES2 can select all output, regardless of its FCB, for transmission.

Modification: \$T OFF(n).ST operator command.

Flash|O=xxxx

Specifies the 1- to 4-character name of a particular flash for which output is selected.

If you allow this parameter to default, JES2 can select all output, regardless of its flash specification, for transmission.

Modification: \$T OFF(n).ST operator command.

Forms=xxxxxxxx

Specifies the 1- to 8-character forms specification for which output is selected. Wildcard specifications are allowed on this parameter.

If you allow this parameter to default, JES2 can select all output, regardless of its forms specification, for transmission.

Modification: \$T OFF(n).ST operator command.

Hold=Yes|No

Specifies whether SYSOUT for held jobs can be transmitted to the offload data set. Output for held jobs is output from jobs that the operator placed on hold using the \$H command.

If you allow this parameter to default and HOLD is not in the work selection list, JES2 can select all output, whether held or not, for transmission. If you allow this parameter to default and HOLD is in the work selection list, no output can be transmitted.

Yes

Specifies that output for held jobs can be transmitted to the offload data set.

No

Specifies that output for held jobs cannot be transmitted to the offload data set.

Modification: \$T OFF(n).ST operator command.

JOBname=jcccccc

Specifies the 1-8 character job name of the job(s) to be offloaded to the offload data set. Wildcard specifications are allowed on this parameter.

If you allow this parameter to default, JES2 can select all output, regardless of its jobname, for transmission.

Modification: \$T OFF(n).ST operator command.

LIMit=m|m-n|m-*

Specifies the amount of output (in records) for which output can be selected.

For both variables *m* and *n*, you can specify a range of values 0-4294967295. *m* and *n* can be equal. If they are not equal, *n* must be larger than *m*.

If you code only *m*, that value becomes both the lower and upper limit. If *m-** is specified, the upper limit is set to the default value of 4294967295.

Default: If you omit this parameter, JES2 uses the default values *m*=0 and *n*=4294967295.

Modification: \$T OFF(n).ST operator command.

NOTify=Yes|No

Specifies whether a notification message is sent to the userid specified on either the JOB statement or the /*NOTIFY control statement.

Yes

Indicates that a notification message is sent when a post-execution job is offloaded to the offload data set.

No

Indicates that a notification message is not sent when a post-execution job is offloaded to the offload data set.

Modification: \$T OFF(n).ST operator command.

OUTDisp=(disposition[,...disposition])

Specifies the disposition(s) that the output must have in order to be eligible for processing by this offload transmitter. The operator can specify one to four of the following valid dispositions:

HOLD|H

Hold the output. JES2 does not process the output until you either change the disposition to WRITE or KEEP, or release the output. When the output is released, the disposition changes to WRITE.

Note: This specification is honored when the output reaches the destination node.

KEEP|K

Process the output then keep a copy of it on spool. After processing, the disposition of this output becomes LEAVE.

LEAVE|L

JES2 does not process the output until you change the disposition to WRITE or KEEP, or release the output. When the output is released, When the output is released, the disposition changes to KEEP.

WRITE|W

Process the output then purge it. If there is a piece of output with an OUTDISP of WRITE, the offloader will select it.

See [z/OS JES2 Initialization and Tuning Guide](#) for more information about specifying output disposition and how JES2 determines output disposition defaults.

Default: Only output with dispositions WRITE and KEEP are selected by this offload transmitter if you do not specify values for OUTDisp=.

Modification: \$T OFF(n).ST operator command

PLIM=m|m-n|m-*

Specifies the amount of output (in pages) for which output can be selected.

For both variables *m* and *n*, you can specify a range of values from 0-4294967295. *m* and *n* can be equal. If they are not equal, *n* must be larger than *m*.

If you code only *m*, that value becomes both the lower and upper limit. If *m-** is specified, the upper limit is set to the default value of 4294967295.

Default: If you omit this parameter, JES2 uses the default values *m*=0 and *n*=4294967295.

Modification: \$T OFF(n).ST operator command.

PRMode=(vvvvvvvv[,vvvvvvvv...])

Specifies the processing mode for which output can be selected. Use commas to separate individual processing modes and enclose the list in parenthesis if more than one processing mode is specified. Wildcard specifications are allowed on this parameter.

If you allow this parameter to default, JES2 can select all output, regardless of the processing mode, for transmission.

Modification: \$T OFF(n).ST operator command.

Queue=c1[...cn]

Specifies the class(es) (A-Z, 0-9) for which output can be selected. A maximum of 15 classes can be specified on this parameter. If you need to exceed the limit of 15 classes, specify Queue=, (that is, null) and do not code Queue in the WS= list on this statement; this allows **all** defined classes to be transmitted.

Modification: \$T OFF(n).ST operator command.

RANGE={J|S|T} nnnnnn[-nnnnnn]J1-999999

Specifies the job ID range (J), started task range (S), or TSU range (T) of those jobs that can be loaded from the offload data set. Use the Jnnnnn form for job routing, the Snnnnn form for STC routing, and the Tnnnnn form for TSU job routing. If you code this parameter, you can specify one or two values:

- If you specify one value, that value becomes both the low and the high end of the range.
- If you specify two values, the first value is the low end of the range and the second value the high end. The two values can be equal. If they are not equal, the second value must be larger than the first value.

Modification: \$T OFF(n).ST operator command.

Routeode=rtcode

Specifies the one to four destination selection criteria for which output can be selected. If more than one route code is specified, enclose the list in parentheses.

If Routeode is not provided, this transmitter will be allowed to select ALL output.

The maximum size of a route code is 18 characters. Wildcard specifications are allowed on this parameter for userids only. You can specify a route code in any of the forms listed below. Note that a slash, a colon, or a matched set of parentheses can be used instead of a period anywhere a period appears as a separator in a route code. For example, you could specify node.remote, node:remote, node/remote, or node(remote) for a route code.

```
node
NnnnnnRmmmmm
Ummmmm
destid
node.remote
node.user
node.Ummmmm
node.destid
remote
user
node.*
*
```

Note: If destid is used, it must be previously defined on a DESTID statement in the initialization stream. Explanations of the different forms of specifying route codes follow:

LOCAL | ANYLOCAL

Indicates that output routed to the local node is selected.

Nnnnnn

Indicates that output routed to the node specified by its binary node identifier is selected. The value specified for *nnnnn* can range from 1 to 32767.

destid

Indicates that output routed to the specified node(s) is selected. You can specify the name of a node, or an alias for the name of a node, for *destid*.

nodename

Indicates that output routed to the node specified by its EBCDIC node name is selected.

NnnnnnRmmmmm

Indicates that output routed to the remote *Rmmmmm* at the node *Nnnnnn* is selected. If the node is the local node, *Nnnnnn* may be omitted. Values specified for both *nnnnn* and *mmmmm* can range from 1 to 32767.

Note: *NnnnnnRmmmmm* is restricted to a maximum of eight characters. Therefore, the combined number of digits *nnnnn* plus *mmmmm* cannot exceed six. Valid combinations are *NnnnnnRmm*, *NnnnRmmm*, *NnnRmmmm*.

Ummmmm

Indicates that output for special local routing is selected. The special routing numbers range from 1 to 32767.

destid

Indicates that output routed to the specified node(s) is selected. If *destid* is specified alone, it refers to both the node and the remote.

node.remote

Indicates that output routed to a remote at the specified node is selected.

node.user

Indicates that output routed to a user at the specified node is selected.

node.Ummmmm

Indicates that output for special local routing at the specified node is selected. The special routing numbers range from 1 to 32767.

node.destid

Indicates that output to be routed to a destination at the specified node is selected. The *destid* refers to both the node and the remote. The node specified in the *destid* must be the same as the node portion of the route code.

remote

Indicates that output routed to a remote is selected. Remote can be specified in any of the following ways:

Rmmmmm

Indicates that output routed to the specified remote is selected. *Rmmmmm* can also be specified as *RMmmmmm* or *RMTmmmmm*. The value specified for *mmmmm* can range from 1 to 32767.

destid

Indicates that output routed to a *destid* referring to a remote is selected.

user

Indicates that output routed to a *userid*, or a generic *userid*, is selected. A generic *userid* is a *userid* that ends in an asterisk (*), and refers to all *userid*s that begin with any characters preceding the *. Note that the * can only be specified in the last position of the *userid*.

A *userid* at the local node must be in the form of a valid TSO/E *userid*. (It must begin with an alphabetic (A-Z) or a special character (@ # \$), and the remaining characters may be alphabetic, numeric, or special characters.) *Userids* at non-local nodes may contain any characters except separators (a period, a colon, a slash, or a set of parentheses), delimiters (a comma, or a blank), or an asterisk (*).

node.*

Indicates that all output destined for the specified node is selected, regardless of the userid or remote specified.

Indicates that all output specified for the local node is selected, regardless of the userid or remote specified.

If you allow this parameter to default, JES2 can select all output, regardless of the route code, for transmission.

Modification: \$T OFF(n).ST operator command.

START=Yes|No

Specifies the initial status of this transmitter when its corresponding offload device is started for a transmit operation, that is when a \$\$ OFFLOAD(n),TYPE=TRANSMIT command is issued.

Yes

Indicates that this transmitter is started when a corresponding \$\$ OFFLOAD(n) command is issued.

No

Indicates that this transmitter is not started when a corresponding \$\$ OFFLOAD(n) command is issued. This transmitter can later be started individually by issuing the \$T OFF(n).ST command and stopped, as required by issuing the \$P OFF(n).ST command.

Modification: \$\$ OFF(n).ST operator command or \$T OFF(n).ST operator command.

UCS|T=xxxx

Specifies the 1- to 4-character print train (universal character set) for output to be transmitted.

If you allow this parameter to default, JES2 can select all output, regardless of its UCS, for transmission.

Modification: \$T OFF(n).ST operator command.

Volume=(v1[,v2][,v3][,v4])|()

Specifies the 5- or 6-character volume serial of a volume containing a spool data set. Only jobs using tracks on this volume(s) can be selected for dumping. As many as four volumes can be specified. Use commas to separate individual volume IDs and enclose the list in parenthesis if more than one ID is specified.

Modification: \$T OFF(n).ST operator command.

Writer=xxxxxxxx

Specifies the 1- to 8-character writer name for which output can be selected. Wildcard specifications are allowed on this parameter.

If you allow this parameter to default, JES2 can select all output, regardless of the writer, for transmission.

Modification: \$T OFF(n).ST operator command.

WS= (Queue,OUTDisp)

Specifies the selection criteria for this device. If a criterion is specified in the work selection list, output selection is based on the corresponding parameter specification on this initialization statement. If the criterion is not listed here, the criterion is not considered during work selection.

A slash can be used within the work selection list to further specify work selection. The use of a slash has the following general meaning: 1) those criterion listing several specifications is prioritized in a left to right priority order when placed to the left of the slash; 2) the placement of a criterion to the left of the slash indicates a required exact match of work selection and job criteria; and 3) placement of a criterion to the right of the slash indicates a preferred (but not required match) of work selection and job criteria. Exceptions to these rules are noted in the following descriptions.

Note: Embedded comments are not allowed within the WS= parameter specification.

Burst

Specifies that the current burst specification is preferred. If specified to the left of the slash, an exact match is required.

CRreator

Specifies that the creator is preferred. If specified to the left of the slash, an exact match is required.

FCB|C

Specifies that the current FCB specification is preferred. If specified to the left of the slash, an exact match is required.

FLash|O

Specifies that the current flash specification is preferred. If specified to the left of the slash, an exact match is required.

Forms

Specifies that the current forms specification is preferred. If specified to the left of the slash, an exact match is required.

Hold

Specifies that the current hold specification is preferred. If specified to the left of the slash, an exact match is required.

JOBname

Specifies that the current job name is preferred. If specified to the left of the slash, an exact match is required.

LIMit

Specifies that the current output quantity limit is preferred. If specified to the left of the slash, output to be transmitted must fall within the specified range.

This subparameter has no effect as a work selection value for files received from a node that does not provide a page count for its files. For more information, see the sending node's reference documentation.

OUTDisp

Specifies that the disposition of the output must match the disposition specified on the OUTDisp= parameter in order for the output to be selected by this SYSOUT transmitter.

Priority

Specifies that JOE priority is considered. The higher the priority value, the higher priority this criterion receives. The priority specification receives greater importance relative to its left to right placement in the criteria string.

The offload SYSOUT transmitter uses priority to select the best output group. Then, all output groups in the same job that meet the required selection criteria are offloaded together, regardless of priority. Priority is not used to order JOEs within a job on the offload data set.

PRMode|PMD

Specifies that one of the current process modes must match. If specified to the left of the slash, an exact match is required and priority order is indicated from left to right. If specified to the right of the slash, an exact match is still required; however, no priority order is indicated.

Queue

Specifies that the current class specification must match. If specified to the left of the slash, an exact match is required and priority order is indicated from left to right. If specified to the right of the slash, an exact match is still required; however, no priority order is indicated.

RANGE

Specifies that the current job range is preferred. If specified to the left of the slash, the current job number must be within the range specified for this device.

Route code

Specifies that one of the current route codes must match. If specified to the left of the slash, an exact match is required and priority order is indicated from left to right. If specified to the right of the slash, an exact match is still required; however, no priority order is indicated.

OFFLOAD(n)

UCS|T

Specifies that the current universal character set is preferred. If specified to the left of the slash, an exact match is required.

Volume

Specifies that one of the currently specified volumes must match. If specified to the left of the slash, an exact match is required and priority order is indicated from left to right. If specified to the right of the slash, an exact match is still required; however, no priority order is indicated.

Writer

Specifies that the current writer name is preferred. If specified to the left of the slash, an exact match is required.

Modification: \$T OFF(n).ST operator command.

Examples for OFF(n).ST

OUTDISP=WRITE, WS=(OUTD/), DISP=DELETE


The offloader will select output with any OUTDISP and delete it after the offloader has completed.

OFFLOAD(n) - Offload Device


The OFFLOAD(n) initialization statement defines the logical offload device used for both offloading (transmitting) and reloading (receiving) operations. This statement defines the offload data set to which pre-execution jobs and SYSOUT data sets are offloaded and from which these jobs and SYSOUT are reloaded.

Specifying n from 1 to 8 associates this offload data set with the specific offload job transmitter (OFF(n).JT), SYSOUT transmitter (OFF(n).ST), job receiver (OFF(n).JR), and SYSOUT receiver (OFF(n).SR). Offload devices are initialized at the multi-access spool member level; therefore, if one member has started a specific offload device, it cannot be started by another member while in use by any other member.

Format Description for OFFLOAD(n)




Modification keywords



Selection limiting keywords

OFFLOAD(n)



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for OFFLOAD(n)

ARCHIVE=ONE | ALL

Specifies which offload devices JES2 prevents from reselecting jobs for offload that have a disposition of DISP=KEEP or DISP=HOLD.

ONE

JES2 prevents a specific offload device from reselecting a job with DISP=KEEP or DISP=HOLD when it was offloaded by that device.

ALL

JES2 prevents **all** offload devices from reselecting a job with DISP=KEEP or DISP=HOLD when it is offloaded by any device.

Modification: \$T OFFLOAD(n) operator command (if the device is drained).

CRTIME

Specifies the creation time to be associated with jobs and output on reload:

RESET

Indicates that the time to be assigned is the time of the reload

RESTORE

Indicates that the time to be assigned is the original creation time (before the data was offloaded).

Modification: \$TOFFLOAD(n) operator command.

DSName=jxxx...x

Specifies the offload data set used to define this offload device. The data set name can be 1- to 44-alphanumeric characters. A period (.) or a hyphen (-) can be included for any character except the first. This parameter does not support the use of a generation data set (GDG) or a partitioned data set (PDS). See “Spool Offload Facility” in [z/OS JES2 Initialization and Tuning Guide](#) for more information concerning offload data set allocation.

Modification: \$T OFFLOAD(n) operator command (if the device is drained).

LABEL=NL|SL|NSL|SUL|BLP|AL|AUL

Specifies the type of label processing that is required for the tape that is to be allocated for a non-cataloged spool offload data set.

Type**Meaning****NL**

No label

SL

IBM standard label

NSL

Non-standard label

SUL

IBM standard label and user-defined label

BLP

Bypass label processing

AL

American National Standard label

AUL

American National Standard label and American National Standard user-defined label

Modification: \$T OFFLOAD(n) operator command (if the device is drained).

PROTECT=Yes|No

Specified whether the spool offload data set requires System Authorization Facility (SAF) protection.

Modification: \$T OFFLOAD(n) operator command (if the device is drained).

RETPD=nnnn | 30

Specifies the retention period (0-9999), in days, this offload data set is to be retained.

Modification: \$T OFFLOAD(n) operator command (if the device is drained).

TRACE=Yes|No

Specifies whether or not trace records are to be cut for data read or written by this offload device. See specific trace ids for more information.

Modification: \$T OFFLOAD(n) operator command.

UNIT=({hhhh | /hhhh | nnnn | ccccccc},nn | 1)

hhhh | /hhhh

Specifies a 3- or 4-digit hexadecimal device number. Device numbers can be specified by any of the following formats:

```
UNIT=hhh
UNIT=/hhh
UNIT=/hhhh
```

where hhh and hhhh represent the device numbers. A slash (/) must precede a 4-digit device number.

nnnn

Specifies a device type.

ccccccc

Specifies a 1- to 8-character group name assigned to the device or group of devices that are to be used to receive non-cataloged spool offload data sets.

nn

Specifies the number (1-59) of devices, that are allocated to mount the volumes containing the offload data set. If you do not specify a second value, JES2 allocates 1 device.

Note: If enough devices are not available to satisfy the value specified here, the allocation will fail.

Generally, the medium used for spool offload is tape; however, the assigned unit can be a DASD device. If a DASD device is specified, and the data set specified does not exist, then the size of the data set is determined from your installation's default as specified on the SPACE parameter in the ALLOCxx parmlib member. However, the default size will likely be too small for an offload data set. Therefore, when using DASD as your spool offload media, IBM suggests that the data set be pre-allocated with a space parameter value large enough to hold the data being offloaded. If the data set becomes full, the spool offload subtask will abnormally end.

UNIT= is only honored on an OFFLOADn TYPE=TRANSMIT operation. Therefore, if you do not specify UNIT=, the offload data set must be pre-cataloged if JES2 is to dynamically allocate a new data set. If the data set is not pre-cataloged and UNIT= is not specified, no data set is allocated.

For an OFFLOAD TYPE=RECEIVE operation, JES2 requires that the data set be pre-cataloged regardless of the UNIT= specification because the catalog information overrides the UNIT= specification.

Modification: \$T OFFLOAD(n) operator command (if the device is drained).

The second value, nn, specifies the number (1-59) of devices that will be allocated to the offload data set.

VALIDATE=Yes

|No

Specifies the action JES2 takes if it determines that the first record of the offload data set is not LRECL=80.

Yes

JES2 drains the offload device and issues \$HASP595 OFFLOADn ERROR READING FIRST RECORD - DRAINING OFFLOAD DEVICE.

No

JES2 continues to read from the offload data set, but skips to the next job header. JES2 then issues \$HASP595 OFFLOADn ERROR READING FIRST RECORD - SKIPPING FOR JOB HEADER. The offload device continues to read from the offload data set and passes the records to the appropriate receiver(s). However, the receiver(s) discards all records until it encounters a job header at which time it continues to process jobs normally.

Modification: \$T OFFLOAD operator command (if the device is drained).

VOLS=nnn|255

Specifies the volume count (1-255) to be used for the spool offload data set.

Note: If your spool offload data set is to be a system-managed DASD data set, specify a VOLS= value no greater than 59.


Modification: \$T OFFLOAD operator command (if the device is drained).

OPTsdef - Start Options Processing Definitions

Use the OPTsdef statement to display or override various JES2 start options. Most of these options can only be overridden when the JES2 initialization process is in CONSOLE mode. The default values for each option are taken from the value specified when JES2 is started (MVS START command or JES cataloged procedure EXEC statement). See *z/OS JES2 Initialization and Tuning Guide* for the default that JES2 uses if the option is not specified when JES2 is started or on the OPTsdef statement.

Note: Only the LIST, LOG, SPOOL and COLD_START_MODE parameters can be specified in the initialization deck.

Format



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameters

CKPTOPT=CKPT1|CKPT2|HIGHEST

Specifies which checkpoint data set JES2 reads as the source for building the JES2 work queues during a restart. CKPT1 and CKPT2 refer to the CKPT1= and CKPT2= parameters on the CKPTDEF

initialization statement, respectively. HIGHEST indicates that you will allow JES2 to read the checkpoint data based on the level tokens associated with the checkpoint data sets. (See the CKPTDEF statement in this chapter and *z/OS JES2 Initialization and Tuning Guide* for further discussion on selecting an appropriate checkpoint data set.)

Note: The method used by JES2 to determine the highest data set to read from, is not foolproof. If you are in a recovery scenario and know that one of the checkpoint data sets does NOT have the current checkpoint information, then you should specify the CKPTn option that reads from the data set that does contain current checkpoint information.

Modification: Hot start.

COLD_START_MODE=z11|z22|DEFAULT

Specifies the checkpoint mode (\$ACTIVATE LEVEL) for JES2 to use for COLD starts. By default, JES2 does COLD starts in z22 mode. To set JES2 COLD starts to z11 mode, specify COLD_START_MODE=z11.

Set this parameter in your initialization deck to ensure that any unplanned COLD starts are done in the intended mode.

If this parameter is specified, initialization issues the following warning messages if JES2 is warm started with a COLD_START_MODE that does not match the mode of the read checkpoint:

```
$HASP442 INITIALIZATION STATEMENTS CONFLICTING WITH SAVED VALUES FOLLOW:
$HASP496 OPTSDEF COLD_START_MODE=Z22 SAVED VALUE OF Z11 WILL BE USED
```

If COLD_START_MODE is not specified, no warning message is issued.

Note: The JES2 start parameter UNACT overrides the COLD_START_MODE parameter and causes JES2 to start in z11 mode.

Modification: Hot start.

CONSOLE=Yes|No

Displays (or changes) the value of the CONSOLE start option. If set to YES, the operator will be prompted for additional initialization statements after the initialization deck is processed. See the *z/OS JES2 Initialization and Tuning Guide* for further information on the interaction of this initialization statement and the CONSOLE initialization control statement.

Modification: Hot start.

LIST=Yes|No

Specifies whether or not to copy subsequent initialization statements to the HASPLIST DD statement.

Modification: Hot start.

LISTOPT=Yes|No

Displays (or changes) the value of the LISTOPT start option. If YES, the initialization statements are printed if a device is specified.

Modification: Hot start.

LOG=Yes|No

Specifies whether or not to copy subsequent initialization statements to the printer specified by the HARDCPY console.

Modification: Hot start.

LOGOPT=Yes|No

Displays (or changes) the value of the LOGOPT start option. If Yes, the initialization statements are logged if a device is specified.

Modification: Hot start.

RECONFIG=Yes|No

Displays (or changes) the value of the RECONFIG start option. If Yes, the operator can specify RECONFIG to cause JES2 to use the checkpoint data set definitions as defined in the initialization data

set, thereby overriding any/all previous checkpoint data set forwarding. (See *z/OS JES2 Initialization and Tuning Guide* for a full discussion of checkpoint data set forwarding and reconfiguration.)

Modification: Hot start.

Note: This parameter **must never** be specified in the PARMLIB member.

REQMSG=Yes|No

Displays (or changes) the value of the REQ|NOREQ start option. If Yes, the \$HASP400 ENTER REQUESTS message is displayed, prompting the operator for the \$\$ command.

Modification: Hot start.

SPOOL=VALIDATE|NOVALIDATE

Specifies whether or not JES2 validates the track group map. VALIDATE will recover potentially lost track groups. NOVALIDATE is faster but will not recover any track groups that are potentially lost.

Note: On an all-member warm start, you can use this parameter or the SPOOL=VALIDATE start option to request that JES2 validate the track group map. This is typically not needed unless you receive indications from JES2 such as the following:

- Persistent JES2 disastrous errors (\$HASP095, error code \$DIS)
- LOGREC symptom records that point to track group allocation or purge problems.

Not all symptom records warrant your use of SPOOL=VALIDATE. Some of the symptom records are considered informational only. See *z/OS JES2 Diagnosis* for a list of the symptom records and an indication of their severity.

Immediate spool validation can then be useful as an immediate validation of the track group map in conjunction with ongoing track group validation cycle wherein all track groups are validated once every 7 days.


Modification: All-member warm start.

OUTCLASS(v) - SYSOUT Class Characteristics


The OUTCLASS(v) statement specifies the SYSOUT class characteristics for a specific output class (v), a range of output classes (v-vn), or a generic range (v-*) of output classes. Valid class specifications are A-Z and 0-9.

Note: If you modify OUTCLASS(v) parameter values and then restart JES2 with a hot start, the parameter values in effect before termination will be used.


Format Description for OUTCLASS(v)



Modification keywords



Selection limiting keywords



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for OUTCLASS(v)

BLNKTRNC=Yes|No

Specifies whether (Yes) or not (No) JES2 truncates trailing blanks for non-page-mode data sets in this output class. Specifying BLNKTRNC=Yes for all non-page-mode data sets provides a significant saving in spool volume space. Non-page-mode data sets include line-mode data printed on PSF printers. If you specify this parameter for composed-text page data sets (for example, output created by the Document Composition Facility), it has no effect. Note that the PRMODE= parameter, on both the JCL and JES2 output device initialization statements, does not affect blank truncation.

Specify BLNKTRNC=No for:

- Data sets that require right-hand blank padding to print properly.
- Data sets containing double-byte font characters.
- Output JES2 writes to JES2 spool. (JES2 will still truncate trailing blanks in RJE data transmissions.)

Performance Considerations: Specify BLNKTRNC=Yes (or permit this parameter to default) for all non-page-mode data sets to provide a significant saving in spool volume space.

Modification: Single-member warm start.

COMPRESS={No|Yes}

Specifies whether (Yes) or (No) JES2 writes compressed data to data sets in this output class.

Performance Considerations: Specify COMPRESS=Yes for data sets to provide a significant saving in spool volume space.

Modification: Single-member warm start.

OUTDisp=([normal][,abnormal])|(WRITE,WRITE)

Specifies the default output disposition for the SYSOUT data sets in this class, depending on the successful completion of the job.

normal

Specifies the output disposition if the job does not abend.

abnormal

Specifies the output disposition if the job abends.

Valid output dispositions are:

HOLD

Hold the output. JES2 does not process the output until you either change the disposition to WRITE or KEEP, or release the output. When the output is released, the disposition changes to WRITE.

Note: This specification is honored when the output reaches the destination node.

KEEP

Process the output then keep a copy of it on spool. After processing, the disposition of this output becomes LEAVE.

LEAVE

JES2 does not process the output until you change the disposition to WRITE or KEEP, or release the output. When the output is released, the disposition changes to KEEP.

PURGE

Purge the output immediately.

WRITE

Process the output then purge it.

See *z/OS JES2 Initialization and Tuning Guide* for more information about specifying output disposition and how JES2 determines output disposition defaults.

Modification: Operator command. If you modify this parameter value and then restart JES2 with a hot start, the parameter value in effect before termination will be used.

OUTPUT=PUNCH|PRINT|DUMMY

Any class may be specified for either print or punch. This parameter defines the installation's standard for output classes so that appropriate print and punch accounting can be maintained. PUNCH specifies that this output class normally is to be punched. DUMMY specifies that JES2 is to process this output class as a dummy data set (the class will still be allocated spool space but will be marked nonprintable to JES2).

If you do not specify this parameter, JES2 specifies that this output class normally is printed. For classes B and K, however, JES2 specifies that this output class normally is punched.

Modification: Single-member warm start.

Note: Users of the TSO/E Interactive Data Transmission Facility should not use the parameter default of PRINT, rather these users should set the parameter to PUNCH in order that incoming files are correctly recognized.

TRKCELL=Yes|No

TRKCELL=Yes specifies that physical records of each data set of this SYSOUT class are to be specially grouped on the spool volume(s), and are to be read from the spool volume in blocks. (See the TRKCELL= parameter on the SPOOLDEF statement for additional information.)


Performance Considerations: Specify track ceiling (TRKCELL=Yes) for all SYSOUT classes processed by 3800 printers to increase device performance.

Modification: Single-member warm start.

OUTDEF - Job Output Definition

The OUTDEF statement defines the job output characteristics of the JES2 member.

Format Description for OUTDEF



Notes:

¹ Omit the comma between initialization statement and first keyword

Restriction: JOE Index optimization can only be enabled by operator command.

Parameter Description for OUTDEF

Note: The BROADCAST parameter is obsolete. JES2 OUTDEF processing always processes as if BROADCAST=YES is in effect.

COPIES=nnn|255

Specifies the maximum number (1-255) of job output copies that can be requested in the accounting field of your JOB statement or on a /*JOBPARM control statement. If the number of copies requested is greater than the value of COPIES, the request is reduced to the value of COPIES. No error message is produced. The setting of this parameter does not affect requests for multiple copies of data sets through the JCL OUTPUT or DD statements or /*OUTPUT control statement.

Modification: \$T OUTDEF operator command.

DMNDSET=Yes|No

Specifies whether inline printer setup is allowed for data sets whose SYSOUT class matches the job message class.

If DMNDSET=Yes, all SYSOUT data sets that are not specified for special processing in any other way (for example, HOLD) and whose class matches the message class, are printed on one printer with appropriate setup messages to the operator as the data sets are printed.

If DMNDSET=No is specified or if the SYSOUT class does not match the message class, separate class work queues are created for each unique setup required. Thus, data sets can be printed simultaneously on all printers available, or deferred until a printer is set up to process all work for the separate class.

See the USERSET= parameter on this statement and *z/OS JES2 Initialization and Tuning Guide* for a discussion of the interrelationship of these two parameters.

Modification: Single-member warm start.

DSLIMIT=10M|4B

The SPOOL data set limit of 10M specifies that any job is limited to 10 Million (9999999) SPOOL data sets for the entire lifetime of the job. After this limit is reached, attempts to create additional SPOOL data sets will fail. Specifying DSLIMIT=4B allows jobs to create additional SPOOL data sets—up to 4 Billion (4294967296) data sets.

Note: The DSLIMIT setting does not have any effect on the first 10M (9,999,999) SPOOL data sets that are created by a job.

Modification: \$T OUTDEF operator command.

JOENUM=nnnnnn

Specifies the number (must be no greater than 2,500,000) of job output elements (JOEs) to be generated. JOEs are required for unique combinations of:

- SYSOUT class, set up characteristics, process mode, and other output criteria that appear in a job that is queued for output whether the SYSOUT is in held status or ready to be printed.
- Forms ID, UCS ID, and FCB ID, and groupid for all jobs currently queued for output.

When determining the number of JOEs, remember that multiple JOEs can be concurrently active for the 3800 printer's output, and that a JOE is not freed until the 3800 stacks its associated output.

Note: Use this parameter to increase the limit for the JNUM resource that is reported on the HASP050 message.

Performance Considerations: If the value specified for JOENUM= is too small, jobs wait a considerable time for printing. Although a value as small as 10 is accepted; a value smaller than the default degrades throughput. (JES2 calculates the default as the JOBNUM= parameter value on the JOBDEF initialization statement times 2.5.) If the value is too large, the processor time and the number of page faults needed to search the elements increases. The default value should keep printers and punches busy without tying up too much virtual storage. As a rough approximation, you can determine the starting value of JOEs per job as twice the number of output classes per job. (For further discussion of the factors affecting the number of job output elements, see *z/OS JES2 Initialization and Tuning Guide*.)

If you use the \$T OUTDEF command to increase JOENUM=, only do so when you can allow your system to experience temporary performance degradation while all JES2 systems read the checkpoint data set.

Modification: \$T OUTDEF operator command to increase or decrease the number of JOEs.

JOEWARN=nnn|80

Specifies the percentage (1–99) of use of job output elements at which the operator is alerted through message \$HASP050. If you specify 0, no alert is given.

Modification: \$T OUTDEF operator command. Note that this parameter cannot be modified through a hot start, quick start, or single-member warm start.

LDEV_OPT=NO|YES

Enables (Yes) or disables (No) POST output work selection optimization for local JES2 managed devices (printers and punches). For details see *z/OS JES2 Initialization and Tuning Guide*.

YES

Enables POST work selection optimization for local devices.

NO

Disables POST output work selection optimization for local devices. POST code reverts to the z/OS version 2.1 level of JES2 work selection processing.

Modification: \$T OUTDEF operator command.

Scope: Single Member.

OUTTIME=CREATE|UPDATE

Specifies whether JES2 saves the time stamp that indicates the creation time of an output's JOE, or whether it instead saves the time when the JOE was last updated. You can use a \$O command to change the disposition of all output based on the time that is elapsed between the current time and the JOE time. Changing held output's disposition based on its age releases spool space and job queue elements (JQEs) occupied by output that is no longer needed. For more information on the \$O command, see [z/OS JES2 Commands](#).

CREATE

JES2 fills in the JOE time only when the job creates the output.

UPDATE

JES2 updates the JOE time every time the JOE is updated.

Modification: \$T OUTDEF operator command.

PRTYHIGH=nnn|255

Specifies the upper priority limit (0-255) to be associated with the JES2 job priority aging feature. A job's output is not priority-aged if its priority is (or becomes) greater than or equal to the value specified in this parameter. If the job is on the \$HARDCPY queue, the job queue element is not aged; only the job output element is aged.

Modification: \$T OUTDEF operator command. Note that this parameter cannot be modified through a hot start, quick start, or single-member warm start.

PRTYLOW=nnn|0

Specifies the lower priority limit (0-255) to be associated with the JES2 job priority-aging feature. A job's output is not priority-aged unless its priority is initially equal to or greater than this value. If the job is on the \$HARDCPY queue, the job queue element is not aged; only the job output element is aged. (See the PRYORATE= parameter; the PRYORATE= specification controls the priority aging rate of jobs scheduled for execution and output.)

Modification: \$T OUTDEF operator command. Note that this parameter cannot be modified through a hot start, quick start, or single-member warm start.

PRTYOUT=Yes|No

Specifies whether the priority specification (PRTY= keyword) on the JCL OUTPUT statement is supported (Yes) or ignored (No).

Modification: \$T OUTDEF operator command.

PRYORATE=nnnn|0

Specifies the number (0-1440) of time periods into which a 24-hour day is to be divided for use in increasing a job's output priority by the JES2 output priority-aging feature.

For example, if 3 is specified, a job's output priority is increased by one for every 8 hours it remains in the system. However, a job's output priority is not increased unless it is at least equal to the value specified in the PRTYLOW= parameter; nor is a job's output priority be increased above the value that is specified in the PRTYHIGH= parameter. If 0 is specified, the values that are specified in the PRTYLOW= and PRTYHIGH= parameters are ignored. See [z/OS JES2 Initialization and Tuning Guide](#) for a discussion of output priority aging.

Modification: \$T OUTDEF operator command. Note that this parameter cannot be modified through a hot start, quick start, or single-member warm start.

OUTPRTY(n)

SAPI_OPT={No|Yes}

Enables (Yes) or disables (No) SAPI POST work selection optimization. For details see [z/OS JES2 Initialization and Tuning Guide](#).

No

Disables SAPI POST work selection optimization. POST code reverts to the z/OS version 1.13 level of JES2 work selection processing.

Yes

Enables SAPI POST work selection optimization.

Modification: \$T OUTDEF operator command.

Scope: Single Member.

SEGLIM=nnnnn|100

Specifies the maximum number of output segments (1-99999) JES2 creates for a SYSOUT data set. When the number of segments exceeds this number, JES2 no longer segments the SYSOUT. SEGLIM=1 prohibits SYSOUT segmentation. SEGLIM=99999 allows practically unlimited SYSOUT segmentation. See [z/OS JES2 Initialization and Tuning Guide](#) for more information about dividing output into segments.

Modification: \$T OUTDEF operator command. If you modify this parameter value and then restart JES2 with a hot start, the parameter value in effect before termination is used.

STDFORM=vvvvvvv|STD

Specifies a 1- to 8-character identifier to be used as a default forms ID when a forms ID is not specified. It also specifies the default initial setup of all printers and punches at JES2 initialization.

Note: Special characters (for example, the period (.)) are not allowed.

Modification: Single-member warm start.

USERSET=Yes|No


Specifies whether the user is permitted (Yes) or not permitted (No) to create demand setup JOEs through use of the JCL OUTPUT statement. If Yes is specified, JES2 forms demand setup output groups according to the user's definition. See the DMNDSET= parameter on this statement and [z/OS JES2 Initialization and Tuning Guide](#) for the relationship between this parameter and user-defined output data set groups.

Modification: Single-member warm start.


OUTPRTY(n) - Job Output Priority

The OUTPRTY(n) statement defines the association between the job output scheduling priorities and the quantity (records or pages) of output. Specify n in OUTPRTY(n) as a value, 1 through 9.

Format Description for OUTPRTY(n)



Modification keywords



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for OUTPRTY(n)

PAGE =nnnnnnnn

Specifies the output page counts (1-16777215) that are associated with the priorities specified in the PRIORITY= parameter.

See the TIME= parameter on the JOBPRTY(n) statement and the PRIORITY= parameter on this statement for additional information.

If this parameter is not specified, the following are used as default values:

OUTPRTY(n)	PRIORITY=	RECORD=	PAGE=
(1)	144	2000	50
(2)	128	5000	100
(3)	112	15000	300
(4)	96	16777215	16777215
(5)	80	.	.
(6)	64	.	.
(7)	48	.	.
(8)	32	.	.
(9)	16	16777215	16777215

Modification: \$T OUTPRTY(n) Operator command.

PRIORITY =nnnn

Specifies the output selection priority (0-255) for the output interval specified by the corresponding RECORD= and PAGE= parameters. When job output elements (JOEs) are built for a job, each JOE is assigned a priority based on the total number of output lines, cards, or pages represented by the JOE.

- If a JOE represents a total of "t" lines or cards, the JOE's priority is PRIORITY(ln), where *ln* is the smallest number for which $t \leq \text{RECORD}$.
- If a JOE represents a total of "t" pages, the JOE's priority is PRIORITY(pg), where *pg* is the smallest number for which $t \leq \text{PAGE}$.

OUTPRTY(n)

- If a JOE represents a combination of both line and page data, the JOE's priority will be computed by the following formula:

$$\frac{PRIORITY(l_n) + PRIORITY(pg)}{2}$$

Where:

PRIORITY(l_n) = the output selection priority calculated for the output line count

PRIORITY(pg) = the output selection priority calculated for the output page count

Fractions are truncated for the calculated priority value.

If you override all nine OUTPRTY(n) values and any output exceeds all RECORD= or PAGE= values you specify, JES2 assigns that output the lowest priority (0). You should specify at least one OUTPRTY(n) to handle extremely large output such as the defaults for OUTPRTY(4) through OUTPRTY(9). See the RECORD= and PAGE= parameters on this statement for additional information.

If this parameter is not specified, the following are used as default values:

OUTPRTY(n)	PRIORITY=	RECORD=	PAGE=
(1)	144	2000	50
(2)	128	5000	100
(3)	112	15000	300
(4)	96	16777215	16777215
(5)	80	.	.
(6)	64	.	.
(7)	48	.	.
(8)	32	.	.
(9)	16	16777215	16777215

Modification: \$T OUTPRTY(n) operator command.

RECORD =nnnnnnnn

Specifies the output line counts (1-16777215) that are associated with the priorities specified in the PRIORITY parameter.

See the PRIORITY= parameter above for additional information.

If this parameter is not specified, the following are used as default values:

OUTPRTY(n)	PRIORITY=	RECORD=	PAGE=
(1)	144	2000	50
(2)	128	5000	100
(3)	112	15000	300
(4)	96	16777215	16777215
(5)	80	.	.
(6)	64	.	.
(7)	48	.	.
(8)	32	.	.


OUTPRTY(n)	PRIORITY=	RECORD=	PAGE=
(9)	16	16777215	16777215

Modification: \$T OUTPRTY(n) operator command.

PCEDEF - Processor Control Element Definition

The PCEDEF statement defines the number of processors for certain JES2 functions.

Format Description for PCEDEF



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for PCEDEF

CNVTNUM=nn|10

Specifies the number (1-25) of converter processors defined to JES2.

Considerations: Specifying 2 or more conversion processors alleviates constraints in converter processing. However, when you define multiple converter PCEs, or if you accept the default of ten converter PCEs, jobs will not always be queued for execution in the order in which they were submitted. Setting CNVTNUM=1 can be a way to run jobs in the order in which they were submitted; either you must have a single member MAS to do this or if you have a multi-member MAS, the system affinity of each job must be the same. With CNVTNUM=1, the system can "hang" depending on the characteristics of the job stream. See *z/OS JES2 Initialization and Tuning Guide* for more information on job queuing and how to control job execution sequence.

Modification: Hot start.

OUTNUM=nn|10

Specifies the number (1-25) of output processors defined to JES2.

Performance Considerations: To alleviate constraint in output processing, use this parameter to define up to 10 output processors (PCEs) per JES2 member. This will provide improved throughput of JES2 output processing if output queuing is constrained. The use of multiple output processors causes JES2 to build more JOEs per unit of time, further increasing checkpoint I/O efficiency. JES2 will, however, consume more system resources (JES2 buffers, processor cycles, and spool I/O) in a shortened period of time.

Modification: Hot start.

PSO NUM=nn|2

Specifies the number (1-10) of PSO processors defined to JES2.

Modification: Hot start.

PURGENUM=nn|10

Specifies the number (1-25) of purge processors defined to JES2.

The number of purge processors specified affects the calculation of the number of SMF buffers specified by the BUFNUM parameter on the SMFDEF statement. See page “[Parameter Description for SMFDEF](#)” on page 405 for a description of the BUFNUM parameter.

Modification: Hot start.

SPINNUM=nn|3

Specifies the number (3-10) of spin processors defined to JES2.

Modification: Hot start.

STACNUM=nn|2

Specifies the number (1-10) of TSO/E STATUS/CANCEL processors defined to JES2.



Modification: Hot start.

POLICYLIB(xxxxxxx) - Define a concatenation for JES2 policy import

The POLICYLIB(xxxxxxx) statement defines a data set concatenation to be used as a source for importing external definition of JES2 policies. For more information, see [\\$POLICY IMPORT - Import new JES2 policy](#) in *z/OS JES2 Commands*.

The statement ensures that only the data sets specified can be allocated. It does not ensure that they exist or can be opened and are usable. That processing occurs when the \$POLICY IMPORT command is started.

Format Description for POLICYLIB(xxxxxxx)

Syntax**Modification keywords**

Parameter Description for POLICYLIB(xxxxxxxx)

(policylib)

Specifies the 1-8 character DD name of a POLICYLIB concatenation to be defined.

Modification

\$T POLICYLIB(xxxxxxxx) command, warm start, or hot start.

DD(nnn)=

Specifies up to 255 data sets to be concatenated for this POLICYLIB DD name. Data sets in this list are compacted after each initialization statement is processed. If you specify DD(1), DD(20), and DD(100) for a new POLICYLIB concatenation, the resulting concatenation has DD(1), DD(2), and DD(3). Though up to 255 data sets can be specified, MVS rules limit any data set concatenation to 255 extents. If any data set has more than one extent, then the total number of data sets that can be supported are reduced.

Modification

\$T POLICYLIB(xxxxxxxx) command, warm start, or hot start.

DSName=dsname

Specifies a 1-44 character data set name which JES2 includes in this POLICYLIB concatenation. This data set name must specify a partitioned data set (PDS).

Modification

\$T POLICYLIB(xxxxxxxx) command, warm start, or hot start.

PATH=pathname

Specifies a 1-88 character path name which JES2 includes in this POLICYLIB concatenation. This path name must specify a directory in MVS zFS file system.

Modification

\$T POLICYLIB(xxxxxxxx) command, warm start, or hot start.

UNIT=hhhh/|hhhh|nnnn|cccccccc

If the POLICYLIB data set to be used is not cataloged, then the unit information for the device that contains the data set must be specified in one of the following ways:

hhhh/|hhhh

Specifies a 3 or 4-digit hexadecimal device number. Any of the following formats can specify device numbers:

- UNIT=hhh
- UNIT=/hhh
- UNIT=/hhhh

hhh and hhhh represent the device numbers. A slash (/) must precede a 4-digit device number.

nnnn

Specifies a device name.

cccccccc

Specifies a 1 to 8 character group name that is assigned to the device or group of devices that contained the noncataloged POLICYLIB data set to be used.

Modification

\$T POLICYLIB(xxxxxxxx) command, warm start, or hot start.

VOLser=xxxxxx

If the POLICYLIB data set to be used is not cataloged, then **VOLser** specifies a 1 - 6 character volume serial number on which the data set resides.

Modification

\$T POLICYLIB(xxxxxxxx) command, warm start, or hot start.

UNCONDitional

Specifies what action is taken if one of the data sets cannot be allocated. If **UNCONDitional** is not specified, then if any data set cannot be allocated, the entire statement fails. If **UNCONDitional**

is specified, then an error that allocates a single data set is ignored. The data set is not added to the concatenation, but it remains assigned to the DD(nnn). If the concatenation is displayed, failed DD(nnn) displays the text 'ALLOCATION FAILED' before the data set name. If all data sets in a concatenation fail to allocate, then the statement fails regardless of whether **UNCONDitional** was specified.


Modification

\$T POLICYLIB(xxxxxxxx) command, warm start, or hot start.

PRINTDEF - Local Print Environment Definition

The PRINTDEF statement defines the JES2 print environment.

Format Description for PRINTDEF



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for PRINTDEF

CCWNUM=nnn

Specifies the maximum number (1-233) of channel command words (CCWs) to be used per channel program area for local impact printers.

Performance Considerations: The value of CCWNUM= should be chosen such that all print lines in a spool buffer can normally be printed with a single channel command chain. Compute this value from the following formula:

$$\text{CCWNUM} = (\text{BUFSIZE= parameter on SPOOLDEF}) / \text{average line length}$$

Estimate the average line length, allowing for truncation of trailing blanks by JES2.

If the value is too small, the number of EXCPs (and therefore the processor time) for printing is increased. If, however, the value is excessive, the size of the address space is unnecessarily increased.

Note: This value is ignored for 3800 printers. JES2 uses a CCW area that has a fixed size for 3800 printers.

If you do not specify a value for this parameter, JES2 specifies one using the following algorithm:

$$\text{CCWNUM} = (\text{BUFSIZE= parameter on SPOOLDEF}) / 80$$

Modification: Single-member warm start.

DBLBUFR=Yes|No

Specifies whether or not double buffering is to be used for local printers. Double buffering can improve performance by allowing an installation to perform read and write operations concurrently. The DBLBUFR= parameter is ignored by printers operating under the control of a functional subsystem.

Modification: Single-member warm start.

FCB=xxxx|6

Specifies the name of the forms control buffer (FCB) image or the carriage control tape that JES2 initially assumes is mounted on every impact printer. FCB is a 1- to 4-character name that is valid in SYS1.IMAGELIB. The forms control buffer identifier can be modified for each printer by means of the PRT(nnnn) statement or the JES2 \$T command. If this FCB is to be a default FCB, the image in SYS1.IMAGELIB **must** have the default bit turned on.

Modification: Single-member warm start.

LINECT=nnn|61

Specifies the maximum number (0-254) of lines to be printed per page on job output. This value is used if you do not specify a value for a line count in the accounting field of your JOB statement, on a /*JOBPARM control statement, on the /*OUTPUT control statement, or on the JCL OUTPUT statement.

- **For MODE=JES printers:** Table 93 on page 299 shows the interaction and overriding order that JES2 uses when determining the number of lines it will use when writing a checkpoint record for printers set to MODE=JES (that is, non-FSS-mode printers).

Table 93. Interaction of PRINTDEF and PRT(n) parameters that JES2 uses to calculate the output checkpoint interval

PRINTDEF LINECT=	PRT(n) CKPTLINE=	"Lines" Setting JES2 Uses to Calculate Checkpoint
> 0	0 (or defaulted)	PRINTDEF LINECT= value
> 0	> LINECT=	PRINTDEF LINECT= value ¹
	< LINECT=	PRT(n) CKPTLINE= value ¹
0	>0	PRT(n) CKPTLINE= value

¹and if CKPTPAGE=>0, then JES2 calculates total checkpoint lines to be the product of this value times the CKPTPAGE= value

- **For MODE=FSS printers:**

- If you set CKPTMODE= on PRT(nnnnn), JES2 uses that value to determine if checkpoints are taken based on page count or time.
- If you set CKPTSEC= on PRT(nnnnn) or allow the default of 0, and CKPTMODE=SEC, this value sets the number of seconds before taking an output checkpoint.

Note: A 3800 printer will not print more than 60 lines per 11-inch page at 6 lines per inch or 80 lines per 11-inch page at 8 lines per inch.

LINECT=0 causes automatic page overflow (normally standard in JES2) to be suppressed unless overridden by the JOB statement accounting parameter or a /*JOBPARM control statement specification.

If a print data set is generated without any ejects (that is, no skips or any channel in the carriage tape), and if 0 is specified in this parameter, or any of the following: the JOB statement accounting field, a /*JOBPARM control statement, the /*OUTPUT control statement, or the JCL OUTPUT statement, the data set is treated as one page when it is advanced, backspaced, interrupted, or warm started while printing.

Modification: \$T PRINTDEF operator command.

NEWPAGE={1|ALL}

Specifies how a 'skip to channel' is counted as a new page. This is the global specification for any local or remote printer that either:

- Does not specify NEWPAGE= on its PRT(nnnn) initialization statement
- or --
- Specifies NEWPAGE=DEFAULT on its PRT(nnnn) initialization statement.

1

Specifies that JES2 treats only skip-to-channel-1 as a new page.

ALL

Specifies that JES2 treats skip-to-any-channel as a new page.

Modification: \$T PRINTDEF operator command.

NIFCB=xxxx

Specifies the name of both the forms control buffer image that JES2 initially loads into every non-impact printer and the installation's default FCB for data sets that do not explicitly request an FCB when printed on an non-impact printer. NIFCB is a 1- to 4-character name that is a valid name in SYS1.IMAGELIB. The FCB identifier can be modified for an individual printer by means of the PRT(nnnn) statement or the JES2 \$T command.

If you do not specify a value for this parameter, forms control is unspecified.

Modification: Single-member warm start.

NIFLASH=xxxx

Specifies the 1- to 4-character name of the initial and default forms flash ID. On printers having a forms flash ID, JES2 will use this default for data sets that do not specify a forms flash ID. The user can override the forms flashing feature by explicitly requesting forms flashing through the JCL DD statement with the SYSOUT parameters, JES2 /*OUTPUT control statement, the JCL OUTPUT statement or, for individual printers through the PRT(nnnn) initialization statement. By specifying 'NONE' as the forms flashing ID, forms flashing is disabled.

Note: If a PAGEDEF= keyword is specified on the JCL OUTPUT statement, the FLASH= parameter on the PRT(nnnn) statement is ignored if the data set is printed on a printer running under the control of a functional subsystem.

If you do not specify a value, forms flashing is unspecified.

Modification: Single-member warm start.

NIUCS=vvvvnnnn|GF10

Specifies the name of both the character arrangement table that JES2 initially loads into every 3800 printer and the installation's default character arrangement table that is loaded into the printer for data sets that do not specify a character arrangement table. The last position of the writable character generation module (WCGM) in the default table, is reserved for the JES2 member; it must not be used. NIUCS is a 1- to 8-character name that is valid in SYS1.IMAGELIB. The character arrangement table can be modified for an individual printer by means of the PRT(nnnn) statement or the JES2 \$T command.

Modification: Single-member warm start.

RDBLBUFR=Yes|No

Specifies whether double (Yes) or single (No) buffering is to be used for remote printers.

Modification: Single-member warm start.

Note: The specification refers to JES2 regular I/O buffers, not to JES2 teleprocessing buffers.

SEPPAGE=([LOCAL=pgtype][,REMOTE=pgtype]) | LOCAL=DOUBLE, REMOTE=HALF)

Specifies the type of separator page JES2 produces on local and remote printers. The values for *pgtype* are:

NONE

Suppress the separator page. However, JES2 still prints the JESNEWS data set when the user's security profile allows.

HALF

Print only the detail box information.

FULL

Print one full separator page, including jobname and jobid in block letters.

DOUBLE

Print two full separator pages, including jobname and jobid in block letters.

Modification: \$T PRINTDEF operator Command.

TRANS=Yes|No

Specifies whether (Yes) or not (No) character translation is to be used for local and remote printers. Character translation causes JES2 to convert lowercase letters to uppercase and change characters that are unprintable on PN trains to blanks unless an installation supplies its own translation tables using installation Exit 15. You can override this specification for a specific printer by specifying the TRANS= parameter on a PRT(nnnn) or R(nnnn).PR(m) statement.

You can also use installation Exit 15 (Output Data Set/Copy Select) to examine or change translation for data sets, and specify custom print character and CCW translation tables. See [z/OS JES2 Installation Exits](#) for information about controlling character and channel control word (CCW) translation using installation Exit 15.

Note:

1. You can use the TRANS= parameter on the PRINTDEF statement to enable character translation for local printers except IBM 3211, IBM 3203, or FSS-mode printers. You can use the TRANS= parameter on the PRT or R(nnnn).PR(m) statement to enable character translation for any non-FSS printer, including IBM 3211 or IBM 3203 printers.
2. For BSC remote printers attached to non-programmable terminals, translation occurs as above if TRANS=Yes; if TRANS=No, JES2 translates non-valid characters to blanks.
3. For BSC remote printers attached to programmable terminals, translation occurs as above if TRANS=Yes. If TRANS=No, translation of incorrect characters to blanks occurs if the remote terminal is defined as not having the transparency feature.
4. For SNA remote printers, JES2 does translation as above if TRANS=Yes; if TRANS=No, JES2 does no translation. **All** characters are considered to be valid, including binary zeros.

Modification: Single-member warm start.

UCS=vvvv|0

Specifies the name of the print chain, print train, or print band default character set that is mounted on every impact printer for which a specific universal character set (UCS) image is not specified. An alternate UCS image can be specified for individual local printers through the UCS= keyword on the PRT(nnnn) initialization statement or modified through the JES2 \$T PRTnnnn command. For remote printers, an alternate UCS image can be specified through the R(nnnn).PR(m) initialization statement or modified with the JES2 \$T Rnnnn.PRm command.

UCS is a 1- to 4-character name that is valid in SYS1.IMAGELIB. If 0 is specified, JES2 bypasses the UCS loading procedure until a job that requires a specific UCS image is processed. If an incorrect specification is encountered, the UCS loading procedure is bypassed, and a setup message is issued to allow specification of a valid image.

Modification: Single-member warm start.

PROCLIB(xxxxxxxx) - Dynamic PROCLIB definition

The PROCLIB(xxxxxxxx) statement defines a dynamic PROCLIB concatenation to be used during conversion processing for jobs on this member. These concatenations can be added, updated, or deleted through operator commands. Dynamic PROCLIB can override PROCxx DDs in the JES2 start PROC but cannot alter or delete them.

The PROCLIB parameter is primed with the static PROCLIB concatenations from the JES2 PROC. PROCLIB(xxxxxxxx) initialization statements that reference the same DD name as a static PROCLIB DD will create a new dynamic PROCLIB but no data sets will be copied from the static PROCLIB. The dynamic PROCLIB concatenation overrides the static PROCLIB.


Note: PROCLIB statement processing only ensures that the data sets specified can be allocated. It does not ensure that they actually exist or can be opened and used as a PROCLIB data set. That processing occurs when the PROCLIB is used by a job during conversion processing.


Table 94 on page 302 describes PROCLIB commands and their results under various scenarios.

Table 94. PROCLIB commands and results. PROCLIB commands and results		
Action	Existing PROCLIB	Results
\$ADD PROCLIB	None	New dynamic PROCLIB added
\$ADD PROCLIB	Dynamic PROCLIB	Error, a dynamic PROCLIB exists
\$ADD PROCLIB	Static PROCLIB	New dynamic PROCLIB created, no data sets copied from the static PROCLIB
\$T PROCLIB	None	Error, no selectable entries to modify
\$T PROCLIB	Dynamic PROCLIB	Appropriate DD entries are modified (starts with existing DDs and makes updates to build a new concatenation)
\$T PROCLIB	Static PROCLIB	A new dynamic PROCLIB is created by copying the existing DDs from the static concatenation to the new dynamic PROCLIB and then makes updates to build a new concatenation
\$DEL PROCLIB	None	Error, no selectable entry to delete


Table 94. PROCLIB commands and results. PROCLIB commands and results (continued)		
Action	Existing PROCLIB	Results
\$DEL PROCLIB	Dynamic PROCLIB	Dynamic PROCLIB is deleted. If there is a static PROCLIB with the same subscript as the dynamic PROCLIB, it becomes active again
\$DEL PROCLIB	Static PROCLIB	Error, cannot delete static PROCLIB

Format Description for PROCLIB





Data Set Selection Criteria



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter description for PROCLIB

xxxxxxx

Specifies the 1-8 character PROCLIB DD name being defined. DD names can be referenced on the JOBCCLASS PROCLIB= statement, the JECL /*JOBPARM PROCLIB= statement and the JCL JCLLIB PROCLIB= statement. If this name matches a DD name in the JES2 start PROC, then this PROCLIB concatenation will be used instead of the one in the JES2 start PROC.

If the PROCLIB DD name matches a static PROCLIB DD name from the JES2 PROC, the PROCLIB statement will logically alter the existing static PROCLIB, not replace it.

Modification: \$T PROCLIB(xxxxxxxx) command, warm start or hot start.

DD(nnn)=

Specifies up to 255 data sets to be concatenated to this PROCLIB DD name. Data sets in this list are compacted after each initialization statement is processed. If you specify DD(1), DD(20), and DD(100) for a new PROCLIB concatenation, the resulting concatenation will be renamed to DD(1), DD(2,) and DD(3). If you then set the data set name for DD(2) to null, JES2 will remove it from the concatenation leaving just DD(1) and DD(2) where DD(2) has the old DD(3) data set specification. Though up to 255 data sets can be specified, MVS rules limit any data set concatenation to 255 extents. If any data set has more than one extent, then the total number of data sets that can be supported will be reduced.

Modification: \$T PROCLIB(xxxxxxxx) command, warm start or hot start.

DSName=jxxx...x

Specifies a 1-44 character data set name which JES2 will include in this PROCLIB concatenation. This data set must be a partitioned data set (PDS). If this value is coded as null (no operand specified), then the DD(nnn) will be deleted from an existing concatenation.

Modification: \$T PROCLIB(xxxxxxxx) command, warm start or hot start.

UNIT=hhhh|/hhhh|nnnn|cccccccc

If the PROCLIB data set to be used is not cataloged, then you must specify the unit information for the device containing the data set in one of the following ways:

hhhh | /hhhh

specifies a 3 or 4 digit hexadecimal device number. Device numbers can be specified in one of the following formats:

- UNIT=hhh
- UNIT=/hhh
- UNIT=/hhhh

where hhh and hhhh represent the device numbers. A slash (/) must precede a 4 digit device number.

nnnn

Specifies a device name.

cccccccc

Specifies a 1-8 character group name assigned to the device or group of devices that contained the non-cataloged initialization data set to be included.

Modification: \$T PROCLIB(xxxxxxxx) command, warm start or hot start.

VOLser=xxxxxx

If the PROCLIB data set to be used is not cataloged, then this specifies a 1-6 character volume serial number on which the data set resides.

Modification: \$T PROCLIB(xxxxxxxx) command, warm start or hot start.

UNCONDitional|CONDitional

Specifies what action JES2 should take if one of the data sets cannot be allocated. If CONDitional is specified (or defaulted) then if any data set cannot be allocated, the entire statement fails. The system will go into console mode to allow the operator to correct the statement. If UNCONDitional is specified, then an error allocating a single data set is ignored. The data set is not added to the concatenation but it remains assigned to the DD(nnn). If the concatenation is displayed, failed DD(nnn) will display the text 'ALLOCATION FAILED' before the data set name. If all the data sets in a concatenation fail to allocate, then the statement fails regardless of whether UNCONDitional was specified.

Modification: \$T PROCLIB(xxxxxxxx) command, warm start or hot start.

PRT(nnnnn)

NAME=xxxxxxx

Intended mostly for \$T command, NAME= allows the name of a dynamic PROCLIB concatenation to be changed. For example, specifying PROCLIB(TEST01) NAME=PROC01 renames the TEST01 PROCLIB concatenation to PROC01.

You cannot rename a static PROCLIB. If a static PROCLIB is overridden by a dynamic PROCLIB, renaming the dynamic PROCLIB will restore the static PROCLIB. In the above example, if PROC01 started as a static PROCLIB, and TEST01 was renamed PROC01, then the statement PROCLIB(PROC01) NAME=TEST01 would rename the dynamic PROCLIB back to TEST01 and restore to active status the static PROC01 concatenation.

Modification: \$T PROCLIB(xxxxxxx) command, warm start or hot start.

PRT(nnnnn) - Local Printer


The PRT(nnnnn) statement specifies the characteristics of one local printer. Each printer device is defined by a PRT(nnnnn) statement with a unique value (1-32767) specified for nnnnn. Printer characteristics are defined by the following parameters.

Use the subscript to define printers individually (nnnnn), in an ascending range (n-*) to indicate from n to 32767 or, in a descending range (*-n) to indicate 32767 to n, or * to indicate all printers.


Adding Printer Attributes

This statement and all its parameters (except START=) can be added after initialization with the **\$ADD PRT(nnnnn) operator command**.

Format Description for PRT(nnnnn)









Modification keywords




Notes:

¹ Omit the comma between initialization statement and first keyword

² *Forms* can be coded up to 8 times








Notes:


¹ *PRMode* can be coded up to 8 times

Selection limiting keywords









Notes:

¹ *form* can be coded up to 8 times

Parameter Description for PRT(nnnnn) (All Printers)

CKPTLINE=nnnnnn|0

Specifies the maximum number of lines (0-32767) in a logical page. JES2 uses this value, the CKPTPAGE= parameter on this statement, and the LINECT= parameter on the PRINTDEF, to determine when to take output checkpoints as follows:

JES2 compares the "line count values" you specified on the PRINTDEF LINECT= and PRT(n) CKPTLINE= parameters and then always uses the lesser value.

Checkpoint Interval = *line count* * CKPTPAGE (if non-zero)

where *line count* is either:

- CKPTLINE if CKPTLINE < LINECT
hence **Checkpoint Interval = CKPTLINE * CKPTPAGE (if non-zero)**
- LINECT if CKPTLINE > LINECT
hence **Checkpoint Interval = LINECT * CKPTPAGE (if non-zero).**

The size of a logical page is also defined as the number of lines printed until:

- A channel skip is encountered
- The line count specified by the LINECT= parameter on the PRINTDEF statement, the /*JOBPARM control statement, the JCL OUTPUT statement, or the JOB statement accounting field has been exceeded.

Note: This operand is ignored if specified for a printer under the control of a functional subsystem. The functional subsystem does its own physical and logical pages checkpoint based on the CKPTPAGE and CKPTSEC values passed to it from JES2.

Modification: \$T PRTnnnnn operator command.

CKPTPAGE=nnnnnn|100

Specifies the number (1-32767) of logical pages for non-page-mode printers and physical pages for page-mode printers to be printed before each checkpoint is taken. This parameter and CKPTLINE= control the amount of checkpoint activity to spool. Although the default is set to 100, a lower value is recommended for slow devices. However, too low a value will degrade performance; therefore, use Exit 15 to protect the JES2 member from users who may specify this value too low in a job. (For further information on Exit 15, see *z/OS JES2 Installation Exits*).

Note: If you code both CKPTPAGE= and CKPTSEC=, and code CKPTMODE=SEC, the CKPTSEC= specification overrides the CKPTPAGE= specification.

Performance Considerations: This parameter should be set low for slow devices and high for faster printers such as the 3800 to prevent excessive checkpoint cycles from occurring for faster devices.

Modification: \$T PRTnnnnn operator command.

Class | QUEUE=c1...cn|AJ

Specifies the output classes to be processed initially by this printer. You can specify any number of classes up to a maximum of 36 classes.

Modification: \$T PRTnnnnn operator command.

CREATOR=cccccccc

Specifies the 1- to 8-character userid whose output can be selected by this printer. Wildcard specifications are allowed on this parameter.

If this parameter is allowed to default, JES2 can select all output for processing, regardless of userid.

Modification: \$T PRTnnnnn operator command.

DEVFCB=xxxx

Specifies a 1- to 4-character name of the forms control buffer (FCB) this printer uses as the default if the printer selects output that does not have an FCB associated with it. If you do not specify DEVFCB=, the printer uses the last FCB that you loaded to process the output if that FCB has the default bit turned on. However, JES2 still determines the default FCB for 3800 printers as described in the FCB= parameter description if you do not specify DEVFCB=. Otherwise, the printer uses the NIFCB specified on the PRINTDEF statement.

Modification: \$T PRTnnnnn operator command.

FCB|C=xxxx

Specifies, for impact printers, the forms control buffer image or the carriage control tape that is to be initially mounted on this printer. For the 3800, xxxx specifies the name of both the FCB image that JES2 initially loads into the printer and the installation's default FCB image for data sets not specifying an FCB, unless you coded DEVFCB=.

For all printers, xxxx is the forms control buffer (FCB) identifier that resides in SYS1.IMAGELIB. If this FCB is to be a default FCB, the image in SYS1.IMAGELIB **must** have the default bit turned on. (For information about the 3800, see *Advanced Function Presentation: Printer Information*.)

If you do not specify this parameter, JES2 specifies a default based upon the type of printer.

- For impact printers, the identifier specified by the FCB= parameter on the PRINTDEF statement
- For 3800 printers, the identifier specified by the NIFCB= parameter on the PRINTDEF statement.
- FCB=RESET causes the printer to use the default FCB.

Modification: \$T PRTnnnnn operator command. For FSS-controlled printers only, if you modify this parameter value and then reconnect the printer on a hot start, the parameter value in effect before termination will be used.

Note: See *z/OS JES2 Initialization and Tuning Guide* for FCB format restrictions that apply to JES2 printers.

Forms=(xxxxxxx[,...])

Specifies the 1- to 8-character forms identifier that is to be initially loaded in this printer. Wildcard specifications are allowed on this parameter. You can supply up to eight different forms identifiers to be used as work selection criteria. If the device only supports one form, it is recommended that you only code one form. The forms identifier specified by the STDFORM parameter on the OUTDEF statement.

Modification: \$T PRTnnnnn operator command. For FSS-controlled printers only, if you modify this parameter value and then reconnect the printer on a hot start, the parameter value in effect before termination will be used.

FSAROLTR=(YES/NO)

Specifies whether the internal rolling trace for an FSS printer is activated or deactivated. Yes is the default.

HONORTRC=Yes| No

Specifies whether or not the TRC=Yes/No parameter specified on the job's OUTPUT JCL statement will be honored or not honored for a given JES mode printer. HONORTRC= only applies to JES mode printer.

JES mode printer (other than D/T3800) deletes (skips) the Table Reference Character if HONORTRC=YES and TRC=Yes is specified for sysout.

JES mode printer (other than D/T3800) treats Table Reference Character as data if HONORTRC=NO and TRC=Yes is specified for sysout.

Modification: \$T PRTnnnnn operator command.

JOBname=jcccccc

Specifies the 1- to 8-character name for a job whose output can be selected by this printer. Wildcard specifications are allowed on this parameter.

If this parameter is allowed to default, JES2 can select all output for processing, regardless of jobname.

Modification: \$T PRTnnnnn operator command.

LIMit=m|m-n|m-*

Specifies that output is selected for specific printers based upon the amount of the output (in records). The values *m* and *n* specify the range (in records) into which a job output element (JOE) must fall to be processed by this printer. The integer *m* specifies the lower output size limit and *n* specifies the upper output size limit.

For both variables *m* and *n*, you can specify a range of values 0-4294967295. *m* and *n* can be equal. If they are not equal, *n* must be larger than *m*.

If you code only *m*, that value becomes both the lower and upper limit. If *m-** is specified, the upper limit is set to the default value of 4294967295.

After a warm start, the original size of the output (before any printing) will be used to determine where the remainder of the output will be printed. That is, the original size of the JOE will be used to determine output device selection.

Default: If you omit this parameter, JES2 uses the defaults *m*=0 and *n*=4294967295.

Modification: \$T PRTnnnnn operator command.

MODE=JES

Specifies this printer is initially started under the operation of JES2. An operator can change the control mode by use of the \$T PRTnnnnn command whenever the printer is drained.

If you do not specify this parameter, the default is JES. Although you can also specify **FSS** here; however, that value is reserved for FSS-controlled printers only.

Modification: \$T PRTnnnnn operator command.

NEWPAGE={1|ALL|DEFAULT}

Specifies how a 'skip to channel' is counted as a new page.

1

Specifies that JES2 treats only skip-to-channel-1 as a new page.

ALL

Specifies that JES2 treats skip-to-any-channel as a new page.

DEFAULT

Specifies that JES2 uses the NEWPAGE= value specified on the PRINTDEF initialization statement.

Modification: \$T PRT(nnnnn) operator command.

Pause=Yes|No

Specifies whether (Yes) or not (No) this printer is to pause between data set groups.

Modification: \$T PRTnnnnn operator command.

Note: This operand has no effect on page-mode printers that operate under the control of a functional subsystem.

PRMode=(vvvvvvvv[,vvvvvvvv...])

Specifies one to eight names that identify the processing modes used by JES2 to direct output data sets to this output device. Wildcard specifications are allowed on this parameter. To specify no processing mode, specify PRMode=() to cause this printer to select no output group if PRMode is also coded on the WS= list. If only one PRMODE is specified, the parentheses are optional.

vvvvvvvv

Specifies the process mode:

LINE

Specifies that the data set contains formatting controls that only a line-mode printer can process.

PAGE

Specifies that the data set contains formatting controls that only a page-mode printer can process.

installation-defined

Specifies that the data set contains formatting characteristics defined at the installation for specific output groups. Users can assign a PRMode= value to the data sets by using JCL OUTPUT statements. However, if the user does not specify a process mode for the data set, JES2 assigns a process mode. IBM suggests that you prefix installation-defined process mode names with the character U.

Installation-defined and IBM-defined process mode designations may be mixed on one PRMODE= parameter statement. For example, you can specify names on this parameter designating the output device as capable of accepting data sets that can be printed on either a plotter device (for example, UPLLOT2) or a page-mode printer device.

```
PRMODE=(UPLLOT2,PAGE)
```

If you do not specify this parameter, JES2 defaults all printers to LINE.

Modification: \$T PRTnnnnn operator command.

RANGE={J|S|T} nnnnnn[-nnnnnn][J1-999999]

Specifies the job ID range for output jobs that can be selected by this printer. Use J to specify batch jobs, S to specify started tasks, and T for TSO/E jobs. You can specify a single job number or range (up to 65534) of jobs.

If you code this parameter, you can specify one or two values:

- If you specify one value, that value becomes both the low and the high end of the range.

- If you specify two values, the first value is the low end of the range and the second value the high end. If they are not equal, the second value must be larger than the first value. If you specify two equal values, this printer can select only those jobs assigned that particular number.

Modification: \$T PRTnnnnn operator command.

Routecde=rtcode

Specifies up to four internal route codes to be assigned to this printer.

The maximum size of a route code is 18 characters. Wildcard specifications are allowed on this parameter for userids only. You can specify a route code in any of the forms listed below.

Ummmmm
destid
remote
user

Note: If you specify a destid on the Routecde parameter, you must place the DESTID initialization statement before the PRTnnnnn statement in the initialization stream. Explanations of the different forms of specifying route codes follow.

Ummmmm

Indicates that output for special local routing is selected. The special routing numbers range from 1 to 32767.

destid

Indicates that output routed to the specified node(s) is selected. If destid is specified alone, it refers to both the node and the remote.

LOCAL | ANYLOCAL

Indicates that output routed to the local node is selected.

remote

Indicates that output routed to a remote is selected. Remote can be specified in any of the following ways:

Rmmmmm

Indicates that output routed to the specified remote is selected. Rmmmmm can also be specified as RMmmmmm or RMTmmmmm. The value specified for mmmmm can range from 1 to 32767.

destid

Indicates that output routed to a destid referring to a remote is selected.

user

Indicates that output routed to a specific userid is selected. Generic userids are also valid. A generic userid is a userid that ends in an asterisk (*), and refers to all userids that begin with the characters preceding the *. Note that the * can only be specified in the last position of the userid.

A userid at the local node must be in the form of a valid TSO/E userid. It must begin with an alphabetic (A-Z) or a special character (@ # or \$), and the remaining characters may be alphabetic, numeric, or special characters.

If you specify only one route code the parentheses are optional. To specify a null route code, use Routecde=() to cause this printer to select no work if Routecde is also specified in the WS= list.

Note: Route codes for local devices should be used cautiously if you have also coded R on the WS= parameter on this statement. When a printer has been assigned a route code or route codes, it is considered available only for a job that requests printed output through the /*ROUTE control statement, through the DEST keyword on the /*OUTPUT control statement, the JCL OUTPUT statement, the output initialization parameter, or through an operator command. A printer with print routing may also be the default destination for jobs read through a local or remote reader specifying PRDEST= and PRLCL=|PRRMT=. See the RDRnn and Rnnnnn.RDn statements for the details of these options.

Modification: \$T PRTnnnnn operator command.

If you do not specify this parameter, the default is LOCAL.

Sep=Yes|No

Specifies whether (Yes) or not (No) separator pages are provided initially between data set groups. (Separator pages can be specified later by the JES2 \$T PRTnnnnn command.) JESNEWS data will not be printed unless the job separator page is requested. This specification can be overridden by an Exit 1 routine.

If you do not specify this parameter, JES2 supplies a default of SEP=Yes. However, if LOCAL=NONE or REMOTE=NONE was specified on the SEPPAGE= parameter of the PRINTDEF initialization statement, separator pages are not be produced even if SEP is specified.

Modification: \$T PRTnnnnn operator command. For FSS-controlled printers only, if you modify this parameter value and then reconnect the printer on a hot start, the parameter value in effect before termination will be used.

SEPDS=Yes|No

Specifies whether (Yes) or not (No) data set separator pages are desired for the data sets within the output groups selected for processing by printers. For this parameter to affect processing, you must customize JES2 or a functional subsystem as follows.

For JES-mode printers (MODE=JES), your systems programmer must have written an Exit 15 (Output Data Set/Copy Separators) that examines the SEPDS= specification and produces separator pages when SEPDS=Yes. Exit 15 controls both the production of separator pages and whether they are affected by the SEPDS= parameter. If Exit 15 is enabled, it is invoked even if SEPDS=No. To enable Exit 15, see *z/OS JES2 Installation Exits*.

For functional subsystem printers (MODE=FSS), JES2 makes an indication of the parameter's setting available to the functional subsystem. If an FSS printer is controlled by PSF, an APSUX03 exit must have been installed to produce data set header pages. APSUX03 is not invoked if SEPDS=NO. For more information about the APSUX03 exit, see *S544-5622 PSF for OS/390 Customization*.

Default: SEPDS=NO

Modification: \$T PRTnnnnn operator command. For FSS-controlled printers only, if you modify this parameter value and then reconnect the printer on a hot start, the parameter value in effect before termination will be used.

Note: Be careful not to confuse this parameter with the SEP=.

SETUP=HALT|NOHALT

Specifies whether JES2 issues the device setup message (\$HASP190) after a change of device characteristics (for example, forms control).

SETUP=HALT halts the printer and issues the setup message. This allows the operator to verify the changes to the printer.

SETUP=NOHALT allows the printer to process output without requiring setup verification by the operator. With SETUP=NOHALT, JES2 can load any printer characteristics that require no manual intervention. have not changed to process output.

Modification: \$T PRTnnnnn operator command. For FSS-controlled printers only, if you modify this parameter value and then reconnect the printer on a hot start, the parameter value in effect before termination will be used.

START=Yes|No

START=No specifies that this printer is to be started by operator command. START=Yes specifies that this printer (if it is ready) will be started automatically when JES2 starts processing.

Default: START=Yes: if the Yes keyword was specified on this initialization statement and unit was not specified for a non-FSS mode printer.

Modification: \$S PRTnnnnn operator command or \$P PRTnnnnn operator command.

TRace=Yes|No

Specifies whether tracing is activated or deactivated for the specified print processor. To trace a printer, you must also provide the following initialization statements:

```
TRace(n) START=Yes
TRACEDEF ACTIVE=Yes
```

Trace IDs 11, 12, 14, 15, and 16 can be specified through the TRACE(n) initialization statement and the \$\$ TRACE command by coding nn for each trace ID. Note that trace ids 14, 15, and 16 apply to FSS printers.

Modification: \$T PRTnnnnn command. For FSS-controlled printers only, if you modify this parameter value and then reconnect the printer on a hot start, the parameter value in effect before termination will be used.

For further information about coding this parameter, see *z/OS JES2 Initialization and Tuning Guide*. For further information about the tracing facility, see *z/OS JES2 Diagnosis*. For an explanation of the \$\$ TRACE command, see *z/OS JES2 Commands*.

TRANS=Yes|No|DEFAULT

If this PRT(nnnnn) statement specifies or defaults to MODE=JES, the TRANS= parameter on this statement affects data translation:

- If the PRT(nnnnn) statement specifies TRANS=Yes, JES2 translates each line of output sent to the device regardless of the device type or the setting of the PRINTDEF TRANS= parameter.
- If the PRT(nnnnn) statement specifies TRANS=No, JES2 does not translate output sent to the device regardless of the device type or the setting of the PRINTDEF TRANS= parameter.
- If the PRT(nnnnn) statement specifies TRANS=DEFAULT, or TRANS= is omitted from the PRT(nnnnn) statement, and the PRINTDEF statement specifies TRANS=Yes, and the device is either a local 1403 or a remote printer, JES2 translates each line of output sent to the device. Otherwise, JES2 does not translate output sent to the device.

Modification: \$T PRTnnnnn,TRANS= operator command. Do not issue this command unless the printer is inactive or drained.

TRKCELL=Yes|No

Yes specifies that an entire track cell is to be despoiled (read from the spool) in one operation, for data sets that belong to a SYSOUT class that has the track-cell characteristic. The number of records in the track cell is governed by the TRKCELL parameter on the SPOOLDEF statement. Specifying TRKCELL=Yes and double buffering (DBLBUFR=Yes on the PRINTDEF statement) indicates double track-cell buffering.

NO indicates that track-cell despooling is not to be used. Instead, spool records are despoiled 1 record per despooling operation.

Performance Considerations: You can use track-cell despooling for any printer supported by JES2. However, TRKCELL=No (the default) is recommended for low-speed printers such as the 3820 because a considerable amount of storage space is saved. But for high-speed printers such as the 3800-3 running under the control of an FSS, TRKCELL=YES is required to prevent performance degradation.

Modification: \$T PRTnnnnn operator command. For FSS-controlled printers only, if you modify this parameter value and then reconnect the printer on a hot start, the parameter value in effect before termination will be used.

UCS|T=vvvv

Specifies, for impact printers, the print train (print chain or print band) that is mounted on this printer. The value of vvvv is the identifier (1-4 characters) of a universal character set (UCS) image that resides in SYS1.IMAGELIB.

For 3800 printers, vvvv specifies both the character arrangement table that JES2 initially loads into the printer and the installation's default character arrangement tables for data sets not specifying any character arrangement. See *Advanced Function Presentation: Printer Information* for

information about the IBM-supplied character arrangement tables and the addition of other character arrangement tables to SYS1.IMAGELIB.)

If you specify an incorrect identifier, JES2 bypasses the UCS loading procedure and issues the \$HASP190 setup message allowing the operator to specify a valid image.

If you do not specify this parameter, JES2 selects the default based upon the type of printer:

- For impact printers, the identifier specified by the UCS= parameter on the PRINTDEF statement.
- For 3800 printers, the identifier specified by the NIUCS= parameter on the PRINTDEF statement.

Modification: \$T PRTnnnnn operator command. For FSS-controlled printers only, if you modify this parameter value and then reconnect the printer on a hot start, the parameter value in effect before termination will be used.

Note: This parameter is not supported for a 1403 printer that does not have the UCS feature. If you specify UCS=0 (or if a zero value was specified for the UCS parameter on the PRINTDEF statement), JES2 will not load the UCS buffer.

UCSVERIFY=Yes|No

Specifies whether (Yes) or not (No) UCS verification processing is performed when a UCS image is loaded for 4245 and 4248 printers. UCS images are loaded on 4245 and 4248 printers only when required for print processing (they are **not** loaded in response to a \$T PRT operator command that specifies a change in UCS setup). Specifying UCSVERIFY=Yes provides UCS verification and causes the band image to be displayed to the 4245 and 4248 printers. UCSVERIFY=No suppresses the image display.

Modification: \$T PRTnnnnn operator command.

UNIT={hhhh|/hhhh}

Specifies a 3- or 4-digit hexadecimal device number. Device numbers can be specified by any of the following formats:

```
UNIT=hhh
UNIT=hhhh
UNIT=/hhh
UNIT=/hhhh
```

where hhh and hhhh represent the device numbers.

A slash (/) can optionally precede the device number (for compatibility with other initialization statements that require a slash to denote a 4-digit device number).

If not specified, JES2 does not assign an available printer; instead, a printer can be dynamically assigned using a \$T PRT command.

Modification: \$T PRTnnnnn operator command. For FSS-controlled printers only, if you modify this parameter value and then reconnect the printer on a hot start, the parameter value in effect before termination will be used.

Note:

1. This parameter is not required if the printer defined by this statement is an SNA-attached IBM 3820 printer. If a UNIT= specification is provided when defining a non-channel attached IBM 3820 printer, JES2 will ignore it.
2. If UNIT= is not specified at this time, the defaults for COPYMARK=, FLASH=, FCB=, and UCS= will be based on the setting of the MODE= parameter. If MODE=FSS, the defaults will be the same as if the device were a non-impact printer. If MODE=JES, the defaults will be set assuming the device is an impact printer.

Volume=(v1[,v2][,v3][,v4])|()

Specifies the 5- to 6-character volume serial number of a volume containing a spool data set. Only output jobs containing tracks on the specified volume can be selected for printing. As many as four volumes can be specified. Use commas to separate individual volume IDs and enclose this list in parenthesis if more than one ID is specified.

Modification: \$T PRTnnnnn operator command

Writer=xxxxxxx

Specifies the 1- to 8-character writer name assigned to this printer. Wildcard specifications are allowed on this parameter.

If you do not specify this parameter, no writer name is assigned.

Modification: \$T PRTnnnnn operator command.

WS=criteria | (W,Q,R,PRM/F,T,C)

Specifies the work selection criteria (listed below) for this device. Criteria that are not specified are not considered during output selection although they are used by JES2 to determine setup requirements. This parameter can be particularly useful when draining a specific spool volume. You specify a list of selection criteria as follows:

- One and only one slash (/) may precede or follow any number of criteria. The slash separates the work selection criteria that must be matched exactly from those that need not be matched exactly to the characteristics of the output. If you do not code a slash, all criteria specified must be matched exactly. (See [z/OS JES2 Initialization and Tuning Guide](#) for a further discussion of device to job matching.)
- The order of those criteria specified before the slash (those that must be matched exactly) may affect output selection. All criteria will be matched regardless of the sequence in which they are listed. See [z/OS JES2 Initialization and Tuning Guide](#) for details on output selection.
- The order of those criteria specified after the slash (those that need not match exactly) indicates the priority (highest to lowest in left to right order) in which JES2 will attempt to match them.
- Queue (class), Route (route) and Volume criteria are exceptions; these must be matched exactly, and will be, no matter where you specify them in the criteria list. However, specifying these criteria before the slash indicates a left to right priority order of multiple values, if multiple values are designated. Specifying either one after the slash indicates no priority order of multiple values, if multiple values are designated on the output device initialization statement.
- If a criterion is omitted from the list of selection criteria, it will not influence work selection, but if characteristics of the selected output differs from the output device's selection criteria, a setup message may be issued to the operator.

Unless otherwise noted, if the criterion is specified before the slash, an exact match is required; if after the slash, an exact match is preferred (and attempted in left to right priority) but not required, only the priority order is considered.

You can specify the following *criteria* on the WS= parameter:

Burst

Specifies that the current BURST= specification is either required or preferred.

Class|Queue

Specifies that a match must be found for the output classes specified on this device. If Q is omitted from the WS list, all output queues (beginning with queue A) will be searched for work.

Note: If specified before the slash, the priority of the device characteristics table class list is from left to right. If specified after the slash, there is no device characteristics table class list priority ordering. To increase performance, this criterion should be placed before the slash.

CReator

Specifies that output for the current userid is preferred. JES2 attempts to consecutively select all eligible output for a particular userid. However, output is only grouped in this manner depending upon the specification of the current work selection list and output queues. If specified to the left of the slash, an exact match is required.

FCB|C

Specifies that the current forms control buffer (FCB) image or carriage control tape is either required or preferred.

FLash|O

Specifies that the current FLASH= specification is either required or preferred.

Forms

Specifies that the current FORMS= specification is either required or preferred. If FORMS is omitted from the criteria list, work selection will not contain any forms checking.

JOBname

Specifies that JES2 gathers all output for a job and attempt to process that output consecutively. The JOBNAME= parameter for a particular device determines what job name JES2 selects when JES2 has processed all output that matches the current job name.

- If JOBname= is specified before the slash in the WS= list:

JES2 selects only those jobs that match the value specified on JOBNAME= for a specific device. When JOBNAME= is specified as a generic name, JES2 only processes jobs that match that pattern and attempts to process all output for that job name consecutively.

- If JOBname= is specified after the slash in the WS= list:

JES2 uses the value specified on JOBNAME= to select new job names for the specific device. If there are no job names that match the JOBNAME= specification, JES2 selects jobs as if JOBname were not listed in the WS= list. A device gathers and processes all output for a particular job before again examining the value specified on JOBNAME= for more jobs.

If you require JES2 to group jobs based on job name but do not want JES2 to prefer a particular JOBNAME= pattern, specify JOBNAME=* on the device statement and code JOBname after the slash in the WS= list.

LIMit

Specifies that the limits of output, as noted on the LIMIT= keyword (on this initialization parameter) will be supported, that is, the amount of generated output must fall within the LIMIT= specification.

This subparameter has no effect as a work selection value for files received from a node that does not provide a page count for its files. For more information, see the sending node's reference documentation.

PRMode|PMD

Specifies that the current PRMODE= specification is preferred. If more than one mode is specified, they are in left to right priority order.

Note: To print output, a match must be found; this criterion should be placed before the slash.

Priority

Specifies that output priority will be considered. Priority is not matched with any other parameter; rather, it specifies that a higher output priority receives greater output preference. If specified before the slash, the importance of selecting output by priority is increased.

Routeode

Specifies that only output destined for a destination specified by a route code listed on the ROUTECDE= parameter is eligible for selection by this device.

Note: If Routeode is specified before the slash, the route code(s) are in left to right priority order; if specified after the slash, there is no such priority order.

RANGE

Specifies that the current job ID range is preferred. If specified to the left of the slash, an exact match is required.

Volume

Specifies that only output with tracks on the currently specified volume can be selected for printing. If specified to the left of the slash, the volumes are considered to be in left to right priority order. If specified to the right of the slash, no priority order exists, but an exact match is still required.

Writer

Specifies that the writer name (W=) specification is either required or preferred.

UCS|T

Specifies that the currently mounted print train (on impact printers only) is either required or preferred. If omitted from the work selection list, the UCS specified for the output is not required to match the device setup, but a setup message will be issued to the operator if the UCS= specifications differ.

Note: Embedded comments are not allowed within the WS= parameter specification.

Modification: \$T PRTnnnnn operator command.

Parameter Description for FSS Printers Only:

CKPTMODE=PAGE|SEC

Specifies whether the checkpointing of information is to be based on page count (CKPTMODE=PAGE) or time (CKPTMODE=SEC).

Note: If this parameter is specified, and both the CKPTPAGE= and CKPTSEC= keywords on this initialization statement have also been specified, this parameter specification determines if the checkpoint interval is based on the number of pages (the CKPTPAGE=pages specification) or time (the CKPTSEC=seconds specification).

Modification: \$T PRTnnnnn operator command.

CKPTSEC=nnnnnn | 0

Specifies the number (0-32767) of seconds before an output checkpoint is taken by a functional subsystem.

Note: If you code both CKPTPAGE= and CKPTSEC=, and you either omit CKPTMODE= or code CKPTMODE=PAGE, the CKPTPAGE= specification overrides the CKPTSEC= specification.

Modification: \$T PRTnnnnn operator command.

COPYMARK=DATASET|JOB|CONSTANT|NONE|DEFAULT

Specifies how a printer increments copy marks or offset stacking.

DATASET

The printer is to increment the copy marks or offset stacking on a data set boundary.

JOB

The printer is to increment the copy marks or offset stacking on a job boundary.

CONSTANT

Copy marks are constant, and no offset stacking is done.

NONE

No copy marks are used and no offset stacking is done.

Note: COPYMARK=NONE only works if the FSS application supports that setting. If it is not supported by the FSS application, COPYMARK=NONE acts like COPYMARK=CONSTANT.

Modification: \$T PRTnnnnn operator command. For FSS-controlled printers only, if you modify this parameter value and then reconnect the printer on a hot start, the parameter value in effect before termination will be used.

FSS=accccccc

Specifies a 1- to 8-character functional subsystem name that supports a page-mode printer. If an FSSname is not defined by an FSS(accccccc) initialization statement, the functional subsystem name assigned on this statement will cause the generation of a default FSS initialization statement. The FSS(accccccc) statement then defines (by default) the subscript(accccccc) and PROC name specified here.

Modification: \$T PRTnnnnn operator command.

Note:

1. This parameter must be specified if MODE=FSS is specified for this PRT(nnnnn) statement. If this parameter is not specified, the MODE setting becomes MODE=JES.
2. You must also specify UNIT=, if this PRT(nnnnn) statement defines a 3827 or 3835 printer.

MODE=FSS

Specifies this printer is initially started under the operation of a functional subsystem. An operator can change the control mode by use of the \$T PRTnnnnn command whenever the printer is drained.

Attention: If a line-mode printer (3800 model 1, for example) is defined as a page-mode printer operating under the control of a functional subsystem, page-mode data **will** be directed to it although the page-mode data will be ignored by the printer. There will be no warning message, initialization error, or message of any type to warn the operator. Incorrect, unexpected output from the printer will result.

MODE= defaults to FSS if FSS= is also specified on this initialization statement and UNIT= was not specified.

Modification: \$T PRTnnnnn operator command.

NPRO=nnnnn|300

Specifies the non-process-runout (NPRO) time interval, in seconds (0-3600). The NPRO time interval is that time interval during which output remains in the paper path but has not reached the stacker. After the NPRO time specification has elapsed, the functional subsystem directs the page-mode printer to force the output to the stacker. NPRO=0 specifies that a timer-based NPRO is not to be used.

Note: This keyword is only supported for 3800 model 3 printers under the control of a functional subsystem.

Modification: \$T PRTnnnnn operator command.

PLIM=m|m-n|m-*

Specifies upper and lower bounds (in pages) for the size of job output elements eligible for this printer. The values *m* and *n* specify the lower and upper limits of the range (in pages) into which a JOE must fall to be processed by this printer.

For both variables *m* and *n*, you can specify a range of values from 0-4294967295. *m* and *n* can be equal. If they are not equal, *n* must be larger than *m*.

If you code only *m*, that value becomes both the lower and upper limit. If *m-** is specified, the upper limit is set to the default value of 4294967295.

Note:

1. If the printing of a data set is interrupted by a warm start, the original number of pages specified in the JOE is used to determine where the remainder of the output is to be printed.
2. When PLIM is specified (non zero value) for r(nnnn).pr(*m*) PRMODE of PAGE will be of significance for remote printers and WS criteria for remote printers.

Default: If you omit this parameter, JES2 uses the defaults *m*=0 and *n*=4294967295.

Modification: \$T PRTnnnnn operator command.

PRESELECT=Yes|No

PRESELECT=Yes, specifies that this FSS printer initially selects two output groups for processing. From then on, the printer will keep two output groups available for processing until you stop the printer. The preselected output groups are not available for processing by other printers.

If you specify PRESELECT=No, this FSS printer will select only one output group for processing.

Note: This parameter is valid only for printers controlled through an FSS.

Performance Considerations:

- If this printer preselects a second output group and is busy printing a large output group, be aware that the operator is unable to change the destination of this second output group. As a result, this

second print job is delayed on this printer until the first output group completes printing, whereas it could have printed elsewhere had it not been preselected.

- If an FSS requests forms repositioning (such as might occur during a paper jam or because of a \$B, \$F, or \$I command), the resulting sequence of the output data sets might be different than expected.

Modification: \$T PRTnnnnn operator command. For FSS-controlled printers only, if you modify this parameter value and then reconnect the printer on a hot start, the parameter value in effect before termination will be used.

Parameter Description for Non-Impact Printers (JES & FSS mode)

Burst=Yes|No

Specifies whether the printed output from a 3800 printer is to be burst into separate sheets (Yes) or to be printed in continuous fanfold form (No). The use of this parameter sets the initial status of the printer for output work selection.

Modification: \$T PRTnnnnn operator command. For FSS-controlled printers only, if you modify this parameter value and then reconnect the printer on a hot start, the parameter value in effect before termination will be used.

DEVFLASH | FLASH|O=xxxx

A 1- to 4-character name that specifies the name of the default forms FLASH ID that JES2 uses on printers that can perform forms flashing. The use of DEVFLASH= or FLASH= are equivalent when used to set the forms FLASH ID. This forms FLASH ID is used for jobs selected by this printer that do not have the FLASH= parameter explicitly coded on the job's JCL. The user can override this default forms FLASH ID by explicitly requesting forms flashing on the job's JCL DD statement (with the SYSOUT parameters), JCL OUTPUT statement, or, /*OUTPUT JES2 control statement. If you specify FLASH=NONE, no forms flashing occurs regardless of the setting of the NIFLASH= parameter on the PRINTDEF statement.

If you omit this parameter, the global default value specified by the NIFLASH= parameter on the PRINTDEF statement is used for the forms FLASH ID.

Modification: \$T PRTnnnnn operator command. For FSS-controlled printers only, if you modify this parameter value and then reconnect the printer on a hot start, the parameter value in effect before termination will be used.

You can change a forms FLASH ID only if it was originally specified by the DEVFLASH= parameter. To do so, issue the \$T PRTnnnnn,DEVFLASH=xxxx command after draining the printer.

MARK=Yes|No

MARK=Yes specifies for a non-impact printer that there is marking on the edge of the separator page.

If you do not specify this parameter, it becomes MARK=No, which specifies (when MODE=JES2) for a non-impact printer that there is no marking on the edge of the trailer separator page. If MODE=FSS, MARK=No specifies for a non-impact printer that although no mark is produced on the edge of the trailer separator page, a unique mark is produced on the carrier strip (that is, the punched, perforated page edge).

Modification: \$T PRTnnnnn operator command. For FSS-controlled printers only, if you modify this parameter value and then reconnect the printer on a hot start, the parameter value in effect before termination will be used.

SEPCHARS=CURRENT|DEFAULT

Specifies whether separator pages printed on the 3800 printer use the character arrangement table loaded in the 3800 (CURRENT) or the installation default character arrangement table (DEFAULT).

JES2 attempts to use the installation default character arrangement table (see the NIUCS= parameter on the PRINTDEF statement) for separator pages if the UCS= parameter is not specified on the PRT statement. These options determine the action taken when the default is not already loaded.

PUN(nn)

If the installation default character arrangement table is not loaded, SEPCHARS=CURRENT tells JES2 to use the first character arrangement table. SEPCHARS=DEFAULT tells JES2 to specify that the table must be loaded before it prints the separator pages.

This parameter is valid only for 3800 JES-mode printers. If you do not specify a default on those printers, JES2 specifies that SEPCHARS=DEFAULT.

Modification: \$T PRTnnnnn operator command.

PUN(nn) - Local Card Punch


The PUN(nn) statement specifies the characteristics of one local card punch. Each punch device is defined by a PUN(nn) statement with a unique value (1-99) specified for nn. Punch characteristics are specified by the following parameters.

The dual reader/punch feature is supported by JES2 as shown in the following example. Assume that a 3525 with the read feature has a unit address of 013 and that the following two items appear in the JES2 initialization data set:


```
RDR(2)  UNIT=013,START=NO  
PUN(1)  UNIT=013
```


When JES2 is started, the reader will be stopped and the punch feature will be activated. If the operator later wants to read data from the 3525, he can stop punch 1 and start reader 2 with JES2 commands.

Format Description for PUN(nn)



Modification keywords







Notes:

- ¹ Omit the comma between initialization statement and first keyword
- ² *Forms* can be coded up to 8 times
- ³ *PRMode* can be coded up to 8 times

Selection limiting keywords





Notes:

¹ Forms can be coded up to 8 times

Parameter Description for PUN(nn)

CKPTLINE=nnnnn|100

Specifies the number of cards (1-32767) to be punched per logical page. This value is the only one used to define a logical page for punches.

Modification: \$T PUN(nn) operator command.

Note: To switch off checkpointing, specify CKPTLINE=0.

CKPTPAGE=nnnnn|1

Specifies the number (1-32767) of logical pages to be punched before each checkpoint is taken.

Modification: \$T PUN(nn) operator command.

{Class|Queue}=c1...cn|BK

Specifies the output classes to be processed initially by this card punch. You can specify any number of classes (A-Z and 0-9) up to the maximum of 15 classes.

Modification: \$T PUN(nn) operator command.

CReator=cccccccc

Specifies the 1- to 8-character userid whose output can be selected by this punch. Wildcard specifications are allowed on this parameter.

If this parameter is allowed to default, JES2 can select all output for processing, regardless of userid.

Modification: \$T PUN(nn) operator command.

Forms=xxxxxxxx,...,xxxxxxxx

Specifies the 1- to 8-alphanumeric character forms name of the forms that are to be loaded initially in this punch. Wildcard specifications are allowed on this parameter.

If you do not specify a value, JES2 provides the forms identifier specified by the STDFORM= parameter on the OUTDEF statement.

Modification: \$T PUN(nn) operator command.

JOBname=jcccccc

Specifies the 1- to 8-character job name for jobs whose output can be selected by this punch. Wildcard specifications are allowed on this parameter.

If this parameter is allowed to default, JES2 can select all output for processing, regardless of jobname.

Modification: \$T PUN(nn) operator command.

LIMit=m|m-n|m-*

Specifies that output is selected for specific punches based upon the amount of the output (in records). The values *m* and *n* specify within what output size range (in records) a job output element (JOE) must fall to be processed by this punch. The integer *m* specifies the lower output size limit and *n* specifies the upper output size limit.

For both variables *m* and *n*, you can specify a range of values from 0-4294967295. *m* and *n* can be equal. If they are not equal, *n* must be larger than *m*.

If you code only *m*, that value becomes both the lower and upper limit. If *m-** is specified, the upper limit is set to the default value of 4294967295.

After a warm start, the original size of the output (before any punching) will be used to determine where the remainder of the output will be punched. That is, the original size of the JOE will be used to determine output device selection.

The default values are *m*=0 and *n*=4294967295.

Modification: \$T PUN(nn) operator command.

Pause=Yes|No

Specifies whether (Yes) or not (No) this card punch is to pause between data set groups.

Modification: \$T PUN(nn) operator command.

PRMode=(vvvvvvvv[,vvvvvvv...])

Specifies one to eight names used by JES2 to direct output data sets to this output device. Wildcard specifications are allowed on this parameter. If only one PRMODE is specified, the parentheses are optional. Users can assign a PRMODE value to the data sets by using JCL OUTPUT statements. However, if the user does not specify a process mode for the data set, JES2 will assign a process mode. If the data set contains formatting controls that can only be processed by a page-mode printer, JES2 defaults the PRMODE= specification to PAGE. For all other data sets, the default is LINE.

Your installation may have output devices capable of printing other than line-mode data sets. If so, you can specify a name(s) on this parameter designating the output device as capable of accepting such data sets. For installation-defined process modes, use the Uvvvvvvv form of the process mode designation. The U identifies the process mode as installation defined. Installation-defined and IBM-defined process mode designations may be mixed on one PRMODE= parameter statement. For example, you can specify names on this parameter designating the output device as capable of accepting data sets that can be printed on either a plotter device (for example, UPLOT2) or a line-mode printer by specifying:

```
PRMODE=(UPLOT2, LINE)
```

Note:

1. You can specify only up to eight process modes on a single device; however, you can specify as many as 255 different modes throughout a particular JES2 member.
2. Within a job entry network, receiving nodes must designate the same process mode as that specified on the data set(s) sent to them. If the receiving node has not specified the same process mode, the data set(s) will not be printed.
3. To specify a null processing mode, use PRMode=().

Default: LINE, except for those data sets containing formatting controls that can only be processed by page-mode printers. The default for these data sets is PAGE.

Modification: \$T PUN(nn) operator command.

RANGE={J|S|T}nnnnn[-nnnnn]|J1-999999

Specifies the job ID range for output jobs that can be selected by this punch. Use “J” to specify batch jobs, “S” to specify stated tasks, and “T” for TSO/E jobs. You can specify a single job number or range (up to 65534) of jobs. If you code this parameter, you can specify one or two values:

- If you specify one value, that value becomes both the low and the high end of the range.
- If you specify two values, the first value is the low end of the range and the second value the high end. The two values can be equal. If they are not equal, the second value must be larger than the first value.

Modification: \$T PUN(nn) operator command.

Routecde=rtcode | LOCAL

Specifies up to four internal route codes to be assigned to this card punch. Wildcard specifications are allowed on this parameter for userids only. A route code indicates that this card punch is to be eligible for punch routing.

The maximum size of a route code is 18 characters. You can specify a route code in any of the forms listed below.

Ummmm
destid
remote
user

Note: If destid is used, it must be previously defined on a DESTDEF statement in the initialization stream. Explanations of the different forms of specifying route codes follow.

Ummmm

Indicates that output for special local routing is selected. The special routing numbers range from 1 to 32767.

destid

Indicates that output routed to the specified node(s) is selected. If destid is specified alone, it refers to both the node and the remote.

remote

Indicates that output routed to a remote is selected. Remote can be specified in any of the following ways:

LOCAL | ANYLOCAL

Indicates that output routed to the local node is selected.

Rmmmm

Indicates that output routed to the specified remote is selected. Rmmmm can also be specified as RMmmmm or RMTmmmm. The value specified for mmmm can range from 1 to 32767.

destid

Indicates that output routed to a destid referring to a remote is selected.

user

Indicates that output routed to a specific userid is selected. Generic userids are also valid. A generic userid is a userid that ends in an asterisk (*), and refers to all userids that begin with any character preceding the *. Note that the * can only be specified in the last position of the userid.

A userid at the local node must be in the form of a valid TSO/E userid. It must begin with an alphabetic (A-Z) or a special character (@ # or \$), and the remaining characters may be alphabetic, numeric, or special characters.

You can override the destinations specified by this parameter with the set operator command (\$T). If you specify only one route code the parentheses are optional. To specify a null route code, use Routecde=() to cause this punch to select no work if Routecde is also specified in the WS list. Use the Unnnn form to specify this punch as a special local punch.

Note: Route codes for local devices should be used cautiously. When a card punch has been assigned a route code or route codes, it is considered available only for a job that requests punched output through the DEST keyword on the /*OUTPUT control statement or JCL OUTPUT statement, or through the /*ROUTE control statement or by operator command.

Modification: \$T PUN(nn) operator command.

Sep=Yes|No

Specifies whether (Yes) or not (No) separator cards are not to be initially provided between data set groups. (Separator cards can be specified later by the JES2 \$T command.) This specification can be overridden by a JES2 Exit 1 routine. See *z/OS JES2 Installation Exits* for information about Exit 1.

Modification: \$T PUN(nn) operator command.

SEPDS=Yes|No

Specifies whether data set separator cards are desired for the data sets within the job output elements (JOEs) selected for processing by the specific device. JES2 does not actually generate data set separator cards based on this parameter specification. If you enabled Exit 15 (Output Data Set/ Copy Separators), SEPDS=Yes causes the exit to generate separator cards for each data set selected by this device. See *z/OS JES2 Installation Exits* for information about Exit 15.

Modification: \$T PUN(nn) operator command.

Note: Be careful not to confuse this parameter with the SEP= parameter.

SETUP=HALT|NOHALT

Specifies whether JES2 issues the device setup message (\$HASP190) after a change of device characteristics (for example, forms control).

SETUP=HALT halts the punch and issues the setup message. This allows the operator to verify the changes to the punch.

SETUP=NOHALT allows the punch to process output without setup verification by the operator. The punch uses any previously existing setup characteristics that you have not changed to process output.

Modification: \$T PUN(nn) operator command.

START=Yes|No

specifies whether (Yes) or not (No) this card punch (if it is ready) starts automatically when JES2 starts processing.

Note: If the punch is to be started automatically and is unavailable when JES2 is started, it remains unusable until the next time JES2 is started, unless the UNIT= keyword is specified on this device statement. If UNIT= is specified, the specified unit is started although it may have been offline during JES2 initialization.

Modification: \$\$ PUNnnnn operator command or \$P PUNnnnn operator command.

TRace=Yes|No|P

Specifies whether tracing is activated or deactivated for all punches. To trace a punch you must also provide the following initialization statements:

```
TRACE(n) START=Yes
TRACEDEF ACTIVE=Yes
```

This parameter setting can be overridden by the \$T PUN(nnnn) operator command. Punch tracing is also controlled by trace IDs 11 and 12, the TRACE(n) and TRACEDEF initialization statements, and the \$\$ TRACE command. (See *z/OS JES2 Initialization and Tuning Guide*, the TRACE(n) and TRACEDEF initialization statements in this chapter, and *z/OS JES2 Commands* for a description of the \$\$ TRACE command for further information concerning the tracing facility.)

Modification: \$T PUN(nn) command

Note: If you modify this parameter value and then restart JES2 with a hot start, the parameter values in effect before termination will be used. (For further information, see *z/OS JES2 Initialization and Tuning Guide*.)

UNIT={hhhh|/hhhh}

Specifies a 3- or 4-digit hexadecimal device number. Device numbers can be specified by any of the following formats:

```
UNIT=hhh
UNIT=hhhh
UNIT=/hhh
UNIT=/hhhh
```

where hhh and hhhh represent the device numbers.

A slash (/) can optionally precede the device number (for compatibility with other initialization statements that require a slash to denote a 4-digit device number).

If UNIT= is specified, this card punch is allowed to start although it may have been offline during JES2 initialization.

If not specified, JES2 does not assign an available card punch; instead, a card punch can be dynamically assigned using a \$T PUNnn command.

Modification: \$T PUN(nn) operator command.

Volume=(v1[,v2][,3][,4])()

Specifies the 5- to 6-character volume serial number of a volume containing a spool data set. Only output jobs containing tracks on the specified volume can be selected for punching. As many as four volumes can be specified. Use commas to separate individual volume IDs and enclose the list in parenthesis if more than one ID is specified.

Modification: \$T PUN(nn) operator command.

Writer=xxxxxxxx

Specifies the 1- to 8-character writer name assigned to this punch. If not specified, there is no writer name. Wildcard specifications are allowed on this parameter.

Modification: \$T PUN(nn) operator command.

WS=criteria | (W,Q,R,PRM/F)

Specifies the output selection criteria (listed below) for this device. Criteria not specified are not considered during output selection, although they are used by JES2 to determine setup requirements.

Unless otherwise noted, if the criterion is specified before the slash, an exact match is required; if after the slash, an exact match is preferred (and attempted in left to right priority) but not required, only the priority order is considered. The criteria that may be coded follow:

Class|Queue

Specifies that a match must be found for the output classes specified on this device. If Q is omitted from the WS= list, all output queues (beginning with queue A) will be searched for work.

Note: If specified before the slash, the priority of the device characteristics table class list is from left to right. If specified after the slash, there is no device characteristics table class list priority ordering. To increase performance, this criterion should be placed before the slash.

Creator

Specifies that output for the current userid is preferred. JES2 attempts to consecutively select all eligible output for a particular userid. However, output is only grouped in this manner depending upon the specification of the current work selection list and output queues. If specified to the left of the slash, an exact match is required.

Forms

Specifies that the current FORMS specification is either required or preferred. If FORMS is omitted from the criteria list, work selection will not contain any forms checking.

JOBname

Specifies that JES2 gathers all output for a job and attempt to process that output consecutively. The JOBNAME= parameter for a particular device determines what job name JES2 selects when JES2 has processed all output that matches the current job name.

- If JOBname= is specified before the slash in the WS= list:

JES2 selects only those jobs that match the value specified on JOBNAME= for a specific device. When JOBNAME= is specified as a generic name, JES2 only processes jobs that match that pattern and attempts to process all output for that job name consecutively.

- If JOBname= is specified after the slash in the WS= list:

JES2 uses the value specified on JOBNAME= to select new job names for the specific device. If there are no job names that match the JOBNAME= specification, JES2 selects jobs as if JOBname were not listed in the WS= list. A device gathers and processes all output for a particular job before again examining the value specified on JOBNAME= for more jobs.

If you require JES2 to group jobs based on job name but do not want JES2 to prefer a particular JOBNAME= pattern, specify JOBNAME=* on the device statement and code JOBname after the slash in the WS= list.

LIMit

Specifies that the limits of output, as noted on the LIMIT= keyword (on this initialization parameter) will be supported, that is, the amount of generated output must fall within the LIMIT= specification.

This subparameter has no effect as a work selection value for files received from a node that does not provide a page count for its files. For more information, see the sending node's reference documentation.

PRMode|PMD

Specifies that the current PRMODE= specification is preferred. If more than one mode is specified, they are in left to right priority order.

Note: To print output, a match must be found; this criterion should be placed before the slash.

Priority

Specifies that output priority will be considered. Priority is not matched with any other parameter; rather, it specifies that a higher output priority receives greater output preference. If specified before the slash, the importance of selecting output by priority is increased.

Note: To prevent performance degradation, this criterion should be placed after the slash.

Routeode

Specifies that only output destined for a destination specified by a route code listed on the ROUTECDE= parameter is eligible for selection by this device.

Note: If Routeode is specified before the slash, the route code(s) are in left to right priority order; if specified after the slash, there is no such priority order. To prevent performance degradation, this criteria should be placed before the slash.

RANGE

Specifies that the current job ID range is preferred. If specified to the left of the slash, an exact match is required.

Volume

Specifies that only output with tracks on the currently specified volume can be selected for printing. If specified to the left of the slash, the volumes are considered to be in left to right priority order. If specified to the right of the slash, no priority order exists, but an exact match is still required.

Writer

Specifies that the writer name (W=) specification is either required or preferred.


Note: Embedded comments are not allowed within the WS= parameter specification.

Modification: \$T PUN(nn) operator command.

PUNCHDEF - Local Card Punch Environment Definition

The PUNCHDEF statement defines the JES2 punch environment.

Format Description for PUNCHDEF



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for PUNCHDEF

CCWNUM=nnn

Specifies the maximum number (1-235) of double words to be used for channel program area for local punches.

Use the following formula to determine this parameter's recommended value:

```
CCWNUM = (BUFSIZE= parameter on SPOOLDEF statement) / average card length
```

Estimate the average card length to allow for JES2's truncation of trailing blanks.

Note: If a 3525 is interpreting (FUNC=I on the DD card), the CCWNUM must be at least 2.

Default: BUFSIZE parameter on the SPOOLDEF statement / 80.

Modification: Single-member warm start.

DBLBUFR=Yes|No

Specifies whether (Yes) or not (No) double buffering is used for local card punches.

Modification: Single-member warm start.

RDBLBUFR=Yes|No

Specifies whether double buffering (Yes) or single buffering (No) is to be used for remote card punches.


Note: The specification refers to JES2 regular I/O buffers, not to JES2 teleprocessing buffers.

Modification: Single-member warm start.


R(nnnn).PR(m) - Remote Printer


The R(nnnn).PR(m) statement specifies the characteristics of one printer at an RJE workstation. The value of nnnn is the number of an RJE workstation as specified in the RMT(nnnn) statement; m is the number of this printer. Printers are numbered consecutively (Rnnnn.PR1 to Rnnnn.PR7) for the number of printers specified (NUMPRT=n in the RMT(nnnn) statement) for this remote terminal. For example, if there are three printers attached to RJE workstation number 28, the printers are numbered R28.PR1, R28.PR2, and R28.PR3. Use the subscripts (nnnn or m) in an ascending range (n-*) to indicate from n to 32767 or, in a descending range (*-n) to indicate 32767 to n, or * to indicate all remote printers. Note that parameter ranging applies to both remotes and remote printers. Characteristics for remote printers are specified by the following parameters.

Format Description for R(nnnn).PR(m)




Modification keywords









- ### Selection limiting keywords







Notes:

¹ *form* can be coded up to 8 times

Parameter Description for R(nnnn).PR(m)

ASIS=Yes|No

ASIS=Yes causes JES2 to send the print data to the remote printer without suppressing extraneous ejects or adding an eject at the end of a data set. The remote printer will receive the data set as it appears on the JES2 spool.

ASIS=No causes JES2 to send print data to the remote printer, suppressing extraneous ejects and inserting an eject at the end of the data set.

Modification: \$T Rnnnn.PRm operator command.

CCTL=Yes|No

CCTL=Yes specifies that carriage control characters are to be placed in the output stream transmitted to this remote printer. This operand is for use with only SNA devices. CCTL=No is required if SELECT=BASICnn is also specified. When CCTL=No is specified, data will not be compressed or compacted, and SCS control characters will not be placed in the output string.

Modification: \$T Rnnnn.PRm operator command.

CKPTLINE=nnnnn|0

Specifies the maximum number (0-32767) of lines in a logical page. The size of a logical page is also defined as the number of lines printed until:

1. A channel skip is encountered.
2. The line count specified by LINECT= parameter on the PRINTDEF statement, the /*JOBPARM control statement, the /*OUTPUT statement, the JCL OUTPUT statement, or the JOB statement accounting field has been exceeded.

If you specify 0 for CKPTLINE=, a logical page is defined only by items 1 and 2, above.

If the line count specified in item 2 does not equal zero, setting CKPTLINE= to a value greater than line count results in the line count being used as the definition of a logical page; it overrides CKPTLINE=.

JES2 uses CKPTLINE= in conjunction with CKPTPAGE= to determine the checkpoint interval for data sets having a line count of zero and no channel skips.

Modification: \$T Rnnnn.PRm operator command.

CKPTPAGE=nnnnn|1

Specifies the number (1-32767) of logical pages to be printed before each checkpoint is taken. (See the description of the CKPTLINE= parameter.)

For SNA remote printers, the CKPTPAGE= and CKPTLINE= parameters determine the number of logical records within an SNA chain. JES2 will not take a checkpoint until it receives acknowledgment that the chain was received successfully by the remote. The chain size is the number of logical pages specified by CKPTPAGE=.

For BSC remote printers, the CKPTPAGE= and CKPTLINE= parameters determine the number of logical records sent to the remote before a checkpoint is taken. JES2 will not take a checkpoint until it receives acknowledgment that the chain was received successfully by the remote.

Modification: \$T Rnnnn.PRm operator command.

{Class|Queue}=c1[...cn]|AJ

Specifies the output classes to be processed by this printer. You can specify any number of classes (A-Z and 0-9) up to a maximum number of 15 classes.

Modification: \$T Rnnnn.PRm operator command.

CMPCT=Yes|No

For SNA remote printers only, specifies that this printer has compaction capabilities and forces this printer to use compaction if the corresponding RJE workstation initialization statement (RMT(nnnn)) specifies COMPACT=Yes. Specifying CMPCT=Yes also causes the data to be compressed. Specifying CMPCT=NO turns off compaction even if compaction is specified on the RMT(nnnn) initialization statement.

Note:

1. If the RMT(nnnn) initialization statement specifies compaction and the R(nnnn).PR(m) initialization statement does not specify CMPCT=NO, compression will be forced regardless of the CMPCT= specification.
2. CMPCT=Yes is valid only if CCTL=Yes.
3. COMPACT= must be nonzero. If COMPACT=0, no compaction table is used and overrides a CMPCT=Yes specification.

Modification: \$T Rnnnn.PRm operator command.

COMPACT=nn|0

Specifies the compaction table (0-99) to be used for all outbound remote printer data. The COMPACT= parameter of RMT(nnnn) must indicate that compaction is supported by this printer. A compaction table value of 0 indicates no compaction table will be used, and will also override CMPCT=Yes, if it was specified.

Note that if a compaction table number is specified that does not match any compaction table defined by a COMPACT initialization statement, JES2 uses the default of 0.

Modification: \$T Rnnnn.PRm operator command.

COMPRESS=Yes|No

Specifies this printer has compression and expansion capabilities. Specifying COMPRESS=Yes forces this printer to use compression only if the corresponding RJE workstation (RMT(nnnn)) and line (LINE(nnnn)) initialization statements have COMPRESS=Yes specified. Specifying COMPRESS=No turns off compression for this remote SNA printer even if the corresponding RMT(nnnn) initialization statement specifies COMPRESS=Yes.

For SNA remote printers only,

- If CCTL=No, then COMPRESS=Yes is not valid.
- If COMPRESS=Yes, JES2 sets the corresponding bit in the RJE BIND to on.

Modification: \$T Rnnnn.PRm operator command.

CReator=ccccccc

Specifies the 1- to 8-character userid whose output can be selected by this printer. Wildcard specifications are allowed on this parameter.

If you allow this parameter to default, JES2 selects all output for processing, regardless of the userid.

Modification: \$T Rnnnn.PRm operator command.

DEVFCB=xxxx

Specifies the forms control buffer (FCB) this printer uses if the printer selects output that does not have an FCB associated with it.

If you do not specify DEVFCB=, the printer uses the last FCB that you loaded to process the output if that FCB has the default bit turned on. Otherwise, the printer uses the FCB specified on the PRINTDEF statement.

Modification: \$T Rnnnn.PRm operator command.

EJECT=Yes|No

Specifies whether JES2 sends a page eject to a remote printer on the printer's first use following the start of an RJE session depending upon the assumed position of the printer. JES2 assumes that the remote printer is not positioned at the top of a page on the first use after JES2 is started, restarted, or after an RJE session fails and the remote printer is not at the top of a page.

EJECT=Yes causes JES2 to send a page eject when the remote printer is not assumed to currently be at the top of a page. Use this parameter value when the output is destined for a physical printer.

EJECT=No ensures that a print stream never begins with a page eject. Workstations that write SYSOUT to media other than paper can use this parameter to create files that do not contain page ejections in the first line.

You can change this parameter after initialization using a \$T command; however, the change takes effect at the beginning of the next RJE session, regardless of whether printing has begun.

Modification: \$T Rnnnn.PRm operator command.

FCB|C=xxxx

Specifies the forms control buffer image or the carriage control tape that is to be initially mounted on this printer.

For all printers, xxxx is the forms control buffer (FCB) identifier that resides in SYS1.IMAGELIB.

If you do not specify a value, JES2 provides impact printers with the value of the FCB parameter on the PRINTDEF statement as a default.

Modification: \$T Rnnnn.PRm operator command.

FCBLOAD=Yes|No

FCBLOAD=Yes specifies that FCB support is to be provided for this printer. If SETUP=PDIR is specified in the RMT(nnnn) statement, FCBLOAD=No is forced.

Note: FCBLOAD= is effective only if this is a 3211 printer attached to a multileaving RJE workstation that has the text-transparency feature (TRANSPAR=Yes specified for both the LINE(nnnn) and the RMT(nnnn) statements), or if this printer is a SNA RJE workstation. (FCBLOAD for an SNA terminal uses only one stop per channel, for a maximum of 12 stops. Also, the length of FCB images that can be used for this printer cannot exceed the line length specified for this printer (PRWDITH) minus 2.)

Modification: \$T Rnnnn.PRm operator command.

Forms=xxxxxxx

Specifies the 1- to 8-character forms identifier of the forms that are to be loaded initially in this printer. Wildcard specifications are allowed on this parameter.

If you specify no value for this parameter, JES2 will use the forms identifier specified by the STDFORM parameter on the OUTDEF statement.

Modification: \$T Rnnnn.PRm operator command.

JOBname=jcccccc

Specifies the 1- to 8-character job name for jobs whose output can be selected by this printer. Wildcard specifications are allowed on this parameter.

If you allow this parameter to default, JES2 selects all output for processing, regardless of the jobname.

Modification: \$T Rnnnn.PRm operator command.

LIMit=m|m-n|m-*

Specifies that output is selected for specific printers based upon the amount of the output (in records). The values *m* and *n* specify within what output size range (in records) a job output element (JOE) must fall to be processed by this printer. The integer *m* specifies the lower output size limit and *n* specifies the upper output size limit.

For both variables *m* and *n*, you can specify a range of values 0-4294967295. *m* and *n* can be equal. If they are not equal, *n* must be larger than *m*.

If you code only *m*, that value becomes both the lower and upper limit. If *m-** is specified, the upper limit is set to the default value of 4294967295.

After a warm start, the original size of the output (before any printing) will be used to determine where the remainder of the output will be printed. That is, the original size of the JOE will be used to determine output device selection.

Default: If you omit this parameter, JES2 uses the defaults *m*=0 and *n*=4294967295.

Modification: \$T Rnnnn.PRm operator command.

LRECL=nnn|120

For SNA remote printers only, specify the logical record length (1-255) of data transmitted to this SNA remote printer. This value must not exceed the printer width specified during RMT generation (through the &PRTSIZE RMT generation statement) for this terminal. (See *z/OS JES2 Initialization and Tuning Guide* for further information.) You can use LRECL in place of the PRWIDTH= parameter when specifying record sizes for records destined for remote devices. When calculating the value of this parameter, carriage control characters (CCTL) should not be included.

Modification: \$T Rnnnn.PRm operator command.

NEWPAGE={1|ALL|DEFAULT}

Specifies when JES2 treats a 'skip to channel' as a new page.

1

Specifies that JES2 treats only skip to channel 1 as a new page.

ALL

Specifies that JES2 treats skip to any channel as a new page.

DEFAULT

Specifies that JES2 uses the NEWPAGE= value specified on the PRINTDEF initialization statement.

Modification: \$T R(nnnn).PR(m) operator command.

PLIM={m|m-n|m-*

Specifies the lower and upper limits (in pages) for the size of output that is to be selected by this printer.

For both variables *m* and *n*, you can specify a range of values from 0 through 2147483647. *m* and *n* can be equal. If they are not equal, *n* must be larger than *m*.

If you code only *m*, that value becomes both the lower and upper limit. If you specify *m**, the upper limit is set to the default value (4294967295).

- Normally, you should only use PLIM= with functional subsystem (FSS) printers capable of printing page-mode data.
- If the printing of an output group is interrupted, JES2 compares the original size of the output (the number of pages before any printing rather than the pages remaining) with the PLIM= specifications.
- When you specify R(nnnn).PR(m) PLIM= as a non-zero value, JES2 honors PRMODE=PAGE for remote printers and WS= criteria for remote printers.

PRMode=(vvvvvvvv[,vvvvvvv...])

Specifies one to eight names used by JES2 to direct output data sets to this output device. Wildcard specifications are allowed on this parameter. If only one PRMODE= is specified, the parentheses are optional. Users can assign a PRMODE= value to the data sets by using JCL OUTPUT statements. However, if the user does not specify a process mode for the data set, JES2 will assign a process mode.

Your installation may have output devices capable of printing other than line-mode data sets. If so, you can specify a name(s) on this parameter designating the output device as capable of accepting such data sets. For installation-defined process modes, use the Uvvvvvvv form of the process mode designation. The U identifies the process mode as installation defined. Installation-defined and IBM-defined process mode designations may be mixed on one PRMODE parameter statement. For example, you can specify names on this parameter designating the output device as capable of accepting data sets that can be printed on either a plotter device (for example, UPLLOT2) or a line-mode printer by specifying:

```
PRMODE=(UPLLOT2,LINE)
```

Note:

1. You can specify only up to eight process modes on a single device; however, you can specify as many as 255 different modes throughout a particular JES2 member.
2. Within a job entry network, receiving nodes must designate the same process mode as that specified on the data set(s) sent to them. If the receiving node has not specified the same process mode, the data set(s) will not be printed.

Default: LINE, except for those data sets containing formatting controls that can only be processed by page-mode printers. The default for these data sets is PAGE causing an error condition because the page-mode specifications are incompatible with remote print processing.

Modification: \$T Rnnnn.PRm operator command.

PRWIDTH=nnn|120

Specifies the number (1-255) of characters to be printed on one line. This value must not exceed the printer width specified during RMT generation of this multileaving terminal (through the &PRTSIZE statement for multileaving workstations). PRWIDTH= should not be set greater than 120 for printers attached to BSC terminals defined as 2770s without the buffer-expansion feature.

Modification: \$T Rnnnn.PRm operator command.

RANGE={J|S|T}nnnnn[-nnnnn]|J1-999999

Specifies the job ID range for output jobs that can be selected by this printer. Use “J” to specify batch jobs, “S” to specify started tasks, and “T” for TSO/E jobs. You can specify a single job number or range (up to 999999) of jobs. If you code this parameter, you can specify one or two values:

- If you specify one value, that value becomes both the low and the high end of the range.
- If you specify two values, the first value is the low end of the range and the second value the high end. The two values can be equal. If they are not equal, the second value must be larger than the first value.

Modification: \$T Rnnnn.PRm operator command.

Routecde=rtcode

Specifies up to four internal route codes to be assigned to this printer.

The maximum size of a route code is 18 characters. Wildcard specifications are allowed on this parameter for userids only. You can specify a route code in any of the forms listed below.

Ummmm
destid
remote
user

Explanations of the different forms of specifying route codes follow:

Ummmm

Indicates that output for special local routing is selected. The special routing numbers range from 1 to 32767.

destid

Indicates that output routed to the specified node(s) is selected. If destid is specified alone, it refers to both the node and the RJE workstation.

Note: If you specify a destid on the Routecde parameter, you must place the DESTID initialization statement before the R(nnnn).PR(m) statement in the initialization stream.

LOCAL | ANYLOCAL

Indicates that output routed to the local node is selected.

remote

Indicates that output routed to a RJE workstation is selected. Remote can be specified in any of the following ways:

Rmmmm

Indicates that output routed to the specified RJE workstation is selected. Rmmmm can also be specified as RMmmmm or RMTmmmm. The value specified for mmmm can range from 1 to 32767.

destid

Indicates that output routed to a destid referring to an RJE workstation is selected.

user

Indicates that output routed to a specific userid is selected. Generic userids are also valid. A generic userid is a userid that ends in an asterisk (*), and refers to all userids that begin with the characters preceding the *. Note that the * can only be specified in the last position of the userid.

A userid at the local node must be in the form of a valid TSO/E userid. It must begin with an alphabetic (A-Z) or a special character (@ # or \$), and the remaining characters may be alphabetic, numeric, or special characters.

You can override the destination specified with the ROUTECDE= keyword with the set operator command (\$T). If you specify only one route code, the parentheses are optional. To specify a null route code, use Routecde=() to cause this printer to select no work if Routecde is also specified in the WS list.

If you do not specify this parameter, JES2 assigns the route code of the RJE workstation to which the printer is attached. (See the description of the RMT(nnnn) statement in this chapter for more information about the route code.)

Modification: \$T Rnnnn.PRm operator command.

SELECT=PRINTnn|EXCHnn|BASICnn

For SNA remote printers only, specifies the device type (PRINT, EXCH, or BASIC) and device subaddress (n-1) to which output queued for this remote device will be sent. The SELECT options and their meanings are:

Option**Meaning**

PRINTnn

Output sent to printer

EXCHnn

Output sent to exchange diskette device

BASICnn

Output sent to basic exchange diskette device

The value nn specifies the desired device number. The value of nn ranges from 1-15 (subaddress 0-14). If nn is omitted, then any available device (subaddress=15) of the specified type (PRINT, EXCH, or BASIC) will be used. When BASIC is specified, CCTL=NO must be specified and LRECL= must not exceed 128. See the RJE workstation publication for your device for valid device type subaddresses and their requirements.

Example: To cause all output queued to this RJE workstation route code to be sent to an exchange diskette device with subaddress 0, specify:

```
SELECT=EXCH1
```

If you do not specify this parameter, JES2 provides for standard device selection of print and subaddress selection based upon printer number.

Modification: \$T Rnnnn.PRm operator command.

Sep=Yes|No

Specifies whether (Yes) or not (No) JES2 initially provides separator pages between data set groups. (Separator pages can be specified later by the JES2 \$T command.) With the exception of the setup message \$HASP190, SEP=NO also suppresses printing of operator messages at the RJE workstation. JES2 will not print JESNEWS data unless the job separator page is printed. This specification can be overridden by JES2 Exit 1. See [z/OS JES2 Installation Exits](#) for information about Exit 1.

Modification: \$T Rnnnn.PRm operator command.

SEPDS=Yes|No

Specifies whether (Yes) or not (No) data set separator pages are desired for the data sets within the output groups selected for processing by printers. For this parameter to affect processing, you must customize JES2 or a functional subsystem as follows.

For JES-mode printers (MODE=JES), your systems programmer must have written an Exit 15 (Output Data Set/Copy Separators) that examines the SEPDS= specification and produces separator pages when SEPDS=Yes. Exit 15 controls both the production of separator pages and whether they are affected by the SEPDS= parameter. If Exit 15 is enabled, it is invoked even if SEPDS=No. To enable Exit 15, see [z/OS JES2 Installation Exits](#).

For functional subsystem printers (MODE=FSS), JES2 makes an indication of the parameter's setting available to the functional subsystem. If an FSS printer is controlled by PSF, an APSUX03 exit must have been installed to produce data set header pages. APSUX03 is not invoked if SEPDS=NO. For more information about the APSUX03 exit, see [PSF for z/OS: Customization](#).

Modification: \$T Rnnnn.PRm operator command.

Note: Be careful not to confuse this parameter with the SEP= parameter.

SETUP=HALT|NOHALT

Specifies whether JES2 issues the device setup message (\$HASP190) after a change of device characteristics (for example, forms control).

SETUP=HALT halts the printer and issues the setup message. This allows the operator to verify the changes to the printer.

SETUP=NOHALT allows the printer to process output without requiring setup verification by the operator. With SETUP=NOHALT, you can load any printer characteristics that require no manual intervention. The printer uses any previously existing setup characteristics that you have not changed to process output.

Modification: \$T Rnnnn.PRm operator command.

START=Yes|No

Specifies whether (Yes) or not (No) this printer is to be started automatically when JES2 starts processing.

Modification: \$S Rnnnn.PRm operator command or \$P Rnnnn.PRm operator command.

SUSPEND=Yes|No

For BSC remote printers only, specifies whether (Yes) or not (No) JES2 interrupts the printing of a data set every time this remote printer sends an end-of-transmission (EOT) message. An RJE workstation operator might interrupt printing in order to transmit jobs or JES2 commands to the JES2 member.

Modification: \$T Rnnnn.PRm operator command.

Note: This parameter applies only to printers that are connected to BSC hardware terminals.

TRACE=Yes|No|P

Note: TRACE=Yes is identical to specifying TRACE=P.

Specifies whether tracing is activated (Yes) or deactivated (No) for all remote printers. To trace a remote printer, you must also provide the following initialization statements:

```
TRACE(n) START=Yes
TRACEDEF ACTIVE=Yes
```

This parameter setting can be overridden by the \$T R(nnnn).PR(m) command. Remote printer tracing is also controlled by trace IDs 11, 12, 14, 15, the TRACE(n) and TRACEDEF initialization statements, and the \$S TRACE command.

Note: TRACE=Yes is identical to specifying TRACE=P. (See *z/OS JES2 Initialization and Tuning Guide*, the TRACE(n) and TRACEDEF initialization statements in this chapter, and *z/OS JES2 Commands* for a description of the \$S TRACE command for further information concerning the tracing facility.)

Modification: \$T Rnnnn.PRm command

Note: If you modify this parameter value and then restart JES2 with a hot start, the parameter value in effect before termination will be used. (For further information, see *z/OS JES2 Initialization and Tuning Guide*.)

TRANS=Yes|No|DEFAULT

If TRANS=Yes specifies that JES2 translates each line of output sent to the device regardless of the device type or the setting of the PRINTDEF TRANS= parameter.

TRANS=No specifies that JES2 does not translate output sent to the device regardless of the device type or the setting of the PRINTDEF TRANS= parameter.

TRANS=DEFAULT (or TRANS= is omitted) specifies that if TRANS=Yes is specified on the PRINTDEF statement, JES2 translates each line of output sent to the device. Otherwise, JES2 does not translate output sent to the device.

Modification: \$T Rnnnn.PRm,TRANS= operator command. Do not issue this command unless the printer is inactive or drained.

UCS|T=xxxx

Specifies the print train, print chain, or print band default universal character set (UCS) image that is mounted on this printer for use by output without a specific UCS attribute. A UCS image for a printer can be modified through the JES2 \$T Rnnnn.PRm command, but the default UCS image that is mounted on this printer for use by output without a specific UCS attribute cannot be changed.

If you do not specify this parameter, JES2 defaults to the identifier specified by the UCS parameter on the PRINTDEF statement.

Modification: \$T Rnnnn.PRm operator command.

Volume=(v1[,v2][,v3][,v4])()

Specifies the 5- to 6-character volume serial number of a volume containing a spool data set. Only output jobs containing tracks on the specified volume can be selected for printing. As many as four volumes can be specified. Use commas to separate individual volume IDs and enclose the list in parenthesis if more than one ID is specified.

Modification: \$T Rnnnn.PRm operator command.

Writer=xxxxxxx

Specifies the 1- to 8-character writer name assigned to this printer. Wildcard specifications are allowed on this parameter.

Default: no writer name

Modification: \$T Rnnnn.PRm operator command.

WS=criteria | (W,Q,R,PRM,LIM/F)

Specifies the output selection criteria (listed below) for this device. Criteria not specified are not considered during output selection, although they are used by JES2 to determine setup requirements.

Unless otherwise noted, if the criterion is specified before the slash, an exact match is required; if after the slash, an exact match is preferred (and attempted in left to right priority) but not required, only the priority order is considered.

You can specify the following criteria:

Burst

Specifies that the current BURST= specification is either required or preferred.

Class|Queue

Specifies that a match must be found for the output classes specified on this device. If Class/Queue is omitted from the WS= list, all output queues (beginning with queue A) will be searched for work.

Note: If specified before the slash, the priority of the device characteristics table class list is from left to right. If specified after the slash, there is no device characteristics table class list priority ordering. To increase performance, this criterion should be placed before the slash.

CREator

Specifies that output for the current userid is preferred. JES2 attempts to consecutively select all eligible output for a particular userid. However, output is only grouped in this manner depending upon the specification of the current work selection list and output queues. If specified to the left of the slash, an exact match is required.

FCB|C

Specifies that the current forms control buffer (FCB) image or carriage control tape is either required or preferred.

Flash|O

Specifies that the current FLASH specification is either required or preferred.

Forms

Specifies that the current FORMS specification is either required or preferred. If FORMS is omitted from the criteria list, work selection will not contain any forms checking.

JOBname

Specifies that JES2 gathers all output for a job and attempt to process that output consecutively. The JOBNAME= parameter for a particular device determines what job name JES2 selects when JES2 has processed all output that matches the current job name.

- If JOBname= is specified before the slash in the WS= list:

JES2 selects only those jobs that match the value specified on JOBNAME= for a specific device. When JOBNAME= is specified as a generic name, JES2 only processes jobs that match that pattern and attempts to process all output for that job name consecutively.

- If JOBname= is specified after the slash in the WS= list:

JES2 uses the value specified on `JOBNAME=` to select new job names for the specific device. If there are no job names that match the `JOBNAME=` specification, JES2 selects jobs as if `JOBNAME` were not listed in the `WS=` list. A device gathers and processes all output for a particular job before again examining the value specified on `JOBNAME=` for more jobs.

If you require JES2 to group jobs based on job name but do not want JES2 to prefer a particular `JOBNAME=` pattern, specify `JOBNAME=*` on the device statement and code `JOBNAME` after the slash in the `WS=` list.

LIMit

Specifies that the limits of output, as noted on the `LIMIT=` keyword (on this initialization parameter) will be supported, that is, the amount of generated output must fall within the `LIMIT=` specification.

This subparameter has no effect as a work selection value for files received from a node that does not provide a page count for its files. For more information, see the sending node's reference documentation.

PRMode|PMD

Specifies that the current `PRMODE` specification is preferred. If more than one mode is specified, they are in left to right priority order.

Note: To print output, a match must be found; this criterion should be placed before the slash.

Priority

Specifies that output priority will be considered. Priority is not matched with any other parameter; rather, it specifies that a higher output priority receives greater output preference. If specified before the slash, the importance of selecting output by priority is increased.

Note: To prevent performance degradation, this criterion should be placed after the slash.

Routeode

Specifies that only output destined for a destination specified by a route code listed on the `ROUTEODE=` parameter is eligible for selection by this device.

Note:

1. If `Routeode` is specified before the slash, the route code(s) are in left to right priority order; if specified after the slash, there is no such priority order. To prevent performance degradation, this criteria should be placed before the slash.
2. **If `WS=` is added to this remote printer statement, you must specify `Routeode` in the `WS=` list.**

RANGE

Specifies that the current job ID range is preferred. If specified to the left of the slash, an exact match is required.

Volume

Specifies that only output with tracks on the currently specified volume can be selected for printing. If specified to the left of the slash, the volumes are considered to be in left to right priority order. If specified to the right of the slash, no priority order exists, but an exact match is still required.

Writer

Specifies that the writer name (`W=`) specification is either required or preferred.

UCS|T

Specifies that the currently mounted print train (on impact printers only) is either required or preferred. If omitted from the work selection list, the UCS specified for the output is not required to match the device setup, but a setup message will be issued to the operator if the UCS specifications differ.

Note:

1. Embedded comments are not allowed within the `WS=` parameter specification.


2. The LIM= subparameter has no effect as a work selection value for files received from a node that does not provide a page count for its files. For more information, see the sending node's reference documentation.

Modification: \$T Rnnnn.PRm operator command.


R(nnnnn).PU(m) - Remote Card Punch


The R(nnnnn).PU(m) statement specifies the characteristics of one card punch at an RJE workstation. The value of nnnnn is the number of an RJE workstation, as specified in the RMT(nnnnn) statement; m is the number of this card punch. Card punches are numbered consecutively (Rnnnnn.PU1 to Rnnnnn.PU7) for the number of card punches specified (NUMPUN=n in the RMT(nnnnn) statement) for this RJE workstation. For example, if there are two punches attached to RJE workstation number 14, the punches are numbered R14.PU1 and R14.PU2. Use the subscripts (nnnnn or m) in an ascending range (n-*) to indicate from n to 32767 or, in a descending range (*-n) to indicate 32767 to n, or * to indicate all remote punches. Note that, on this statement, parameter ranging applies to both RJE workstations and remote punches. Characteristics for remote punches are specified by the following parameters.

Format Description for R(nnnnn).PU(m)




Modification keywords






Notes:

- ¹ Omit the comma between initialization statement and first keyword
- ² Forms can be coded up to 8 times
- ³ PRMode can be coded up to 8 times

Selection limiting keywords



Notes:

¹ Forms can be coded up to 8 times

Parameter Description for R(nnnnn).PU(m)

CCTL=Yes|No

For SNA remote punches only, specify that carriage control characters are to be placed in the output stream transmitted to this remote punch. CCTL=No is required when the SELECT=BASICnn parameter of the R(nnnnn).PU(m) initialization statement is specified. When CCTL=No is specified, data will not be compressed or compacted, and SCS control characters will not be placed in the output string.

Modification: \$T Rnnnnn.PUm operator command.

CKPTLINE=nnnnnn|100

Specifies the number (1-32767) of cards to be punched per logical page. CKPTLINE is the only value used to define a logical page for punches.

Modification: \$T Rnnnnn.PUm operator command.

Note: To switch off checkpointing, specify CKPTLINE=0.

CKPTPAGE=nnnnnn|1

Specifies the number (1-32767) of logical pages to be punched before each checkpoint is taken. (See the description of the CKPTLINE= parameter.)

For SNA remote punches, the CKPTPAGE= and CKPTLINE= parameters determine the number of logical records within an SNA chain. JES2 will not take a checkpoint until it receives acknowledgment that the chain was received successfully by the RJE workstation. The chain size is the number of logical pages specified by CKPTPAGE=.

For BSC remote punches, the CKPTPAGE= and CKPTLINE= parameters determine the number of logical records sent to the RJE workstation before a checkpoint is taken. The checkpoint is not taken until JES2 receives acknowledgment that the RJE workstation successfully received the data.

Modification: \$T Rnnnnn.PUm operator command.

Class | Queue=c1[...cn]

Specifies the output classes, in priority sequence, to be processed initially by this card punch. You can specify any number of classes (A-Z and 0-9) up to a maximum number of 15 classes.

Modification: \$T Rnnnnn.PUm operator command.

CMPCT=Yes|No

For SNA remote punches only - Specifies that this punch has compaction capabilities. CMPCT=Yes forces this punch to use compaction if the corresponding RJE workstation initialization statement (RMT(nnnnn)) specifies COMPACT=Yes. Specifying CMPCT=Yes also causes the data to be compressed. CMPCT=NO turns off compaction even if compaction is specified on the RMT(nnnnn) initialization statement.

Note:

1. If the RMT(nnnnn) initialization statement specifies compaction and the R(nnnnn).PU(m) initialization statement does not specify CMPCT=No, compression will be forced regardless of the COMPRESS= specification.
2. CMPCT=Yes is valid only if CCTL=Yes.
3. COMPACT= must be nonzero. If COMPACT=0, no compaction table is used and overrides a CMPCT=Yes specification.

Modification: \$T Rnnnnn.PUm operator command.

COMPACT=nn|0

Specifies the compaction table (0-99) to be used for all outbound remote punch data. The COMPACT= parameter of the RMT(nnnnn) statement must indicate that compaction is supported by this punch. A compaction table value of 0 indicates no compaction table will be used, and will also override CMPCT=Yes, if it was specified.

Note that if a compaction table number is specified that does not match any compaction table defined by a COMPACT initialization statement, JES2 uses the default of 0.

Modification: \$T Rnnnnn.PUm operator command.

COMPRESS=Yes|No

Specifies that this punch has compression/expansion capabilities. COMP=Yes forces this punch to use compression only if the corresponding RJE workstation (RMT(nnnnn)) initialization statement has COMPRESS=Yes specified. COMP=No turns off compression for this punch even if the corresponding RMT(nnnnn) initialization statement specifies COMPRESS=Yes.

For SNA remote punches only:

- COMPRESS=Yes is valid only if CCTL=Yes.
- If COMPRESS=Yes, the corresponding bit in the RJE BIND is set on.

Modification: \$T Rnnnnn.PUm operator command.

CREATOR=ccccccc

Specifies the userid whose output can be selected by this punch. Wildcard specifications are allowed on this parameter.

If you allow this parameter to default, JES2 selects all output for processing, regardless of the userid.

Modification: \$T Rnnnnn.PUm operator command.

FLUSH=Yes|No

Specifies whether (Yes) or not (No) JES2 causes a blank card to be punched at the end of each data set or following each copy of a data set.

Intelligent workstations can use this parameter to create files that do not contain blank cards between data sets.

Modification: \$T Rnnnnn.PUm operator command.

FORMS=xxxxxxx

Specifies the 1- to 8-character forms identifier of the forms that are to be loaded initially in this card punch. Wildcard specifications are allowed on this parameter.

If you do not specify a value, JES2 uses the identifier specified by the STDFORM parameter on the OUTDEF statement.

Modification: \$T Rnnnnn.PUm operator command.

JOBname=jcccccc

Specifies the name of jobs whose output can be selected by this punch.

If you allow this parameter to default, JES2 selects all output for processing, regardless of the jobname. Wildcard specifications are allowed on this parameter.

Modification: \$T Rnnnnn.PUm operator command.

LIMit=m|m-n|m-*

Specifies that output is to be selected for specific punches based upon the amount of the output (in records). The designated values *m* and *n* specify within what output size range (in records) a job output element (JOE) must fall to be processed by this punch. The integer *m* specifies the lower output size limit and *n* specifies the upper output size limit.

For both variables *m* and *n*, you can specify a range of values 0-4294967295. *m* and *n* can be equal. If they are not equal, *n* must be larger than *m*.

If you code only *m*, that value becomes both the lower and upper limit. If *m-** is specified, the upper limit is set to the default value of 4294967295.

After a warm start, the original size of the output (before any punching) will be used to determine where the remainder of the output will be punched. That is, the original size of the JOE will be used to determine output device selection.

Default: If you omit this parameter, JES2 uses the defaults *m*=0 and *n*=4294967295.

Modification: \$T Rnnnnn.PUm operator command.

LRECL=nnn|80

For SNA remote punches only, specifies the maximum logical record length (1-255) of data transmitted to this punch.

Modification: \$T Rnnnnn.PUm operator command.

PRMode=(vvvvvvvv[,vvvvvvv...])

Specifies one to eight names used by JES2 to direct output data sets to this output device. Wildcard specifications are allowed on this parameter. If only one PRMODE is specified, the parentheses are optional. Users can assign a PRMODE value to the data sets by using JCL OUTPUT statements. However, if the user does not specify a process mode for the data set, JES2 will assign a process mode.

Your installation may have output devices capable of punching other than line-mode data sets. If so, you can specify one or more names on this parameter designating the output device as capable of accepting such data sets. For installation-defined process modes, use the Uvvvvvvv form of the process mode designation. The U identifies the process mode as installation defined. Installation-defined and IBM-defined process mode designations may be mixed on one PRMODE= parameter. For example, you can specify names on this parameter designating the output device as capable of accepting data sets that can be printed on either a plotter device (for example, UPLOT2) or a line-mode printer by specifying:

```
PRMODE=(UPLOT2, LINE)
```

Note:

1. You can specify only up to eight process modes on a single device; however, you can specify as many as 255 different modes throughout a particular JES2 member.
2. Within a job entry network, receiving nodes must designate the same process mode as that specified on the data set(s) sent to them. If the receiving node has not specified the same process mode, the data set(s) will not be printed.
3. To specify a null processing mode use PRMode=().

Default: LINE, except for those data sets containing formatting controls that can only be processed by page-mode printers. The default for these data sets is PAGE causing an error condition because the page-mode specifications are incompatible with remote punch processing.

Modification: \$T Rnnnnn.PUm operator command.

RANGE={J|S|T}nnnnnn[-nnnnnn]|J1-65534

Specifies the job ID range for output jobs that can be selected by this punch. Use “J” to specify batch jobs, “S” to specify started tasks, and “T” for TSO/E jobs. You can specify a single job number or range (up to 65534) of jobs.

If you code this parameter, you can specify one or two values:

- If you specify one value, that value becomes both the low and the high end of the range.
- If you specify two values, the first value is the low end of the range and the second value the high end. The two values can be equal. If they are not equal, the second value must be larger than the first value.

Modification: \$T Rnnnnn.PUm operator command.

Routeode=

Specifies up to four internal route codes to be assigned to this punch. A route code indicates that this punch is eligible for special routing.

The maximum size of a route code is 18 characters. Wildcard specifications are allowed on this parameter for userids only. You can specify a route code in any of the forms listed below.

Ummmmm
destid
remote
user

Explanations of the different forms of specifying route codes follow:

Ummmmm

Indicates that output for special local routing is selected. The special routing numbers range from 1 to 32767.

destid

Indicates that output routed to the specified node(s) is selected. If destid is specified alone, it refers to both the node and the RJE workstation remote.

Note: If you specify a destid on the Routeode parameter, you must place the DESTID initialization statement before the R(nnnnn).PU(m) statement in the initialization stream.

LOCAL | ANYLOCAL

Indicates that output routed to the local node is selected.

remote

Indicates that output routed to an RJE workstation is selected. *remote* can be specified in any of the following ways:

Rmmmmm

Indicates that output routed to the specified RJE workstation is selected. Rmmmmm can also be specified as RMmmmmm or RMTmmmmm. The value specified for mmmmmm can range from 1 to 32767.

destid

Indicates that output routed to a destid referring to an RJE workstation is selected.

user

Indicates that output routed to a specific userid is selected. Generic userids are also valid. A generic userid is a userid that ends in an asterisk (*), and refers to all userids that begin with the characters preceding the *. Note that the * can only be specified in the last position of the userid.

A userid at the local node must be in the form of a valid TSO/E userid. (It must begin with an alphabetic (A-Z) or a special character (@ # or \$), and the remaining characters may be alphabetic, numeric, or special characters.)

You can override the destination specification with the set operator command (\$T). If you specify only one route code, the parentheses are optional. To specify a null route code use Routecde=() to cause this punch to select no work if Routecde is also specified in the WS list. Use the Unnnnn form to specify this punch as a special local punch.

If you do not specify a route code value, JES2 assigns the route code of the RJE workstation to which the punch is attached. (See the description of the RMT(nnnnn) statement in this chapter for more information about the route code.)

Modification: \$T Rnnnnn.PUm operator command.

SELECT=PUNCHnn|EXCHnn|BASICnn

For SNA remote punches only, specifies the device type (PUNCH, EXCH, or BASIC) and device subaddress (n-1) to which output queued for this remote device will be sent. The SELECT options and their meanings are:

Option

Meaning

PUNCH(nn)

Output sent to punch (card format)

EXCHnn

Output sent to exchange diskette device

BASICnn

Output sent to basic exchange diskette device

The value nn specifies the desired device number. The value of nn may range from 1-15 (subaddress 0-14). If nn is omitted, then any available device (subaddress 15) of the specified type (PUNCH, EXCH, or BASIC) will be used. When BASIC is specified, NOCCTL must be specified and LRECL must not exceed 128. See the RJE workstation publication for your device for valid device type subaddresses and their requirements.

Example: To cause all output to this RJE workstatio route code to be sent to a basic exchange diskette with subaddress 0, specify:

```
SELECT=BASIC1
```

Note: If this is the only punch defined, Specification of BASICnn or EXCHnn for a SNA device will cause the media-byte presentation service portion of the bind to be changed to reflect non-card format.

If you do not specify a value, JES2 defaults to the standard device selection of punch and subaddress selection based upon punch number.

Modification: \$T Rnnnnn.PUm operator command.

Sep=Yes|No

Specifies whether (Yes) or not (No) separator cards are provided initially between data set groups. (Separator cards can be specified later by operator command.) This specification can be overridden if an installation exit routine is provided by JES2 Exit 1. See [z/OS JES2 Installation Exits](#) for information about Exit 1.

Modification: \$T Rnnnnn.PUm operator command.

SEPDS=Yes|No

Specifies whether you desire data set separator cards for the data sets within the job output elements (JOEs) selected for processing by the specific device. If you enabled Exit 15 (Output Data Set/Copy Separators), the exit can test for SEPDS=Yes to cause the exit to generate separator cards for each data set selected by this device. See [z/OS JES2 Installation Exits](#) for information about Exit 15.

Modification: \$T Rnnnnn.PUm operator command.

Note: Be careful not to confuse this parameter with the SEP= parameter.

SETUP=HALT|NOHALT

Specifies whether JES2 issues the device setup message (\$HASP190) after a change of device characteristics (for example, forms control).

SETUP=HALT halts the punch and issues the setup message. This allows the operator to verify the changes to the punch.

SETUP=NOHALT allows the punch to process output without requiring setup verification by the operator. The punch uses any previously existing setup characteristics that you have not changed to process output.

Modification: \$T Rnnnnn.PUm operator command.

START=Yes|No

Specifies whether (Yes) or not (No) this punch is started automatically when JES2 starts processing.

Modification: \$S Rnnnnn.PUm operator command or \$P Rnnnnn.PUm operator command.

SUSPEND=Yes|No

For BSC remote punches only, Specifies whether (Yes) or not (No) JES2 interrupts the punching of a data set every time this remote punch sends an end-of-transmission (EOT) message. An RJE workstation operator might interrupt punching in order to transmit jobs or JES2 commands to the JES2 member.

Modification: \$T Rnnnnn.PUm operator command.

Specifies whether tracing is activated or deactivated for all remote punches. To trace a remote punch, you must also provide the following initialization statements:

```
TRACE(n) START=Yes
TRACEDEF ACTIVE=Yes
```

TRace=Yes|No|P

Note: TRACE=Yes is identical to specifying TRACE=P. This parameter setting can be overridden by the \$T R(nnnnn).PU(M) operator command. Remote punch tracing is also controlled by trace IDs 11 and 12, the TRACE(n) and TRACEDEF initialization statements, and the \$S TRACE command. (See *z/OS JES2 Initialization and Tuning Guide*, the TRACE(n) and TRACEDEF initialization statements in this chapter, and *z/OS JES2 Commands* for a description of the \$S TRACE command for further information concerning the tracing facility.)

Modification: \$T Rnnnnn.PUm command

Note: If you modify this parameter value and then restart JES2 with a hot start, the parameter value in effect before termination will be used. (For further information, see *z/OS JES2 Initialization and Tuning Guide*.)

Volume=(v1[,v2][,v3][,v4])|()

Specifies the 5- to 6-character volume serial number of a volume containing a spool data set. Only output jobs containing tracks on the specified volume can be selected for punching. As many as four volumes can be specified. Use commas to separate individual volume IDs and enclose the list in parenthesis if more than one ID is specified.

Modification: \$ T Rnnnnn.PUm command.

Writer=xxxxxxx

Specifies the 1- to 8-character writer name assigned to this punch. Wildcard specifications are allowed on this parameter.

Default: no writer name

Modification: \$T Rnnnnn.PUm operator command.

WS=criteria | (W,Q,R,PRM,LIM/F)

Specifies the output selection criteria (listed below) for this device. Criteria not specified are not considered during output selection, although they are used by JES2 to determine setup requirements.

Unless otherwise noted, if the criterion is specified before the slash, an exact match is required; if after the slash, an exact match is preferred (and attempted in left to right priority) but not required, only the priority order is considered. The criteria that may be coded follow:

Class|Queue

Specifies that a match must be found for the output classes specified on this device. If Class/Queue is omitted from the WS list, all output queues (beginning with queue A) will be searched for work.

Note: If specified before the slash, the priority of the device characteristics table class list is from left to right. If specified after the slash, there is no device characteristics table class list priority ordering. To increase performance, this criterion should be placed before the slash.

CReator

Specifies that output for the current userid is preferred. JES2 attempts to consecutively select all eligible output for a particular userid. However, output is only grouped in this manner depending upon the specification of the current work selection list and output queues. If specified to the left of the slash, an exact match is required.

Forms

Specifies that the current FORMS specification is either required or preferred. If FORMS is omitted from the criteria list, work selection will not contain any forms checking.

JOBname

Specifies that JES2 gathers all output for a job and attempt to process that output consecutively. The JOBNAME= parameter for a particular device determines what job name JES2 selects when JES2 has processed all output that matches the current job name.

- If JOBname= is specified before the slash in the WS= list:

JES2 selects only those jobs that match the value specified on JOBNAME= for a specific device. When JOBNAME= is specified as a generic name, JES2 only processes jobs that match that pattern and attempts to process all output for that job name consecutively.

- If JOBname= is specified after the slash in the WS= list:

JES2 uses the value specified on JOBNAME= to select new job names for the specific device. If there are no job names that match the JOBNAME= specification, JES2 selects jobs as if JOBname were not listed in the WS= list. A device gathers and processes all output for a particular job before again examining the value specified on JOBNAME= for more jobs.

If you require JES2 to group jobs based on job name but do not want JES2 to prefer a particular JOBNAME= pattern, specify JOBNAME=* on the device statement and code JOBname after the slash in the WS= list.

LIMit

Specifies that the limits of output, as noted on the LIMIT= keyword (on this initialization parameter) will be supported, that is, the amount of generated output must fall within the LIMIT= specification.

This subparameter has no effect as a work selection value for files received from a node that does not provide a page count for its files. For more information, see the sending node's reference documentation.

PRMode|PMD

Specifies that the current PRMODE specification is preferred. If more than one mode is specified, they are in left to right priority order.

Note: To punch output, a match must be found; this criterion should be placed before the slash.

Priority

Specifies that output priority will be considered. Priority is not matched with any other parameter; rather, it specifies that a higher output priority receives greater output preference. If specified before the slash, the importance of selecting output by priority is increased.

Note: To prevent performance degradation, this criterion should be placed after the slash.

Route code

Specifies that only output destined for a destination specified by a route code listed on the ROUTECDE= parameter is eligible for selection by this device.

Note:

1. If Route code is specified before the slash, the route code(s) are in left to right priority order; if specified after the slash, there is no such priority order. To prevent performance degradation, this criteria should be placed before the slash.
2. **If WS= is added to this remote punch statement, you must specify Route code in the WS= list.**

RANGE

Specifies that the current job ID range is preferred. If specified to the left of the slash, an exact match is required.

Volume

Specifies that only output with tracks on the currently specified volume can be selected for punching. If specified to the left of the slash, the volumes are considered to be in left to right priority order. If specified to the right of the slash, no priority order exists, but an exact match is still required.

Writer

Specifies that the writer name (W=) specification is either required or preferred.




Note: Embedded comments are not allowed within the WS= parameter specification.

Modification: \$T Rnnnnn.PUm operator command.






R(nnnnnn).RD(m) - Remote Card Reader

The R(nnnnnn).RD(m) statement specifies the characteristics of one card reader at a remote terminal. The value of nnnnnn is the number of the remote terminal, as specified in the RMT(nnnnnn) statement; m is the number of this reader. Readers are numbered consecutively (Rnnnnnn.RD1 to Rnnnnnn.RD7) for the number of readers (NUMRD=n in the RMT(nnnnnn) statement) specified for this remote terminal. For example, if there are three card readers attached to remote terminal 2, the readers are numbered R2.RD1, R2.RD2, and R2.RD3. Use the subscripts (nnnnnn or m) in an ascending range (n-*) to indicate from n to 32767 or, in a descending range (*-n) to indicate 32767 to n, or * to indicate all remote readers. Note that parameter ranging applies to both remotes and remote readers. Characteristics of remote readers are specified by the following parameters.


Format Description for R(nnnnnn).RD(m)



Modification keywords



Selection limiting keywords



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for R(nnnnnn).RD(m)

Class=v|A

Specifies the job class to be assigned to all jobs that are entered at this card reader and that do not specify a job class in the CLASS operand of their JOB statements.

Modification: \$T Rnnnnnn.RDm operator command.

Hold=Yes|No

Specifies whether (Yes) or not (No) all jobs entered at this card reader are held after JCL conversion until they are released for execution by the operator.

Modification: \$T Rnnnnnn.RDm operator command.

MSGclass=v|A

Specifies the default message class to be assigned to jobs that are entered at this card reader and that do not specify a MSGclass operand in their JOB statements.

Modification: \$T Rnnnnnn.RDm operator command.

PRIOINC=nn|@

Specifies a number (0-15) to be added to the selection priority of each job entered at this card reader. If the total of this number and a job's priority exceeds the priority level specified by PRIOLIM=, JES2 will use the priority level specified by PRIOLIM=.

Modification: \$T Rnnnnnn.RDm operator command.

PRIOLIM=nn|15

Specifies the maximum priority level (0-15) that can be assigned to jobs entered at this card reader. If a job's priority (with or without the increment specified by PRIOINC=) exceeds this level, it will be reduced to this level.

Modification: \$T Rnnnnnn.RDm operator command.

PRTDEST=jnnnnnnnn[.jnnnnnnnn]

Specifies the default print destination for the print output from all jobs that are entered at this card reader and that do not have a /*ROUTE statement or DEST parameter.

If you do not specify a route code value, JES2 defaults to the route code (ROUTECD= specified on the RMT(nn) statement) for this remote terminal.

Modification: \$T Rnnnnnn.RDm operator command.

Note: If you specify PRTDEST=, you must place the DESTID initialization statement before the R(nnnnnn).RD(m) statement in the initialization stream.

PUNDEST=jnnnnnnnn[.jnnnnnnnn]

Specifies the default punch destination for the punch output from all jobs that are entered at this card reader and that do not have a /*ROUTE statement or DEST parameter.

If you do not specify a route code value, JES2 defaults to the route code (ROUTECD= specified on the RMT(nn) statement) for this remote terminal.

Modification: \$T Rnnnnnn.RDm operator command.

Note: If you specify PUNDEST=, you must place the DESTID initialization statement before the R(nnnnnn).RD(m) statement in the initialization stream.

START=Yes|No

Specifies whether (Yes) or not (No) this card reader is to start automatically when JES2 starts processing.

Modification: \$S Rnnnnnn.RDm operator command or \$P Rnnnnnn.RDm operator command.

Specifies whether tracing is activated (Yes) or deactivated (No) for all remote readers. To trace a remote reader, you must also provide the following initialization statements:

TRACE(n) START=Yes
TRACEDEF ACTIVE=Yes

TRACE=Yes|No|P

This parameter setting can be overridden by the \$T R(nnnnnn).RD(m) operator command. Internal reader tracing is also controlled by trace IDs 11 and 12, the TRACE(n) and TRACEDEF initialization statements, and the \$S TRACE command. (See *z/OS JES2 Initialization and Tuning Guide*, the TRACE(n) and TRACEDEF initialization statements in this chapter, and *z/OS JES2 Commands* for a description of the \$S TRACE command for further information concerning the tracing facility.)

Modification: \$T Rnnnnnn.RDm command.

Note: TRACE=Yes is identical to specifying TRACE=P. If you modify this parameter value and then restart JES2 with a hot start, the parameter value in effect before termination will be used. (For further information, see *z/OS JES2 Initialization and Tuning Guide*.)

Xeqdest=jnnnnnnnn

Specifies the name of the node where jobs entered on the device are to be executed.

Modification: \$T Rnnnnnn.RDm operator command

RDR(nn) - Local Card Reader

The RDR(nn) statement specifies the characteristics of one local card reader. Each reader is defined by a RDR(nn) statement with a unique value (1-99) specified for nn. Use the subscript (nn) in an ascending range (n-*) to indicate from n to 99 or, in a descending range (*-n) to indicate 99 to n, or * to indicate all readers.

The dual reader/punch feature is supported by JES2 as shown in the following example. Assume that a 3525 with the read feature has a unit address of 013 and that the following two items appear in the JES2 initialization data set:


RDR(nn)

```
RDR(2) UNIT=013,START=N0  
PUN(1) UNIT=013
```


When JES2 is started, the reader is stopped and the punch feature is activated. If the operator later wishes to read data from the 3525, punch 1 can be stopped and reader 2 started with JES2 operator commands.

Reader characteristics are specified by the following parameters.


Format Description for RDR(nn)



Modification keywords



Selection limiting keywords



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for RDR(nn)

Auth=(Job=Yes|No,Device=Yes|No,System=Yes|No)

Specifies the command authority for this card reader. These values authorize certain JES2 commands to be entered at this card reader.

Job=Yes|No

Specifies that the device can (Yes) or cannot (No) issue commands which require job authority.

Device=Yes|No

Specifies that the device can (Yes) or cannot (No) issue commands which require device authority.

System=Yes|No

Specifies that the device can (Yes) or cannot (No) issue commands which require system authority.

Note: This parameter has no effect when the associated resource class and profile in RACF 1.9 or higher are active. For more information on JES2 security, see [z/OS JES2 Initialization and Tuning Guide](#).

This parameter affects JES2 command statements only. Use the AUTH= parameter of the JOBCLASS initialization statement to specify the authorization for JCL command statements. (JES2 command statements begin with /* in columns 1 and 2. JCL command statements begin with // in columns 1 and 2.)

Modification: \$T RDRnn operator command.

Class=v|A

Specifies the default job class (A-Z,0-9) to be assigned to all jobs entered at this card reader that do not specify a job class in the CLASS operand of their JOB statements.

Modification: \$T RDRnn operator command.

Hold=Yes|No

Specifies whether (Yes) or not (No) all jobs entered at this card reader are held after JCL conversion until they are released for execution by the operator.

Modification: \$T RDRnn operator command.

MSGclass=v|A

Specifies the default message class (A-Z, 0-9) to be assigned to jobs entered at this card reader that do not specify a MSGCLASS operand in their JOB statements.

Modification: Operator command.

PRTDEST=jnnnnnn[.jnnnnnn]|LOCAL

Specifies the default print destination for the print output from all jobs that are entered at this card reader and that do not have a /*ROUTE statement or DEST parameter.

Modification: \$T RDRnn operator command.

Note: If destid is used, it must be previously defined on a DESTDEF statement in the initialization stream.

PRIINC=nn|0

Specifies a number (0-15) to be added to the selection priority of each job entered at this card reader. If the total of this number and a job's priority exceeds the priority level specified by the PRIOLIM= parameter, JES2 will use the priority level specified by PRIOLIM=.

Modification: \$T RDRnn operator command.

PRIOLIM=nn|15

Specifies the maximum priority level (0-15) that can be assigned to jobs entered at this card reader. If a job's priority (with or without the increment specified by PRIINC=) exceeds this level, it will be reduced to this level.

Modification: \$T RDRnn operator command.

PUNDEST=jnnnnnn[.jnnnnnn]|LOCAL

Specifies the default punch destination for the punch output from all jobs that are entered at this card reader and that do not have a /*ROUTE statement or DEST parameter.

Modification: \$T RDRnn operator command.

Note: If destid is used, it must be previously defined on a DESTDEF statement in the initialization stream.

START=Yes|No

START=Yes specifies that this reader (if ready) will be started automatically by JES2 after initialization and that no additional commands will be required to reactivate it when it becomes inactive.

START=No specifies that this reader is initialized in the drained state. This requires that an operator command, \$S RDRnn, must be issued before the first usage of the reader. In addition, after every EOF, this reader will become inactive and will require a \$S RDRnn command to be reactivated.

Modification: \$S RDRnn command or \$P RDRnn command.

Note:

1. This automatic reader start feature is not available to secondary JES2 subsystems.
2. If the reader is to be started automatically and is unavailable when JES2 is started, it remains unusable until the next time JES2 is started unless the UNIT= keyword is specified on this device statement. If UNIT= is specified, the reader is allowed to start although it may have been offline during JES2 initialization.

TRace=Yes|No|P

Specifies tracing is activated (Yes) or deactivated (No) for all readers. To trace a reader, you must also provide the following initialization statements:

```
TRACE(n) START=Yes
TRACEDEF ACTIVE=Yes
```

Note: TRACE=Yes is identical to specifying TRACE=P.

Tracing readers is also controlled by trace IDs 11 and 12, the TRACE(n) and TRACEDEF initialization statements, and the \$T RDRnn command. (See *z/OS JES2 Initialization and Tuning Guide*, the TRACE(n) and TRACEDEF initialization statements in this chapter, and *z/OS JES2 Commands* for a description of the \$T RDRnn command for further information concerning the tracing facility.)

Modification: \$T RDRnn command.

Note: If you modify this parameter value and then restart JES2 with a hot start, the parameter value in effect before termination will be used. (For further information, see *z/OS JES2 Initialization and Tuning Guide*.)

UNIT={hhh|/hhhh}

Specifies a 3- or 4-digit hexadecimal device number. Device numbers can be specified by any of the following formats:

```
UNIT=hhh
UNIT=hhhh
UNIT=/hhh
UNIT=/hhhh
```

where hhh and hhhh represent the device numbers.

A slash (/) can optionally precede the device number (for compatibility with other initialization statements that require a slash to denote a 4-digit device number).

If UNIT= is specified, this device is allowed to start although it may have been offline during JES2 initialization.

If you do not specify this parameter, JES2 does not assign an available reader; instead, a reader can be dynamically assigned using a \$T RDRnn command.

Modification: \$T RDRnn operator command.

CKPTVRNS

Indicates checkpoint version subtask errors

CONVERT

Indicates JCL conversion subtask errors

DISTERR

Indicates disastrous errors

EOM

Indicates end of memory subtask errors

GENERAL

Indicates generalized subtask recovery errors

IMAGE

Indicates image subtask errors

LIM

Indicates resource limits subtask errors

MAIN

Indicates JES2 main task errors (catastrophic and abends)

MIGR

Indicates spool migration subtask errors

NODUMP

Indicates no dump disastrous errors. Altering this setting allows dumps to be taken even when no dump was requested.

OFFLOAD

Indicates offload subtask errors

PQE

Indicate print/punch queue errors

SMF

Indicates SMF subtask errors

SPOOL

Indicates spool subtask errors

VTAM

Indicates VTAM subtask errors

WTO

Indicates WTOsubtask errors

COUNT=nn

For the MAIN type, COUNT= specifies the number (1-99) of errors (within the INTERVAL= time period) below which the operator does not become involved in the recovery process. The operator becomes involved with the recovery process at the point *nn* errors are experienced within the INTERVAL= period. For subtasks and disastrous error TYPE= specifications, this parameter specifies the number of errors at which automatic SVC dumps are no longer taken, if the errors occur within the INTERVAL= period. Therefore, this means that if a single automatic dump is desired for a subtask or disastrous error, COUNT=2 must be specified.

Default: See the following table of default values (by error type):

Type

COUNT=

ALLOCATE

2

ASST

2

CBIO

2

CKPT
 2
CKPTONCF
 2
CKPTONDA
 2
CKPTVRNS
 2
CONVERT
 2
DISTERR
 2
EOM
 2
GENERAL
 2
IMAGE
 1
LIM
 2
LIM
 24
MAIN
 10
MIGR
 2
NODUMP
 0
OFFLOAD
 1
PQE
 1
SMF
 2
SPOOL
 2
VTAM
 2
WTO
 2

*
 Depends on the type of error received

Modification: \$T RECVopts operator command.

INTERVAL=nnnn

Specifies the number of hours (0-9999) in the current interval in which JES2 is counting errors. Zero indicates no operator involvement.

Default: See the following table of default values (by error type):

Type
INTERVAL=

ALLOCATE

24

ASST

24

CBIO

24

CKPT

24

CKPTONCF

24

CKPTONMDA

24

CKPTVRNS

24

CONVERT

24

DISTERR

24

EOM

24

GENERAL

24

IMAGE

24

MAIN

1

MIGR

24

NODUMP

24

OFFLOAD

24

PQE

24

SMF

24

SPOOL

24

VTAM

24

WTO

24

Depends on the type of error received

Modification: \$T RECVopts operator command.

REDIRect(vvvvvvvv) - Direct Output of Display Commands

Use the REDIRECT(vvvvvvvv) initialization statement to control where JES2 directs the response to certain display commands, when they are entered at a console identified by vvvvvvvv. For vvvvvvvv,


specify a 2- to 8-character console identifier from which an operator enters the command, or a 2-decimal digit console identifier.

In a sysplex, if a JES2 subsystem has SCOPE=SYSTEM on its CONDEF initialization statement, redirection will not be in effect for that subsystem. To have that subsystem take part in the redirection, issue the \$T REDirect command on that JES2.

Adding Applications

This statement and all its parameters can be added after initialization with the **\$ADD REDirect(vvvvvvvv) operator command**.

Format Description for REDirect(vvvvvvvv)



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for REDirect(vvvvvvvv)

command

Specifies the display command for which JES2 is to direct responses to either a display area on the command entry console or another console, as indicated by consolid. The display commands that may be specified are the following:

DA=

Display active jobs command

DCONNECT=

Display network connections

DEF=

Display JES2 parameter definitions

DF=

Display forms queue

DI=

Display initiators

DJ=

Display job, started task (STC), or TSO/E logon (TSU) information

DN=

Display queued jobs

DNODE=

Display NJE nodes

DQ=

Display number of queued jobs

DSPL=

Display spool volumes

DU=

Display units

LJ=

List job output, started task (TSU), or TSO/E logon (TSU) information.

For more information about these commands, see [z/OS JES2 Commands](#).**consolid**

Specifies the console (or console and area) to which JES2 sends the response to the redirected command. The consolid can be specified in one of the following formats:

a

Specifies a display area on the entry console.

hh

Specifies the 1- or 2-digit decimal console identifier.

hha

Specifies the 1- or 2-digit decimal console identifier (hh) and a display area of that console (a).

xxxxxxxx

Specifies the 2- to 8-character symbolic name of a console.

xxxxxxxx-a

Specifies the 2- to 8-character symbolic name of a console (xxxxxxxx) and a 1-character identifier for a display area of that console (a).

Figure 1 on page 378 shows examples of valid console ids.

```

1          -- MVS console with ID 1
D          -- Area "D" of the entry console
23B       -- Area "B" of MVS console 23
PRTPOOL1  -- MVS console with symbolic name PRTPOOL1
PRTPOOL1-C -- Area "C" of console with symbolic name PRTPOOL1

```

Figure 1. Examples of Valid Console IDs[z/OS MVS Planning: Operations](#) explains how to plan your installation's console configuration.

If you do not specify this statement at initialization, JES2 directs all command responses to an area of the command entry console as specified in the RDIRAREA= parameter of the CONDEF initialization statement.

Modification: \$T REDIRect operator command, to modify redirection for a command already named on a REDIRect(vvvvvvvv) initialization statement. However, if a REDIRect(vvvvvvvv) does not exist for a particular console and you want to direct responses to display commands elsewhere, you must issue the \$ADD REDIRect command with the appropriate parameters.

REP - Replacing Code Through the JES2 Patching Facility

The REP initialization statement is one of several statements used by the JES2 patching facility. For the other statements, see “[VERify - Verifying Code Through the JES2 Patching Facility](#)” on page 432 and “[NAME - Naming the Module to Change Through the JES2 Patching Facility](#)” on page 219. The JES2 patching facility allows you to specify temporary replacement data (patches) for the following:

- Any module in JES2 (HASJES20 or an installation exit load module)
- Any absolute storage address from the address space where JES2 is loaded.
- On a hot start, any address in a data space created by JES2 (that is, owned by JES2AUX)
- On any warm start, any address in the JES2 checkpoint data set.

Patching facility statements are placed in the JES2 initialization data set and applied when JES2 is initialized. The JES2 patching facility applies temporary patches to the in-storage copy of JES2 modules. Because some of the initialization code has already been executed before the patch facility initialization statements are processed, patches made to those portions of the code are ineffective; those portions of code **do not** execute again until you restart JES2. Most patches are applied immediately as the statements are processed. However, checkpoint updates are deferred until the checkpoint record is read. Non-checkpoint patches are not saved across a warm start. JES2 reloads the load modules at different stages in processing:


- Subsystem support modules are reloaded during all starts except a hot start.
- HASPJES20 is reloaded in response to a JES2 START command any time the JES2 member is started.

In addition, you should be aware that the JES2 patching facility does **not** support:

- Patching a module or data area residing in read-only storage. For example, you cannot use the facility to modify modules in PLPA or PSA.
- Patching a HASPFSSM load module that has been loaded into a functional subsystem address space. Use AMASPZAP (the service aid program that modifies both instructions and data) to patch the HASPFSSM load module.
- Altering the JES2 dump formatting exit modules (HASMxxxx).
- Using a patch across a restart of JES2. Because these patches are valid only until a load module is reloaded, they must be reapplied every time JES2 is started.

The JES2 patching facility statements in the JES2 initialization data set can be specified in either the JES2 patching format or in the AMASPZAP format. All patches in the JES2 patching form should precede any AMASPZAP patches. If you supply the NAME statement or first format type of the AMASPZAP patch, JES2 resets prior verification errors. For more information on AMASPZAP patches, see “SPZAP” in [z/OS MVS Diagnosis: Tools and Service Aids](#).

Format Description for REP



Notes:

- ¹ Omit the comma between initialization statement and first keyword or variable

Parameter Description for REP

{REPLACE|REP}

The data on the statement replaces the data at the location specified by the csect and address fields.

csect[dspname|CKPTname]*

Specifies the control section (or control block), data space name, or checkpoint CTENT in which the data to be modified resides. If an asterisk (*) is coded, JES2 uses the CSECT, dataspace or CTENT in effect on a previous JES2 patch statement. Table 95 on page 380 and Table 96 on page 384 contain lists of the possible patch names that can be coded and area to which these names refer. If the CSECT is listed in Table 95 on page 380, you can specify the last four characters of the CSECT name.

If an installation exit CSECT is referenced, the JES2 Patching Facility requires the entire module name, except for the reserved names HASPXJ00-HASPXJ31. If you do not link it the installation exit routines HASPXJ00 - HASPXJ31 with the HASJES20 load module, you must specify the full 8-character CSECT name. Furthermore, do not name an exit with the same three or four characters (xxxx) as used for a JES2 module. For example, an installation-defined exit named CKPT or TABS (that is, HASPCKPT or HASPTABS, with the HASP characters removed) would modify the IBM-supplied HASPCKPT or HASPTABS module.

Table 95. Patch Name to CSECT Reference

CSECT Referenced	AMASPZAP Patch Name	JES2 Patch Name
HASCARMS	HASCARMS	ARMS
HASCARSO	HASCARSO	ARSO
HASCBLDM	HASCBLDM	BLDM
HASCCNVS	HASCCNVS	CNVS
HASCDAU	HASCDAU	DAU
HASCENF	HASCENF	ENF
HASCGGKY	HASCGGKY	GGKY
HASCGGST	HASCGGST	GGST
HASCHAM	HASCHAM	HAM
HASCINJR	HASCINJR	INJR
HASCJBST	HASCJBST	JBST
HASCJBTR	HASCJBTR	JBTR
HASCLINK	HASCLINK	LINK
HASCNJAS	HASCNJAS	NJAS
HASCNJEX	HASCNJEX	NJEX
HASCNJGP	HASCNJGP	NJGP
HASCNJE	HASCNJE	NJE
HASCNJJR	HASCNJJR	NJJR
HASCNJJT	HASCNJJT	NJJT
HASCNJSR	HASCNJSR	NJSR
HASCNJST	HASCNJST	NJST
HASCNJRC	HASCNJRC	NJRC
HASCNJRQ	HASCNJRQ	NJRQ

Table 95. Patch Name to CSECT Reference (continued)

CSECT Referenced	AMASPZAP Patch Name	JES2 Patch Name
HASCOFST	HASCOFST	OFST
HASCPHAM	HASCPHAM	PHAM
HASCPCYC	HASCPCYC	PCYC
HASCPPOOL	HASCPPOOL	POOL
HASCRQUE	HASCRQUE	RQUE
HASCSAPI	HASCSAPI	SAPI
HASCSCAN	HASCSCAN	SCAN
HASCSIFI	HASCSIFI	SIFI
HASCSIRQ	HASCSIRQ	SIRQ
HASCSISC	HASCSISC	SISC
HASCSJFA	HASCSJFA	SJFA
HASCSJFS	HASCSJFS	SJFS
HASCSRAX	HASCSRAX	SRAX
HASCSRIP	HASCSRIP	SRIP
HASCTP	HASCTP	TP
HASCUBES	HASCUBES	UBES
HASCUBFR	HASCUBFR	UBFR
HASCUBRM	HASCUBRM	UBRM
HASCUBSR	HASCUBSR	UBSR
HASCXJCT	HASCXJCT	XJCT
Absolute Storage Location	-	ABS
HASPARM	HASPARM	ARM
HASPARMO	HASPARMO	ARMO
HASPBSC	HASPBSC	BSC
HASPCFAL	HASPCFAL	CFAL
HASPCFBF	HASPCFBF	CFBF
HASPCFDE	HASPCFDE	CFDE
HASPCFE	HASPCFE	CFE
HASPCFFC	HASPCFFC	CFFC
HASPCFLE	HASPCFLE	CFLE
HASPCFMT	HASPCFMT	CFMT
HASPCFQL	HASPCFQL	CFQL
HASPCFQU	HASPCFQU	CFQU
HASPCFRD	HASPCFRD	CFRD

<i>Table 95. Patch Name to CSECT Reference (continued)</i>		
CSECT Referenced	AMASPZAP Patch Name	JES2 Patch Name
HASPCFRE	HASPCFRE	CFRE
HASPCFRL	HASPCFRL	CFRL
HASPCFRS	HASPCFRS	CFRS
HASPCFR2	HASPCFR2	CFR2
HASPCFSI	HASPCFSI	CFSI
HASPCFT1	HASPCFT1	CFT1
HASPCFUN	HASPCFUN	CFUN
HASPCFWP	HASPCFWP	CFWP
HASPCFWR	HASPCFWR	CFWR
HASPCKDS	HASPCKDS	CKDS
HASPCKPT	HASPCKPT	CKPT
HASPCKRR	HASPCKRR	CKRR
HASPCKVR	HASPCKVR	CKVR
HASPCNVT	HASPCNVT	CNVT
HASPCOMM	HASPCOMM	COMM
HASPCON	HASPCON	CON
HASPCSV	HASPCSV	CSV
HASCDAL	HASCDAL	DSAL
HASPDOC	HASPDOC	DOC
HASCDSOC	HASCDSOC	DSOC
HASCDSS	HASCDSS	DSS
HASPDYN	HASPDYN	DYN
HASPEVTL	HASPEVTL	EVTL
HASPFSSM	HASPFSSM*	--
HASPFSSP	HASPFSSP	FSSP
HASP Common Communication Table	-	HCCT
HASPHOPE	HASPHOPE	HOPE
HASPIRA	HASPIRA	IRA
HASPIRDA	HASPIRDA	IRDA
HASPIRMA	HASPIRMA	IRMA
HASPIRPL	HASPIRPL	IRPL
HASPIRRE	HASPIRRE	IRRE
HASPIRSI	HASPIRSI	IRSI
HASPJOS	HASPJOS	JOS

Table 95. Patch Name to CSECT Reference (continued)

CSECT Referenced	AMASPZAP Patch Name	JES2 Patch Name
HASPJQS	HASPJQS	JQS
HASPMISC	HASPMISC	MISC
HASPMMSG	HASPMMSG	MSG
HASPNATS	HASPNATS	NATS
HASPNET	HASPNET	NET
HASPNJT	HASPNJT	NJT
HASPNPM	HASPNPM	NPM
HASPNRM	HASPNRM	NRM
HASPNSR	HASPNSR	NSR
HASPNST	HASPNST	NST
HASPNUC	HASPNUC	NUC
HASPODSM	HASPODSM	ODSM
HASPPCY	HASPPCY	PCY
HASPPRPU	HASPPRPU	PRPU
HASPPSO	HASPPSO	PSO
HASPRAS	HASPRAS	RAS
HASPRDR	HASPRDR	RDR
HASPRGR	HASPRGR	RGR
HASPRTAM	HASPRTAM	RTAM
HASPSASR	HASPSASR	SASR
HASPSERV	HASPSERV	SERV
HASPSIR	HASPSIR	SIR
HASPSJFR	HASPSJFR	SJFR
HASPSNA	HASPSNA	SNA
HASPSPIN	HASPSPIN	SPIN
HASPSPOL	HASPSPOL	SPOL
HASPTCP	HASPTCP	TCP
HASCSRDS	HASCSRDS	SRDS
HASCSRIC	HASCSRIC	SRIC
HASCSRJB	HASCSRJB	SRJB
HASPSSRV	HASPSSRV	SSRV
HASPSTAB	HASPSTAB	STAB
HASPSTAC	HASPSTAC	STAC
HASPSTAM	HASPSTAM	STAM

<i>Table 95. Patch Name to CSECT Reference (continued)</i>		
CSECT Referenced	AMASPZAP Patch Name	JES2 Patch Name
HASPSUBS	HASPSUBS	SUBS
HASPSXDV	HASPSXDV	SXDV
HASPSXIT	HASPSXIT	SXIT
HASPSXJB	HASPSXJB	SXJB
HASPSXNJ	HASPSXNJ	SXNJ
HASPSXOT	HASPSXOT	SXOT
HASPTABS	HASPTABS	TABS
HASPTERM	HASPTERM	TERM
HASPTRAK	HASPTRAK	TRAK
HASPWARM	HASPWARM	WARM
HASPCF	HASPCF	PCF
HASPCXEQ	HASPCXEQ	CXEQ
HASPCJ00-HASPCJ31	HASPCJ00-HASPCJ31	CJ00-CJ31**
xxxxxxxx***	xxxxxxxx	xxxxxxxx
* This module cannot be modified by using JES REP (replace) facilities. ** Reserved names for installation exit modules. *** Any load module previously specified in a LOADMOD control statement.		

<i>Table 96. Other Area that can be Patched</i>		
Area Name	Default Base	Description
jes2JQRB		JQE request block data space
jes2NAT		NAT data space
jes2PCL		PCL data space
jes2SAPI*	0	SYSOUT API data space
jes2TBUF		TCP/IP buffer data space
jes2TJEV*	0	TJEV data space
jes2STAC*	0	Status and Cancel request data base
jes2PSO*	0	Process SYSOUT data space
jes2IRDS*	0	Internal reader data space
jes2CKVR*	0	Checkpoint versions data space
CKPTTGM**	X'18'	Checkpointed track group map

Table 96. Other Area that can be Patched (continued)

Area Name	Default Base	Description
CKPTJQT**	X'18'	Checkpointed JQE track group extension
CKPTNITC**		
CKPTSCQ**	X'18'	Checkpointed shared communications queue
CKPTJIX**	X'18'	Checkpointed JQE index
CKPTJQE**	X'18'	Checkpointed job queue element
CKPTJQX**	X'18'	Checkpointed JQE extension
CKPTPST**	X'18'	Checkpointed JOE post element
CKPTJOE**	X'18'	Checkpointed job output element
CKPTRECY**		
CKPTTGR**	X'18'	Checkpointed track group record
CKPTBERT**	X'18'	Checkpointed block extension reuse table
CKPTRSO**	X'18'	Checkpointed remote signon table
CKPTLCK**	X'18'	Checkpointed offload lock
CKPTDAS**	X'18'	Checkpointed direct access SPOOL table
CKPTMSTR**	0	Checkpointed master record (Not for CKPTed HCT)***
CKPTHCT**	\$SAVEBEG	Checkpointed HCT
* <i>jes2</i> is the name of the owning subsystem ** Checkpoint REPs are not processed until the checkpoint data set is read in. *** The checkpointed HCT can only be patched using the name CKPTHCT. Attempts to patch the checkpointed HCT in the master record will have no effect.		

address|*

Specifies the 1-to 8-digit hexadecimal address of the data to be modified. This address does not have to be aligned in any way. The address should be taken directly from a JES2 assembler listing that contains the referenced CSECT.

If an asterisk (*) is coded, the address will be interpreted as one greater than the last address reference on the previous JES2 patch statement.

data

Specifies the bytes of data to be modified at the specified location. Specify this number as a multiple of 2 hexadecimal digits. The data within the parameter may be separated by commas, never blanks. If all the data will not fit into one patch statement (71 bytes), you must use another patch statement.

If the data specifies a location within a JES2 CSECT, as specified at assembly time, the JES2 patch processing routine will relocate this data by the base location of the CSECT if indicated. Specify this relocation by following the data to be relocated with the name of the CSECT (abbreviated as in “csect” above) enclosed in parentheses. The address specified in the data field should be taken directly from a JES2 assembly listing containing the referenced CSECT. You can specify a minimum of 6 hexadecimal digits (3 bytes), and a maximum of 8 digits (4 bytes) for relocation.

comments

Following the last required parameter and its blank delimiter, the rest of the control statement space can be used for comments.

Examples of JES2 patching facility statements are shown in [Figure 2 on page 386](#) and [Figure 3 on page 387](#).

```

/*****/
/*
/*          CORRECT PROGRAMMING ERROR IN HASPRDR          */
/*
/*****/
VER RDR      1E2      41E00001          /* VERIFY INSTRUCTION */
REP *        1E2      4590B258          /* BAL TO PATCH SPACE */
VER NUC      258      B258,B25A,B25C,B25E,B260 /* VERIFY PATCH SPACE */
REP *        258      41202000          /* ADD INSTRUCTION   */
REP *        *        41E00001          /* REPLACE INSTRUCTION*/
REP *        *        07F9             /* RETURN             */
/*****/
/*
/*          CORRECT BAD ADDRESS CONSTANT IN HASPPRPU       */
/*
/*****/
VER PRPU     32E      58F0C65C          /* VERIFY INSTRUCTION */
REP *        330      B264             /* MODIFY DISPLACEMENT*/
VER NUC      264      B264,B266          /* VERIFY PATCH SPACE */
REP *        264      00000520(PRPU)    /* ADDRESS CONSTANT   */
/*****/
/*
/*          MODIFY BLOCK CHARACTER TABLE TO SLASH        */
/*          THE LETTER Z (POSITION 26) AND THE NUMBER ZERO */
/*          (POSITION 27) ON OUTPUT SEPARATORS.           */
/*          --A TABLE ENTRY IS 24 BYTES LONG--          */
/*
/*****/

```

Figure 2. Examples of JES2 Patching Format


```

/*****/
/*
/*          CORRECT PROGRAMMING ERROR IN HASPRDR          */
/*
/*****/
NAME HASPRDR HASPRDR          /* IDENTIFY SECTION */
VER 1E2 41E00001          /* VERIFY INSTRUCTION */
REP 1E2 4590B258          /* BAL TO PATCH SPACE */
NAME HASPNUC HASPNUC          /* IDENTIFY SECTION */
VER 258 B258,B25A,B25C,B25E,B260 /* VERIFY PATCH SPACE */
REP 258 41202000          /* ADD INSTRUCTION */
REP * 41E00001          /* REPLACE INSTRUCTION*/
REP * 07F9          /* RETURN */
/*****/
/*
/*          CORRECT BAD ADDRESS CONSTANT IN HASPPRPU          */
/*
/*****/
NAME HASPPRPU HASPPRPU          /* IDENTIFY SECTION */
VER 32E 58F0C65C          /* VERIFY INSTRUCTION */
REP 330 B264          /* MODIFY DISPLACEMENT*/
NAME HASPNUC HASPNUC          /* IDENTIFY SECTION */
VER 264 B264,B266          /* VERIFY PATCH SPACE */
REP 264 00000520(PRPU)          /* ADDRESS CONSTANT */
/*****/
/*
/*          MODIFY BLOCK CHARACTER TABLE TO SLASH          */
/*          THE LETTER Z (POSITION 26) AND THE NUMBER ZERO   */
/*          (POSITION 27) ON OUTPUT SEPARATORS.              */
/*          --A TABLE ENTRY IS 24 BYTES LONG--              */
/*
/*****/


```

Figure 3. Examples of JES2 AMASPZAP Format

REQJOBID - Specify JESLOG Characteristics

The REQJOBID initialization statement describes attributes to be assigned to request jobID address spaces. JES2 creates a "request jobID job" when an address space not running under JES2 requests a JES2 job structure. RACF is a user of this interface.

Format Description for REQJOBID



Parameter Description for REQJOBID

JESLOG=

Specifies for request jobID address spaces JESLOG data attributes to be used for JESMSG LG and JESYSMSG data sets.

SPIN

JESLOG data is to be immediately spun off for request jobID address spaces

(SPIN,+hh:mm)

Indicates to spin JESLOG every hh:mm time interval.

where:

- hh is hours and has a range of 0 through 23
- mm is minutes and has a range of 00 through 59

Note: You must specify a minimum of 10 minutes or JES2 issues an error message. Also, for time intervals of less than one hour, you must specify the following format: JESLOG=(SPIN,+00:mm).

(SPIN, hh:mm)

Indicates to spin JESLOG at hh:mm every 24 hours.

(SPIN, nnn)

Indicates to spin JESLOG whenever either JESMSGGLG or JESYSMSG has nnn lines. nnn is the number (1–999) of lines in the data set.

Note: You must specify a minimum of 500 lines or JES2 issues an error message.

(SPIN, nnnK)

Indicates to spin JESLOG whenever either JESMSGGLG or JESYSMSG has "nnnK" lines. Use "K" to indicate thousands of lines.

(SPIN, nnnM)

Indicates to spin JESLOG whenever either JESMSGGLG or JESYSMSG has "nnnM" lines. Use "M" to indicate millions of lines.

SUPPRESS

Indicates that JES2 will suppress writing to the JESLOG data sets during the execution of jobs defined for this job class. JES2 only writes data to the JESLOG data sets during each job's input service and post-execution processing phases.

NOSPIN

Indicates that JESLOG data will not be spun, but will not be suppressed. NOSPIN is the default.

Modification: \$T REQJOBID operator command


RESGROUP - Resource Group

The **RESGROUP(group...)** statement defines one or more JES2 resource groups. JES2 resource groups are used to aggregate usage of JES2 resources by jobs that are similar in some respect that is meaningful to a particular JES2 installation.

Resource group structures are stored in the JES2 checkpoint and therefore are MAS-wide in scope.

For more information about JES2 resource groups, see [JES2 Resource groups](#) in the *z/OS JES2 Initialization and Tuning Guide*.

Format Description



Parameter Description

RESGROUP statement does not have any parameters currently.

RMT(nnnnn) - BSC RJE Workstation

The RMT(nnnnn) statement specifies the characteristics of one RJE workstation. The following descriptions apply to the characteristics of a BSC (binary synchronous communication) RJE workstation. For a description of the SNA RJE workstation, see “RMT(nnnnn) - SNA RJE Workstation” on page 398.

Specify a RMT(nnnnn) statement for each RJE workstation to be defined. RJE workstations can be numbered from RMT(1) to RMT(32767). You can use the subscript to specify a specific remote terminal (nnnnn), a range of terminals (n-*) indicating n to the highest numbered terminal (32767), or all terminals (*). This remote remains defined unless the RMT(nnnnn) device parameters NUMPRT=, NUMPUN=, and NUMRDR= are all set to zero, thereby setting the device count to zero. All remote definitions are ignored if no LINES are defined.

An RJE workstation can be defined with all defaults if you specify a RMT statement that contains no operands. These default operands include specifying this terminal as a 2770 terminal with no features.


You don't have to define each RJE workstation to each member of your MAS. You only need to define each RJE workstation to one member of your MAS; however, be sure that each workstation has a unique subscript number (*nnnnn* in *RMT(nnnnn)*). For example, if you define *RMT(13)* on one member as a 3780 BSC terminal, *RMT(13)* should not be defined on **any other member**.

If an RJE workstation has attached devices, use the following initialization statements to describe their characteristics.


- R(nnnnn).PR(m) - specifies remote printer characteristics
- R(nnnnn).PU(m) - specifies remote card punch characteristics
- R(nnnnn).RD(m) - specifies remote card reader characteristics

JES2 associates devices with RJE workstations by correlating the nnnnn in the above three statements to the nnnnn in an RMT(nnnnn) statement. JES2 does not support multiple printers, punches, or readers for remote BSC **hardware** (MULTILV=NO) terminals.


Format Description for RMT(nnnnn) (BSC)




Modification keywords



Selection limiting keywords



RMT(nnnnn) (BSC)



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for RMT(nnnnn) (BSC)

DEVTYPE=type|2770

To specify the type of terminal or system at this remote location, specify one of the following:

Hardware Terminals	Multileaving Terminals	Systems
2770	2922	S/36
2780	M20-2	S/360
3781 (See note 1 below.)	M20-4	S/370
3781	M20-5	1130
	M20-6	S/3

If you are initializing a terminal that is not explicitly supported by JES2 (that is, one that is not listed above) but emulates one of the above listed terminals, consult the documentation for that terminal to be certain you set characteristics (such as buffer sizes) appropriately for that terminal.

Note:

1. To ensure that punch output is directed to the proper device, specify '3781' to define remote 3780 terminals that contain punches.
2. Specify a 3740 hardware terminal as a 2780.

Modification: \$T RMT(nnnnn) operator command.

BLOCK=Yes|No

Specifies whether or not this terminal has a blocked (Yes) or unblocked (No) data record format.

Modification: \$T RMT(nnnnn) operator command.

BUFEXPAN=0|1|2

Specifies whether or not this 2770 terminal has a buffer-expansion feature.

0

Indicates that this terminal does not have a buffer expansion feature.

1

Indicates that this terminal has the buffer expansion feature and implies a remote terminal buffer size of 264 bytes.

2

Indicates that this terminal has the additional buffer expansion feature and implies a remote terminal buffer size of 520 bytes.

Modification: \$T RMT(nnnnn) operator command.

Note: If a printer attached to this remote has PRWIDTH= specified greater than 120, specify BUFEXPAN= 1 or 2.

BUFSIZE=nnnnn

Specifies the largest buffer (127-3960) that can be sent to or received from this BSC terminal. This parameter enforces minimum buffer size specification based on device type for BSC.

Following are the minimum values required to support various non-programmable terminals.

Minimum SIZE

Terminal Type

127

2770, without any type of buffer expansion

264

2770, with buffer expansion (BUFEXPAN=1 on RMT(nnnnn) statement)

520

2770, with additional buffer expansion (BUFEXPAN=2 on RMT(nnnnn) statement)

400

2780

520

3780

Performance Considerations: This parameter can be used to reduce JES2 processor overhead when driving multileaving RJE workstations on high-speed lines. Proper specification can also increase throughput.

You can change this parameter value at the RJE workstation by: (1) regenerating the initial program load (IPL) data set or (2) specifying the multileaving buffer size before signon by placing an &MLBFSIZ initialization statement before the /*SIGNON statement. (See MVS Remote Workstation Generation, GC28=1433 for RJE statement descriptions.)

If you do not specify a value, JES2 provides the following defaults for the following device types:

<i>Table 97. JES2 BUFSIZE Defaults for RJE Workstations</i>		
Workstation	Type	BUFSIZE Value
Multileaving Terminals and Systems	N/A	MBUFSIZE= value on TPDEF statement
Hardware Terminal	2770 without buffer expansion (BUFEXPAN=0)	127
Hardware Terminal	2770 with buffer expansion (BUFEXPAN=1)	264
Hardware Terminal	2770 with additional buffer expansion (BUFEXPAN=2)	520
Hardware Terminal	2780	400
Hardware Terminal	3780	520
Hardware Terminal	3781	520

Modification: \$T RMT(nnnnn) operator command.

COMPRESS=Yes|No

Specifies whether (Yes) or not (No) this (2770 or 3780) terminal has the compression/expansion feature.

If you specified COMPRESS=No on the LINE(nnnnn) statement, for the line this terminal is to use, it overrides the value specified here. If you specified COMPRESS=Yes on the LINE(nnnnn) statement, whatever you specify here will take effect if COMP= is specified on the remote device (Rnnnnn.XXn initialization statement).

Note: COMPRESS=Yes and HTABS=Yes are mutually exclusive. If both are specified, HTABS=Yes will be changed to HTABS=No.

Modification: \$T RMT(nnnnn) operator command.

CONDEST=nnnnn

Specifies the route code (1-32767) to be used for responses to commands entered from this RJE workstation. The value specified here should be equivalent to the nnnnn specification on a RMT(nnnnn) statement.

Note: This routing only affects nonspooled responses.

If you do not specify a value for this parameter, JES2 assigns the number of this terminal (RMT(nnnnn)) as its route code.

Modification: \$T RMT(nnnnn) operator command.

CONS=Yes|No

Specifies whether (Yes) or not (No) this multileaving terminal has an operator console or that it is simulating a console, as specified by the &PRTCONS RMT generation statement. See the MVS Remote Workstation Generation, GC28=1433 for an explanation of all RMT generation statements.

If JES2 determines that this remote can not have a console, JES2 forces the value of this parameter to NO.

Note: CONS=NO will not interrupt any streams for console messages. Console data will be sent when a session becomes available to the virtual console device. If CONS=NO is specified, data destined to a console can still be sent.

Modification: \$T RMT(nnnnn) operator command.

Discintv=nnnnn|0

Specifies the interval (in seconds) after which, if there is no successful text transmission in either direction, this terminal will be disconnected from the processing unit. Error recovery tries and idle time are not counted as successful text transmission. The value of nnnnn may be from 0 to 8160 seconds; JES2 rounds this value to the next highest multiple of 32.

If you do not specify a value, this parameter defaults to 0, which indicates that this terminal is not to be disconnected.

Modification: \$T RMT(nnnnn) operator command.

HTABS=Yes|No

Specifies whether (Yes) or not (No) this (2770 or 2780) terminal has the horizontal format-control feature.

Note: COMPRESS=Yes and HTABS=Yes are mutually exclusive. If both are specified, HTABS will be changed to HTABS=No.

Modification: \$T RMT(nnnnn) operator command.

LINE=nnnnn|0

Specifies the number (0-65535) of the teleprocessing line that is connected to this terminal. Use a number (1-65535) to specify a dedicated line or 0 to specify a non-dedicated line.

If you specify no line number, JES2 assigns a default of LINE=0, which provides a nondedicated line. This line can then be used by multiple BSC RJE workstation with similar features when started with a /*SIGNON JCL statement.

Modification: \$T RMT(nnnnn) operator command.

LOCAL190=INFO|ACTION

INFO specifies that operator setup messages (\$HASP190) issued at the local (processor) console for this remote device are to be “information” messages, while ACTION specifies that the setup messages require operator action before they can be deleted from a display console.

Modification: \$T RMT(nnnnn) operator command.

MFORM=J|M|T

Specifies the amount of information to be displayed in JES2 operator console messages for this RJE workstation.

J

Indicates that the message is displayed with the jobname and job ID of the issuer.

M

Indicates that only the message text is displayed.

T

Indicates that the message is displayed with a time stamp, jobname, and job ID of the issuer.

Modification: \$T RMT(nnnnn) operator command.

MRF2780=Yes|No

Specifies whether (Yes) or not (No) this 2780 terminal has the multiple-record feature.

Modification: \$T RMT(nnnnn) operator command.

MSGPRT=Yes|No

Specifies whether JES2 prints messages routed to a printer attached to the console of an RJE workstation.

MSGPRT=YES causes JES2 to print messages if the remote console is unavailable. MSGPRT=NO causes JES2 to discard messages if the RJE workstation console is unavailable.

Modification: \$T RMT(nnnnn) operator command.

MULTILV=Yes|No

Specifies whether (Yes) or not (No) this terminal will use the BSC (binary synchronous communication) multileaving interfaces. If Yes is specified, the terminal type must specify a multileaving workstation. No defines this RJE workstation as an RJE BSC hardware terminal.

Modification: \$T RMT(nnnnn) operator command.

NUMPRT=n|1

Specifies the number (0-7) of printers at this RJE workstation. Use the R(nnnnn).PR(m) initialization statement to specify the characteristics of each printer. JES2 can use values greater than 1 only if you coded MULTILV=Yes on this statement. A maximum total of 8 printers and punches may be specified.

Modification: \$T RMT(nnnnn) operator command.

NUMPUN=n|0

Specifies the number (0-7) of card punches at this terminal. Use the R(nnnnn).PU(m) initialization statement to specify the characteristics of each card punch. JES2 can use values greater than 1 only when you coded MULTILV=Yes on this statement. A maximum total of 8 printers and punches may be specified.

Modification: \$T RMT(nnnnn) operator command.

NUMRDR=n|1

Specifies the number (0-7) of card readers at this RJE workstation. Use the R(nnnnn).RD(m) initialization statement to specify the characteristics of each reader.

Modification: \$T RMT(nnnnn) operator command.

Password=xxxxxxx

Specifies a 1- to 8-character security password to prevent unauthorized users from using this RJE workstation's resources.

Modification: \$T RMT(nnnnn) operator command.

RECFM=FIXED|VARIABLE

Specifies whether the data record for this terminal is fixed-length (FIXED) or variable-length (VARIABLE).

Modification: \$T RMT(nnnnn) operator command.

RMT150=Yes|No

Yes specifies that if this RJE workstation has a console, the \$HASP150 message is first sent to this console and then also sent to the local operator. No specifies that the \$HASP150 message is sent only to the local operator.

Note:

1. If Yes is specified for this RJE workstation, and SYSTEM36 (S/36), CONS=Yes, and MULTILV=Yes are also specified, the remote printer will pause momentarily to ensure that the \$HASP150

message arrives at the console before the data sets begin to print on the printer. There is no pause for systems other than SYSTEM36.

2. This parameter is not valid for hardware terminals.

Modification: \$T RMT(nnnnn) operator command.

Route~~c~~de=nnnnn

Specifies the route code (1-32767) to be assigned to this terminal and its associated printers, punches, and readers. The value specified here should be equivalent to the nnnnn specification on a RMT(nnnnn) statement.

If you do not specify a route code, JES2 assigns the number of this terminal (RMT(nnnnn)) as its route code.

Modification: \$T RMT(nnnnn) operator command.

SHARABLE=Yes|No|Default

Specifies whether (Yes) or not (No) JES2 allows the line specified on the LINE= parameter to be used by other RJE workstations.

Yes

Indicates that multiple RMT definitions can also specify and use the line specified on the LINE= parameter. A /*SIGNON JCL statement is required to start these RJE workstations.

No

Indicates that no other RJE workstations can specify and use the line specified on the LINE= parameter.

DEFAULT

Indicates that you want JES2 to determine the value of this parameter based on all RJE workstations definitions. JES2 sets this parameter to SHARABLE=No if a specific line number (LINE=nnnnn) is specified on only one RMT(nnnnn) statement. JES2 sets this parameter to SHARABLE=Yes if a specific line number (LINE=nnnnn) is specified on multiple RMT(nnnnn) statements.

Note:

1. If a RMT(nnnnn) statement specifies a LINE= parameter with SHARABLE=NO, but another RMT(nnnnn) statement specifies the same LINE= value, JES2 forces SHARABLE=Yes on all RMT definitions with the LINE= value at the installation when initialization completes.
2. If only one RMT(nnnnn) statement specifies a line and you do not specify the SHARABLE= parameter at initialization, you must use the \$T command to set SHARABLE=Yes before you can use a \$ADD RMT(nnnnn) or a \$T RMT(nnnnn) command for another RMT definition that specifies the same LINE= value. Therefore, SHARABLE=Yes is recommended to avoid this situation, unless you want to specifically reserve a given line for use by a single RJE workstation.

Modification: \$T RMT(nnnnn) operator command.

TRANSPAR=Yes|No

Specifies whether (Yes) or not (No) this terminal has the text-transparency feature. If you specify TRANSPAR=Yes, you must also specify TRANSPAR=Yes on the LINE(nnnnn) statement that defines the line for this RJE workstation.

Modification: \$T RMT(nnnnn) operator command.

WAITIME=nn|1

Specifies the length of time in seconds (0-30) that RTAM should wait at the completion of the processing of any input stream, or printed or punched output stream, to allow the operator to enter an input stream at this RJE workstation.

Modification: \$T RMT(nnnnn) operator command when the remote is inactive.

RMT(nnnnn) - SNA RJE Workstation

The RMT(nnnnn) statement specifies the characteristics of one RJE workstation. The following descriptions apply to the characteristics of a SNA remote terminal. For a description of the BSC RJE workstation, see “RMT(nnnnn) - BSC RJE Workstation” on page 389.

Specify a RMT(nnnnn) statement for each RJE workstation to be defined. RJE workstations can be numbered from RMT(1) to RMT(32767). You can use the subscript to specify a specific remote terminal (nnnnn), a range of terminals (n-*) indicating n to the highest numbered terminal (32767), or all terminals (*). This remote remains defined unless the RMT(nnnnn) device parameters NUMPRT=, NUMPUN=, and NUMRDR= are all set to zero, and CONS=NO thereby setting the device count to zero. All remote definitions are ignored if no LINEs are defined.

An RJE workstation can be defined with all defaults if you specify a RMT statement that contains no operands.

Note: Effectively, the defaults specify this remote as a 2770 BSC RJE workstation with no features, not a SNA RJE workstation.


You don't have to define each RJE workstation to each member of your MAS. You only need to define each RJE workstation to one member of your MAS; however, be sure that each workstation has a unique subscript number (nnnnn in RMT(nnnnn)). For example, if you define RMT(13) on one member as a SNA LUTYPE1, RMT(13) should not be defined on **any other member**.

If an RJE workstation has attached devices, use the following initialization statements to describe their characteristics:


- R(nnnnn).PR(m)--specifies remote printer characteristics
- R(nnnnn).PU(m)--specifies remote punch characteristics
- R(nnnnn).RD(m)--specifies remote card reader characteristics

JES2 associates devices with RJE workstations by correlating the nnnnn in the above three statements to the nnnnn in an RMT(nnnnn) statement. SNA RJE workstation characteristics are specified by the following parameters.


Format Description for RMT(nnnnn) (SNA)





Modification keywords



Selection limiting keywords







Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for RMT(nnnnn) (SNA)

Autolog=Yes|No

Specifies whether (Yes) or not (No) this RJE workstation remote can be automatically logged on. You must be certain to also specify the LUNAME= parameter.

Modification: \$T RMT(nnnnn) operator command.

BUFSIZE=nnnnn|256

Specifies the largest request unit (256-3840 bytes) that can be sent to or received from this SNA RJE workstation. A value of nnnnn outside this range defaults to 256.

Performance Considerations: Use this parameter to reduce JES2 processor overhead when driving multileaving remote workstations on high-speed lines. Proper specification can also increase throughput.

Modification: \$T RMT(nnnnn) operator command.

COMPACT=Yes|No

Specifies whether (Yes) or not (No) this RJE workstation supports compaction, allowing a compaction table to be sent for use with a printer or punch data set. If more than one session is active and Yes is specified, all sessions are eligible to receive a compaction table.

Use the COMPACT initialization statement to define compaction tables. If more than one session is active and COMPACT=Yes, all sessions are eligible to receive a compaction table.

Modification: \$T RMT(nnnnn) operator command.

COMPRESS=Yes|No

Specifies whether (Yes) or not (No) this SNA terminal will use the compression/expansion feature. If COMPACT=Yes (compaction) is specified, compression (COMPRESS=Yes) is forced.

Modification: \$T RMT(nnnnn) operator command.

CONDEST=nnnnn

Specifies the route code (1-32767) to be used for responses to commands entered from this RJE workstation. The value specified here should be equivalent to the nnnnn specification on a RMT(nnnnn) statement.

Note: This routing only affects nonspooled responses. If you do not specify a value, JES2 assigns the number of this terminal (RMT(nnnnn)) as its route code.

Modification: \$T RMT(nnnnn) operator command.

CONS=Yes|No

Specifies whether (Yes) or not (No) this RJE workstation has an operator console.

Modification: \$T RMT(nnnnnn) operator command.

Note: This parameter should only be specified for those SNA RJE stations that have a separate console.

DEVTYPE=LUTYPE1

Specifies that this RJE workstation is a SNA terminal (for example, a 3770 terminal, a 3791 workstation, or a System/32 workstation) that can be accessed only by means of a logical line (that is, a line defined by a LINE(nnnnnn) statement with the UNIT=SNA parameter).

Modification: \$T RMT(nnnnnn) operator command. (If DEVTYPE= is changed to a valid value other than LUTYPE1, this SNA remote workstation will be changed to a BSC remote workstations.)

Discintv=nnnnn|0

Specifies the maximum interval (0-8160) in seconds after which, if there is no successful text transmission in either direction, JES2 ends the session between the SNA RJE workstation and the processing unit. Error recovery tries and idle time are not counted as successful text transmission. JES2 rounds this value to the next higher multiple of 32.

If you do not specify a value, this parameter defaults to 0, indicating that the session is not to be ended and the terminal is not to be disconnected.

Modification: \$T RMT(nnnnnn) operator command.

LINE=nnnnn|0

Specifies the number (0-65535) of a logical line that is connected (and dedicated) to this RJE workstation. This line must be defined by a LINEnnnnn statement, with the UNIT=SNA parameter specified. An exception to this rule is specifying LINE=0, which causes JES2 to reset the remote to a nondedicated terminal.

If you specify no line number, JES2 uses a default of LINE=0 to indicate that the terminal is nondedicated and can use any nondedicated, SNA line.

Modification: \$T RMT(nnnnnn) operator command.

LOCAL190=INFO|ACTION

Specifies the type for operator setup messages (\$HASP190) issued at the local processor console for this RJE workstation.

INFO

Specifies that these messages (\$HASP190) are to be “information” type messages that do not require an operator action to be deleted from a display console.

ACTION

Specifies that these messages (\$HASP 190) are flagged as “action” messages that require a positive operator action to be deleted from a display console.

Modification: \$T RMT(nnnnnn) operator command.

LOGON=logon

Specifies the logon DCT to which this remote device should be connected as defined by the LOGON(nnn) initialization parameter.

LUNAME=xxxxxxx

Specifies the logical unit name of this RJE workstation. If specified, this name must be the same as the name defined to VTAM at system initialization. A logical unit name must be specified if the automatic logon capability is used. The logical unit associated with the logical unit name should be the first of the terminal's logical units to logon to JES2. Otherwise, the LUNAME associated with the session is taken from the name pointed to by the parameter list VTAM passes to the JES2 logon exit.

Modification: \$T RMT(nnnnnn) operator command.

MFORM=J|M|T

Specifies the amount of information to be displayed in JES2 operator console messages for this remote workstation.

J

Indicates that the message is displayed with the jobname and job ID of the issuer.

M

Indicates that only the message text is displayed.

T

Indicates that the message is displayed with a time stamp, jobname, and job ID of the issuer.

Modification: \$T RMT(nnnnn) operator command.

MSGPRT=Yes|No

Specifies whether JES2 keeps messages on spool routed to an unavailable RJE workstation console.

MSGPRT=Yes causes JES2 to keep messages on spool if the remote console is unavailable.

MSGPRT=No causes JES2 to discard messages if the RJE workstation does not have a console defined.

Modification: \$T RMT(nnnnn) operator command.

NUMPRT=n|1

Specifies the number (0-7) of logical printers at this RJE workstation. If there is a separate printer for each console, do not include it in this count. The maximum value for NUMPRT= is 6 if CONS=Yes is specified, 7 otherwise. Use a zero to specify no printers. Use the R(nnnnn).PR(m) statement to specify the characteristics of the printer(s). A maximum total of 8 printers and punches can be defined for RJE workstations without a console or only 7 printers and punches for RJE workstations with a console defined.

Modification: \$T RMT(nnnnn) operator command.

NUMPUN=n|0

Specifies the number (0-7) of logical card punches at this RJE workstation. SNA RJE workstations can support up to 7 punch data streams. Use the R(nnnnn).PU(m) initialization statement to specify the characteristics of the card punch(s). A maximum total of 8 printers and punches can be defined for RJE workstations without a console or only 7 printers and punches for RJE workstations with a console defined.

Modification: \$T RMT(nnnnn) operator command.

NUMRDR=n|1

Specifies the number (0-7) of logical card readers at this RJE workstation. SNA RJE workstations can support up to 7 reader data streams. Use the R(nnnnn).RD(m) initialization statement to specify the characteristics of the reader(s).

Modification: \$T RMT(nnnnn) operator command.

Password=xxxxxxx

Specifies a security password to prevent unauthorized users from using this RJE workstation's resources.

Modification: \$T RMT(nnnnn) operator command.

RMT150=Yes|No

Yes specifies that if this RJE workstation has a console, the \$HASP150 message is first sent to this console and then also sent to the local operator. NO specifies that the \$HASP150 message is sent only to the local operator.

Note: Yes is only valid if CONS=Yes is also specified for this remote terminal.

Modification: \$T RMT(nnnnn) operator command.

Routeede=nnnnn

Specifies the route code (1-32767) to be assigned to this terminal and its associated printers, punches, and readers. The value specified here should be equivalent to the nnnnn specification on a RMT(nnnnn) statement.

If you do not specify a route code, JES2 assigns the number of this terminal (RMT(nnnnn)) as its route code.

Modification: \$T RMT(nnnnn) operator command.

SETUP=PDIR|MSG

PDIR specifies that a peripheral data information record (PDIR), containing setup information, is constructed and sent to the remote workstation. The remote workstation is responsible for processing the header and generating any required messages. SETUP=PDIR allows spooling of data and generation of multiple copies of a data set (from the original sent by JES2) at a remote workstation.

MSG specifies that JES2 is to inform the remote operator of any setup requirements through the \$HASP190 message. Upon completion of setup, the operator must issue a \$S command to start JES2 transmission.

Modification: \$T RMT(nnnnn) operator command.

START=Yes|No

Specifies whether (Yes) or not (No) JES2 should start this RJE workstation after initialization. To use this feature, you must be certain to specify the LUNAME= parameter. Also, you must start the LOGON(n) and LINE(nnnnn) that this RMT(nnnnn) uses earlier in the initialization stream.

Modification: \$S RMTnnnnn operator command or \$P RMTnnnnn operator command.

WAITIME=nn|1

Specifies the length of time (0-30) in seconds that RTAM should wait at the completion of the processing of any input stream, printed output stream, or punched output stream to allow the operator to enter an input stream at this RJE workstation.


Note: If this parameter is set too low, contention might occur during SNA logon processing, resulting in \$HASP094 messages and the termination of the SNA remote session. Increase this parameter to allow the SNA remote adequate time to respond during logon processing so that proper LU type 1 protocol is followed.

Modification: \$T RMT(nnnnn) operator command if the RJE workstation is inactive.

SMFDEF - JES2 SMF Buffer Definition

The SMFDEF statement defines the System Management Facilities (SMF) buffers to JES2.

Format Description for SMFDEF



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for SMFDEF

BUFNUM=nnnn|5

Specifies the number (0-1000) of system management facilities (SMF) buffers JES2 obtains. If the value specified is less than 2, JES2 will neither produce SMF records nor take the SMF exit, IEFUJP.

When determining the value of nnnn, be aware that the SMF buffers used for the 3800 printer output remain in use until all associated output is stacked. Additionally, multiple SMF buffers can be active concurrently for the 3800. Therefore, the minimum number of SMF buffers, for an installation that uses 3800 printers should be:

$$5 + n + (30 / p) y + o + pu$$

SOCKET

where:

n=

number of non-3800 printers

p=

average number of pages per data set for each 3800 printer

y=

number of 3800 printers

o=

3 x (number of offload devices)

pu=

2 x (number of purge processors)

Use your present SMF records to determine the average number of pages per data set currently processed by each 3800. Dividing 30 by this value (the average number of pages per data set currently processed by each 3800 printer) provides the average number (generally not more than 2) of job output elements (JOEs) that represent active work on all 3800 printers. (Active work is represented by those JOEs that were sent to the 3800 printer but have not been completely stacked.)

The value specified for BUFNUM is rounded up so that the storage used for SMF buffers is a whole number of pages.

Note: Use this parameter to increase the limit for the JNUM resource that is reported on the HASP050 message.

Modification: Single-member warm start.

BUFWARN=nnn|80


Specifies the percentage (0-100) of SMF buffers in use at which the operator will be alerted by message \$HASP050 JES2 RESOURCE SHORTAGE. If you specify 0, no alert is given.

Modification: \$T SMFDEF operator command.


SOCKET(xxxxxxxx) - Define NJE/TCP IP address and port

The SOCKET statement specifies a TCP/IP address and PORT combination that represents either a local address and port that is to be listened on by a NETSRV, or a remote address and port with which an NJE connection is established. The SOCKET statement maps the IP address to an NJE node name.


Format Description for SOCKET(xxxxxxxx)



Modification keywords



Selection limiting keywords



Parameter Description for SOCKET(xxxxxxxxx)

CONNECT=(Yes|No|DEFAULT,interval)

Specifies whether an NJE connection should be automatically attempted for this socket. If **DEFAULT** is specified, processing defers to the **CONNECT=(YES|NO)** value that is specified on the associated **NODE** statement. The *interval* is the approximate time (in minutes) between attempted connections.

The valid range for *interval* is 0 to 1440. A value of 0 indicates that the default interval (from NJEDEF CONNECT=) should be used. The default CONNECT value is DEFAULT, and the default *interval* is 0.

IPADDR=xxxxxxx

Specifies the TCP/IP address or host name associated with this socket. The default value, *LOCAL, indicates all IP addresses available at the start NetServer time are to be considered. The value for IPADDR= can be from 1 to 255 characters. However, because of limitations in the initialization deck, the maximum value in initialization is 63 characters.

Modification: \$T SOCKET command.

LINE=nnnnn

Specifies a TCP/IP line that is to be dedicated to this socket. The range of the value is 0-65535. The default of 0 means no dedicated line. (Model description after the one on APPL).

Modification: \$T SOCKET command.

NETSRV=nnn

Specifies the device number of the NETSRV to be used when connecting to this remote socket.

Modification: \$T SOCKET command.

NODE=xxxxxxx

Specifies the NJE node associated with this socket.

Modification: \$T SOCKET command.

PORT=xxxxxxx

Specifies the port number associated with this socket. The default is the value associated with VMNET (typically 175) if SECURE=NO, or the value associated with NJENET-SSL (typically 2252) if SECURE=YES.

Modification: \$T SOCKET command.

REST=nnnn

Specifies an integer (0-2000) that represents the resistance rating of the connection, which is viewed by the installation manager and coordinated with other installations. Resistance is an arbitrary value set to indicate a specific ability or inability of the socket to route work that has typical workload requirements. See [z/OS JES2 Initialization and Tuning Guide](#) for detailed information about selecting a resistance value.

Modification: \$T SOCKET command.

SECURE=Yes|No

Specifies whether (YES) or not (NO) JES2 uses SSL/TLS when communicating with this socket. It also indicates the default PORT to be used with the connection. The default SECURE value is No.

If the socket is associated with a NETSERV, then the SECURE= value that is specified for the SOCKET also provides the setting for SECURE= on the NETSERV when the NETSERV specifies SECURE=USE_SOCKET:


- Specifying SECURE=YES on the SOCKET is the same as specifying SECURE=REQUIRED on the NETSERV.
- Specifying SECURE=NO on the SOCKET is the same as specifying SECURE=OPTIONAL on the NETSERV.

Modification: \$T SOCKET command.

SPOOL - Bind spool volumes

The SPOOL initialization statement binds the specified spool volumes for cold start scan processing. Binding can enhance performance if the spool prefix defined by the \$T SPOOLDEF command includes generic characters. Multiple spool initialization statements can be specified.

Format Description for SPOOL



Notes:

¹ Omit the comma between initialization statement and first keyword

² *sysaff* can be coded up to 32 times

Parameter description for SPOOL

volume

Specifies one or more spool volumes to be scanned at cold start processing.

DSName=dsname

Specifies the 1-44 character name of a JES2 spool volume data set. If not specified, the default data set name, the \$T SPOOLDEF command defines the name, is used.

Sysaff=sysaff

Specifies the JES2 members to associate the specified spool volume with. The member list can include any combination of keywords, which are separated by commas.


memname|*

Specifies the identifier (1 to 4 characters by using A-Z, 0-9, \$, #, and @) of a member in the JES2 multi-access spool configuration that has affinity for the job. Use an asterisk to specify the member that runs the command.

SPOOLDEF - Spool Volume Definition

The SPOOLDEF statement defines the JES2 spooling environment.

Format



Notes:

¹ Omit the comma between the initialization statement and the first keyword

Parameters

ADVANCED_FORMAT=[ENABLED|DISABLED]

ADVANCED_FORMAT=[ENABLED|DISABLED]

Specifies whether advanced format JES2 structures can be created and likely exist in the MAS. These JES2 structures enable SPOOL encryption and compression capabilities. For more information, see [Compressing SPOOL data sets in z/OS JES2 Initialization and Tuning Guide](#).

ENABLED

Advanced format JES2 structures can be created and likely exist in the MAS.

Notes:

1. All MAS members must be at JES2 z/OS V2R4 or later.
2. When ENABLED is set, any MAS members at a release before JES2 z/OS V2R4 are not allowed to join the MAS. Even if ADVANCED_FORMAT=DISABLED is set later, members before JES2 z/OS V2R4 are not allowed to join the MAS. ADVANCED_FORMAT=ENABLED allows the creation of advanced format JES2 structures, which are only compatible with JES2 z/OS V2R4 or later.

DISABLED

Advanced format JES2 structures can no longer be created. Advanced format JES2 structures can exist in the MAS if this feature was previously enabled.

When ADVANCED_FORMAT is enabled at least once in the MAS, advanced format JES2 structures exist in the MAS and down level JES2 members no longer are allowed to join the MAS.

Modification: \$T SPOOLDEF operator command or JES2 cold start.

BUFSIZE=[nnnn|3992]

Specifies the size (1944-3992) in bytes, of each JES2 buffer. If the value specified is not a multiple of 8, it is rounded up automatically.

Each JES2 buffer is allocated to virtual storage, such that input/output block (IOB), which is 88 bytes, and the data area (the number of bytes in BUFSIZE) are always contained in a single 4K-page. The maximum value, 3992, allows 10 buffers per track for a 3380 and 12 buffers per track for a 3390.

Specifying too small a value for BUFSIZE= increases the need for spool I/O activity, which degrades performance. A BUFSIZE= specification of 3992 maximizes both central and virtual storage usage for most JES2 members. This value also provides good DASD usage. See [z/OS JES2 Initialization and Tuning Guide](#) for DASD usage values based on BUFSIZE= values.

The BUFSIZE= parameter specification affects the size of the track group map (TGM) and the number of peripheral data definition blocks (PDDBs) which can fit into each input/output table (IOT). Therefore, BUFSIZE= must be set to attain a balance between better DASD or processor usage and central storage considerations.

Modification: Cold start.

CYL_MANAGED=[FAIL|ALLOWED]

Specifies whether MAS members can handle spool and checkpoint data set allocation on EAV cylinder-managed storage. This allocation covers both new and old disposition. The default value is FAIL.

FAIL

By specifying CYL_MANAGED=FAIL, spool or checkpoint data sets are allocated in EAV cylinder-managed space. FAIL is not allowed under either of the following conditions:

- A spool or checkpoint data set currently is in EAV storage.
- A start spool command is pending.

ALLOWED

Specifying CYL_MANAGED=ALLOWED enables both spool and checkpoint data sets to be allocated in EAV cylinder-managed space. LARGEDS must be set to ALLOWED or ALWAYS not set to FAIL.

Notes:

1. CYL_MANAGED keyword is removed when in z22 activation level. CYL_MANAGED=FAIL is not allowed when you activate z22 level (it must be CYL_MANAGED=ALLOWED).
2. The CYL_MANAGED= keyword takes effect only on a COLD START of JES2. On a WARM START, the setting currently active in the CHECKPOINT remains in effect.

Scope: MAS-Wide.

DSNAME=[jxx...x|SYS1.HASPACE]

Specifies a 1–44-character name (hyphens (-) can be included for any character except the first) which is to be used as the data set name of the JES2 spool data set. This data set is normally named SYS1.HASPACE, but its name can be changed. For example, it might be named TESTING.HASPACE by specifying the following initialization statement:

```
SPOOLDEF DSNAME=TESTING.HASPACE /* ALTERNATE TEST SPOOL DATA SET */
```

Modification: Any JES2 restart.

DSNMASK=[jxx...x|SYS1.HASPACE]

Displays the 1–44 character data set mask name, including generic characters. If the DSNAME parameter is specified with the **SPOOL** initialization statement or the **\$S SPOOL** command, the DSNAME value must match either the \$D SPOOLDEF DSNAME value or the \$D SPOOLDEF DSNMASK value. If the \$D SPOOLDEF DSNMASK value is null, the DSNAME value must match the \$D SPOOL DSNAME value.

Modification: **\$T SPOOLDEF** operator command or any JES2 restart.

FENCE=(ACTIVE=[YES|NO],VOLUMES=[nnn|1])

ACTIVE=[YES|NO]

Determines whether any fencing is active at the time. The default value is NO.

VOLUMES=[nnn|1]

Specifies the number of volumes a job is fenced to. The default value is 1.

Note: Setting FENCE=(ACTIVE=YES,VOLUMES=1) causes JES2 to function as it did previously with FENCE=YES. For compatibility, the code allows FENCE=YES and converts it to ACTIVE=YES and VOLUMES=1.

For more information about how **SPOOLDEF** relates to Exit 11 \$TRACK and Exit 12 \$STRACK, see [Exit 11: Spool partitioning allocation \(\\$TRACK\)](#) and [Exit 12: Spool partitioning allocation \(\\$STRAK\)](#) in *z/OS JES2 Installation Exits*.

Modification: **\$T SPOOLDEF** operator command. This parameter cannot be changed on a warm start.

SPOOLNUM=[nnn|32]

Specifies the maximum number (1–53, rounded up to a multiple of 32 or 253) of spool volumes that can be defined at any one time to a multi-access spool complex. Spool volumes are defined by using either the VOLUME= parameter on this initialization statement during a JES2 cold start, or by using the **\$S SPL** (start spool) operator command. This parameter can be increased with a **\$T SPOOLDEF** command after an **\$ACTIVATE** command is issued in the MAS.

Notes:

1. If you specify other than a multiple of 32 volumes, JES2 automatically rounds that value up to a multiple of 32. Also, a **\$D SPOOLDEF** command displays the JES2-defined (rounded-up) value, not the value specified here if that value was not a multiple of 32.
2. A value for SPOOLNUM= of 254–256 is automatically decreased to 253 by JES2.
3. To avoid a future cold start, set this value to a value greater than your current requirements dictate and use the **\$S SPL** command to start volumes, as required.

As you set this parameter to values greater than 32, storage in the JES2 address space is used. For each additional 32 volumes specified, the JQE control block is increased by 4 bytes; these bytes are required for the JQE spool volumes used mask.

Modification: COLD START to decrease, and **\$T SPOOLDEF** to increase.

LARGEDS=[FAIL|ALLOWED|ALWAYS]

Specifies whether large SPOOL data sets (greater than 65,535 tracks) can be started or not. Also, indicates when to use the new format SPOOL record addresses (MTTRs).

FAIL

Specifies any attempt to start a SPOOL data set with more than 65,535 tracks is to fail.

ALLOWED

Specifies that SPOOL data set with up to the current size limit (1,048,575 tracks) is allowed. New format SPOOL addresses are used when you start a new volume that contains a SPOOL data set with greater than 65,535 tracks.

ALWAYS

Processing is the same as ALLOWED, except the new format SPOOL addresses are used when you start any volume, regardless of data set size. This setting is intended for testing applications that can use SPOOL addresses to access records on SPOOL when an actual large data set is not available.

Notes:

1. When LARGEDS is set to ALLOWED or ALWAYS, JES2 members at levels earlier than z/OS V1R7 can join the MAS until a COLD start is performed. IBM suggests not setting LARGEDS to ALLOWED or ALWAYS until all MAS members have stabilized on a z/OS release 7 level of JES2 or later.
2. Even if LARGEDS is set to ALLOWED or ALWAYS, SPOOL volumes with more than 15 records per track (for example, when you use buffer sizes less than 2,943 on a 3390) cannot use the new format for SPOOL record addresses. Those SPOOL volumes also do not support data sets larger than 65,535 tracks.
3. LARGEDS=FAIL is not supported in z11 mode. In z11 mode, on a COLD start, JES2 defaults to LARGEDS=ALLOWED. On all other starts, it defaults to the value that was used when JES2 shutdown. If LARGEDS=FAIL is specified on a COLD start, the default value of ALLOWED is used.

Modification: \$T SPOOLDEF operator command or JES2 cold start.

TGSIZE=[nnn|30]

Specifies the number (1–255) of JES2 buffers to be contained in a track group. JES2 uses this value to determine the number of tracks in a track group on each spool device. This value is the default for the number of track groups for each new spool volume that is added to the complex. Because the number of tracks in a track group varies based on the track capacity of the device, the resultant value is rounded to the minimum integral number of tracks that can contain the specified number of buffers.

If you specify TGSIZE=, it must contain a value from 1–255. Regardless of the value that is specified, the minimum resulting track group size is one track and the maximum is the smaller of 255 and the number of tracks in the first extent of the SYS1.HASPACE data set with the least number of tracks.

Note: If you do not specify TGSIZE= as the same value on all members of the complex, JES2 might not use the value that is specified here for a new spool volume.

Attempt to tailor the value of TGSIZE to fit most of the jobs in your system. SMF type 26 records can be used to assist your choice of a value for this parameter.

Small values for TGSIZE= can cause an excessive number of track group allocations per job thus increasing processor usage. For example, an IEFBR14 job requires 13 spool buffers for control blocks and JCL data sets; therefore, set the value of TGSIZE= greater than 13. Large values for TGSIZE= can waste spool space and unnecessarily increase seek time.

Modification: \$T SPOOLDEF to increase and a JES2 cold start to decrease.

TGSPACE=(MAX=[nnnnnnnn|16288],WARN=[nnn|80])

Specifies the maximum number (1–132,649,472) of track groups that are required before the next cold start. This value should include the track groups for all concurrently mounted spool volumes and for all planned spool additions when you determine each spool volume's requirement. Specify TGSPACE=(MAX=) as a multiple of 16,288. If you do not, JES2 automatically increases your specification to the next highest multiple of 16,288 without returning a message. Therefore, if you

display the SPOOLDEF parameters by the **\$D SPOOLDEF** command, the value JES2 returns does not match the value that is originally specified here.

Note:

- If the number of track groups you allocated on each spool volume is not divisible by 8, a discrepancy exists between the maximum allocatable track groups and the sum of the allocated track groups plus the number of track groups available.
- Use this parameter to increase the limit for the JNUM resource that is reported on the HASP050 message.

Table 98 on page 415 lists the number of track groups per volume for various devices:

Table 98. The number of track groups per volume listed by device type (and TGSIZE=30)

DEVICE	BUFSIZE	CYL/VOL	TRKS/GRP*	TRACK GRPS/ VOL*
3390-3	3992	3339	3	16690
3390-9	3992	10017	3	50080

* These values assume the default TGSIZE=30 was used. See [z/OS JES2 Initialization and Tuning Guide](#) for further statistics that relate to the specification of this parameter and resultant DASD usage.

Note: Assume that cylinder 0 is not available; it is used to hold the VTOC.

The TGSPACE=(MAX=) on SPOOLDEF, as a performance factor, should consider future spool volume additions. *nnnnnnn* should be large enough to accommodate planned expansion; therefore, set this parameter higher than your present requirements dictate. The performance cost should be minimal. The following equation determines how storage is calculated:

$$(((nnnnnnn + 16287) / 16288) \times 16288) / 8) \times 4$$

The values chosen for TGSPACE=, BUFSIZE=, and TGSIZE= (as specified on this initialization statement), are related and thus all affect efficient use of spool devices. For more information about selected values that affect spool device usage and device usage in storage-constrained environments, see [DASD utilization tables](#) in *z/OS JES2 Initialization and Tuning Guide*.

If you do not specify a value, this parameter defaults to 16288. This value is the number of track groups that are needed to allow all three track groups (master, JES2-detected badtracks, and BADTRACK statement-specified tracks) to efficiently fit on one page of storage.

If you use the **\$T SPOOLDEF** command to increase TGSPACE=(MAX=), do so only when you can allow your system to experience temporary performance degradation while all JES2 systems read the checkpoint data set.

WARN= specifies a percentage (1–99) threshold of track groups usage that triggers message \$HASP050 JES2 RESOURCE SHORTAGE. The WARN= percentage is calculated only from spool volumes that are active and can have space that is allocated (ACTIVE=YES and RESERVED=NO).

Modification: **\$T SPOOLDEF** operator command to increase, or by using a cold start. A JES2 cold start must be used to decrease.

Restriction: This parameter cannot be modified through a hot start, quick start, or single-member warm start.

TRKCELL=[nnn]3]

Specifies the size (1–120) of a track cell in terms of spool buffers. TRKCELL= specifies the number of direct-access spool records to be logically ordered on a spool track and the number of records to be despoiled (read from the spool) in one operation during print processing. A data set uses the track-cell method only if the SYSOUT class of the data set has the TRKCELL= characteristic. For more information, see “OUTCLASS(v) - SYSOUT Class Characteristics” on page 285. Similarly, track cells, rather than single buffers, are despoiled during print processing only if the printer is defined with the TRKCELL=YES parameter on the **PRTnnnn** statement. For more information about the **PRTnnnn** initialization statement, see “PRT(nnnnn) - Local Printer” on page 306.

If TRKCELL= is greater than the number of records on a track of a spool volume, the entire track is considered a track cell. If TRKCELL= is less than or equal to the number of records on a track of a spool volume, the track is divided into as many track cells as fit evenly. For more information, see *z/OS JES2 Initialization and Tuning Guide*.

After this division, any remaining records are used as follows:

- If the number of remaining records is greater than or equal to one-half the TRKCELL= value, the records are available to any data set (with or without the track-cell characteristic).
- If the number of remaining records is less than one-half the TRKCELL= value, the records are available only for data sets without the track-cell characteristic.

The following performance specification considerations should be noted when you define a value for TRKCELL=.

- In the NJE environment, the SYSOUT receiver flags the data sets in a class (with TRKCELL= specified on the **OUTCLASS** statement) it receives with the **TRKCELL=** attribute. To avoid degraded performance when you print data sets on a printer that supports track-cell despooling (TRKCELL=YES parameter on the **PRTnnnn** statement), use the TRKCELL= specification to prevent spool tracks from containing “short” track-cells (that is, those track-cells with a length less than half TRKCELL=).
- Print buffers typically are in central storage during JES2 printing and despooling operations. Therefore, a large value for **TRKCELL=** increases JES2 central storage requirements.

Modification: Cold start.

Volume=[xxxxx]SPOOL]

Specifies the 4-character to 5-character prefix assigned to JES2's spool volumes. The first 4–5 characters of the volume serial must be identical to the characters specified by this parameter. Those volumes that begin with this prefix and a data set named the same as the DSNAME specification are considered JES2 volumes.

The maximum number of spool volumes in use by JES2 must not exceed 253 at any one time.

IBM suggests that you limit the prefix to 4 characters. If you use a 5-character prefix, the suffix is limited to a single character (A-Z, 0-9, \$, #, @), which restricts you to a maximum of 39 volumes. Limiting the prefix to 4 characters helps you avoid future cold starts.

Volume=[volume]*]

If no generic characters are specified, volume specifies a 4 or 5 character prefix to be assigned to JES2 spool volumes. Volume must be the first 4 or 5 characters of the existing prefix. If generic characters are specified, then all new spool volumes must match this 1–5 character pattern. The asterisk character (*) prefix enables the usage of any volume for SPOOL.


Modification: If originally specified with 5 characters and the fifth character is removed, then **\$T** operator command is allowed or cold start.

SSI(nnn) - Subsystem Interface Definition


The SSI(nnn) statement specifies whether tracing is available for individual subsystem interface function definitions. Specify nnn as a number (1-256); see *z/OS MVS Using the Subsystem Interface* for the SSI number.

Note: If you modify SSI(nnn) parameter values and then restart JES2 with a hot start, the parameter values in effect before termination will be used.


Format Description for SSI(nnn)



Modification keywords



Selection limiting keywords



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for SSI(nnn)

TRace=Yes|No

Specifies whether (Yes) or not (No) tracing is active for the specified subsystem interface function.

Note: If TRace=Yes, JES2 does not create any trace data for SSI function 54.

Modification: \$T SSI(nnn) operator command.

SUBMITLIB(xxxxxxxx) - JCL library definition


The SUBMITLIB(xxxxxxxx) statement defines a data set concatenation to be used when submitting batch jobs that use the \$SUBMIT command on this member. These concatenations can contain any combination of partitioned data sets (PDSs) or file system paths. SUBMITLIBs can be added, updated, or deleted through operator commands.

If a file system path is specified, files in the path with 1-8 character uppercase file names that conform to standard PDS member names can be accessed using the FILEDATA=TEXT allocation option.


Similar to PROCLIB concatenations, JES2 does not by default get the SYSDSN ENQs for data sets in the SUBMITLIB concatenations. If you would like these ENQs to be obtained (for example, to prevent the data sets from being deleted), then, like PROCLIB, you can set the DSI program property attribute that is associated with the HASJES20 program by using the SCHEDxx member of PARMLIB. If HASJES20 is defined with DSI, then JES2 requests the appropriate ENQs when the SUBMITLIB data sets are dynamically allocated.

Note: SUBMITLIB statement processing only ensures that the data sets specified can be allocated. It does not ensure that they actually exist or can be opened and used as a SUBMITLIB data set. That processing occurs when the SUBMITLIB is used by a \$SUBMIT command.


Format description for SUBMITLIB(xxxxxxxx)




Modification keywords




Selection limiting keywords



Data Set Specifications



Data Set Selection Criteria



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter description for SUBMITLIB(xxxxxxxx)

xxxxxxxx

Specifies the 1-8 character SUBMITLIB DD name being defined. The SUBMITLIB DD name can be specified as DDNAME= on the \$SUBMIT command or defaulted on the DD_DEFAULT= keyword on the SUBMITDEF statement.

Modification: \$T SUBMITLIB(xxxxxxxx) command, warm start or hot start.

DD(nnn)=

Specifies up to 255 data sets to be concatenated to this SUBMITLIB DD name. Data sets in this list are compacted after each initialization statement is processed. If you specify DD(1), DD(20), and DD(100) for a new SUBMITLIB concatenation, the resulting concatenation is renamed to DD(1), DD(2), and DD(3). If you then set the data set name for DD(2) to null, JES2 removes it from the concatenation leaving just DD(1) and DD(2) where DD(2) has the old DD(3) data set specification. Though up to 255 data sets can be specified, MVS rules limit any data set concatenation to 255 extents. If any data set has more than one extent, then the total number of data sets that can be supported is reduced.

Modification: \$T SUBMITLIB(xxxxxxxx) command, warm start or hot start.

DSName=jxxx...x

Specifies a 1-44 character data set name which JES2 includes in this SUBMITLIB concatenation. This data set must be a partitioned data set (PDS). If this value is coded as null (no operand specified), then the DD(nnn) is deleted from an existing concatenation.

Modification: \$T SUBMITLIB(xxxxxxxx) command, warm start or hot start.

UNIT=hhhh|/hhhh|nnnn|ccccccc

If the SUBMITLIB data set to be used is not cataloged, then you must specify the unit information for the device containing the data set in one of the following ways:

hhhh | /hhhh

Specifies a 3 or 4 digit hexadecimal device number. Device numbers can be specified in one of the following formats:

- UNIT=hhh
- UNIT=/hhh
- UNIT=/hhhh

Where, hhh and hhhh represent the device numbers. A slash (/) must precede a 4 digit device number.

nnnn

Specifies a device name.

CCCCCCCC

Specifies a 1-8 character group name that is assigned to the device or group of devices that contained the non-cataloged initialization data set to be included.

Modification: \$T SUBMITLIB(*xxxxxxxx*) command, warm start or hot start.

VOLser=xxxxxx

If the SUBMITLIB data set to be used is not cataloged, then this specifies a 1-6 character volume serial number on which the data set resides.

Modification: \$T SUBMITLIB(*xxxxxxxx*) command, warm start or hot start.

PATH='xxxxxxxx'

Specifies a 1-88 character file system PATH which JES2 includes in this SUBMITLIB concatenation. Files in this path with a 1-8 character name can be accessed by the \$SUBMIT command. This path is allocated with the FILEDATA=TEXT allocation option. If the PATH= value is coded as null (no operand specified), then the DD(*nnn*) is deleted from an existing concatenation.

Modification: \$T SUBMITLIB(*xxxxxxxx*) command, warm start or hot start.

UNCONDitional|CONDitional

Specifies what action JES2 should take if one of the data sets or paths cannot be allocated. If CONDitional is specified (or defaulted), then if any data set or path cannot be allocated, the entire statement fails. The system is in console mode to allow the operator to correct the statement. If UNCONDitional is specified, then an error allocating a single data set or path is ignored. The entry is not added to the concatenation, but it remains assigned to the DD(*nnn*). If the concatenation is displayed, failed DD(*nnn*) displays the text 'ALLOCATION FAILED' before the data set name or path value. If all the data sets and paths in a concatenation fail to allocate, then the statement fails regardless of whether UNCONDitional was specified.

Modification: \$T SUBMITLIB(*xxxxxxxx*) command, warm start or hot start.

NAME=xxxxxxxx

Intended mostly for \$T command, NAME= allows the name of a SUBMITLIB concatenation to be changed. For example, specifying SUBMITLib(TEST) NAME=PROD renames the TEST SUBMITLIB concatenation to PROD. **Modification:** \$T SUBMITLIB(*xxxxxxxxt*) command, warm start or hot start.

Modification: \$T SUBMITLIB(*xxxxxxxx*) command, warm start or hot start.


SUBMITRDR - Submit reader

The SUBMITRDR statement specifies the default characteristics of the reader that is used by the \$SUBMIT command. The submit reader is a logical device that is used to submit jobs, control statements, and commands to JES2 from a member of a SUBMITLIB concatenation.


Format Description for SUBMITRDR




Modification keywords



Selection limiting keywords



Auth keywords



Notes:

- ¹ Omit the comma between initialization statement and first keyword

Parameter description for SUBMITRDR

Auth=(Job=Yes|No,Device=Yes|No,System=Yes|No)

The SUBMITRDR statement specifies the command authority for submit readers (commands that are received by using the \$SUBMIT command). These values authorize certain JES2 commands to be submitted by using \$SUBMIT.

Note: This parameter has no effect when the associated resource class and profile in RACF 1.9 or higher are active. For more information about using JES2 security facilities, see [z/OS JES2 Initialization and Tuning Guide](#).

Job=Yes|No

Specifies that the device can (Yes) or cannot (No) issue commands that require job authority.

Device=Yes|No

Specifies that the device can (Yes) or cannot (No) issue commands that require device authority.

System=Yes|No

Specifies that the device can (Yes) or cannot (No) issue commands that require system authority.

This parameter affects JES2 control statements only. Use the AUTH parameter of the JOBCCLASS initialization statement to specify the authorization for JCL statements. (JES2 control statements begin with /* in columns 1 and 2. JCL statements begin with // in columns 1 and 2.)

Modification: \$T SUBMITRDR operator command.

Class=class

Specifies the default job class to be assigned to all jobs submitted by using the \$SUBMIT command. This is used when a job does not specify a job class in the CLASS= operand of their JOB statements.

DD_default=ddname

Specifies the SUBMITLIB subscript (DD name) that is used as the default for the DDNAME= keyword on the \$SUBMIT command. The *ddname* value is validated at the time of the \$SUBMIT command.

Modification: \$T SUBMITRDR operator command.

Hold=Yes|No

Specifies that all jobs submitted by using the \$SUBMIT command are held (Yes) or not held (No) after JCL conversion until they are released for execution by the operator. This can be overridden by the HOLD= keyword on the \$SUBMIT command.

Modification: \$T SUBMITRDR operator command.

PRTYINC=nn|0

Specifies an integer (0-15) to be **added** to the selection priorities of all jobs submitted by using the \$SUBMIT command. If the total of this number and the priority of a job exceeds the value specified by PRTYLIM=, JES2 assumes the priority that is specified by PRTYLIM=.

Modification: \$T SUBMITRDR operator command.

PRTYLIM=nn|15

Specifies the maximum priority level (0-15) that can be assigned to jobs submitted by using the \$SUBMIT command. If the priority of a job (with or without the increment that is specified by PRTYINC=) exceeds this level, it is reduced to this level.

Modification: \$T SUBMITRDR operator command.

TRace=Yes|P|No

Specifies whether tracing is activated or deactivated for the \$SUBMIT command. To trace input processing for \$SUBMIT, you must also provide the following initialization statements:

```
TRACE(n) START=YES
TRACEDEF ACTIVE=YES
```

Note: Specifying TRACE=P is the same as specifying TRACE=Yes.

This parameter setting can be overridden by the \$T SUBMITRDR operator command. \$SUBMIT tracing is also controlled by trace IDs 11 and 12, the TRACE(n) and TRACEDEF initialization statements, and the \$TRACE command. For more information about the tracing facility, see *z/OS JES2 Initialization and Tuning Guide*, the “TRACE(n) - Initial tracing value setting” on page 428 and “TRACEDEF - Trace Facility Definition” on page 430 initialization statements, and \$D TRace(nnn) - Display current status of trace IDs.

Modification: \$T SUBMITRDR operator command.

ASID_trace=hhhh

Specifies the ASID qualifier that is associated with \$SUBMIT trace points. Only trace points with the specified ASID are recorded. This setting has no effect if TRace=NO was specified.

Modification: \$T SUBMITRDR operator command.

JOBName_trace=nnnnnnnn

Specifies the job name qualifier that is associated with \$SUBMIT trace points. Only trace points that are associated with the specified job name are recorded. This setting has no effect if TRace=NO was specified.

Modification: \$T SUBMITRDR operator command.


JOB_Number_trace=nnnnnnnn

Specifies the job number qualifier that is associated with \$SUBMIT trace points. Only trace points associated with the specified job number are recorded. This setting has no effect if TRace=NO was specified.

SUBTDEF - Define General Purpose Subtasks

SUBTDEF specifies the number of general purpose subtasks you need attached during JES2 initialization.

Format Description for SUBTDEF



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for SUBTDEF

GSUBNUM=n|10


Defines the maximum number (1-50) general purpose subtasks available. This allows you to call service routines from the JES2 main task. (See *z/OS JES2 Initialization and Tuning Guide* for additional information about using the general purpose subtasking facility.)

Modification: Hot start.

TPDEF - Teleprocessing Definitions

The TPDEF statement defines the JES2 teleprocessing characteristics.

Format Description for TPDEF



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for TPDEF

AUTOINTV=nnn|32

Specifies the autologon timer interval (10-600 seconds) (the time between JES2 automatic logon attempts) for this installation. The timer is necessary only when a previous logon attempt by an autologon remote has failed or messages are queued for the remote, and the normal events (output for the remote, JES2 RJE resources becoming available, and so forth) that would drive the autologon scan have not occurred.

Proper specification of this parameter decreases the number of unnecessary output searches. Too low a number could cause excessive time spent searching the queues, resulting in performance degradation. Too high a number could cause excessive spool usage because messages for remotes that are not logged on are using the spool.

Modification: \$T TPDEF operator command.

BSCBUF=

Specifies information about the BSC teleprocessing buffers JES2 allocates below 16 megabytes in virtual storage.

LIMIT=nnnn

Specifies the maximum number (10-9999) of BSC teleprocessing buffers JES2 allocates below 16 megabytes in virtual storage.

Performance Considerations: Each signed-on JES2 multileaving terminal requires at least two JES2 teleprocessing buffers. Each signed-on NJE member requires at least two JES2 teleprocessing buffers and should normally have one additional for input, one additional for each output transmitter, plus additional (spare) buffers for console and path manager communications. All other signed-on terminals require at least one buffer each.

If a multileaving terminal has more than one output function running concurrently, additional buffers can be used to increase performance. If your installation is not storage-constrained and can tolerate a greater use of virtual storage, over specifying the LIMIT= parameter on the BUFDEF statement and the LIMIT= parameter on this statement can prove useful. Over specifying these parameters can prevent system degradation caused by a lack of available buffers and does not increase the working set for buffers which are not used. For additional information, see the SIZE= subparameter and the MBUFSIZE= parameter.

This parameter defaults to the greater of either:

```
2 x (number of BSC lines specified by LINE(nnnnn) statements)
--OI--
10
```

Modification: \$T TPDEF operator command to increase the limit. Hot Start to decrease the limit.

SIZE=nnnn|520

Specifies the size (520-3960) in bytes of the BSC teleprocessing buffers JES2 allocates below 16 megabytes in virtual storage.

Note: Use the \$D NJEDEF command to display the actual SIZE= value.

If necessary, JES2 increases the value specified for SIZE= without notice to the appropriate minimum value indicated above if RMT(nnnnn) initialization statements are specified for the above terminal types with the indicated features.

Performance Considerations: BSC buffers do not span MVS pages. Therefore, be certain that the value specified for this parameter allows for reasonable utilization of a 4K-page after JES2:

- Adds the 24-byte buffer prefix plus the 112-byte IOB (input/output buffer) for a total of 136 bytes.
- Does any necessary automatic upward rounding to a multiple of 8, and to evenly fit buffers on a page.

Modification: Warm start.

WARN=nnn|80

Specifies a threshold percentage (0-100) of the maximum use of teleprocessing buffers below 16 megabytes in virtual storage at which JES2 issues the \$HASPO50 to warn the operator of a resource shortage. If you specify 0, no alert is given.

Modification: \$T TPDEF operator command.

SNABUF=

Specifies information about the SNA teleprocessing buffers JES2 allocates above 16 megabytes in virtual storage.

Note: If necessary, JES2 increases the value specified for SIZE= without notice if the BUFSIZE= parameter on the RMT(xx) statement is larger than the specified size on the TPDEF statement. Also note that any change to buffer size will affect both RJE and NJE.

LIMIT=nnnn

Specifies the maximum number (10-9999) of teleprocessing buffers JES2 allocates above 16 megabytes in virtual storage.

LIMIT= defaults to the greater of either:

```
2 x (number of SNA lines specified by LINE(nnnnn) statements)
--or--
10
```

Modification: \$T TPDEF operator command to increase the limit. Hot Start to decrease the limit.

SIZE=nnnn|400

Specifies the size (256-32512) in bytes of the JES2 teleprocessing buffers JES2 allocates above 16 megabytes in virtual storage.

Performance Considerations: Be certain that the value specified for this parameter allows for reasonable utilization of a 4K-page after JES2:

- Adds the 24-byte buffer prefix plus the 232-byte RPL (request parameter list) for a total of 256 bytes.
- Does any necessary automatic upward rounding to a multiple of 8, and to evenly fit buffers on a page.

Modification: Warm start.

WARN=nnn|80

Specifies a threshold percentage (0-100) of the maximum use of teleprocessing buffers above 16 megabytes in virtual storage at which JES2 issues the \$HASPO50 to warn the operator of a resource shortage. If you specify 0, no alert is given.

Modification: \$T TPDEF operator command.

MBUFSIZE=nnnn|400

Specifies the size (128-3960) in bytes (dependent upon JES2 macro expansions) of each JES2 multileaving buffer. The specification for this parameter must be a positive even integer. Satisfactory support of one device of each type (reader, printer, punch console) on 8K-terminal processors is based on the assumption that MBUFSIZE= not be increased above 400, even if support of a non-programmable terminal requires increasing the value specified in the BSCBUF= parameter to 516. In support of 8K-multileaving workstations, this parameter can be increased above 400 if the BUFSIZE= parameter on the corresponding RMT(nnnnn) statement is likewise increased. A smaller multileaving buffer size may be specified for a particular remote terminal on its RMT(nnnnn) initialization statement.

MBUFSIZE= must be a multiple of 2. If not, it is automatically rounded up. If the value specified is greater than that specified on SIZE= for BSCBUF= on SNABUF=, then BSCBUF= and SNABUF= are rounded up.

Note:

1. To avoid having the SIZE= subparameters for both BSCBUF= and SNABUF= overwritten by the MBUFSIZE= parameter, ensure that the value of both SIZE= subparameters is greater than that specified by MBUFSIZE=.
2. This parameter is only valid for BSC-programmable terminals that have been specified as MULTILV=YES and do not also have BUFSIZE= specified. This parameter does not affect hardware remotes, SNA remotes, BSC NJE terminals, or SNA NJE terminals.

3. If you want a specific multileaving terminal to use a different buffer size, you should explicitly specify that buffer size on the BUFSIZE parameter of the RMT(nnnnn) (BSC) initialization statement.

Modification: Hot start.

RMTMSG=nnn|100

Specifies the maximum number (1-255) of messages that may be queued by RTAM to a multileaving remote console. When the count is exceeded, messages will be spooled until the message backlog for that remote console goes to zero.

Modification: \$T TPDEF operator command.

Performance Considerations: Always set the value for RMTMSG= to a value considerably lower than the value set for the BUFNUM= parameter on the CONDEF statement. This will ensure that no one BSC multi console can acquire all of the communication buffers (CMBs) and thereby lock out host console messages.

RMTNUM=nnnnn

Specifies the highest number (0-32767) that can be defined for an RJE workstation on this member. When JES2 is active, RJE workstations cannot be added if they specify a higher subscript than this value.

If you do not specify this parameter or an RMTnnnnn initialization statement specifies an RJE workstation higher than the RMTNUM= specification, JES2 sets RMTNUM= to the highest number specified for an RJE workstation on this member during initialization.

Performance Considerations: Because RMTNUM= allocates storage (68 bytes of storage below 16Mb of virtual storage for each RJE workstations) whether they are defined or not, you should set this parameter low enough to minimize the unused virtual storage at your installation. However, setting this value conservatively higher than the number of currently defined RJE workstations can be useful should you need to add RJE workstations without restarting JES2. See *z/OS JES2 Initialization and Tuning Guide* for further information on providing for future growth of your RJE workstation environment.

Modification: Hot start.

SESSIONS=

Specifies information about the maximum of VTAM sessions.

LIMIT=nnnnn

Specifies the maximum number (1-32767 of VTAM sessions (nnnnn) that can be active at any one time. Terminals or SNA NJE nodes attempting to log on when nnnnn sessions are already active are not allowed to log on.

If you do not specify a value for this parameter, it defaults to the number of LINE(nnnnn) initialization statements specifying the UNIT=SNA keyword.

Note:

1. The default value is not sufficient to allow all SNA RJE and NJE lines to be simultaneously connected to JES2 if some of the terminals represent multiple logical units.
2. Although the valid range for this parameter is (1-32767, if you do not define any sessions, by using the LINE initialization statement with UNIT=SNA defined, SESSIONS= defaults to 0.

Note: Use this parameter to increase the limit for the JNUM resource that is reported on the HASP050 message.

WARN=nnn|80

Specifies a threshold percentage (0-100) of the maximum used number of VTAM sessions at which JES2 issues the \$HASP050 to warn the operator of a resource shortage.

Modification: \$T TPDEF command.

TRACE(n) - Initial tracing value setting



The TRACE initialization statement is used to set the initial values for tracing options. The operator can override these values with the \$S and \$P TRACE(n) commands.

The TRACE statement can control an individual trace ID (TRACE(n)), a range of trace IDs (TRACE(n-m)), or a generic range of trace IDs (TRACE(n-*)). If, for example, you specify TRACE(1-*), all defined trace IDs from 1 through 255 are activated.


Note:

1. Individual trace IDs can be started or stopped independent of the overall trace facility by using the START=Yes|No parameter on this statement whether or not the trace facility is active (that is, ACTIVE=Yes or No on TRACEDEF is also specified).
2. Trace IDs 1 through 47 are defined for use by JES2.
3. If you modify this parameter value and then restart JES2 with a hot start, the parameter value in effect before termination will be used.


Format Description for TRACE(n)



Modification keywords



Selection limiting keywords



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for TRACE(n)

START=Yes|No

Specifies whether (Yes) or not (No) a specific trace ID or range of IDs is activated. The range of trace IDs used by JES2 is 1-47.

Note: Do not confuse this parameter with the ACTIVE=Yes|No parameter specification on the TRACEDEF statement that is used to turn the entire TRACE facility on or off.

Modification: \$\$ TRACE(n) operator command or \$P TRACE(n) operator command.

ASID=xxxx

Specifies the ASID used when filtering this JES2 trace point.

JOBNAME=nnnnnnnn

Specifies the jobname used when filtering this JES2 trace point.

JOB_NUMBER=nnnnnnnn

specifies the job number used when filtering this JES2 trace point.

Note: If more than one of ASID=, JOBNAME=, and JOB_NUMBER= are specified for a specific trace ID, only one of the conditions must match for the trace to be taken. In the JES2 address space, the values specified always refer to the job that JES2 is processing. For example, never specify the JES2 address space as ASID= because JES2 never processes requests on the behalf of JES2. Outside the JES2 address space, these filters refer to the address space where the trace is being taken. For jobs being submitted through the internal reader, it is the job name, job number, and ASID of the submitter of a job that are compared to the filters, not the values of the job being submitted. The same applies to FSS or SAPI devices. The filters refer to the SAPI or FSS address space, not the job that the FSS or SAPI application is processing.

TCB_ADDRESS=xxxxxxxxxx


Specifies the TCB address in order to further limit tracing to the specified TCB. This is in addition to any filtering that is applied. This operand is ignored if ASID=, JOBNAME=, and JOB_NUMBER= are not specified. The TCB address must match even in the JES2 address space.

TRACEDEF - Trace Facility Definition

The TRACEDEF initialization statement controls the overall status of the TRACE facility and the amount of storage you will allow the TRACE facility to use in your complex. Individual trace ids are controlled by the TRACE(n) initialization statement.

Note: If you modify TRACEDEF parameter values and then restart JES2 with a hot start, the parameter values in effect before termination will be used.

Format Description for TRACEDEF



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for TRACEDEF

ACTIVE=Yes|No

Specifies whether (Yes) or not (No) the TRACE facility is started. The operator can use the \$T TRACEDEF, ACTIVE= command to start tracing if it was initially set off (that is, ACTIVE=No).

Note: Do not confuse this parameter with the START=Yes|No parameter specification on the TRACE(n) statement which is used to activate individual (or a range of) trace IDs.

Modification: \$T TRACEDEF operator command.

HAM=(TRACE=,BUFSIZE=,JOBNAME=,JOB_NUMBER=)

Specifications for the HAM (HASP Access Method) rolling CTRACE. The CTRACE is established when the JES subsystem data set is allocated and is deleted when the data set is unallocated.

The sub name of the trace is HAM\$asid@sdbaddrx and it is located in 64-bit private storage of the address space making the HAM requests.

TRACE=value

Specifies the types of requests that should be processed. Multiple values can be specified, one per keyword.

Values are:

FSS or NOFSS

FSS read processing

GET or NOGET

read processing of instream data sets

PSO or NOPSO

read processing of PSO data sets

PUT or NOPUT

write processing of SYSOUT data sets

SAPI or NOSAPI

read processing of SAPI data sets

BROWSE or NOBROWSE

SPOOL Data Set Browse processing when in-storage buffers are not being requested

BROWSE_LIVE or NOBROWSE_LIVE

SPOOL Data Set Browse processing when in-storage buffers are being requested

NONE

turn all options off

ALL

turn all options on

BUFSIZE=nn

Specifies the size of the trace buffer to get in segments (megabytes).

JOBNAME=xxxxxxx

Specifies the jobname (including generics) used when filtering HAM CTRACE. This is the name of the job performing the HAM requests. Note: If both JOBNAME and JOB_NUMBER are specified, a match on either one of the conditions activates the trace.

JOB_NUMBER=nnnnnnnn

Specifies the job number used when filtering the HAM CTRACE. This is the job number of the job performing the HAM requests.

Note: If both JOBNAME and JOB_NUMBER are specified, a match on either one of the conditions activates the trace.

LOG=(CLASS=,SIZE=,START=)

Specifies the trace table logging environment.

CLASS=v|A

Specifies the output class (A-Z, 0-9) of the trace log data set.

Modification: \$T TRACEDEF operator command.

SIZE=nnnnnnnnnn|500

Specifies the maximum size (100-2147483647) (in bytes) that the trace log data set may attain before it is queued for printing.

Note: The proper setting for the this parameter will assure that JES2 will not use all available virtual storage in CSA.

Modification: \$T TRACEDEF operator command.

START=Yes|No

Specifies whether (Yes) or not (No) the trace log information is formatted and periodically added to the trace log data set. Yes further specifies that the trace log data set will be spun off and printed before it exceeds its maximum size (as specified by the SIZE= subparameter).

Modification: \$T TRACEDEF operator command.

PAGES=nnnn|9

Specifies the number (9–1000) of 4K-pages available to each trace table. The default value is 9. Specifying values 1 through 8 will be increased to 9 automatically. There is a limit of 3000 pages for maximum trace storage which is the number of tables times the number of pages per table. This will limit the number of tables to 333 max.

Modification: Single-member warm start.

TABLES=nnnn|3

Specifies the number (0-333) of trace tables that JES2 creates at initialization. Each table is 4K-bytes x PAGES= value in size. If you specify 1 or 2, the value is automatically increased to 3. If 0 is specified, the TRACE facility cannot be started or tracing will be deactivated when the number of tables is reduced to 0.

Note: Use this parameter to increase the limit for the JNUM resource that is reported on the HASP050 message.

Modification: \$T TRACEDEF operator command.

TABWARN=nnn|80

Specifies the percentage (0-100) of trace table use at which the operator will be alerted through message \$HASP050 JES2 RESOURCE SHORTAGE. If you specify 0, no alert will be given.

Modification: \$T TRACEDEF operator command.

VERify - Verifying Code Through the JES2 Patching Facility

The VERify initialization statement is one of several statements used by the JES2 patching facility. For the other statements, see “REP - Replacing Code Through the JES2 Patching Facility” on page 379 and “NAME - Naming the Module to Change Through the JES2 Patching Facility” on page 219. The JES2 patching facility allows you to verify data (patches) for the following:

- Any module in JES2 (for example, HASJES20 or an installation exit load module)
- Any absolute storage address from the address space where JES2 is loaded.
- On a hot start, any address in a data space created by JES2 (that is, owned by JES2AUX)
- On any warm start, any address in the JES2 checkpoint data set.

Note: You can verify data patches for HASCxxxx modules if they do not reside in read-only storage (PLPA).

The JES2 patching facility applies temporary patches to the in-storage copy of JES2 modules. You place patching facility statements in the JES2 initialization stream; these patches are applied when you initialize JES2. Because some of the initialization code has already been executed before the patch facility initialization statements are processed, patches made to those portions of the code are ineffective; those portions of code **do not** execute again until you restart JES2. Most patches are applied immediately as the statements are processed. However, checkpoint updates are deferred until the checkpoint record is read. Non-checkpoint patches are not saved across a warm start. JES2 reloads the load modules at different stages in processing:


- Subsystem support modules are reloaded during all starts except a hot start.
- HASPJES20 is reloaded in response to a JES2 START command any time the subsystem is started.

In addition, you should be aware that the JES2 patching facility does **not** support:

- Patching a module or data area residing in read-only storage. For example, you cannot use the facility to modify modules in PLPA or PSA.
- Patching a HASPFSSM load module that has been loaded into a functional subsystem address space. Use AMASPZAP (the service aid program that modifies both instructions and data) must be used to patch the HASPFSSM load module.
- Altering the JES2 dump formatting exit modules (HASMxxxx).
- Using a patch across a restart of JES2. Because these patches are valid only until a load module is reloaded, they must be reapplied every time JES2 is started.

The JES2 patching facility statements in the JES2 initialization data set can be specified in either the JES2 patching format or in the AMASPZAP format. All patches in the JES2 patching form should precede any AMASPZAP patches. If you supply the NAME statement or first format type of the AMASPZAP patch, JES2 resets prior verification errors. If a VERify statement fails, following REP statements are rejected until the next NAME statement is reached. For more information on AMASPZAP patches, see “SPZAP” in *z/OS MVS Diagnosis: Tools and Service Aids*.

Format Description for VERify



Notes:

¹ Omit the comma between initialization statement and first keyword or variable

Parameter description for VERify

VERify

The data on the statement is compared with the data at the location specified by the csect and address fields. If the data does not match, an error message is displayed in the parameter library list data set.

csect|dspname|CKPTname|*

Specifies the control section (or control block), dataspace name, or checkpoint CTENT in which the data to be verified resides.

If an asterisk (*) is coded, JES2 uses the CSECT, dataspace, or CTENT in effect on the previous JES2 patch statement. [Table 99 on page 433](#) contains a list of the possible patch names which can be coded and area to which these names refer. If the CSECT is listed in [Table 99 on page 433](#), you can specify the last four characters of the CSECT name. See [Table 95 on page 380](#) for more information.

If an installation exit CSECT is referenced, the JES2 patching facility requires the entire module name, except for the reserved names HASPXJ00-HASPXJ31. If you do not linkedit the installation exit routines HASPXJ00-HASPXJ31 with the HASJES20 load module, you must specify the full 8-character CSECT name.

Furthermore, do not name an exit with the same three or four characters (xxxx) as used for a JES2 module. For example, an installation-defined exit named CKPT or TABS (that is, HASPCKPT or HASPTABS, with the HASP characters removed) would modify the IBM-supplied HASPCKPT or HASPTABS module.

<i>Table 99. Patch Name to CSECT Reference</i>		
CSECT Referenced	AMASPZAP Patch Name	JES2 Patch Name
HASCARMS	HASCARMS	ARMS
HASCARSO	HASCARSO	ARSO
HASCBLDM	HASCBLDM	BLDM
HASCCNVS	HASCCNVS	CNVS
HASCDAU	HASCDAU	DAU
HASCDLAL	HASCDLAL	DLAL
HASCDSOC	HASCDSOC	DSOC
HASCDSS	HASCDSS	DSS
HASCENF	HASCENF	ENF
HASCGGKY	HASCGGKY	GGKY
HASCGGST	HASCGGST	GGST
HASCHAM	HASCHAM	HAM

Table 99. Patch Name to CSECT Reference (continued)

CSECT Referenced	AMASPZAP Patch Name	JES2 Patch Name
HASCINJR	HASCINJR	INJR
HASCJBST	HASCJBST	JBST
HASCJBTR	HASCJBTR	JBTR
HASCLINK	HASCLINK	LINK
HASCNJAS	HASCNJAS	NJAS
HASCNJEX	HASCNJEX	NJEX
HASCNJGP	HASCNJGP	NJGP
HASCNJE	HASCNJE	NJE
HASCNJJR	HASCNJJR	NJJR
HASCNJJT	HASCNJJT	NJJT
HASCNJSR	HASCNJSR	NJSR
HASCNJST	HASCNJST	NJST
HASCNJRC	HASCNJRC	NJRC
HASCNJRQ	HASCNJRQ	NJRQ
HASCOFST	HASCOFST	OFST
HASCPHAM	HASCPHAM	PHAM
HASCPPOOL	HASCPPOOL	POOL
HASCRQUE	HASCRQUE	RQUE
HASCSAPI	HASCSAPI	SAPI
HASCSCAN	HASCSCAN	SCAN
HASCSIJI	HASCSIJI	SIJI
HASCSIRQ	HASCSIRQ	SIRQ
HASCSISC	HASCSISC	SISC
HASCSJFA	HASCSJFA	SJFA
HASCSJFS	HASCSJFS	SJFS
HASCSRAX	HASCSRAX	SRAX
HASCSRDS	HASCSRDS	SRDS
HASCSRIC	HASCSRIC	SRIC
HASCSRIP	HASCSRIP	SRIP
HASCSRJB	HASCSRJB	SRJB
HASCTP	HASCTP	TP
HASCUBES	HASCUBES	UBES
HASCUBFR	HASCUBFR	UBFR
HASCUBRM	HASCUBRM	UBRM

<i>Table 99. Patch Name to CSECT Reference (continued)</i>		
CSECT Referenced	AMASPZAP Patch Name	JES2 Patch Name
HASCUBSR	HASCUBSR	UBSR
HASCXJCT	HASCXJCT	XJCT
Absolute Storage Location	-	ABS
HASPARM	HASPARM	ARM
HASPARMO	HASPARMO	ARMO
HASPBSC	HASPBSC	BSC
HASPCFAL	HASPCFAL	CFAL
HASPCFBF	HASPCFBF	CFBF
HASPCFDE	HASPCFDE	CFDE
HASPCFE	HASPCFE	CFE
HASPCFFC	HASPCFFC	CFFC
HASPCFLE	HASPCFLE	CFLE
HASPCFMT	HASPCFMT	CFMT
HASPCFQL	HASPCFQL	CFQL
HASPCFQU	HASPCFQU	CFQU
HASPCFRD	HASPCFRD	CFRD
HASPCFRE	HASPCFRE	CFRE
HASPCFRL	HASPCFRL	CFRL
HASPCFRS	HASPCFRS	CFRS
HASPCFR2	HASPCFR2	CFR2
HASPCFSI	HASPCFSI	CFSI
HASPCFT1	HASPCFT1	CFT1
HASPCFUN	HASPCFUN	CFUN
HASPCFWP	HASPCFWP	CFWP
HASPCFWR	HASPCFWR	CFWR
HASPCKDS	HASPCKDS	CKDS
HASPCKPT	HASPCKPT	CKPT
HASPCKRR	HASPCKRR	CKRR
HASPCKVR	HASPCKVR	CKVR
HASPCNVT	HASPCNVT	CNVT
HASPCOMM	HASPCOMM	COMM
HASPCON	HASPCON	CON
HASPCSV	HASPCSV	CSV
HASPDOC	HASPDOC	DOC

<i>Table 99. Patch Name to CSECT Reference (continued)</i>		
CSECT Referenced	AMASPZAP Patch Name	JES2 Patch Name
HASPDYN	HASPDYN	DYN
HASPEVTL	HASPEVTL	EVTL
HASPFSSM	HASPFSSM*	--
HASPFSSP	HASPFSSP	FSSP
HASP Common Communication Table	-	HCCT
HASPHOPE	HASPHOPE	HOPE
HASPIRA	HASPIRA	IRA
HASPIRDA	HASPIRDA	IRDA
HASPIRMA	HASPIRMA	IRMA
HASPIRPL	HASPIRPL	IRPL
HASPIRRE	HASPIRRE	IRRE
HASPIRSI	HASPIRSI	IRSI
HASPJOS	HASPJOS	JOS
HASPJQS	HASPJQS	JQS
HASPMISC	HASPMISC	MISC
HASPMMSG	HASPMMSG	MSG
HASPNATS	HASPNATS	NATS
HASPNET	HASPNET	NET
HASPNJT	HASPNJT	NJT
HASPNPM	HASPNPM	NPM
HASPNRM	HASPNRM	NRM
HASPNSR	HASPNSR	NSR
HASPNST	HASPNST	NST
HASPNUC	HASPNUC	NUC
HASPODSM	HASPODSM	ODSM
HASPPRPU	HASPPRPU	PRPU
HASPPSO	HASPPSO	PSO
HASPRAS	HASPRAS	RAS
HASPRDR	HASPRDR	RDR
HASPRTAM	HASPRTAM	RTAM
HASPSASR	HASPSASR	SASR
HASPSERV	HASPSERV	SERV
HASPSIR	HASPSIR	SIR
HASPSJFR	HASPSJFR	SJFR

Table 99. Patch Name to CSECT Reference (continued)

CSECT Referenced	AMASPZAP Patch Name	JES2 Patch Name
HASPSNA	HASPSNA	SNA
HASPSPIN	HASPSPIN	SPIN
HASPSPOL	HASPSPOL	SPOL
HASPTCP	HASPTCP	TCP
HASPSSRV	HASPSSRV	SSRV
HASPSTAB	HASPSTAB	STAB
HASPSTAC	HASPSTAC	STAC
HASPSTAM	HASPSTAM	STAM
HASPSUBS	HASPSUBS	SUBS
HASPSXDV	HASPSXDV	SXDV
HASPSXIT	HASPSXIT	SXIT
HASPSXJB	HASPSXJB	SXJB
HASPSXNJ	HASPSXNJ	SXNJ
HASPSXOT	HASPSXOT	SXOT
HASPTABS	HASPTABS	TABS
HASPTERM	HASPTERM	TERM
HASPTRAK	HASPTRAK	TRAK
HASPWARM	HASPWARM	WARM
HASPXCF	HASPXCF	XCF
HASPXEQ	HASPXEQ	XEQ
HASPXJ00-HASPXJ31	HASPXJ00-HASPXJ31	XJ00-XJ31**
xxxxxxxx***	xxxxxxxx	xxxxxxxx
* This module cannot be modified by using JES REP (replace) facilities. ** Reserved names for installation exit modules. *** Any load module previously specified in a LOADMOD control statement.		

address|*

Specifies the 1- to 8-digit hexadecimal address of the data to be verified. This address does not have to be aligned in any way. The address should be taken directly from a JES2 assembler listing that contains the referenced CSECT.

If an asterisk (*) is coded, the address will be interpreted as one greater than the last address reference on the previous JES2 patch statement.

data

Specifies the bytes of data to be verified at the specified location. Specify this number as a multiple of 2 hexadecimal digits. The data within the parameter may be separated by commas, never blanks. If all the data will not fit into one patch statement (71 bytes), use another patch statement.

If the data specifies a location within a JES2 CSECT, as specified at assembly time, the JES2 patch processing routine will relocate this data by the base location of the CSECT if indicated. Specify this relocation by following the data to be relocated with the name of the CSECT (abbreviated as in “csect” above) enclosed in parentheses. The address specified in the data field should be taken directly from a JES2 assembly listing containing the referenced CSECT. You can specify a minimum of 6 hexadecimal digits (3 bytes), and a maximum of 8 digits (4 bytes) for relocation.

comments

Following the last required parameter and its blank delimiter, the rest of the control statement space can be used for comments.

Examples of JES2 patching facility statements are shown in [Figure 4 on page 438](#) and [Figure 5 on page 439](#).

```

/*****
/*
/*          CORRECT PROGRAMMING ERROR IN HASPRDR          */
/*
/*****
VER RDR      1E2      41E00001          /* VERIFY INSTRUCTION */
REP *        1E2      4590B258          /* BAL TO PATCH SPACE */
VER NUC      258      B258,B25A,B25C,B25E,B260 /* VERIFY PATCH SPACE */
REP *        258      41202000          /* ADD INSTRUCTION */
REP *        *        41E00001          /* REPLACE INSTRUCTION*/
REP *        *        07F9             /* RETURN */
/*****
/*
/*          CORRECT BAD ADDRESS CONSTANT IN HASPPRPU      */
/*
/*****
VER PRPU     32E      58F0C65C          /* VERIFY INSTRUCTION */
REP *        330      B264             /* MODIFY DISPLACEMENT*/
VER NUC      264      B264,B266          /* VERIFY PATCH SPACE */
REP *        264      00000520(PRPU)    /* ADDRESS CONSTANT */
/*****
/*
/*          MODIFY BLOCK CHARACTER TABLE TO SLASH        */
/*          THE LETTER Z (POSITION 26) AND THE NUMBER ZERO */
/*          (POSITION 27) ON OUTPUT SEPARATORS.           */
/*          --A TABLE ENTRY IS 24 BYTES LONG--           */
/*
/*****

```

Figure 4. Examples of JES2 Patching Format

```

/*****/
/*
/*          CORRECT PROGRAMMING ERROR IN HASPRDR          */
/*
/*****/
NAME HASPRDR HASPRDR          /* IDENTIFY SECTION */
VER 1E2 41E00001          /* VERIFY INSTRUCTION */
REP 1E2 4590B258          /* BAL TO PATCH SPACE */
NAME HASPNUC HASPNUC          /* IDENTIFY SECTION */
VER 258 B258,B25A,B25C,B25E,B260 /* VERIFY PATCH SPACE */
REP 258 41202000          /* ADD INSTRUCTION */
REP * 41E00001          /* REPLACE INSTRUCTION*/
REP * 07F9          /* RETURN */
/*****/
/*
/*          CORRECT BAD ADDRESS CONSTANT IN HASPPRPU          */
/*
/*****/
NAME HASPPRPU HASPPRPU          /* IDENTIFY SECTION */
VER 32E 58F0C65C          /* VERIFY INSTRUCTION */
REP 330 B264          /* MODIFY DISPLACEMENT*/
NAME HASPNUC HASPNUC          /* IDENTIFY SECTION */
VER 264 B264,B266          /* VERIFY PATCH SPACE */
REP 264 00000520(PRPU)          /* ADDRESS CONSTANT */
/*****/
/*
/*          MODIFY BLOCK CHARACTER TABLE TO SLASH          */
/*          THE LETTER Z (POSITION 26) AND THE NUMBER ZERO   */
/*          (POSITION 27) ON OUTPUT SEPARATORS.              */
/*          --A TABLE ENTRY IS 24 BYTES LONG--              */
/*
/*****/

```

Figure 5. Examples of JES2 AMASPZAP Format

ZAPJOB




Attention: If improperly used, the ZAPJOB initialization statement can cause JES2 ABENDs including ABENDs on multiple systems. Be certain to review the entire ZAPJOB documentation before using this initialization statement.

Use ZAPJOB to remove all traces of a job structure from the JES2 job queue. It is intended to be used in situations where a job cannot be removed using normal JES2 commands or by a JES2 restart. **Ensure that the job and any output it might have created is not active in any JES2 process or active on a device.** Zapping a job that is active can lead to ABENDs and the loss of a PCE until JES2 is restarted. ZAPJOB will not correct queue errors. If the JOB or output queue has an error, a JES2 restart is required to rebuild the job queue.

When specifying a job to zap, IBM suggests specifying as many operands as are known for that job. This reduces the possibility of accidentally zapping the wrong job because of a typing error.

- A \$ZAPJOB command can be placed in the initialization data set. This is not the same as using the ZAPJOB initialization statement. A \$ZAPJOB command in the initialization data set is processed after JES2 initialization has completed. A ZAPJOB initialization statement removes the job before verifying the job queue. Because of the risk of forgetting to remove it, IBM suggests that you do not place \$ZAPJOB commands in the initialization data set.
- The ZAPJOB initialization statement can only be entered from CONSOLE mode. This prevents you from forgetting a ZAPJOB statement that you placed into the initialization data, thereby impacting jobs on future JES2 starts. See the JES2 Initialization and Tuning Guide for information on how to enter CONSOLE mode during initialization.
- On ZAPJOB, you must specify one of: JOBID=, JOBKEY=, JQEINDEX=, or JQEOFF=.
- If a job has a job key of zero (job has not had a job key assigned or has partially purged) you must specify JOBKEY=0, JQEINDEX= or JQEOFF= to "zap" the job.

Format Description for ZAPJOB



Notes:

¹ Omit the comma between initialization statement and first keyword

Parameter Description for ZAPJOB

JOBNAME=cccccccc

The name of the job to be zapped. JOBNAME is an optional keyword; however, JOBNAME= cannot be specified by itself. You must also specify one of JOBID=, JOBKEY=, JOEINDEX=, or JOEOFF=.

JOBID=jjjnnnnn/j0nnnnnn

The JES2 JOBID of the job to be zapped. You can specify any of the valid formats for a JES2 JOBID such as J12345, JOB12345, S12345, STC12345, T12345, TSU12345.

JOBKEY=xxxxxxx

The hexadecimal job key that is associated with the job. You can normally obtain the JOBKEY= value from a dump. If you specify JOBKEY=0, then you must also specify JOBID=, JOEINDEX=, or JOEOFF=.

JQEINDEX=xxxx

The index (in hexadecimal) of the JQE to be zapped. You can normally obtain the JQEINDEX= value from a dump.

JQE0FF=xxxxxx

The offset (in hexadecimal) of the JQE to be zapped. You can normally obtain the JQEOFF= value from a dump.

Appendix A. Sample JES2 initialization data set

The following initialization data set is available in SYS1.SHASSAMP so that you do not have to code the entire data set. However, it is only an example.

Note: To enhance readability, the code and comments have been separated. The JES2 initialization data set does not have column restrictions or dependencies.

```

/*****PROPRIETARY-STATEMENT*****/ 00000800
/*                                */ 00001600
/*      LICENSED MATERIALS-PROPERTY OF IBM      */ 00002400
/*      5694-A01 (C) COPYRIGHT IBM CORP 1994, 2005 */ 00004000
/*                                */ 00005600
/*      STATUS:  HJE7720                      */ 00006400
/*                                */ 00007200
/*01* EXTERNAL CLASSIFICATION:  NONE           */ 00007400
/*01* END OF EXTERNAL CLASSIFICATION:          */ 00007600
/*                                */ 00007800
/*****END-OF-PROPRIETARY-STATEMENT*****/ 00008000
/*                                */ 00008800
/*****/ 00010000
/*                                */ 00020000
/*      HASIPARM - sample template for coding initialization */ 00022000
/*      statements for the JES2 component of MVS.          */ 00024000
/*                                */ 00026000
/*      HASIPARM contains sample templates for the JES2    */ 00028000
/*      initialization parameter statements.  It is part of the set */ 00030000
/*      of HASIxxxx example files which should be tailored, */ 00032000
/*      renamed, and placed in production libraries as part of the */ 00034000
/*      installation of the JES2 component of MVS.          */ 00036000
/*                                */ 00040000
/*      Refer to the JES2 Initialization and Tuning Guide and */ 00050000
/*      Reference publications for complete descriptions of each */ 00060000
/*      statement and its parameters, and other information about */ 00070000
/*      JES2 initialization.                                */ 00080000
/*                                */ 00100000
/*      WARNING: This data set will NOT "run" as it is presented */ 00101000
/*      here.  Minimally, you MUST remove all the @@ and @@    */ 00102000
/*      symbols.  The @@s are used to flag parameters for which */ 00103000
/*      there either is no JES2 default or that default is based on */ 00104000
/*      other parameter specifications.  The @@s are used to flag */ 00105000
/*      those parameters whose default values you should carefully */ 00106000
/*      study to avoid blindly using them without consideration */ 00107000
/*      of your specific requirements.  For those with terminals */ 00108000
/*      without the cent sign (? and at sign (@), they are      */ 00108500
/*      hex '4A' and '7C', respectively.                      */ 00109000
/*      Note also that some statements below violate the      */ 00110000
/*      continuation rules to provide additional comments where */ 00120000
/*      they would not normally be valid.                    */ 00130000
/*                                */ 00139000
/*****/ 00148000
/*                                */ 00157000
/* * Init Deck Management Considerations                */ 00166000
/* -----                                              */ 00175000
/*                                */ 00175200
/* * Placement + PDS Member Partitions                  */ 00175400
/* -----                                              */ 00175600
/*                                */ 00175800
/* * In order for the JES2 component to be started, a subsystem */ 00176000
/* * cataloged JCL procedure (PROC) is required.  The JCL procedure */ 00176200
/* * used for JES2 should point to a file (or files) containing JES2 */ 00176400
/* * initialization parameters, such as the HASIPARM file.      */ 00176600
/*                                */ 00176800
/* * Historically, IBM has distributed JES2 initialization    */ 00177000
/* * parameters in the SYS1.PARMLIB dataset.  The sample JES2  */ 00177200
/* * cataloged JCL procedure, HASIPROC, still specifies the    */ 00177400
/* * JES2PARM member of SYS1.PARMLIB in its HASPPARM DD.  The  */ 00177600
/* * choice of SYS1.PARMLIB or some other dataset should be    */ 00177800
/* * made based on the local installation's multi-system dataset */ 00178000
/* * sharing requirements, system programmer management      */ 00178200
/* * procedures, performance (e.g. using a dataset that has a  */ 00178400
/* * large block size), etc.                                */ 00178600
/*                                */ 00178800
/* * By default, JES2 uses the HASPPARM DD within its PROC to  */ 00179000
/* * read initialization parameters.                      */ 00179200
```

```

/*
/* To simplify the management of initialization statements, IBM
/* recommends that most of the members be shared across all
/* members in the JESplex.
/*
/* The DD that points to the JES2 initialization parameters
/* can point to a concatenation of files. An installation
/* may wish to use the HASIPARM sample information, and then
/* place their final initialization parameters in multiple
/* files. This may allow the sharing of a large percentage
/* of the parameters between multiple JES2 subsystems in the
/* installation's complex, facilitate management of the
/* parameters by different groups of programmers, and lessen
/* the number of files that need to be updated for a new
/* release of JES2.
/*
/* The JES2 parameters must be read from a dataset(s) that has
/* a fixed record format (RECFM), such as RECFM=FB, and that
/* has 80 character records (LRECL=80). The dataset(s) can be
/* blocked with a BLKSIZE that is a multiple of 80.
/*
/* The following example of partitioning the JES2 initialization
/* statements may be useful in managing the parameters and
/* maintaining the order dependencies listed below.
/*
/*   - xxxDEF - Global Definitions (alphabetically or functional)
/*   - NODE, APPL, CONNECT, NJE LINES
/*   - DESTID
/*   - Local Devices (RDR, PRT, PUN)
/*   - RMT & RJE LINES
/*   - RJE, NJE Passwords (protect in a separate data set)
/*   - Parameters unique to each system
/*
/* Here is a sample JES2 start-up procedure that uses symbolic
/* parameters so any of the members can be changed through an
/* operator provided override. (This is probably an extreme
/* example of breaking up the parameters, and there is nothing
/* wrong with keeping all the statements in a single member.)
/*
/* //JES2 PROC MDEF=J2DEF,MNOD=J2NJE,MDST=J2DEST,
/* //
/* // MLOC=J2LOCL,MRJE=J2RJE,PASS=J2PASS,
/* // SYSN= <== Don't Default this member
/* // -- Specify on S JES2,SYSN=x command
/* //IEFPROC EXEC PGM=HASJES20,...
/* //HASPPARM DD DSN=SYS1.PARMLIB(&MDEF),DISP=SHR Global Definitions
/* // DD DSN=SYS1.PARMLIB(&MNJE),DISP=SHR NJE
/* // DD DSN=SYS1.PARMLIB(&MDST),DISP=SHR Symbolic Dests
/* // DD DSN=SYS1.PARMLIB(&MLOC),DISP=SHR Local Devices
/* // DD DSN=SYS1.PARMLIB(&MRJE),DISP=SHR RJE
/* // DD DSN=SYS1.PARMLIB(&PASS),DISP=SHR In a protected lib
/* // DD DSN=SYS1.PARMLIB(J2SYS&SYSN.),DISP=SHR Unique
/* // etc.
/*
/* Common Parameters for all JESplex Members
/* -----
/*
/* The following statements should have identical parameter
/* settings across all members in the JESplex:
/*   - xxxDEF (global parameters) except where noted below
/*   - JOBCLASS, OUTCLASS, etc.
/*   - NODE, DESTID, CONNECT, RMT, LINE
/*   - Local Devices (RDRs, PRTs, PUNs), OFFLOAD
/*
/* Consider letting the MASDEF OWNMEMB parameter default to
/* the SMFPRMxx SID value.
/*
/* The following parameters will probably be set differently on
/* each system:
/*   - INIT(nnn) classes tailored for each system
/*   - AUTOESYS RESTART=YES|NO
/*   - Local Device & Line definitions unique to each system
/*   - START parameter can only be YES on one system for
/*     local devices & lines shared by all
/*   - MASDEF HOLD= and DORMANCY= values
/*   - LOGON(n) should specify a unique APPLID for JES2 on each
/*     member
/*   - CONDEF CONCHAR must be different if you are using
/*     SCOPE=SYSPLEX (but needs to be the same if you want
/*     to exploit the MVS ROUTE *ALL command for JES2 commands).
/*   - PCEDEF Number of PCEs should vary with JES workload
/*
/* Order Dependencies

```

```

*/ 00179400
*/ 00179600
*/ 00179800
*/ 00180000
*/ 00180200
*/ 00180400
*/ 00180600
*/ 00180800
*/ 00181000
*/ 00181200
*/ 00181400
*/ 00181600
*/ 00181800
*/ 00182000
*/ 00182200
*/ 00182400
*/ 00182600
*/ 00182800
*/ 00183000
*/ 00183200
*/ 00183400
*/ 00183600
*/ 00183800
*/ 00184000
*/ 00184200
*/ 00184400
*/ 00184600
*/ 00184800
*/ 00185000
*/ 00185200
*/ 00185400
*/ 00185600
*/ 00185800
*/ 00186000
*/ 00186200
*/ 00186400
*/ 00186600
*/ 00186800
*/ 00187000
*/ 00187200
*/ 00187400
*/ 00187600
*/ 00187800
*/ 00188000
*/ 00188200
*/ 00188400
*/ 00188600
*/ 00188800
*/ 00189000
*/ 00189200
*/ 00189400
*/ 00189600
*/ 00189800
*/ 00190000
*/ 00190200
*/ 00190400
*/ 00190600
*/ 00190800
*/ 00191000
*/ 00191200
*/ 00191400
*/ 00191600
*/ 00191800
*/ 00192000
*/ 00192200
*/ 00192400
*/ 00192600
*/ 00192800
*/ 00193000
*/ 00193200
*/ 00193400
*/ 00193600
*/ 00193800
*/ 00194000
*/ 00194200
*/ 00194400
*/ 00194600
*/ 00194800
*/ 00195000
*/ 00195200
*/ 00196200
*/ 00196400

```



```

/* ----- */
/*
/* There are a few cases where the order of JES2 initialization
/* statements is significant.
/* The cases where order does make a difference are:
/*
/*   - EXIT(19) statement must be before any statements
/*     that are to be scanned by the exit routine.
/*   - DESTDEF must come before DESTID statements, or
/*     destination names whose meaning might be changed
/*     by the DESTDEF statement.
/*   - NODE names before references to the node name in
/*     the following statements:
/*     - CONNECT
/*     - APPL
/*     - DESTID
/*     - Device Route Codes
/*   - DESTID names before references by Device Route Codes
/*
/* Here is a suggested order for JES2 initialization statements:
/*   - xxxDEF - global system definitions for MAS, Ckpt, Spool,
/*     Buffers, Job, Output, queues, Exits, etc.
/*   - NJE NODE, APPL, CONNECT
/*   - DESTID
/*   - Devices - Local, LINEs, Remotes, Spool Off.
/*
/* Ranges
/* -----
/*
/* Use Ranges in Subscripts of JES2 initialization statements
/* to manage in groups. For example:
/*
/* INIT(11-21) CLASS=X, START=YES
/* JOBCCLASS(*) COMMAND=IGNORE, LOG=YES
/* SSI(*) TRACE=NO
/*
/* Caution
/* -----
/*
/* Don't use an asterisk subscript (*, or n-*) on device
/* statements because of excessive overhead during JES2
/* initialization. For example, NODE(*) means NODE(1-32767)
/* and will significantly elongate JES2 initialization time.
/*
/* Keeping up with Dynamic Changes
/* -----
/*
/* If any changes to initialization parameter settings with the $T,
/* $ADD or $DEL commands, you must also make these changes to your
/* initialization decks or they will be lost when JES2 restarts.
/* For additional information on the effect of a hot start, refer
/* to The Init and Tuning Guide and The Init and Tuning Reference.
/*
/* The MVS ROUTE *ALL command can be used to change or add
/* symmetrically to the JESplex via $T and $ADD commands
/* (if the command characters are identical).
/*
/* *****
/*
/* SYNTAX RULES for JES2 Initialization Statements:
/*
/*   - Statements may be coded free-form in Columns 1 through 71
/*   - Column 72 may be used for a Continuation Character, but is
/*     NOT Required. A trailing comma indicates continuation.
/*   - Blanks are used to separate statement object from operands.
/*     Blanks are not allowed within the statement object.
/*   - Comments are NOT allowed within a range.
/*   - Comments must be bounded by the slash-asterisk,
/*     asterisk-slash type delimiters.
/*   - Statements must have at least one parameter coded on the
/*     same line as the statement name.
/*
/* *****
/*
/* NOTES on the Format of this Member:
/*
/*   - The Order of Statements is Alphabetical within the following
/*     categories:
/*   - ALL Initialization Statements, showing new statements,
/*     new and changed operands, etc.
/*   - An abbreviated list of statements and operands ADDED
/*     in the JES2 SP 4.1.0 and later releases

```

```

*/ 00196600
*/ 00196800
*/ 00197000
*/ 00197200
*/ 00197400
*/ 00197600
*/ 00197800
*/ 00198000
*/ 00198200
*/ 00200400
*/ 00200500
*/ 00200600
*/ 00200700
*/ 00200800
*/ 00200900
*/ 00201000
*/ 00201100
*/ 00201200
*/ 00201300
*/ 00201400
*/ 00201500
*/ 00201600
*/ 00201700
*/ 00201800
*/ 00201900
*/ 00202000
*/ 00204000
*/ 00206000
*/ 00206200
*/ 00206400
*/ 00206600
*/ 00206800
*/ 00207000
*/ 00207200
*/ 00207400
*/ 00207600
*/ 00207800
*/ 00208000
*/ 00208200
*/ 00208400
*/ 00208600
*/ 00208800
*/ 00209000
*/ 00209200
*/ 00209400
*/ 00209600
*/ 00209800
*/ 00210000
*/ 00210200
*/ 00210400
*/ 00210600
*/ 00210800
*/ 00211000
*/ 00211200
*/ 00211400
*/ 00211600
*/ 00211800
*/ 00212000
*/ 00212200
*/ 00212400
*/ 00212600
*/ 00212800
*/ 00213000
*/ 00213200
*/ 00213400
*/ 00213600
*/ 00213800
*/ 00214000
*/ 00214200
*/ 00214400
*/ 00214600
*/ 00214800
*/ 00215000
*/ 00215200
*/ 00215400
*/ 00215600
*/ 00215800
*/ 00216000
*/ 00216200
*/ 00216400
*/ 00216600
*/ 00216800

```

```

/*      - An abbreviated list of statements and operands CHANGED      */ 00217000
/*      in the JES2 SP 4.1.0 and later releases                      */ 00217200
/*      - An abbreviated list of statements and operands DELETED     */ 00217400
/*      in SP 2.2.0 JES2 or later releases.                          */ 00217600
/*      - An abbreviated list of statement operands which cannot     */ 00217800
/*      be changed without a COLD start.                             */ 00218000
/*                                                                    */ 00218200
/* COLUMN layouts of the following statements are as follows:         */ 00218400
/*                                                                    */ 00218600
STMT      PARAMETER=DEFAULT,      COMMENTS      CHG-CODE*/ 00218800
/*                                                                    */ 00219000
/*      1- 8 - Statement Name                                         */ 00219200
/*      10-29 - Parameters set to default values                     */ 00219400
/*              ¢¢ - Indicates there is no default, or the default is */ 00219600
/*                  based on other parameters.                       */ 00219800
/*              @@ - Indicates the default should not be taken blindly.*/ 00220000
/*      30-60 - Comments                                              */ 00220200
/*      62-69 - How the Parameter can be changed. One or more of the */ 00220400
/*              following flags will appear in the change code list.  */ 00220600
/*              They are listed in order of flexibility and power, but */ 00220800
/*              these capabilities are not hierarchical. For example,  */ 00221000
/*              some parameters can be changed only by cold starts     */ 00221200
/*              and commands.                                          */ 00221400
/*                                                                    */ 00221600
/*              a - can be added by $ADD                              */ 00221800
/*              o - can be altered by operand $T                      */ 00222000
/*              r - can be removed by $DEL                            */ 00222200
/*              h - can be altered/added by a hot start               */ 00222400
/*                  (if no H, the parm is ignored during hot start)   */ 00222600
/*              w - can be altered/added by JES2 Warm or Quick Start */ 00222800
/*              n - can be altered/added by a JES2                    */ 00223000
/*                  All Member Warm Start                             */ 00223200
/*              c - can be altered/added by JES2 Cold Start           */ 00223400
/*                                                                    */ 00223600
/******                                                                    */ 00223800
/*                                                                    */ 00224000
/**01* Change Activity:                                              */ 00224200
/*                                                                    */ 00225000
/* $430P429=10X      HJE4430 920811 HGF:  JES2 to SAMPLIB(HASIPROC) */ 00225900
/*                                                                    */ 00226200
/* $510P307=PL10307  HJE5510 931020 :    Init Deck Sample Updates  */ 00226500
/*                                                                    */ 00226700
/* $520LJQV=          HJE5520 940115 JPK:  JES2 TO SAMPLIB(HASIPARM) */ 00226900
/* $520D001=MODRJE    HJE5520 940415 T_K1: Modifiable RJE           */ 00227100
/* $520P112=SNIFFER   HJE5520 941006 GMD:  Spool reclaim changes     */ 00227300
/*                                                                    */ 00227400
/* $R01P003=PTM       HJE6601 950914 VLC:  PTM 3 (External Classifi */ 00227500
/*                                                                    */ 00227600
/* $R04LCMD=WLM       HJE6604 960913 CLW:  Job Commands              */ 00227900
/* $R04LWLM=WLM       HJE6604 970313 CLW:  Sampling anomalies        */ 00228200
/* $R04P144=WLM       HJE6604 970619 CLW:  Misc. errors.            */ 00228300
/* $ES1LBSZ=PTMS      HJE6608 990325 E_S7: Increase SNA Buffer Size  */ 00228400
/*                                                                    */ 00268400
/* $ES1LBSZ=PERF      HJE7703 990427 E_S7: Increase SNA Buffer Size  */ 00308400
/* $JS2LSPA=PERF      HJE7703 990817 JMS:  Spool allocation          */ 00348400
/* $CLWP038=BASEQ     HJE7703 000131 CLW:                               */ 00388400
/* $CLWP038=BASEQ     HJE7703 000201 CLW:  Dynamic BLOB resizing    */ 00428400
/* $ES7P037=PAGS      HJE7703 000208 E_S7: Set Tracedef pages=9     */ 00468400
/* $ES7P037=PAGS      HJE7703 000208 E_S7: Set Tracedef pages=9     */ 00508400
/* $JK0LLRJ=LRJOB     HJE7705 000608 J_K2: Long Running Job Support */ 00510000
/* $JK1LLRJ=LRJOB     HJE7705 000829 J_K2: Long Running Job Support */ 00520000
/* $JK0LLRJ=LRJOB     HJE7705 000919 J_K2: Long Running Job Support */ 00522000
/* $JK1LLRJ=LRJOB     HJE7705 000919 J_K2: Long Running Job Support */ 00531000
/* $TW4P118=MONITOR   HJE7707 020411 TJW:  Increase RDINUM default  */ 00540000
/* $CW9LMLM=NJETCP    HJE7720 030212 CLW:  Line manager recovery    */ 00544000
/* $CW9LMLM=NJETCP    HJE7720 030328 CLW:  Line manager recovery    */ 00546000
/* $NW1LBLD=BASEQ     HJE7720 040315 NAW:  Fix PROCLIB continuation */ 00547000
/* $NW1LBLD=BASEQ     HJE7720 040322 NAW:  Fix PROCLIB continuation */ 00547400
/* $OA07604=APAR      HJE7720 040524 S_F:  was closed as sug       */ 00547500
/* $CWXLTCP=NJETCP    HJE7720 041117 CLW:  Sample/test exits       */ 00547600
/* $CWXLTCP=NJETCP    HJE7720 050131 CLW:  Sample exits            */ 00548000
/*                                                                    */ 00548400
/* A000000-999999     Created for JES2 4.3.0                        */ 00588400
/******                                                                    */ 00628400
/*                                                                    */ 00668400
/*                                                                    */ 00800000
/*                                                                    */ 00810000
/******                                                                    */ 00820000
/*                                                                    */ 00830000
/*                                                                    */ 00840000
/*              *-----*                                           */ 00840000
/*              | ALL Initialization Parameters |                     */ 00850000
/*              *-----*                                           */ 00860000

```

```

/*
/* Note: Not ALL Parameters are shown, especially for devices.
/*
/*
/*****
/*
/*-----*
/*      SNA/NJE Applications
/*      VTAM Application ID          aohwnc|
/*-----*
/*
APPL(#####) COMPACT=, /* APPL - VTAM Application ID          aohwnc*/
/*      (pre-SP311 APPL APPLID=)      /*
/* COMPACT - Compaction Table Num      ohwnc*/
/*      LINE=##### /* Line dedicated to the SNA NJE      ohwnc*/
/*      session (added SP410)          /*
/* LOGON=1, /* LOGON DCT to be used by this      ohwnc*/
/*      session (added OS240)          /*
/* LOGMODE=, /* Logon mode table entry name      ohwnc*/
/*      (added SP410)                  /*
/* NODE=####, /* NJE Node Number          ohwnc*/
/* REST=####, /* Session Resistance          ohwnc*/
/*
/*
/*****
/*
/*-----*
/*      Addresses of Bad Spool Tracks
/*      Note: Statement is not displayable
/*-----*
BADTRACK VOL=####, /* Full Spool Volume Serial Number hwnnc*/
/* ADDR=(#####-#####) /* Starting cyl/head of Bad Track hwnnc*/
/*      - Ending cyl/head of Bad Track hwnnc*/
/*
/*
/*****
/*
/*-----*
/*      LOCAL BUFFERS
/*-----*
BUFDEF BELOWBUF= /* Characteristics for buffers below /*
/*      16 meg line (added SP410)      /*
/* (LIMIT=####, /* Number of Buffers          ohwnc*/
/*      (pre-SP410=BUFNUM=)           /*
/* WARN=80), /* Warning Threshold %          ohwnc*/
/*      (pre-SP410=BUFWARN)           /*
/* EXTBUF= /* Characteristics for extended buffers /*
/*      (added SP410)                  /*
/* (LIMIT=####, /* Number of Buffers          ohwnc*/
/*      (pre-SP410=BUFNUM=)           /*
/* WARN=80) /* Warning Threshold %          ohwnc*/
/*      (pre-SP410=BUFWARN)           /*
/*
/*
/*****
/*
/*-----*
/*      CHECKPOINT PARAMETERS
/*      This example assumes CKPT1 is
/*      on DASD and CKPT2 is on a
/*      Coupling Facility.
/*      CKPT1 and CKPT2 can be on either.
/*-----*
CKPTDEF CKPT1=(DSNAME=####, /* 1-44 char. dsn for 1st CKPT ds onnc*/
/* VOLSER=####, /* 1st CKPT volume onnc*/
/* INUSE=NO), @@/* initial status of CKPT1 onnc*/
/*      NOTE: Refer to the Commands Manual /*
/*      for additional information /*
/* CKPT2=(STRNAME=####, /* 1-16 char. structure name for onnc*/
/*      2nd CKPT data set. /*
/*      (STRNAME added in SP510) /*
/* INUSE=NO), @@/* initial status of CKPT2 onnc*/
/* CKPTOPT=HIGHEST, /* Which ckpt to use on JES2 restart onnc*/
/*      (added SP430) /*
/* DUPLEX=ON, /* MODE=DUPLEX - whether to use ohwnc*/
/*      CKPT2 as the duplex data set /*
/*      MODE=DUAL - ignored /*
/* LOGSIZE=, /* Number of 4k pages for change log nc*/
/* MODE=DUPLEX, /* method of CKPT operation onnc*/
/* NEWCKPT1=(DSNAME=####, /*
/*      1-44 char. CKPT1 replacement ownnc*/
/* VOLSER=####), /* Replacement volume for CKPT1 ownnc*/

```

```

NEWCKPT2=(STR=####),/* 1-16 char. structure name for */ 01560000
/* CKPT2 replacement own*/ 01570000
/* (added in SP510) */ 01575000
OPVERIFY=YES, /* Prompt oper. to confirm action own*/ 01580000
/* to be taken for an I/O error on CKPT */ 01590000
/* (added in SP510) */ 01600000
RECONFIG=NO, /* Use the most recently used own*/ 01610000
/* checkpoint datasets */ 01620000
VERSIONS=(NUMBER=0, /* Number of checkpoint versions ohwnc*/ 01752000
/* JES2 will maintain-0 indicates */ 01754300
/* JES2 will determine the maximum */ 01754400
/* number of versions to maintain. */ 01754600
/* (added SP410) */ 01754800
WARN=80), /* Threshold percentage at which ohwnc*/ 01755700
/* operator is to be notified. */ 01756400
/* (added SP410) */ 01757100
VOLATILE=(ONECKPT=WTOR, 01757800
/* Specifies JES2 should issue WTOR to */ 01758500
/* determine action if one CKPT is on a */ 01759200
/* volatile coupling facility */ 01759900
/* (added in SP510) ohwnc*/ 01760600
ALLCKPT=WTOR) 01763600
/* Specifies JES2 should issue WTOR to */ 01767000
/* determine action if all CKPTs are on */ 01790000
/* volatile coupling facilities */ 01800000
/* (added in SP510) ohwnc*/ 01810000
/* */ 01812000
/***** */ 01818000
/* ----- */ 01824000
| Checkpoint Space Definitions | 01830000
*-----* 01836000
01842000
CKPTSPACE BERTNUM=#####, @@ /* Number of BERTs oc*/ 01848000
/* (added in OS/390 R4) */ 01854000
BERTWARN=80, /* $HASP050 threshold for BERTs ohwnc*/ 01860000
/* (added in OS/390 R4) */ 01866000
/* */ 01880000
/***** */ 01890000
/* ----- */ 01900000
| Compaction Table Definitions | 01910000
*-----* 01920000
01930000
COMPACT NAME=##### /* Name of Compaction Table hwnc*/ 01940000
NUMBER=#### /* Compaction Table Number hwnc*/ 01950000
/* Table Definition */ 01960000
CHARS=(####, /* - Number of Master Characters hwnc*/ 01970000
?????..,/* - Master Characters hwnc*/ 01980000
?????..)/* - Non-Master Characters hwnc*/ 01990000
/* */ 02000000
/* */ 02010000
/***** */ 02020000
/* ----- */ 02030000
| CONSOLE PARAMETERS | 02040000
*-----* 02050000
02060000
CONDEF AUTOCMD=20, /* Number of Auto Cmds hwnc*/ 02070000
BUFNUM=100, @@ /* Number of CMBs ohwnc*/ 02110000
BUFWARN=80, /* Warning Threshold % ohwnc*/ 02130000
CMDNUM=100, /* Maximum number of CMBs for JES2 */ 02140000
/* commands from common storage own*/ 02150000
/* (added in SP510) */ 02160000
CONCHAR=$, /* Console Cmd Character own*/ 02170000
DISPLEN=64, /* $SCAN Cmd/init Display Length ohwnc*/ 02182000
DISPMAX=100, /* $SCAN Cmd/init Max Lines ohwnc*/ 02186000
MASMSG=200, /* Number of Queued Msgs ohwnc*/ 02190000
RDIRAREA=Z, /* Default console out-of-line ohwnc*/ 02210000
/* area (added SP410) */ 02220000
RDRCHAR=$, /* Reader Cmd Character ohwnc*/ 02230000
SCOPE=SYSTEM /* Specifies scope of command wnc*/ 02241000
/* prefix (added SP410) */ 02244000
/* */ 02250000
/* */ 02260000
/***** */ 02270000
/* ----- */ 02280000
| Static NJE Connections | 02290000
*-----* 02300000
02310000
CONNECT NODEA=####, /* Overall Statement - oarhwnc*/ 02320000
/* Node number or node name hwnc*/ 02322000
/* on 'A' end */ 02325000
MEMBERA=1, /* Member number on 'A' end hwnc*/ 02330000
/* (pre-SP311=MEMBA, required) */ 02331000

```

```

/*      (SP311 - defaults to 1)      */ 02334000
NODEB=####, /* Node number or node name      hwncl*/ 02340000
/*      on 'B' end                      */ 02345000
MEMBERB=1, /* Member number on 'B' end      hwncl*/ 02350000
/*      (pre-SP311=MEMBB, required)    */ 02352000
/*      (SP311 - defaults to 1)      */ 02355000
PATHMGR=?? /* Support path manager protocols      o*/ 02356000
/*      (added SP410)                  */ 02357000
REST=0 /* Resistance of connection      ohwnc*/ 02360000
/* NOTE: the values for REST= CANNOT */ 02370000
/* be 0 (as shown here).              */ 02380000
/* If the parameter is not            */ 02390000
/* coded at all, then the default     */ 02400000
/* will be 0. The parameter is        */ 02410000
/* shown this way only to include     */ 02420000
/* the default value here.            */ 02430000
/*                                     */ 02440000
/*                                     */ 02450000
/*****                                     */ 02460000
/*                                     */ 02470000
/*                                     */ 02480000
/*      |      DEBUG PARAMETERS      | 02480000
/*      |      (revised by OW05639)  | 02481000
/*      |      Do not use unless necessary | 02484000
/*      |      |                      | 02490000
/*      |      |                      | 02500000
/*      |      |                      | 02501000
DEBUG  BERT=YES, /* ABEND if BERT error detected      ohwnc*/ 02501000
/*      CKPT=NO, /* Verify integrity of checkpoint    ohwnc*/ 02502000
/*      MISC=NO, /* Count certain JES2 events      ohwnc*/ 02503000
/*      SECURITY=NO, /* Issue WTO for security failures ohwnc*/ 02503500
/*      STORAGE=NO, /* Verify GETWORKed areas          ohwnc*/ 02504000
/*      SYMREC=NO, /* Issue $WTO with SYMREC          ohwnc*/ 02505000
/*      VERSION=NO /* Verify integrity of ckpt vers    ohwnc*/ 02507000
/*                                     */ 02508000
/*                                     */ 02511000
/*****                                     */ 02511900
/*                                     */ 02512800
/*      |      Defining How Destinations | 02513700
/*      |      Are Processed              | 02514600
/*      |      (added by OY54524)        | 02515500
/*      |      |                      | 02516400
/*      |      |                      | 02517300
/*      |      |                      | 02518200
DESTDEF LOCALNUM=9999, /* 9999 is the maximum special local wnc*/ 02518200
/*      routing allowed on this member ncl*/ 02519100
/*      JES2 interprets Nnnnn as node ncl*/ 02520000
/*      userids can be specified without ncl*/ 02520900
/*      a node specification          */ 02521800
/*      JES2 interprets Rnnnn as remote ncl*/ 02522700
/*      JES2 interprets RMnnnn as remote ncl*/ 02523600
/*      JES2 interprets RMTnnnn as remote ncl*/ 02524500
/*      JES2 interprets Unnnn as special ncl*/ 02525400
/*      local routing                  ncl*/ 02526300
/*      local dests are displayed      ohwnc*/ 02527200
/*      without 'LOCAL' as the prefix */ 02528100
/*                                     */ 02530000
/*                                     */ 02540000
/*****                                     */ 02550000
/*                                     */ 02560000
/*      |      Symbolic Destinations    | 02570000
/*      |      |                      | 02580000
/*      |      |                      | 02590000
/*      |      |                      | 02600000
DESTID(#####) DEST=##### /* DESTID - User-Defined Name      aowncl*/ 02600000
/*      (pre-SP311 DESTID NAME=)      */ 02601000
/*      DEST - NJE/RJE/LOCAL Routecode owncl*/ 02610000
/*      Do not display the destid for owncl*/ 02611000
/*      job and SYSOUT routing          */ 02611500
/*                                     */ 02612000
/*                                     */ 02630000
/*****                                     */ 02640000
/*                                     */ 02650000
/*      |      Default Estimated Sysout Bytes/Job | 02660000
/*      |      |                      | 02670000
/*      |      |                      | 02680000
/*      |      |                      | 02690000
ESTBYTE NUM=99999, /* 99999000 Bytes for 1st Msg      ohwnc*/ 02690000
/*      INT=99999, /* then 99999000 Byte Intervals ohwnc*/ 02700000
/*      OPT=0 /* Allow Jobs to Continue          ohwnc*/ 02710000
/*                                     */ 02720000
/*                                     */ 02730000
/*****                                     */ 02740000
/*                                     */ 02750000
/*      |      Default Estimated Execution Time | 02760000
/*      |      |                      | 02770000
/*      |      |                      | 02780000
/*      |      |                      | 02790000

```

```

ESTIME    NUM=2,          /* 2 minutes for 1st Message      ohwnc*/ 02790000
          INT=1,          /* then at 1 minute Intervals    ohwnc*/ 02800000
          OPT=NO          /* No HASP308 message           ohwnc*/ 02810000
/*                                                */ 02820000
/*                                                */ 02830000
/*****/
/*          *-----*
|          | Default Estimated Sysout Lines/Job | 02860000
|          |-----*
|          | 02870000
|          | 02880000
/*          | 02890000
ESTLNCT    NUM=2,          /* 2000 Lines for 1st Message      ohwnc*/ 02900000
          INT=2000,        /* then at 2000 Line Intervals    ohwnc*/ 02910000
          OPT=0            /* Allow Jobs to Continue         ohwnc*/ 02920000
/*                                                */ 02930000
/*                                                */ 02940000
/*****/
/*          *-----*
|          | Default Estimated Sysout Pages/Job | 02960000
|          |-----*
|          | 02970000
|          | 02980000
/*          | 02990000
ESTPAGE    NUM=40,        /* 40 Pages for 1st Message       ohwnc*/ 03000000
          INT=10,         /* then at 10 Page Intervals     ohwnc*/ 03010000
          OPT=0            /* Allow Jobs to Continue         ohwnc*/ 03020000
/*                                                */ 03030000
/*                                                */ 03040000
/*****/
/*          *-----*
|          | Default Estimated Sysout Cards/Job | 03060000
|          |-----*
|          | 03070000
|          | 03080000
/*          | 03090000
ESTPUN     NUM=100,       /* 100 Cards for 1st Message      ohwnc*/ 03100000
          INT=2000,       /* then at 2000 Card Intervals    ohwnc*/ 03110000
          OPT=0            /* Allow Jobs to Continue         ohwnc*/ 03120000
/*                                                */ 03130000
/*                                                */ 03140000
/*****/
/*          *-----*
|          | Exit Number - Routine Association | 03160000
|          |-----*
|          | 03170000
|          | 03180000
/*          | 03190000
EXIT(NNN)  ROUTINES=CCCCCCCC, /* Name on $ENTRY statement      wnc*/ 03200000
          STATUS=ENABLED,    /* The Exit is Enabled initially  ownnc*/ 03220000
          TRACE=NO           /* Tracing not active            ownnc*/ 03230000
/*                                                */ 03240000
/*                                                */ 03250000
/*****/
/*          *-----*
|          | Functional Subsystem Definition | 03270000
|          |-----*
|          | 03280000
|          | 03290000
/*          | 03300000
FSS(CCCCCCCCC) PROC=CCCCCCCC, /* FSS - Token for PRINTERnn FSS= aownc*/ 03303000
/*          (pre-SP311 FSSDEF FSSNAME=)    */ 03310000
/*          PROC -FSS Procedure to Start FSS ownnc*/ 03320000
          HASPFSSM=HASPFSM, /* FSS Load Module for FSS Support ownnc*/ 03326000
          AUTOSTOP=NO      /* Can FSS addr. space be removed orwnc*/ 03327000
/*          if all printers are inactive?   */ 03330000
/*                                                */ 03340000
/*                                                */ 03352000
/*****/
/*          *-----*
|          | Include additional init decks | 03360000
|          |-----*
|          | 03368000
|          | 03376000
/*          | 03384000
INCLUDE    DSNAME=CC(C),   /* Up to 44 char data set name & member */ 03392000
          VOLSER=CCCCCCCC, /* Volume serial for data set          */ 03400000
          UNIT=CCCC        /* Unit information for data set        */ 03408000
/*                                                */ 03416000
/*                                                */ 03430000
/*****/
/*          *-----*
|          | Logical Initiators | 03440000
|          |-----*
|          | 03450000
|          | 03460000
|          | 03470000
/*          | 03480000
INIT(nnnn) NAME=CCC,      /* Initiator Name                  wnc*/ 03500000
          CLASS=A,        /* Initial Job Classes              ownnc*/ 03510000
          START=YES       /* Start Automatically              wnc*/ 03520000
/*                                                */ 03530000
/*                                                */ 03540000
/*****/
/*          *-----*
|          | Logical Initiator definition | 03550000
|          |-----*
|          | 03560000
|          | 03570000

```

```

INITDEF PARTNUM=3 @@ /* Number of Initiators wnc*/ 03580000
/* */ 03590000
/* */ 03610000
/* */ 03620000
/***** */ 03630000
/* *-----* */ 03640000
| Internal Readers | 03650000
*-----* */ 03660000
/* */ 03670000
INTRDR AUTH=(JOB=NO, /* Allow Job cmds ownc*/ 03672000
        DEVICE=NO, /* Allow Device Cmds ownc*/ 03674000
        SYSTEM=NO), /* Allow system cmds ownc*/ 03676000
        /* (pre-SP420 AUTH=0 for all 3 */ 03678000
        /* subparameters) */ 03680000
        BATCH=YES, /* Allow batch jobs to use wnc*/ 03682000
        /* internal readers */ 03684000
        /* (added SP420) */ 03686000
        CLASS=A, /* Default Job Class ownc*/ 03690000
        HOLD=NO, /* Don't Hold Jobs Read ownc*/ 03700000
        HONORLIM=NO, /* Do output excession for INTRDR ownc*/ 03702000
        /* (added by OW06743) */ 03705000
        PRYINC=0, /* Don't Prty Age Jobs wnc*/ 03710000
        PRY LIM=15, /* Limit Job Prty to 15 wnc*/ 03720000
        TRACE=NO, /* Allow tracing ownc*/ 03784000
        /* (added SP420) */ 03785000
/* */ 03790000
/* */ 03800000
/***** */ 03810000
/* *-----* */ 03820000
| Job Class definitions | 03830000
*-----* */ 03840000
/* */ 03850000
JOBCLASS(? ACCT=NO, /* Acct# not req oc*/ 03860000
        ACTIVE=NO, /* Class not used on new jobs */ 03865000
        AUTH=ALL, /* Allow all Cmd oc*/ 03870000
        BLP=NO, /* Ignore BLP oc*/ 03880000
        COMMAND=VERIFY, /* Verify Cmds oc*/ 03885000
        CONDPURG=NO, /* Conditional purge for oc*/ 03886000
        /* JOBCLASS(STC) or JOBCLASS(TSU) */ 03887000
        /* (moved in OS/390 R4) */ 03888000
        COPY=NO, /* Not TYPRUN=COPY oc*/ 03890000
        GROUP=name, /* Associate jobclass with group name / 03893000
        HOLD=NO, /* Not TYPRUN=HOLD oc*/ 03895000
        IEFUJP=YES, /* Take SMF Job Purge Exit oc*/ 03900000
        IEFUSO=YES, /* Take SYSOUT Excess Exit oc*/ 03910000
        JESLOG=(NOSPIN), /* JOBLLOG/SYSMSG spin specifications oc*/ 03915000
        JOURNAL=YES, /* Journal this Job Class oc*/ 03920000
        LOG=YES, /* Print JES2 JOB LOG oc*/ 03930000
        MODE=JES, /* Run in JES mode, not WLM mode oc*/ 03931000
        /* (added in OS/390 R4) */ 03932000
        MSGCLASS=A, /* Message class for JOBCLASS(STC) oc*/ 03933000
        /* or JOBCLASS(TSU) */ 03934000
        /* (moved in OS/390 R4) */ 03935000
        MSGLEVEL=(0,1), /* Job, All Msgs oc*/ 03940000
        OUTDISP=(,), /* Disposition of system output oc*/ 04092000
        /* normal termination and abnormal */ 04093000
        /* termination (added SP410) */ 04094000
        /* (pre-SP410=CONDPURG) */ 04095000
        OUTPUT=YES, /* Produce Output for Job oc*/ 04110000
        QHELD=NO, /* Hold jobs prior to execution oc*/ 04116000
        /* (added by APAR OW06439) */ 04122000
        PERFORM=000, /* SRM Performance Group 0 oc*/ 04130000
        PGMNAME=NO, /* Pgmnm not rq oc*/ 04135000
        PROCLIB=00, /* Use //PROCO0 DD oc*/ 04140000
        REGION=1M, /* Region Size oc*/ 04143000
        /* (format changed SP410) */ 04146000
        RESTART=NO, /* No Requeue (XEQ) on IPL oc*/ 04150000
        SCAN=NO, /* Not TYPRUN=SCAN oc*/ 04170000
        SCHENV=cccccccc, /* Default SCHENV oc*/ 04180000
        SWA=BELOW, /* SWA cbs below 16m line oc*/ 04190000
        /* (added by APAR OY02574) */ 04200000
        /* (superseded by APAR OY03444) */ 04210000
        TIME=(0030,00), /* Job Step Time oc*/ 04212000
        /* (format changed SP410) */ 04215000
        TYPE6=YES, /* Produce SMF 6 Records oc*/ 04220000
        TYPE26=YES, /* Produce SMF 26 Records oc*/ 04240000
        XBM=cccccccc, /* Proc name for XBM/2 job oc*/ 04274000
        /* (changed in SP313) */ 04278000
        XEQCOUNT=MAX=* /* Maximum jobs allowed in this oc*/ 04278500
        /* class simultaneously */ 04279000
        /* (added in OS/390 R4) */ 04279500
/* */ 04280000

```

```

/*                                                                    */ 04290000
/*****                                                                    */ 04300000
/*                                                                    *-----* 04310000
|      Job Characteristics      | 04320000
*-----*                                                                    */ 04330000
/*                                                                    */ 04340000
JOBDEF  ACCTFLD=OPTIONAL, /* Accounting field optional      ohwnc*/ 04350000
        BAD_JOBNAME_CHAR=?, /* The character used to          ohwnc*/ 04350200
        /* substitute for bad jobname */ 04350400
        /* characters */ 04350600
        CNVT_ENQ=FAIL, /* Fail job conversion if a DSN */ 04351000
        /* ENQ is not available */ onc*/ 04352000
        DUPL_JOB=DELAY, /* Don't allow jobs with duplicate */ 04355000
        /* names to execute concurrently */ onc*/ 04360000
        /* (added OS130) */ 04365000
        JCLERR=NO, /* No Term. Job w/JCL Error      ohwnc*/ 04370000
        JNUMWARN=80, /* Warn Threshold % for Job Numb. */ onc*/ 04380000
        JOBNUM=1000, /* Job Queue Size                  oc*/ 04410000
        JOBWARN=80, /* Warning Threshold % For JQEs    onc*/ 04430000
        PRTYHIGH=10, /* Upper Limit for Aging           onc*/ 04450000
        PRTYJECL=YES, /* PRIORITY JECL Supported         ohwnc*/ 04470000
        PRTYJOB=NO, /* PRTY= on JOB Not Sup'd         ohwnc*/ 04490000
        PRTYLOW=5, /* Lower Limit for Aging           onc*/ 04510000
        PRTYRATE=0, /* Prty Aging Rate X/Day           onc*/ 04530000
        RANGE=(1-9999), /* Local Job Number Range         oc*/ 04550000
        RASSIGN=YES, /* Allow assignment of job numbers ohwnc*/ 04560000
        /* outside RANGE (added 0W20844) */ 04570000
/*                                                                    */ 04590000
/*                                                                    */ 04600000
/*****                                                                    */ 04610000
/*                                                                    *-----* 04620000
|      Default PRTY Calculations  | 04630000
*-----*                                                                    */ 04640000
/*                                                                    */ 04650000
JOBPRTY(1) PRIORITY=9, /* Job Prty=9 if                  ohwnc*/ 04660000
            TIME=2 /* < 2 min. exec. time            ohwnc*/ 04670000
JOBPRTY(2) PRIORITY=8, /* Job Prty=8 if                  */ 04710000
            TIME=5 /* < 5 min. exec. time          */ 04720000
            /* etc. */ 04722000
/*                                                                    */ 04724000
/*                                                                    */ 04726000
/*****                                                                    */ 04728000
/*                                                                    *-----* 04728500
|      Line JOB Transmitters      | 04729000
*-----*                                                                    */ 04729500
/*                                                                    */ 04729700
L(NNNN).JT(N) LIMIT=(0-*), /* Select Any # Lines            ohwnc*/ 04729900
                        /* (added OS240) */ 04730100
                        WS=(/) /* Work selection criteria      ohwnc*/ 04730300
                        /* (added OS240) */ 04730500
/*                                                                    */ 04730700
/*                                                                    */ 04731300
/*****                                                                    */ 04732000
/*                                                                    *-----* 04732700
|      Line SYSOUT Transmitters    | 04733400
*-----*                                                                    */ 04734100
/*                                                                    */ 04734800
L(NNNN).ST(N) LIMIT=(0-*), /* Select Any # Lines            ohwnc*/ 04735500
                        /* (added SP430) */ 04736200
                        OUTDISP=, /* Select output dispositions    ohwnc*/ 04736400
                        /* (added OS130) */ 04736600
                        PLIM=(0-*), /* Select Any # Pages            ohwnc*/ 04736900
                        /* (added SP430) */ 04737600
                        WS=(/) /* Work selection criteria      ohwnc*/ 04738300
                        /* (added SP430) */ 04739000
/*                                                                    */ 04740000
/*                                                                    */ 04750000
/*****                                                                    */ 04760000
/*                                                                    *-----* 04770000
|      TP Lines for RJE/NJE        | 04780000
|      BSC Line                    | 04785000
*-----*                                                                    */ 04790000
/*                                                                    */ 04800000
/*                                                                    */ 04803000
LINE(NNNN) AUTODISC=YES, /* Alternate name for LINE: LNEa aohwnc*/ 04806000
                        /* automatic disconnect (NO) */ 04808000
                        /* (pre-SP311=ADISCON/NOADISC) */ 04810000
                        CODE=A, /* BSC adapter code (B)          ohwnc*/ 04812000
                        /* (pre-SP311=CODEA/CODEB) */ 04815000
                        COMPRESS=YES, /* Data compression avail.      ohwnc*/ 04818000
                        /* (pre-SP311=COMP/NOCOMP) */ 04818600
                        DUPLEX=HALF, /* Half duplex line (FULL)       ohwnc*/ 04819200
                        /* (pre-SP311=HDUPLEX/FDUPLEX) */

```



```

INTERFAC=A,          /* BSC adapter interface (B)      ohwnc*/ 04819800
                    /* (pre-SP311=IFACEA/IFACEB)    */ 04820400
JRNUM=DEFAULT,       /* Number of job receivers on     hwnc*/ 04821000
                    /* this line (Range=0-7)         */ 04821600
                    /* (added SP430)                 */ 04822200
JTNUM=DEFAULT,       /* Number of job transmitters on  hwnc*/ 04822800
                    /* this line (Range=0-7)         */ 04823400
                    /* (added SP430)                 */ 04824000
LINECCHR=EBCDIC,     /* Line control char. form (USASCII) */ 04824600
                    /* (pre-SP311=EBCDIC/USASCII) ohwnc*/ 04825200
LOG=N,               /* Monitor channel end completions (Y) */ 04827000
                    /* or discontinue monitor (N) ohwnc*/ 04830000
PASSWORD=,           /* 1-8 char. security password    ohwnc*/ 04840000
REST=0,              /* Resistance rating of the line  ohwnc*/ 04840900
SPEED=LOW,           /* <=9600 bits per second (HIGH) ohwnc*/ 04841800
                    /* (Used for models 360/20 2&4) */ 04842700
                    /* (pre-SP311=LOWSPEED/HISPEED) */ 04843600
SRNUM=DEFAULT,       /* Number of SYSOUT receivers on  hwnc*/ 04844500
                    /* this line (Range=0-7)         */ 04845400
                    /* (added SP430)                 */ 04845600
STNUM=DEFAULT,       /* Number of SYSOUT transmitters  hwnc*/ 04845800
                    /* on this line (Range=0-7)      */ 04846000
                    /* (added SP430)                 */ 04846200
TRACEIO=NO,          /* Trace i/o operations on line (YES) */ 04846800
                    /* or stop tracing (NO)         ohwnc*/ 04847200
                    /*                               */ 04848000
                    /* NOTE: The following parameters are */ 04850000
                    /* ignored if UNIT=SNA            */ 04860000
TRANSPAR=NO,         /* Text transparency (YES)        ohwnc*/ 04960000
                    /* (Required for BSC NJE lines)   */ 04970000
                    /* (pre-SP311=NOTRANS/TRANSP)    */ 04975000
UNIT=$$$             /* Unit address EP, CTC or 'SNA' ohwnc*/ 04976300
/*                   *-----* 04976400
                    | TP Lines for RJE/NJE | 04976500
                    | SNA Line             | 04976600
                    *-----* 04976700
                    */ 04976800
LINE(NNNN) LOG=N,    /* Monitor channel end completions (Y) */ 04976900
                    /* or discontinue monitor (N) aohwnc*/ 04977000
JRNUM=DEFAULT,       /* Number of job receivers on     ohwnc*/ 04977100
                    /* this line (Range=0-7)         */ 04977200
                    /* (added SP430)                 */ 04977300
JTNUM=DEFAULT,       /* Number of job transmitters on  ohwnc*/ 04977400
                    /* this line (Range=0-7)         */ 04977500
                    /* (added SP430)                 */ 04977600
PASSWORD=,           /* 1-8 char. security password    ohwnc*/ 04977800
SRNUM=DEFAULT,       /* Number of SYSOUT receivers on  ohwnc*/ 04978000
                    /* this line (Range=0-7)         */ 04978200
                    /* (added SP430)                 */ 04978400
STNUM=DEFAULT,       /* Number of SYSOUT transmitters  ohwnc*/ 04978600
                    /* on this line (Range=0-7)      */ 04978800
                    /* (added SP430)                 */ 04979000
TRACEIO=NO,          /* Trace i/o operations on line (YES) */ 04979200
                    /* or stop tracing (NO)         ohwnc*/ 04979400
UNIT=SNA             /* Indicate SNA device            ohwnc*/ 04979600
/*                   */ 04980000
/*                   */ 04990000
/*****              */ 05000000
/*                   *-----* 05010000
                    | Exit Load Modules   | 05020000
                    *-----* 05030000
                    */ 05040000
LOADMOD(module_name) STORAGE=PVT 05045000
                    /* Exit load module name ($MODULE) hwnc*/ 05050000
                    /* (pre-SP311 LOAD module_name) */ 05050500
                    /* Load module into private also hwnc*/ 05051000
                    /* CSA and LPA */ 05052000
/*                   */ 05060000
/*                   */ 05070000
/*****              */ 05080000
/*                   *-----* 05090000
                    | Identify JES2 APPLIDs to VTAM | 05100000
                    *-----* 05110000
                    */ 05120000
LOGON(n) Applid=JES2, /* Access control blk (ACB) name aohwnc*/ 05130000
LOG=Y,               /* Monitor VTAM interface (Y) ohwnc*/ 05131000
                    /* or discontinue monitoring (N) */ 05132000
TRACEIO=NO,          /* Trace i/o activity (YES) ohwnc*/ 05136000
                    /* or stop tracing activity (NO) */ 05137000
PASSWORD=            /* 1-8 char. security password ohwnc*/ 05140000
/*                   */ 05150000
/*                   */ 05160000

```

```

/*****/ 05170000
/*      *-----* 05180000
|      | Multi-Access Spool | 05190000
|      | MASDEF - this members | 05193000
|      | characteristics | 05196000
|      *-----* 05200000
/* 05210000
/* Times are in 1/100 sec. unless spec'd*/ 05220000
MASDEF AUTOEMEM=OFF, /* Restart this members work ohwnc*/ 05230000
/* if this member fails */ 05232000
CKPTLOCK=ACTION, /* Issue HASP479 during JES start hwnc*/ 05236000
/* if needed */ 05240000
DORMANCY=(100, /* Minimum Dormancy Time ohwnc*/ 05244000
500), /* Maximum Dormancy Time ohwnc*/ 05250000
HOLD=99999999, /* Minimum Hold Time ohwnc*/ 05270000
LOCKOUT=1000, /* Lock-out Warning Time ohwnc*/ 05290000
OWNMEMB=cccc, /* Member identifier of this member wnc*/ 05310000
/* This replaces OWNSID in SP510 */ 05316000
RESTART=NO, /* This member cannot $ESYS others ohwnc*/ 05322000
SHARED=CHECK, /* Check for Shared DASD oc*/ 05330000
/* SID(1)=cccc, /* replaced by MEMBER statements wnc*/ 05350000
/* in SP510 */ 05360000
SYNCTOL=120, /* Synch.Tolerance (Sec.) ohwnc*/ 05370000
XCFGRPNM=cccc /* 1-8 char. MAS unique XCF groupname nc*/ 05380000
/* 05390000
/*      *-----* 05390100
|      | Multi-Access Spool | 05391000
|      | MEMBER - Used to define all | 05391900
|      | members | 05392800
|      *-----* 05393700
/* 05394600
MEMBER(n) NAME=cccc /* Member number (1-32) and 1-4 wnc*/ 05395500
/* character member name */ 05396400
/* This replaces SID parm from MASDEF */ 05397300
/* as of SP510 */ 05398200
/* 05400000
/*****/ 05410000
/*      *-----* 05420000
|      | Network/Local Account # Translation | 05430000
|      *-----* 05440000
/* 05450000
NETACCT NACCT=cccccccc, /* Network Account Number wnc*/ 05460000
NTHRU=cccccccc, /* Upper limit for NACCT wnc*/ 05470000
JACCT=cccc, /* JES2 Account Number wnc*/ 05480000
JTHRU=cccc, /* Upper limit for JACCT wnc*/ 05490000
TYPE=cc? /* Translate Both Ways wnc*/ 05500000
/* 05500800
/* 05501700
/*****/ 05502600
/*      *-----* 05503500
|      | Network Server definitions | 05504400
|      *-----* 05505300
/* 05506200
NETSRV(n) SOCKET=cccccccc, /* Socket for IP address and port ownc*/ 05507100
STACK=cccccccc, /* TCP/IP stack to use ownc*/ 05507200
TRACE=NO /* Trace traffic on server ownc*/ 05508000
/* 05508900
/* 05510000
/* 05520000
/*****/ 05530000
/*      *-----* 05540000
|      | NJE Definitions | 05550000
|      *-----* 05560000
/* 05570000
/* 05575000
NJedef DELAY=120, /* Max. Msg Delay Time ohwnc*/ 05580000
HDRBUF=(LIMIT=cccc, /* number of NJE header + trailer ohwnc*/ 05584000
/* buffers */ 05588000
/* (added in SP510) */ 05592000
WARN=80), /* Warning threshold ohwnc*/ 05596000
JRNUM=0, /* Num. of job receivers hwnc*/ 05600000
JTNUM=0, /* Num. of job xmitters hwnc*/ 05620000
LINENUM=0, /* Num. of lines for NJE hwnc*/ 05640000
MAILMSG=NO, /* Don't automatically issue ohwnc*/ 05645000
/* notification message */ 05650000
MAXHOP=0, @@ /* Num. of iterations to limit hwnc*/ 05655000
/* hoping in network */ 05660000
/* 0 means no hop counting */ 05665000
/* (added SP420) */ 05670000
/* 05680000
NODENUM=1, /* Max. Number of NJE nodes ownc*/ 05680000
OWNNODE=1, /* This Node's Number c*/ 05720000
PATH=1, /* Num. of Paths/Alt'nate wnc*/ 05740000

```

```

RESTMAX=79992000, /* Max. resistance tolerance ohwnc*/ 05760000
RESTNODE=100, /* This node's resistance ohwnc*/ 05780000
RESTTOL=0, /* Alt. resistance tolerance ohwnc*/ 05800000
SRNUM=0, /* Num. of sysout receivers hwnc*/ 05820000
STNUM=0, /* Num. of sysout transmitters hwnc*/ 05840000
TIMETOL=20 /* Time variation between clocks ohwnc*/ 05853000
/* (added SP410) */ 05856000
/* */ 05900000
/* */ 05910000
/***** */ 05920000
/* *-----* */ 05930000
| NJE Node Definitions | 05940000
| This statement needs to be | 05941000
| BEFORE any statement referring | 05942000
| to this node name in a | 05943000
| production init deck. This | 05944000
| includes: APPL, CONNECT, | 05945000
| DESTID and device route codes | 05946000
|-----* */ 05950000
/* */ 05960000
NODE(NNNN) AUTH=(DEVICE=YES, /* Authority at this node ohwnc*/ 05970000
/* Device Authority at this node ohwnc*/ 05980000
/* (pre-SP311=DEVAUTH/NODEVATH) */ 05985000
JOB=YES, /* Job Authority at this node ohwnc*/ 05990000
/* (pre-SP311=JOBATH/NOJOBATH) */ 06000000
NET=NO, /* No Network Auth at this node ohwnc*/ 06005000
/* (pre-SP311=NONETATH/NETAUTH) */ 06006000
SYSTEM=YES), /* System Authority at this node ohwnc*/ 06010000
/* (pre-SP311=SYSAUTH/NOSYSATH) */ 06015000
COMPACT=0, /* No compaction hwnc*/ 06016000
DIRECT=NO, /* This node should always be ownnc*/ 06017000
/* directly attached (adjacent) */ 06018000
/* (added ZOS170) */ 06019000
ENDNODE=NO, /* This node is eligible for store ownnc*/ 06020000
/* and forward operations */ 06022000
HOLD=NONE, /* Whether or not to hold jobs ohwnc*/ 06025000
/* that are received at this node */ 06030000
LINE=####, /* Line dedicated to session ohwnc*/ 06035500
/* (added SP410) */ 06036000
LOGON=1, /* LOGON DCT to be used by this ohwnc*/ 06036100
/* session (added OS240) */ 06036200
LOGMODE=, /* Logon mode table entry name ohwnc*/ 06036500
/* (added SP410) */ 06037000
NAME=#####, /* Node name ownnc*/ 06037100
PASSWORD=(SEND=#####,VERIFY=#####), /* 1-8 char. security passwords ohwnc*/ 06037400
/* Connection to adjacent node ownnc*/ 06037500
/* (added SP410) */ 06038000
PENCRIPT=NO, /* Password encryption option ohwnc*/ 06038100
/* (added in SP313) */ 06038200
PRIVATE=NO, /* Broadcast connection to node ownnc*/ 06038500
/* (added SP410) */ 06039000
RECEIVE=BOTH, /* Receive both jobs and sysout ohwnc*/ 06040000
REST=0, /* Nodal Resistance ohwnc*/ 06041000
SENTREST=ACCEPT, /* Use partial resistance from ohwnc*/ 06042000
/* this node during signon */ 06043000
/* (added by OY52946) ohwnc*/ 06044000
SIGNON=COMPAT, /* Use compat or secure signon */ 06044200
/* protocol ohwnc*/ 06044400
/* (added ZOS170) */ 06044600
SUBNET=$$$$$$, /* Subnet name which includes ownnc*/ 06045000
/* node (added SP410) */ 06046000
TRACE=NO, /* Specifies tracing connection ohwnc*/ 06047000
/* (added SP410) */ 06048000
TRANSMIT=BOTH, /* Transmit both jobs and sysout ohwnc*/ 06049000
/* No SNA Capability hwnc*/ 06050000
/* (SP311=BSC/SNA deleted) */ 06055000
/* */ 06060000
/* */ 06070000
/***** */ 06080000
/* *-----* */ 06090000
| Offload Data Set | 06100000
|-----* */ 06110000
/* */ 06120000
/* Defines a logical offload device */ 06130000
OFFLOAD1 DSN=#, /* Up to 44 char. data set name ohwnc*/ 06150000
ARCHIVE=ONE, /* Hold as archived on ONE or ALL */ 06160000
/* offload devices ohwnc*/ 06170000
/* (added OS110) */ 06180000
CRTIME=RESET, /* Set new create time for ohwnc*/ 06185000
/* reloaded jobs */ 06190000
/* (added ZOS170) */ 06195000

```

```

LABEL=SL,          /* Type of label processing done ohwnc*/ 06200000
                  /* (added in APAR 0Z92050) */ 06210000
PROTECT=NO,        /* Whether ds has SAF protection ohwnc*/ 06220000
                  /* (added in APAR 0Z92050) */ 06230000
RETPD=####,        /* DS retention period (in days) ohwnc*/ 06240000
                  /* (added in APAR 0Z92050) */ 06250000
UNIT=(#####,      /* Unit addr/dev type/group name ohwnc*/ 06251000
                  /* (added in APAR 0Z92050) */ 06252000
1),                /* No. of devices allocated to ds ohwnc*/ 06252500
                  /* (pre-0Z92050 UNITCT=) */ 06253000
VALIDATE=YES,      /* Validate header record ohwnc*/ 06253200
                  /* (added 0S110) */ 06253800
VOLS=##?           /* Device volume number hownc*/ 06255000
                  /* (added in SP420) */ 06256000
/*                */ 06260000
/*                */ 06270000
/*****            */ 06280000
/*                */ 06290000
                  *-----*
                  | Offload Job Receiver | 06300000
                  *-----*
                  */ 06320000
                  */ 06330000
OFF1.JR CLASS=,     /* Reload All Classes ohwnc*/ 06340000
CREATOR=,          /* Reload All Users ohwnc*/ 06342000
                  /* (added in SP420) */ 06345000
HOLD=,            /* Reload Held & Non-Held ohwnc*/ 06350000
JOBNAME=,         /* Reload Any Job Name ohwnc*/ 06360000
                  /* Modify Jobs on Reload */ 06370000
MOD=(CLASS=,      /* - Don't Change Class ohwnc*/ 06380000
HOLD=,            /* - Don't Change Hold ohwnc*/ 06390000
ROUTECD=,         /* - Don't Change Dest'n ohwnc*/ 06400000
SYSAFF=),         /* - Don't Change SysAff. ohwnc*/ 06410000
NOTIFY=NO,        /* Don't Notify on Reload ohwnc*/ 06420000
RANGE=J1-2147483647, 06430000
                  /* Reload All Job Numbers ohwnc*/ 06435000
ROUTECD=(),       /* Reload Jobs w/Any Dest ohwnc*/ 06440000
                  /* (modified SP410) */ 06445000
START=YES,        /* Started with $S OFFLOAD hwnc*/ 06450000
SYSAFF=(),        /* Reload Jobs with Any Aff ohwnc*/ 06460000
WS=(CLASS/)       /* Job Selection Criteria ohwnc*/ 06470000
/*                */ 06480000
/*                */ 06490000
/*****            */ 06500000
/*                */ 06510000
                  *-----*
                  | Offload Job Transmitter | 06520000
                  *-----*
                  */ 06540000
                  */ 06550000
OFF1.JT CLASS=,     /* Select No Classes ohwnc*/ 06560000
CREATOR=,          /* Select Any users ohwnc*/ 06565000
DISP=DELETE,      /* Purge after Offload ohwnc*/ 06570000
HOLD=,            /* Select Held & Non-Held ohwnc*/ 06580000
JOBNAME=,         /* Select Any Job Name ohwnc*/ 06590000
NOTIFY=NO,        /* Don't Notify on Offld. ohwnc*/ 06600000
RANGE=J1-65534,   /* Select All Job Numbers ohwnc*/ 06610000
ROUTECD=(),       /* Select Jobs w/Any Dest ohwnc*/ 06620000
                  /* (modified SP410) */ 06625000
START=YES,        /* Started with $S OFFLOAD hwnc*/ 06630000
SYSAFF=(),        /* Select Jobs with Any Aff ohwnc*/ 06640000
VOLUME=(),        /* Select Any Spool Volume ohwnc*/ 06650000
WS=(CLASS/)       /* Job Selection Criteria ohwnc*/ 06660000
/*                */ 06670000
/*                */ 06680000
/*****            */ 06690000
/*                */ 06700000
                  *-----*
                  | Offload Sysout Receiver | 06710000
                  *-----*
                  */ 06730000
                  */ 06740000
OFF1.SR BURST=,     /* Select Any Burst Setting ohwnc*/ 06750000
CREATOR=,          /* Select Any Users ohwnc*/ 06756000
                  /* (added in SP420) */ 06762000
FCB=,             /* Select Any FCB ohwnc*/ 06770000
FLASH=,           /* Select Any/No Flash ohwnc*/ 06780000
FORMS=,           /* Select Any FORMS ID ohwnc*/ 06790000
HOLD=,            /* Select Held/Non-Hld Jobs ohwnc*/ 06800000
JOBNAME=,         /* Select Any Job Name ohwnc*/ 06810000
MOD=(BURST=,      /* - Don't Change Burst ohwnc*/ 06810300
FCB=,             /* - Don't Change FCB ohwnc*/ 06810600
FLASH=,           /* - Don't Change Flash ohwnc*/ 06810900
FORMS=,           /* - Don't Change Forms ohwnc*/ 06811200
HOLD=,            /* - Don't Change Hold ohwnc*/ 06811500
OUTDISP=,         /* - Output disposition change ohwnc*/ 06811800
                  /* (pre SP410 DSHOLD=) */ 06812100
PRMODE=,          /* - Don't Change PRMODE ohwnc*/ 06812400

```

```

        QUEUE=,          /* - Don't Change Class          ohwnc*/ 06812700
        ROUTECDE=,       /* - Don't Change Destn        ohwnc*/ 06813000
        UCS=,            /* - Don't Change UCS          ohwnc*/ 06813300
        WRITER=),        /* - Don't Change writer       ohwnc*/ 06813600
NOTIFY=NO,              /* Don't Notify on reload      ohwnc*/ 06813900
OUTDISP=(W,H,K,L),     /* Specifies output disposition ohwnc*/ 06815000
                        /* (pre SP410 was DS=ANY)      */ 06820000
                        /* (added SP410)               */ 06822000
                        /* Modify Following on Reload  ohwnc*/ 06825000
        PRMODE=(),       /* Select Any PRMODE           ohwnc*/ 06950000
        QUEUE=,          /* Select Any Sysout Class     ohwnc*/ 06960000
        RANGE=J1-2147483647,
                        /* Reload All Job Numbers      ohwnc*/ 06975000
        ROUTECDE=(),     /* Select Jobs w/Any Dest      ohwnc*/ 06980000
                        /* (modified SP410)           */ 06985000
        START=YES,       /* Started with $S OFFLOAD     hwnc*/ 06990000
        UCS=,            /* Select any UCS              ohwnc*/ 07000000
        WRITER=,         /* Select any Writer           ohwnc*/ 07010000
        WS=(Q,OUTDISP/)  /* Job Selection Criteria      ohwnc*/ 07020000
                        /* - Output disposition match  */ 07032000
                        /* (added SP410)             */ 07035000
/*                                                                */ 07040000
/*                                                                */ 07050000
/*****                                                                */ 07060000
/*                                                                */ 07070000
                        *-----*
                        | Offload Sysout Transmitter | 07080000
                        *-----*
                        /*                                                                */ 07100000
                        /*                                                                */ 07110000
OFF1.ST BURST=,          /* Select Any Burst Set'g      ohwnc*/ 07120000
        CREATOR=,        /* Select Any Users            ohwnc*/ 07122000
                        /* (added in SP420)           */ 07125000
        DISP=DELETE,     /* Purge after Offload         ohwnc*/ 07130000
        FCB=,            /* Select Any FCB              ohwnc*/ 07150000
        FLASH=,          /* Select Any/No Flash         ohwnc*/ 07160000
        FORMS=,          /* Select Any FORMS ID        ohwnc*/ 07170000
        HOLD=,           /* Selct Held&Non-Hld Jobs     ohwnc*/ 07180000
        JOBNAM=,         /* Select Any Job Name        ohwnc*/ 07190000
        LIMIT=(0-*),     /* Select Any # Lines          ohwnc*/ 07200000
        NOTIFY=NO,       /* Don't Notify on Offld.      ohwnc*/ 07210000
        OUTDISP=(W,K),   /* Specifies output disposition ohwnc*/ 07212000
                        /* (pre SP410 DS=)           */ 07215000
        PLIM=(0-*),      /* Select Any # Pages          ohwnc*/ 07220000
        PRMODE=(),       /* Select Any PRMODE           ohwnc*/ 07230000
        QUEUE=,          /* Select Any Sysout Class     ohwnc*/ 07240000
        RANGE=J1-65534,  /* Select All Job Numbers      ohwnc*/ 07250000
        ROUTECDE=(),     /* Select Jobs w/Any Dest      ohwnc*/ 07260000
                        /* (modified SP410)           */ 07265000
        START=YES,       /* Started with $S OFFLOAD     hwnc*/ 07270000
        UCS=,            /* Select any UCS              ohwnc*/ 07280000
        VOLUME=(),       /* Select Any Spool Volume     ohwnc*/ 07290000
        WRITER=,         /* Select any Writer           ohwnc*/ 07300000
        WS=(Q,OUTDISP/)  /* Job Selection Criteria      ohwnc*/ 07310000
                        /* - Output disposition match  ohwnc*/ 07323000
                        /* (added SP410)             */ 07326000
/*                                                                */ 07330000
/*                                                                */ 07340000
/*****                                                                */ 07341000
/*                                                                */ 07342000
                        *-----*
                        | JES2 Options Definition | 07343000
                        *-----*
                        /*                                                                */ 07345000
                        /*                                                                */ 07346000
OPTSDEF LIST=NO,         /* Do not copy following init. hwnc*/ 07347000
                        /* stmts. to HARDCOPY console */ 07347200
        LOG=YES,         /* Copy following init stmts to hwnc*/ 07347400
                        /* printer defined on HASPLIST */ 07347600
        SPOOL=NOVALIDATE /* Do not validate track group map nc*/ 07347800
                        /*-----*/ 07348000
                        /* The following options can only */ 07348200
                        /* be overridden when the JES2 */ 07348400
                        /* initialization process is in */ 07348600
                        /* CONSOLE mode. */ 07348700
                        /*-----*/ 07348800
/* CKPTOPT=HIGHEST      /* Use highest checkpoint to   hwnc*/ 07350000
                        /* restart */ 07350300
/* CONSOLE=YES          /* Prompt for more init. stmts. hwnc*/ 07350400
/* LISTOPT=NO           /* Support LIST start option   hwnc*/ 07351200
/* LOGOPT=YES           /* Support LOG start option    hwnc*/ 07353900
/* RECONFIG=YES         /* Allow op to specify RECONFIG hwnc*/ 07354800
/* REQMSG=YES           /* Display HASP400 message     hwnc*/ 07355700
/*                                                                */ 07356600
/*                                                                */ 07357500
/*****                                                                */ 07358400

```

```

/*          *-----* 07360000
|          | Output Class Attributes | 07370000
|          *-----* 07390000
/*          */ 07400000
OUTCLASS(A) BLNKTRNC=YES, /* Truncate trailing blanks wnc*/ 07410000
OUTDISP=(WRITE,WRITE),   /* SYSOUT disposition normal/ own*/ 07440000
                        /* abnormal job termination */ 07450000
                        /* (pre SP410 HOLD=,CONDPURG=) */ 07460000
                        OUTPUT=PRINT, /* Print class wnc*/ 07490000
                        TRKCELL=YES   /* TRACK-CELL this class wnc*/ 07510000
/*          */ 07530000
/*          */ 07540000
/*****/ 07550000
/*          *-----* 07560000
|          | Output Characteristics | 07570000
|          *-----* 07580000
/*          */ 07590000
OUTDEF  BROADCAST=NO, /* Whether shared broadcasting oc*/ 07600000
        /* is in use by this complex */ 07610000
        COPIES=255, /* Max. # of Copies Allowed ohwnc*/ 07630000
        DMNDSET=NO, /* No Demand Setup wnc*/ 07650000
        JOENUM=0, /* Max. # of JOEs oc*/ 07670000
        JOEWARN=80, /* Warning Threshold % ohwnc*/ 07710000
        OUTTIME=CREATE, /* Specifies when JOE time saved ohwnc*/ 07722000
        /* (added SP410) */ 07725000
        PRTYHIGH=255, /* Ceiling for PRTY Aging ohwnc*/ 07730000
        PRTYLOW=0, /* Floor for PRTY Aging ohwnc*/ 07750000
        PRTYOUT=NO, /* No PRTY= on // OUTPUT ohwnc*/ 07770000
        PRYORATE=0, /* Don't priority age ohwnc*/ 07776000
        SEGLIM=100, /* Max. number output segments own*/ 07782000
        /* (added SP410) */ 07785000
        STDFORM=STD, /* Default Forms ID wnc*/ 07790000
        USERSET=NO, /* No User Demand-Setup wnc*/ 07810000
/*          */ 07830000
/*****/ 07840000
/*          *-----* 07850000
|          | Default Output Priority | 07860000
|          *-----* 07870000
/*          */ 07880000
        /* based on records (line mode) */ 07890000
        /* or pages (page mode) */ 07900000
OUTPRTY(1) PRIORITY=144, /* Output PRTY is 144 if ohwnc*/ 07910000
RECORD=2000, /* < 2000 records (LINE) ohwnc*/ 07920000
PAGE=50 /* or < 50 pages (PAGE) ohwnc*/ 07930000
OUTPRTY(2) PRIORITY=128, /* Output PRTY is 128 if ohwnc*/ 07970000
RECORD=5000, /* < 5000 records (LINE) ohwnc*/ 07980000
PAGE=100 /* or < 100 pages (PAGE) ohwnc*/ 07990000
/*          */ 080030000
/*          */ 08040000
/*          */ 08050000
/*****/ 08060000
/*          *-----* 08070000
|          | JES2 Processor Numbers | 08080000
|          *-----* 08090000
/*          */ 08100000
PCEDEF  CNVTNUM=2, /* Number of Converter PCEs hwnc*/ 08110000
OUTNUM=2, /* Number of Output PCEs hwnc*/ 08130000
PSONUM=2, /* Number of PSO PCEs hwnc*/ 08150000
PURGENUM=2, /* Number of Purge PCEs hwnc*/ 08170000
SPINNUM=3, /* Number of Spin PCEs hwnc*/ 08180100
        /* (added in SP420) */ 08180400
        STACNUM=2 /* Number of STATUS/CANCEL PCEs hwnc*/ 08181000
        /* (added in SP313) */ 08184000
/*          */ 08190000
/*          */ 08200000
/*****/ 08210000
/*          *-----* 08220000
|          | Printing Characteristics | 08230000
|          *-----* 08240000
/*          */ 08250000
PRINTDEF CCWNUM=0, /* # CCWs / Print Buffer wnc*/ 08260000
DBLBUFR=YES, /* Double Buffer Lcl Prts wnc*/ 08280000
FCB=6, /* Initial FCB Loaded wnc*/ 08300000
LINECT=61, /* 61 Lines/Page ohwnc*/ 08320000
NIFCB=****, /* No 3800 FCB Loaded wnc*/ 08340000
NIFLASH=****, /* No 3800 Flash Loaded wnc*/ 08360000
        /* NOTE: the values for NIFCB= and */ 08380000
        /* NIFLASH= CANNOT be null or */ 08390000
        /* asterisks (as shown here). */ 08400000
        /* If the statements are not */ 08410000
        /* coded at all, then the default */ 08420000

```

```

/*      will be asterisks. The      */ 08430000
/*      statements are shown this way */ 08440000
/*      only to include the default  */ 08450000
/*      values here.                  */ 08460000
NIUCS=GF10, /* 3800 Char. Set Loaded      wnc*/ 08470000
RDBLBUFFR=NO, /* Single Buffer Rmt Prts      wnc*/ 08490000
SEPPAGE=(LOCAL=DOUBLE, /* Separator page defaults      ohwnc*/ 08510000
/* (added SP410)                */ 08525000
/* Local printer (pre SP410 SEPLINE) */ 08530000
REMOTE=HALF), /* Remote printer (pre SP410 RSEPLINE)*/ 08540000
TRANS=YES, /* PN-Xlate for 1403/Rm.Pr      wnc*/ 08550000
UCS=0 /* Bypass UCS-Loading          wnc*/ 08570000
/*      */ 08590000
/*      */ 08600000
/***** */ 08600200
/*      *-----* */ 08600900
/*      | Dynamic PROCLIB definition | */ 08601600
/*      *-----* */ 08602300
/*      */ 08603000
PROCLIB(#####) DD(nn)=(DSNAME=, /* Concatenated DD num      aorhwnc*/ 08603700
/* Up to 44 character          ohwnc*/ 08604400
/* data set name              ohwnc*/ 08605100
VOLSER=#####, /* Volser for data set      ohwnc*/ 08605800
UNIT=#####), /* Unit info for data set ohwnc*/ 08606500
UNCONDITIONAL /* Create PROCLIB if error ohwnc*/ 08607200
/*      */ 08607900
/*      */ 08608600
/***** */ 08610000
/*      *-----* */ 08620000
/*      | Local Printers           | */ 08630000
/*      *-----* */ 08640000
/*      */ 08650000
/*      */ 08660000
/*      */ 08670000
/*      */ 08670000
PRT(nnnn) CKPTLINE=0, /* Max lines in a logical page ohwnc*/ 08700000
CKPTPAGE=100, /* Max seconds before a CKPT ohwnc*/ 08710000
Queue=AJ, /* Job class that can be chosen ohwnc*/ 08711000
/* (Alias for CLASS is QUEUE) */ 08712000
CREATOR=, /* User to choose ohwnc*/ 08715000
/* (added in SP420) */ 08720000
DEVFCB=#####, /* Specifies printer default FCB ohwnc*/ 08721000
/* (added in SP313) */ 08724000
FCB=#####, /* Forms control buffer image ohwnc*/ 08730000
/* (Alias for FCB is C) */ 08740000
FORMS=#####, /* Form identifier ohwnc*/ 08750000
HONORTRC=YES, /* TRC specification on OUTPUT JCL ohwnc*/ 08751000
/* statement will be honored */ 08754000
JOBNAME=, /* Job name to choose ohwnc*/ 08760000
LIMIT=0-*, /* Amount of output (in records) ohwnc*/ 08770000
MODE=JES, /* PRT is started in JES mode ohwnc*/ 08775000
PAUSE=NO, /* PRT won't pause between ohwnc*/ 08780000
/* datasets. */ 08785000
/* (modified SP420) */ 08790000
PRMODE=LINE, /* Process mode ohwnc*/ 08792000
RANGE=J?####, /* Job range to choose from ohwnc*/ 08794000
ROUTECD=LOCAL, /* Route code assigned to prt ohwnc*/ 08796000
/* (modified SP410) */ 08800000
SEP=YES, /* Separator pages printed ohwnc*/ 08805000
/* (modified SP420) */ 08810000
/*      */ 08815000
/*      */ 08820000
SPACE=, /* SPACING FOR PRINTER TO USE o*/ 08820000
/* (added in SP420) */ 08820000
SEPDS=NO, /* No separator pages between ohwnc*/ 08880000
/* output groups within same job */ 08885000
/* (modified SP420) */ 08890000
SETUP=HALT, /* Specifies optional printer ohwnc*/ 08890200
/* halt for setup */ 08890500
/* (added in SP313) */ 08890800
START=YES, /* printer comes up started hwnc*/ 08891100
/* (modified SP420) */ 08891400
TRACE=NO, /* No tracing on printer ohwnc*/ 08892000
/* output groups within same job */ 08895000
TRKCELL=NO, /* Records despoiled 1 at a time ohwnc*/ 08895300
/* (added by APAR OY01334) */ 08895600
TRANS=DEFAULT, /* Use PRINTDEF default for ohwnc*/ 08896000
/* translating line of print */ 08897000
/* (added SP430) */ 08898000
UCS=####, /* Print Train ohwnc*/ 08900000
/* For 3800, character arrangement table*/ 08910000
/* (Alias for UCS is T) */ 08920000
UCSVERIFY=NO, /* No UCS verification ohwnc*/ 08922000
/* (added in SP420) */ 08925000

```

```

UNIT=####, /* Unit address of device ohwnc*/ 08930000
VOLUME=(), /* VOLS that jobs are chosen from ohwnc*/ 08940000
WRITER=, /* Writer name assigned to PRT ohwnc*/ 08960000
WS=(W,R,Q,PRM,LIM/F,UCS,FCB) /* Work selection criteria ohwnc*/ 08970000
/* /* 08980000
/* 09010000
/* 09010200
| 3800 Printer statement - subset | 09010400
| of important parameters for | 09010600
| this device type | 09010800
*-----* 09011000
/* 09011100
PRT(NNNN) QUEUE=AJ, /* Job class that can be chosen ohwnc*/ 09011400
/* (Alias for CLASS is QUEUE) /* 09011800
DEVFCB=####, /* Specifies printer default FCB ohwnc*/ 09012000
/* (added in SP313) /* 09012200
FCB=####, /* Forms control buffer image ohwnc*/ 09012600
/* (Alias for FCB is C) /* 09012800
MODE=JES, /* PRT is started in JES mode ohwnc*/ 09013500
UNIT=####, /* Unit address of device ohwnc*/ 09014600
/* 09018100
/* The following parameters are /* 09020000
/* honored for 3800 defined printers. /* 09030000
/* 09040000
/* 09050000
/* 09052000
BURST=NO, /* Output is not burst ohwnc*/ 09054000
/* (modified SP420) /* 09054000
DEVFLASH=####, /* Default forms overlay ohwnc*/ 09056000
/* (added by APAR OY67855) /* 09058000
/* DEVFLASH and FLASH are /* 09060000
/* synonymous at initialization /* 09062000
/* but different for $T /* 09064000
FLASH=####, /* Initial forms overlay ohwnc*/ 09070000
/* (alias for FLASH is 0) /* 09080000
MARK=NO, /* No mark on sep page edge(MARK) ohwnc*/ 09090000
/* (modified SP420) /* 09092000
/* 3800 printer copy identification /* 09094000
/* module o*/ 09096000
/* (added in SP420) /* 09098000
SEPCHARS=DEFAULT /* Default char. table (SEPEXIST) hwnc*/ 09100000
/* (modified SP420) /* 09105000
/* 09150000
/* 09150100
/* 09150200
| FSS Printer statement - subset | 09150300
| of important parameters for | 09150400
| mode=FSS devices | 09150500
*-----* 09150500
/* 09150600
/* 09151000
/* 09151500
PRT(NNNN) QUEUE=BC, /* Job class that can be chosen ohwnc*/ 09152000
/* (Alias for CLASS is QUEUE) /* 09152000
CKPTMODE=SEC, /* Max seconds before a CKPT ohwnc*/ 09152500
/* (Added in SP420) /* 09152600
CKPTSEC=0, /* No. of seconds before a CKPT ohwnc*/ 09153000
COPYMARK=DATASET, /* Level of separation indicator ohwnc*/ 09153200
/* markings /* 09153500
/* (Added IN SP410 and via APAR /* 09153600
DEVFCB=####, /* Specifies printer default FCB ohwnc*/ 09154000
/* (added in SP313) /* 09154200
FSS=#####, /* Name of FSS that supports prt ohwnc*/ 09154500
FCB=####, /* Forms control buffer image ohwnc*/ 09156000
/* (Alias for FCB is C) /* 09156500
MODE=FSS, /* PRT is started in FSS mode ohwnc*/ 09157000
NPRO=300, /* Non process run out time (secs) ohwnc*/ 09280000
PLIM=0-*, /* Page limits for output ohwnc*/ 09320000
PRESELECT=YES, /* 3800 won't preselect output ohwnc*/ 09330000
/* (added SP420) /* 09340000
SETUP=HALT, /* Specifies optional printer ohwnc*/ 09350000
/* halt for setup /* 09355000
/* (added in SP313) /* 09360000
TRANS=DEFAULT, /* For 3800 default is no for ohwnc*/ 09361000
/* translating line of print /* 09362000
/* (added SP430) /* 09363000
UNIT=#### /* Unit address of device ohwnc*/ 09366000
/* 09370000
/* 09380000
/* 09390000
/* 09400000
| Punch Parameters | 09410000
*-----* 09420000
/* 09420000
PUNCHDEF CCWNUM=#, /* # CCWs / Punch Buffer wnc*/ 09430000
DBLBUFR=NO, /* Single Buffer Lcl Puns wnc*/ 09450000

```



```

RDBLBUFR=NO          /* Single Buffer Rmt Puns          wnc*/ 09470000
/*                    */ 09490000
/*                    */ 09500000
/*****                */ 09510000
/*                    */ 09520000
/*                    | Local Punches | 09530000
/*                    *-----* 09540000
/*                    */ 09550000
/*                    */ 09560000
PUN(nn) CKPTLINE=100, /* Alternate name for PUNnn: PUNCHnn */
/* No. of cards to punch per page ohwnc*/ 09570000
CKPTPAGE=1,          /* No. of pages pun'd before CKPT ohwnc*/ 09580000
Queue=BK,             /* Output class processed by PUN ohwnc*/ 09582000
/* (alias for QUEUE is CLASS) */ 09584000
/* (modified in SP420) */ 09586000
CREATOR=,             /* User to choose ohwnc*/ 09590000
/* (added in SP420) */ 09600000
FORMS=¢¢¢¢,          /* Forms identifier loaded in PUN ohwnc*/ 09620000
JOBNAME=,             /* Jobs selected by this PUN ohwnc*/ 09630000
LIMIT=0-*,           /* Range for output record no. ohwnc*/ 09640000
PAUSE=NO,             /* No pausing between DS groups ohwnc*/ 09670000
PRMODE=(LINE),        /* Process mode ohwnc*/ 09690000
RANGE=J?¢¢¢¢,        /* Job id range to select from ohwnc*/ 09700000
ROUTECD=LOCAL,       /* Route code(s) assigned to PUNn ohwnc*/ 09720000
/* (modified SP410) */ 09725000
SEP=YES,             /* Separator cards for ds groups ohwnc*/ 09726000
/* (modified in SP420) */ 09727000
SEPDS=NO,            /* No sep. for ds's within job ohwnc*/ 09730000
SETUP=HALT,          /* Specifies optional punch ohwnc*/ 09730500
/* halt for setup */ 09731000
/* (added in SP313) */ 09731500
START=YES,           /* PUN1 comes up started hwnc*/ 09732000
/* (modified SP420) */ 09735000
TRACE=YES,           /* Allow tracing ohwnc*/ 09736000
UNIT=¢¢¢¢,           /* Unit address of PUNnn ohwnc*/ 09740000
VOLUME=(),           /* VOLIDS of jobs to be punched ohwnc*/ 09750000
WRITER=,            /* Writer name assigned to PUNn ohwnc*/ 09770000
WS=(W,R,Q,PRM,LIM/F) /* Work selection criterion ohwnc*/ 09780000
/*                    */ 09785000
/*                    */ 09810000
/*                    */ 09820000
/*****                */ 09830000
/*                    */ 09840000
/*                    | Local Readers | 09850000
/*                    *-----* 09860000
/*                    */ 09870000
/*                    */ 09880000
RDR(NN) AUTH=(JOB=NO, /* Alternate name for RDRnn: READERnn */
/* Allow job cmds ownc*/ 09890000
DEVICE=NO,          /* Allow device cmds ownc*/ 09900000
SYSTEM=NO),         /* Allow system cmds ownc*/ 09902000
/* (pre-SP420 AUTH=0 for all 3 */ 09904000
/* subparameters) */ 09906000
CLASS=A,            /* Default job class ohwnc*/ 09910000
HOLD=NO,            /* Jobs not held after conv.(HOLD) ohwnc*/ 09920000
MSGCLASS=A,         /* Default message class ohwnc*/ 09930000
PRIORINC=0,         /* Increment to job's select prio. hwnc*/ 09960000
PRIOLIM=15,        /* Maximum selection priority hwnc*/ 09970000
PRTDEST=LOCAL,      /* Default print destination ohwnc*/ 09972000
/* (added in SP420) */ 09975000
PUNDEST=LOCAL,      /* Default punch destination ohwnc*/ 09980000
/* (added in SP420) */ 09990000
START=NO,           /* RDR doesn't come up started hwnc*/ 10020000
TRACE=NO,           /* No tracing on punch ohwnc*/ 10025000
UNIT=¢¢¢¢,          /* Unit address of reader ohwnc*/ 10030000
XEQDEST=¢¢          /* Default execution node ohwnc*/ 10040000
/*                    */ 10050000
/*****                */ 10060000
/*                    *-----* 10070000
/*                    | Recovery Options | 10080000
/*                    *-----* 10090000
/*                    */ 10100000
/*                    */ 10110000
/* Error Type */ 10115000
/* (pre-SP311 RECVOPTS TYPE=)
/* Recovery options for all ohwnc*/ 10130000
RECVOPTS(*) COUNT=2, /* Number of occurrences to count */ 10400000
/* NOTE: For IMAGE and OFFLOAD, COUNT= */ 10410000
/* defaults to 1. */ 10420000
INTERVAL=24         /* Interval (in hours) in which ohwnc*/ 10440000
/* errors are counted */ 10450000
/*                    */ 10460200
/*                    */ 10460400
/*****                */ 10460600
/*                    *-----* 10460800

```

	Console Display Command Routings	10461000
	Definition	10461200
	-----	10461400
		*/ 10461600
REDIRECT(¢¢¢¢? DA=¢¢,	/* Entry console of redirected	aohwnc*/ 10461800
	/* display commands	*/ 10462000
	/* (added SP410)	*/ 10462200
	/* The target console is identified in	*/ 10462400
	/* the following operands:	*/ 10462600
	/* DA - Display active jobs	ohwnc*/ 10462800
DCONNECT=¢¢,	/* Disp JES2 network connections	ohwnc*/ 10463000
DEF=¢¢,	/* Disp JES2 parameter definitions	ohwnc*/ 10463100
DF=¢¢,	/* Display forms queue	ohwnc*/ 10463200
DI=¢¢,	/* Display initiators	ohwnc*/ 10463600
DJ=¢¢,	/* Display job, stc, tsu info	ohwnc*/ 10464000
DN=¢¢,	/* Display queued jobs	ohwnc*/ 10464400
DNODE=¢¢,	/* Display NJE nodes	ohwnc*/ 10464600
DQ=¢¢,	/* Display number of queued jobs	ohwnc*/ 10464800
DSPL=¢¢,	/* Display SPOOL colums	ohwnc*/ 10465200
DU=¢¢,	/* Display units	ohwnc*/ 10465400
LJ=¢¢,	/* Display job output info	ohwnc*/ 10465500
LS=¢¢,	/* Display STC output info	ohwnc*/ 10465600
LT=¢¢	/* Display TSU output info	ohwnc*/ 10466000
/*		*/ 10470000
/*		*/ 10480000
/*	*****	10481000
/*	Request job ID job options	10482000
	-----	10483000
		*/ 10484000
		*/ 10485000
REQJOBID JESLOG=(NOSPIN)	/* Don't spin JESLOG data sets	ohwnc*/ 10486000
/*		*/ 10487000
/*		*/ 10488000
/*	*****	10490000
/*	*-----*	10500000
	Remote Parameters	10510000
	-----	10520000
		*/ 10530000
	-----	10540000
	RMT1 defines a BSC remote terminal	10550000
	A RMTnnnn statement with no operands	10560000
	defaults to a BSC remote terminal.	10570000
	-----	10580000
		*/ 10585000
	/* BSC remote terminal	*/ 10590000
RMT(1) DEVTYPE=2770,	/* Terminal type	aohwnc*/ 10592000
	/* (pre-SP311=2770)	*/ 10594000
BLOCK=YES,	/* Data record format	ohwnc*/ 10596000
	/* (pre-SP311=BLOCKED/UNBLOCK)	*/ 10598000
BUFEXPAN=0,	/* No additional buffer expansion	ohwnc*/ 10600000
	/* (pre-SP311=ABUFEX/NOABUFEX &	*/ 10610000
	/* BUFEX/NOBUFEX)	*/ 10615000
BUFSIZE=¢¢¢¢,	/* Largest buffer sent/received	ohwnc*/ 10620000
COMPRESS=NO,	/* No compression/expansion	ohwnc*/ 10630000
	/* (pre-SP311=COMP/NOCOMP)	*/ 10635000
CONDEST=1,	/* command response route code	ohwnc*/ 10640000
	/* default is this remote number	*/ 10641000
CONS=NO,	/* No operator console	ohwnc*/ 10642000
	/* (pre-SP311=CONSOLE/NOCON)	*/ 10645000
DISCINTV=0,	/* Idle time in secs before auto	ohwnc*/ 10650000
	/* disconnect (No timeout if DISCINT=0)	*/ 10660000
HTABS=NO,	/* No horizontal format control	ohwnc*/ 10670000
	/* (pre-SP311=NOTABS/TABS)	*/ 10675000
LINE=¢¢¢¢,	/* Line number dedicated to rmt	ohwnc*/ 10680000
SHARABLE=¢¢?	/* Line allowed to be shared by	ohwnc*/ 10681000
	/* other remotes	ohwnc*/ 10682000
LOCAL190=ACTION,	/* Oper. setup messages are	ohwnc*/ 10683000
	/* action	*/ 10686000
	/* (pre-SP311=INFO/ACTION)	*/ 10688000
LOGON=2,	/* LOGON DCT to be used by this	ohwnc*/ 10688400
	/* remote (added OS240)	*/ 10689000
MFORM=T,	/* Console msg. display info.	ohwnc*/ 10690000
MRF2780=NO,	/* No multi-record feature	ohwnc*/ 10700000
	/* (pre-SP311=MRF/NOMRF)	*/ 10710000
MSGPRT=YES,	/* Specifies remote console	ohwnc*/ 10712000
	/* message print option	*/ 10714000
	/* (added in SP313)	*/ 10716000
MULTILV=NO,	/* No multileaving	ohwnc*/ 10720000
	/* (pre-SP311=MULTI/HARDWARE)	*/ 10725000
NUMPRT=1,	/* No. of printers at remote	ohwnc*/ 10730000
NUMPUN=0,	/* No. of punches at remote	ohwnc*/ 10740000
NUMRDR=1,	/* No. of readers at remote	ohwnc*/ 10750000

```

PASSWORD=#####, /* Security password ohwnc*/ 10760000
RECFM=VARIABLE, /* Type of data record (fixed) ohwnc*/ 10765000
/* (pre-SP311=VARIABLE/FIXED) ohwnc*/ 10766000
RMT150=NO, /* Msg 150 sent to local operator ohwnc*/ 10767000
/* (pre-SP311=MSG150/NOMSG150) ohwnc*/ 10769000
ROUTECD=1, /* ROUTECODE - the default is the ohwnc*/ 10770000
/* nnn value of RMTnnn ohwnc*/ 10780000
TRANSPAR=NO, /* No text transparency ohwnc*/ 10810000
/* (pre-SP311=NOTRANSP/TRANSP) ohwnc*/ 10820000
WAITIME=## /* Time to wait after input ohwnc*/ 10830000
/* output before allowing input again ohwnc*/ 10840000
/* ohwnc*/ 10850000
/*-----*
| RMT2 defines a SNA remote terminal | 10870000
| LUTYPE1 must be specified to | 10880000
| indicate a SNA remote terminal. | 10890000
/*-----*/ 10900000
/* SNA terminal ohwnc*/ 10910000
RMT(2) DEVTYPE=LUTYPE1, /* Terminal type (no SNA default) ohwnc*/ 10911000
/* (pre-SP311=LUTYPE1) ohwnc*/ 10914000
AUTOLOG=YES, /* Automatic logon ohwnc*/ 10920000
BUFSIZE=256, /* Largest buffer sent/received ohwnc*/ 10930000
COMPACT=NO, /* No compaction ohwnc*/ 10940000
/* (pre-SP311=NOCMPCT/CMPCT) ohwnc*/ 10945000
COMPRESS=NO, /* No compression/expansion ohwnc*/ 10950000
/* (pre-SP311=NOCOMP/COMP) ohwnc*/ 10955000
CONDEST=2, /* Route code for cmd responses ohwnc*/ 10960000
/* default is nnn of RMTnnn ohwnc*/ 10970000
CONS=NO, /* No operator consoles ohwnc*/ 10980000
/* (pre-SP311=NOCON/CONSOLE) ohwnc*/ 10985000
DISCINTV=0, /* Idle time (in secs) before ohwnc*/ 10990000
/* auto disconnect ohwnc*/ 11000000
/* disconnect (No timeout if DISCINT=0) ohwnc*/ 11005000
LINE=####, /* Line number dedicated to rmt ohwnc*/ 11010000
LOCAL190=ACTION, /* Operator setup messages are ohwnc*/ 11013000
/* action (pre-SP311=SETUPACT/SETUPINF) ohwnc*/ 11016000
LUNAME=, /* Logical unit name of rmt term ohwnc*/ 11020000
MFORM=T, /* Display time stamp, job name + ohwnc*/ 11022000
/* job id for this remote ohwnc*/ 11025000
MSGPRT=YES, /* Specifies remote console ohwnc*/ 11028000
/* message print option ohwnc*/ 11031000
/* (added in SP313) ohwnc*/ 11034000
NUMPRT=1, /* No. of printers at remote ohwnc*/ 11040000
NUMPUN=0, /* No. of punches at remote ohwnc*/ 11050000
NUMRDR=1, /* No. of readers at remote ohwnc*/ 11060000
PASSWORD=#####, /* Security password ohwnc*/ 11070000
RMT150=NO, /* Msg. 150 sent to local ohwnc*/ 11075000
/* operator. ohwnc*/ 11076000
/* (pre-SP311=MSG150/NOMSG150) ohwnc*/ 11078000
ROUTECD=2, /* Routecode - the default is the ohwnc*/ 11080000
/* nnn value of RMTnnn ohwnc*/ 11090000
SETUP=MSG, /* Setup requirements (PDIR) ohwnc*/ 11100000
/* (pre-SP311=SETUPMSG/SETUPHDR) ohwnc*/ 11110000
START=NO, /* Do not automatically start ohwnc*/ 11132000
WAITIME=1 /* Wait time for operator ohwnc*/ 11134000
/* ohwnc*/ 11140000
/* ohwnc*/ 11150000
/****** ohwnc*/ 11160000
/*-----*
| Remote Printers | 11180000
/*-----*/ 11190000
/* ohwnc*/ 11200000
R(n).PR(n) ASIS=NO, /* Suppress Extraneous Ejects ohwnc*/ 11205000
CCTL=YES, /* Carriage cntl chars. (SNA only) ohwnc*/ 11210000
/* (added in SP420) ohwnc*/ 11215000
CKPTLINE=0, /* Max lines in a logical page ohwnc*/ 11220000
CKPTPAGE=1, /* Max pages before a CKPT ohwnc*/ 11230000
QUEUE=AJ, /* Output classes processed ohwnc*/ 11240000
/* Alias for QUEUE is Class ohwnc*/ 11250000
CMPCT=NO, /* Compaction capabilities(SNA) ohwnc*/ 11251000
COMPRESS=NO, /* Compression/expansion ohwnc*/ 11252000
COMPACT=0, @@ /* Compaction table (SNA) ohwnc*/ 11253000
CREATOR=, /* Choose all users ohwnc*/ 11255000
/* (added in SP420) ohwnc*/ 11260000
DEVFCB=####, /* Specifies printer default FCB ohwnc*/ 11261000
/* (added in SP313) ohwnc*/ 11262000
EJECT=YES, /* Eject after start ohwnc*/ 11265000
/* (added in SP420) ohwnc*/ 11270000
FCB=####, /* Forms control buffer image ohwnc*/ 11300000
/* (Alias for FCB is C) ohwnc*/ 11310000
FCBLOAD=NO, /* FCB support provided ohwnc*/ 11320000
/* (modified in SP420) ohwnc*/ 11325000

```

```

FORMS=####, /* Form identifier ohwnc*/ 11330000
JOBNAME=, /* name of jobs to be selected ohwnc*/ 11340000
LIMIT=0-*, /* Amount of output (in records) ohwnc*/ 11350000
LRECL=120, /* For data transmitted to (SNA) ohwnc*/ 11390000
PLIM=0-*, /* Amount of output (in pages) ohwnc*/ 11390500
PRMODE=LINE, /* Process mode ohwnc*/ 11391000
PRWIDTH=120, /* Chars. printer per line ohwnc*/ 11392000
RANGE=J?####, /* Job range to choose from ohwnc*/ 11393000
ROUTECD=RN, /* Route code assigned to prt ohwnc*/ 11394000
SELECT=PRINT##, /* Device type and subaddress to ohwnc*/ 11395000
/* which output is queued. */ 11396000
SEP=YES, /* Separator pages printed (NOSEP) ohwnc*/ 11400000
/* (modified in SP420) */ 11405000
SEPDS=NO, /* No separator pages between ohwnc*/ 11490000
/* output groups within same job */ 11500000
SETUP=HALT, /* Specifies optional printer ohwnc*/ 11500200
/* halt for setup */ 11500400
/* (added in SP313) */ 11500600
START=YES, /* remote printer comes up started hwnc*/ 11500800
SUSPEND=YES, /* Prt-interrupt feature allowed ohwnc*/ 11501000
TRACE=YES, /* Enable Tracing ohwnc*/ 11501200
TRANS=DEFAULT, /* Use PRINTDEF default for ohwnc*/ 11502000
/* translating line of print */ 11504000
/* (added SP430) */ 11506000
UCS=####, /* Print Train ohwnc*/ 11510000
/* For 3800, character arrangement table*/ 11520000
/* (Alias for UCS is T) */ 11530000
VOLUME=(), /* VOLS that jobs are chosen from ohwnc*/ 11540000
WRITER=, /* Writer name assigned to PRT ohwnc*/ 11560000
WS=(W,R,Q,PRM,LIM/F) 11570000
/* Work selection criteria ohwnc*/ 11580000
/* */ 11610000
/* */ 11620000
/***** */ 11630000
/* *-----* */ 11640000
| Remote Punches | 11650000
*-----* */ 11660000
/* */ 11670000
R(n).PU(n) CCTL=YES, /* Carriage cntrl chars.(SNA only) ohwnc*/ 11680000
/* (modified in SP420) */ 11685000
CKPTLINE=100, /* No. of cards to punch per page ohwnc*/ 11690000
CKPTPAGE=1, /* No. of pages pun'd before CKPT ohwnc*/ 11710000
QUEUE=BK, /* Output class processed by PUN ohwnc*/ 11720000
/* (alias for QUEUE is CLASS) */ 11730000
CMPCT=NO, /* Compaction capabilities(SNA) ohwnc*/ 11760000
COMPRESS=NO, /* Compression/expansion ohwnc*/ 11770000
COMPACT=0, @@ /* Compaction table (SNA) ohwnc*/ 11780000
CREATOR=, /* User to choose ohwnc*/ 11790000
/* (added in SP420) */ 11800000
FLUSH=YES, /* Blank card after each dataset ohwnc*/ 11810000
/* (added in SP420) */ 11820000
FORMS=####, /* Forms identifier loaded ohwnc*/ 11825000
JOBNAME=, /* Jobs selected by this PUN ohwnc*/ 11830000
LIMIT=0-*, /* Range for output record no. ohwnc*/ 11842000
LRECL=80, /* For data transmitted to (SNA) ohwnc*/ 11850000
PRMODE=(LINE), /* Process mode ohwnc*/ 11851000
RANGE=J?####, /* Job id range to select from ohwnc*/ 11852000
ROUTECD=####? /* Route code(s) assigned to PUNn ohwnc*/ 11853000
/* (modified SP410) */ 11854000
SELECT=PUN##, /* Device type and subaddress to ohwnc*/ 11855000
/* which output is queued. */ 11856000
SEP=YES, /* Separator cards for ds groups ohwnc*/ 11860000
/* (modified in SP420) */ 11865000
SEPDS=NO, /* No set. for DS's within job ohwnc*/ 11940000
/* (modified in SP420) */ 11942000
SETUP=HALT, /* Specifies optional punch ohwnc*/ 11942400
/* halt for setup */ 11943000
/* (added in SP313) */ 11944000
START=YES, /* Rn.PUn is initially started hwnc*/ 11944500
SUSPEND=YES, /* Punch interrupt allowed (BSC) ohwnc*/ 11945000
/* (modified in SP420) */ 11945500
TRACE=NO, /* No tracing on punch ohwnc*/ 11946000
VOLUME=(), /* VOLIDS of jobs to be punched ohwnc*/ 11950000
WRITER=, /* Writer name assigned to PUNn ohwnc*/ 11970000
WS=(W,R,Q,PRM,LIM/F) 11980000
/* Work selection criterion ohwnc*/ 11990000
/* */ 12020000
/* */ 12030000
/***** */ 12040000
/* *-----* */ 12050000
| Remote Readers | 12060000
*-----* */ 12070000

```

```

R(n).RD(n) CLASS=A, /* Default job class ohwnc*/ 12080000
HOLD=NO, /* Jobs not held after conversion ohwnc*/ 12090000
MSGCLASS=A, /* Default message class ohwnc*/ 12110000
PRIORINC=0, /* Increment to get select prio. wnc*/ 12120000
PRIOLIM=15, /* Maximum selection priority wnc*/ 12150000
PRTDEST=LOCAL, /* Default print destination ohwnc*/ 12160000
/* (added in SP420) */ 12162000
PUNDEST=LOCAL, /* Default punch destination ohwnc*/ 12165000
/* (added in SP420) */ 12170000
START=NO, /* RDR doesn't come up started ohwnc*/ 12230000
TRACE=YES, /* Enable tracing on punch ohwnc*/ 12233000
XEQDEST=LOCAL /* Default execution destination ohwnc*/ 12234000
/* (modified SP420) */ 12236000
/* 12237000
/* 12237100
/* 12237200
/***** 12237300
/* *-----* 12237400
| Network Socket definitions | 12237500
*-----* 12237600
12237700
SOCKET(#####) IPADDR=#####, /* IP address ohwnc*/ 12237800
PORT=nnnnn, /* Related Port ohwnc*/ 12237900
LINE=nnnnn, /* Related line ohwnc*/ 12238000
NODE=nnnnn /* Related node ohwnc*/ 12238100
NETSRV=nnn, /* Server to use ohwnc*/ 12238200
REST=nnnnn /* Resistance ohwnc*/ 12238300
12238500
/* 12240000
/***** 12245000
/* *-----* 12250000
| SMF Definitions | 12260000
*-----* 12270000
12280000
SMFDEF BUFNUM=5, /* Number of SMF Buffers wnc*/ 12290000
BUFWARN=80 /* Warning Threshold % ohwnc*/ 12310000
/* 12350000
/* 12360000
/***** 12370000
/* *-----* 12380000
| Spool Definitions | 12390000
*-----* 12400000
12410000
SPOOLDEF BUFSIZE=3992, /* Maximum Buffer Size c*/ 12420000
DSNAME=SYS1.HASPACE, /* Spool Data Sets' Name c*/ 12440000
FENCE=(ACTIVE=NO), /* Don't Force to Minimum volume oc*/ 12460000
SPOOLNUM=32, /* Max. number of SPOOL volumes oc*/ 12500000
TGFSIZE=30, /* 30 Buffers/Track Group wnc*/ 12580000
TGSPACE=(MAX=16288, /* Fits TGMs into 4K page oc*/ 12582000
/* (TGNUM prior to SP510) */ 12588000
WARN=80), /* Usage warning threshold % onc*/ 12600000
/* (TGWARN prior to SP510) */ 12610000
TRKCELL=3, /* 3 Buffers/Track-cell c*/ 12620000
VOLUME=SPOOL /* Spool Volume Serial oc*/ 12640000
/* 12660000
/* 12670000
/***** 12670400
/* *-----* 12671200
| SSI Definitions | 12672000
*-----* 12673600
12674400
SSI(nnn) TRACE=NO /* Tracing is not active for this ownc*/ 12675200
/* SSI function */ 12676800
/* 13050000
/* 13060000
/***** 13070000
/* *-----* 13070700
| Subtask definition | 13071600
| added in SP313 | 13072500
*-----* 13073400
13074300
SUBTDEF GSUBNUM=10 /* Specify the number of general hwnc*/ 13075200
/* purpose subtask */ 13076100
/* 13077000
/* 13077900
/***** 13078800
/* *-----* 13080000
| TP (NJE/RJE) Characteristics | 13090000
*-----* 13100000
13110000
/* TP buffer definition hwnc*/ 13120000
/* Characteristics for buffers below */ 13130000

```

```

/*      16 meg line (added SP410) */ 13140000
TPDEF AUTOINTV=32, /* autologon timer interval ohwnc*/ 13145000
      BSCBUF=(LIMIT=####, /* BELOWBUF= pre-OS270 */ 13146000
/* NUMBER OF BUFFERS ohwnc*/ 13150000
/* (pre-SP311 BUFNUM=##) */ 13160000
      SIZE=520, /* Size of Buffers in bytes hwnc*/ 13170000
/* (pre-SP410 BUFSIZE=) */ 13180000
      WARN=80), /* Warning Threshold % ohwnc*/ 13190800
/* (pre-SP311 BUFWARN) */ 13191500
/* Characteristics for extended buffers */ 13192200
/* (added SP410) */ 13192900
/* EXTBUF= pre-OS270 ohwnc*/ 13193100
      SNABUF=(LIMIT=####, /* Number of buffers ohwnc*/ 13193600
/* (pre-SP311 BUFNUM=##) */ 13194300
      SIZE=400, /* Size of Buffers in bytes hwnc*/ 13195000
/* (pre-SP410 BUFSIZE=) */ 13195700
      WARN=80), /* Warning Threshold % ohwnc*/ 13197800
/* (pre-SP311 BUFWARN) */ 13198500
      MBUFSIZE=400, /* Multi-leaving buffer size hwnc*/ 13200000
      RMTMSG=100, /* Max. # Msgs Queued to remote ohwnc*/ 13220000
      RMTNUM=####, /* Highest allowed RMT (for $ADD) hwnc*/ 13230000
      SESSIONS=(LIMIT=####, 13280000
/* Max number of sessions ohwnc*/ 13288000
/* (pre-OS130 SESSION) */ 13296000
      WARN=##) /* Warning threshold ohwnc*/ 13304000
/* (added OS130) */ 13312000
/* */ 13320000
/* */ 13330000
/***** */ 13340000
/* *-----* */ 13350000
/* | Start/Stop Trace Identifiers | 13360000
/* *-----* */ 13370000
/* */ 13380000
TRACE(n) START=NO /* Whether or not to collect trace hwnc*/ 13400000
/* data for specified id(s) */ 13405000
/* */ 13470000
/* */ 13480000
/***** */ 13480400
/* *-----* */ 13480800
/* | $TRACE Facility | 13481200
/* *-----* */ 13481600
/* */ 13482000
TRACEDEF ACTIVE=NO, /* Whether or not to start the wnc*/ 13484800
/* trace facility */ 13485200
/* LOG=(START=NO, /* Whether or not to format and ownnc*/ 13486000
/* add data to trace log dataset */ 13486400
/* SIZE=500, /* Max size of trace log dataset ownnc*/ 13487200
/* CLASS=A), /* Trace log dataset output class ownnc*/ 13488000
/* PAGES=9, /* Number of 4K pages per table @R10P037*/ 13488200
/* TABLES=3, /* Number of trace tables ownnc*/ 13488400
/* TABWARN=80 /* Warning Threshold % ownnc*/ 13488600
/***** */ 13490000
/* *-----* */ 13500000
/* | Delete a job from the system | 13510000
/* *-----* */ 13520000
/* */ 13530000
ZAPJOB /* Console mode only. See JES2 */ 13540000
/* initialization and tuning reference */ 13550000
/* */ 13560000
/* */ 13570000
/***** */ 13870000
/* */ 13880000
/* *-----* */ 13890000
/* | ADDED Initialization Parameters | 13900000
/* *-----* */ 13910000
/* */ 13920000
/* The following initialization parameters have been added to JES2 */ 13930000
/* in the JES2 SP4.1.0 release. Review the general sections */ 13940000
/* above for details on the parameters. */ 13941000
/* */ 13944000
/* */ 13950000
/* APPL LOGMODE,LINE */ 13953000
/* BUFDEF BELOWBUF,EXTBUF */ 13956000
/* CKPTDEF VERSIONS,CKPTDCON */ 13957000
/* CONDEF SCOPE,RDIRAREA */ 13960000
/* CONNECT PATHMGR,STATUS,STATIC,CES,TIME */ 13970000
/* JOBCLASS OUTDISP */ 13972000
/* LOADMOD RMODE */ 13985000
/* NJEDEF TIMETOL,OWNNAME */ 13990000
/* NODE(nnnn) LINE,LOGMODE,PATHMGR,PRIVATE,SUBNET,TRACE */ 14000000
/* OFFn.SR OUTDISP */ 14010000
/* OFFn.ST OUTDISP */ 14020000
/* OUTCLASS OUTDISP */

```

```

/*      OUTDEF      SEGLIM,OUTTIME      */ 14020900
/*      PRINTDEF    SEPPAGE              */ 14021800
/*      STCCCLASS   OUTDISP              */ 14022700
/*      TPDEF       BELOWBUF,EXTBUF      */ 14023600
/*      TSUCLASS    OUTDISP              */ 14024500
/*                                          */ 14025400
/* The following initialization parameters have been added to JES2 */ 14026300
/* in the JES2 SP4.2.0 release. Review the general sections      */ 14027200
/* above for details on the parameters.                          */ 14028100
/*                                          */ 14029000
/*      INTRDR      BATCH                 */ 14029900
/*      NJEDEF      MAXHOP                 */ 14030800
/*      OFFn.JR     CREATOR                */ 14031700
/*      OFFn.JT     CREATOR                */ 14032600
/*      OFFn.SR     CREATOR                */ 14033500
/*      OFFn.ST     CREATOR                */ 14034400
/*      OUTDEF      PRYORATE               */ 14035300
/*      PCEDEF      SPINNUM                */ 14036200
/*      PRTn        CREATOR                */ 14037100
/*      PUNn        CREATOR                */ 14038000
/*      RnPRnn      CREATOR,EJECT          */ 14038900
/*      RnPUnn      CREATOR,FLUSH          */ 14039800
/*      RnRDnn      PRTDEST,PUNDEST,XEQDEST,SYSAFF */ 14040700
/*      RnRDnn      PRTDEST,PUNDEST,XEQDEST,SYSAFF */ 14041600
/*      RDRn        PRTDEST,PUNDEST,XEQDEST,SYSAFF */ 14042500
/*                                          */ 14043400
/* The following initialization parameters have been added to JES2 */ 14044300
/* in the JES2 SP4.3.0 release. Review the general sections      */ 14045200
/* above for details on the parameters.                          */ 14046100
/*                                          */ 14047000
/*      DESTDEF     LOCALNUM,NDEST,RDEST,RMDEST,RMTDEST,UDEST, */ 14047900
/*                                          */ 14048800
/*      DESTID      PRIMARY                */ 14049700
/*      LINEnnn     JRNUM,JTNUM,SRNUM,STNUM */ 14050600
/*      Ln.STn      WS,LIMIT,PLIM          */ 14051500
/*      NODEn       ENDNODE,SENTREST       */ 14052400
/*      NJEDEF      MAILMSG                 */ 14053300
/*      PRTn        TRANS                   */ 14054200
/*      Rn.PRnn     TRANS                   */ 14055100
/*                                          */ 14056000
/* The following initialization parameters have been added to JES2 */ 14056900
/* in the JES2 SP5.1.0 release. Review the general sections      */ 14057800
/* above for details on the parameters.                          */ 14058700
/*                                          */ 14059600
/*      CKPTDEF     CKPT1=(STRNAME=),CKPT2=(STRNAME=),OPVERIFY, */ 14060500
/*                                          */ 14061400
/*                                          */ 14062300
/*      CONDEF      CMDNUM                  */ 14063200
/*      MASDEF      OWNMEMB,XCFGRPNM       */ 14064100
/*      MEMBER      HDRBUF                  */ 14065000
/*      NJEDEF      SPOOL                   */ 14065900
/*      OPTSDEF     TGLOST,TGSPACE         */ 14066800
/*      SPOOLDEF    TGLOST,TGSPACE         */ 14067700
/*                                          */ 14068600
/* The following initialization parameters have been added to JES2 */ 14069500
/* in the JES2 SP5.2.0 release. Review the general sections      */ 14070400
/* above for details on the parameters.                          */ 14071300
/*                                          */ 14072200
/*      DEBUG       CKPT,MISC,STORAGE,VERSION */ 14073100
/*      JOBCLASS    QHELD                   */ 14074000
/*      RMTnnnn     SHARABLE                 */ 14074900
/*      TPDEF       RMTNUM                   */ 14075800
/*                                          */ 14076700
/* The following initialization parameters have been added to JES2 */ 14077600
/* in the JES2 OS1.1.0 release. Review the general sections      */ 14078500
/* above for details on the parameters.                          */ 14079400
/*                                          */ 14080300
/*      DEBUG       SYMREC                   */ 14081200
/*      OFFLOAD     ARCHIVE,VALIDATE        */ 14082100
/*                                          */ 14083000
/* The following initialization parameters have been added to JES2 */ 14083900
/* in the JES2 OS1.3.0 release. Review the general sections      */ 14084800
/* above for details on the parameters.                          */ 14085700
/*                                          */ 14086600
/*      JOBDEF      DUPL_JOB                 */ 14087500
/*      Ln.STn      OUTDISP                  */ 14088400
/*      TPDEF       SESSIONS=(LIMIT=,WARN=) */ 14089300
/*                                          */ 14090200
/* The following initialization parameters have been added to JES2 */ 14091100
/* in the JES2 OS2.4.0 release. Review the general sections      */ 14092000
/* above for details on the parameters.                          */ 14092900
/*                                          */ 14093800

```

```

/*      JOBCLASS  MODE,MSGCLASS,CONDPURG,XEQCOUNT      */ 14077500
/*      Ln.JTn    WS,LIMIT                                */ 14077800
/*      CKPTSPACE BERTNUM,BERTWARN                      */ 14078100
/*      NODE      LOGON                                  */ 14078400
/*      APPL      LOGON                                  */ 14078700
/*      RMTnnnn   LOGON                                  */ 14079000
/*                                                     */ 14079300
/* The following initialization parameters have been added to JES2 */ 14079600
/* in the JES2 OS2.7.0 release. Review the general sections      */ 14079900
/* above for details on the parameters.                          */ 14080200
/*                                                     */ 14080500
/*      JOBDEF     CNVT_ENQ                              */ 14080800
/*                                                     */ 14081100
/* The following initialization parameters have been added to JES2 */ 14081400
/* in the JES2 OS2.10 release. Review the general sections       */ 14081700
/* above for details on the parameters.                          */ 14082000
/*                                                     */ 14082300
/*      JOBCLASS   SCHENV                                */ 14082600
/*      ZAPJOB     all                                   */ 14082900
/*                                                     */ 14083200
/* The following initialization parameters have been added to JES2 */ 14083500
/* in the JES2 z/OS 1.2 release. Review the general sections     */ 14083800
/* above for details on the parameters.                          */ 14084100
/*                                                     */ 14084400
/*      INCLUDE    DSNAME,VOLSER,UNIT                   */ 14084700
/*      JOBCLASS   JESLOG                                */ 14085000
/*      PROCLIB    DD,DSNAME,VOLSER,UNIT,UNCONDITIONAL    */ 14085300
/*      REQJOBID   JESLOG                                */ 14085600
/*                                                     */ 14086200
/* The following initialization parameters have been added to JES2 */ 14086500
/* in the JES2 z/OS 1.7 release. Review the general sections     */ 14086800
/* above for details on the parameters.                          */ 14087100
/*                                                     */ 14087400
/*      NETSRV                                           */ 14087700
/*      SOCKET                                           */ 14088000
/*      LINE       UNIT=TCP                              */ 14088300
/*      NODE       NETSRV,SIGNON,DIRECT                  */ 14088600
/*      OFFLOAD    CRTIME                                */ 14088700
/*                                                     */ 14088900
/******/ 14089200
/*      */ 14089500
/*      */ 14090000
/******/ 14100000
/*      */ 14110000
/*      *-----* 14120000
/*      | CHANGED Initialization Parameters | 14130000
/*      *-----* 14140000
/*      */ 14150000
/* The following initialization parameters have been changed in    */ 14160000
/* the JES2 SP4.1.0 release. Review the general sections above   */ 14170000
/* for details on the parameters, and for changes that were made */ 14180000
/* by releases previous to JES2 SP4.1.0.                         */ 14190000
/*      */ 14200000
/*      CONNECT NODEA      -now may specify symbolic name      */ 14201000
/*      CONNECT NODEB      -now may specify symbolic name      */ 14202000
/*      JOBCLASS REGION,TIME - new defaults                    */ 14203000
/*      NODE      PASSWORD - now includes SEND= and VERIFY=    */ 14204000
/*      NODE      REST      - Maximum changed                  */ 14205000
/*      OFFn.JT  ROUTECDE   - now accepts destid or userid value */ 14206000
/*      OFFn.JR  ROUTECDE   - now accepts destid or userid value */ 14207000
/*      OFFn.ST  ROUTECDE   - now accepts destid or userid value */ 14208000
/*      OFFn.ST  WS         - now includes OUTDISP specification */ 14209000
/*      OFFn.SR  ROUTECDE   - now accepts destid or userid value */ 14210000
/*      OFFn.SR  WS         - now includes OUTDISP specification */ 14211000
/*      OFFn.SR  MOD        - now includes OUTDISP specification */ 14212000
/*      PRTnnnn  ROUTECDE   - now accepts destid or userid value */ 14213000
/*      PUNnnnn  ROUTECDE   - now accepts destid or userid value */ 14214000
/*      Rn.PRnn  ROUTECDE   - now accepts destid or userid value */ 14215000
/*      Rn.PUnn  ROUTECDE   - now accepts destid or userid value */ 14216000
/*      OUTDEF   JOENUM     - maximum value specified increased */ 14217000
/*      STCCCLASS REGION,TIME - increased defaults              */ 14218000
/*      TSUCLASS REGION,TIME - increased defaults              */ 14218900
/*      */ 14219200
/* The following initialization parameters have been changed in    */ 14219800
/* the JES2 SP4.2.0 release. Review the general sections above   */ 14220700
/* for details on the parameters, and for changes that were made */ 14221600
/* by releases previous to JES2 SP4.2.0.                         */ 14222500
/*      */ 14222700
/*      ESTLNCT  NUM        - Maximum changed                  */ 14222900
/*      ESTPAGE  NUM,INT    - Maximum changed                  */ 14223100
/*      ESTPUN   NUM,INT    - Maximum changed                  */ 14223300
/*      INTRDR   AUTH       - No longer a numeric value        */ 14223500

```



```

/*      LINEn   UNIT      - Unit can be dynamically added      */ 14223700
/*      PRtn    UNIT      - Unit can be dynamically added      */ 14223900
/*      PRtn    FORMS     - Up to 8 forms can be specified     */ 14224100
/*      PUNn    UNIT      - Unit can be dynamically added      */ 14224300
/*      RDRn    AUTH      - No longer a numeric value          */ 14224500
/*      RDRn    UNIT      - Unit can be dynamically added      */ 14224700
/*                                                                */ 14224900
/* The following initialization parameters have been changed in  */ 14225100
/* the JES2 SP4.3.0 release. Review the general sections above */ 14225300
/* for details on the parameters, and for changes that were made */ 14225500
/* by releases previous to JES2 SP4.3.0.                        */ 14225700
/*                                                                */ 14225900
/*      LOADMOD  RMODE     - Is now display only, set function  */ 14226100
/*                                                                */ 14226300
/*                                                                */ 14226500
/*                                                                */ 14226700
/* The following initialization parameters have been changed in  */ 14226900
/* the JES2 SP5.2.0 release. Review the general sections above */ 14227100
/* for details on the parameters, and for changes that were made */ 14227300
/* by releases previous to JES2 SP5.2.0.                        */ 14227500
/*                                                                */ 14227700
/*      JOBDEF   JOBWARN   - cannot be changed on a             */ 14228100
/*      JOBDEF   JNUMWARN   single member warm start           */ 14228500
/*      JOBDEF   PRtyHIGH   or a quick start                    */ 14228900
/*      JOBDEF   PRtyLOW    */ 14229300
/*      JOBDEF   PRtyRATE   */ 14229600
/*                                                                */ 14230000
/*      OPTSDEF   SPOOL     - default changed to NOVALIDATE     */ 14232000
/*                                                                */ 14234000
/*      OUTDEF    JOEWARN   - cannot be changed on a             */ 14236000
/*      OUTDEF    PRtyHIGH   single member warm start           */ 14238000
/*      OUTDEF    PRtyLOW    or a quick start                    */ 14240000
/*      OUTDEF    PRyORATE   */ 14242000
/*                                                                */ 14244000
/*      SPOOLDEF   TGSPACE=(TGWARN) - cannot be changed on a    */ 14246000
/*                                                                */ 14248000
/*                                                                */ 14250000
/*                                                                */ 14252000
/*      TPDEF     BELOWBUF=(SIZE) - minimum and default changed */ 14254000
/*                                                                */ 14254100
/* The following initialization parameters have been changed in  */ 14254200
/* the JES2 OS1.3.0 release. Review the general sections above */ 14254300
/* for details on the parameters, and for changes that were made */ 14254400
/* by releases previous to JES2 OS1.3.0.                        */ 14254500
/*                                                                */ 14254600
/*      PUNn      FORMS     - Up to 8 forms can be specified     */ 14254700
/*      Rn.PRn    FORMS     - Up to 8 forms can be specified     */ 14254800
/*      Rn.PUn    FORMS     - Up to 8 forms can be specified     */ 14254900
/*      OFFn.ST   FORMS     - Up to 8 forms can be specified     */ 14255000
/*      OFFn.SR   FORMS     - Up to 8 forms can be specified     */ 14255100
/*                                                                */ 14256000
/* The following initialization parameters have been changed in  */ 14256200
/* the JES2 OS2.4.0 release. Review the general sections above */ 14256400
/* for details on the parameters, and for changes that were made */ 14256600
/* by releases previous to JES2 OS2.4.0.                        */ 14256800
/*                                                                */ 14257000
/*      JOBCLASS  all       - Can only be changed on a cold      */ 14257200
/*                                                                */ 14257400
/*                                                                */ 14257420
/* The following initialization parameters have been changed in  */ 14257440
/* the JES2 z/OS 1.7 release. Review the general sections above */ 14257460
/* for details on the parameters, and for changes that were made */ 14257480
/* by releases previous to JES2 z/OS 1.7                        */ 14257500
/*                                                                */ 14257520
/*      NODE      NAME      - Can be modified when the node     */ 14257540
/*                                                                */ 14257560
/*                                                                */ 14257580
/*                                                                */ 14257600
/******/ 14258000
/*                                                                */ 14260000
/*                                                                */ 14262000
/******/ 14264000
/*                                                                */ 14270000
/*                                                                */ 14280000
/*                                                                */ 14290000
/*                                                                */ 14300000
/*                                                                */ 14310000
/* The following initialization parameters have been deleted.    */ 14320000
/*                                                                */ 14340000
/* parameter      release      reason/new action                */ 14350000
/* -----      -      -      -      */ 14355000
/* INTRDR  RDINUM  z/OS 1.7  No longer supported                */ 14355200

```

```

/* CKPTDEF APPLCOPY      z/OS 1.2      No longer supported      */ 14355300
/* SPOOLDEF TGBPERVL     OS2.10        No longer required      */ 14355500
/* TPDEF BELOWBUF        OS2.7.0       Replaced by BSCBUF      */ 14355600
/* TPDEF EXTBUF          OS2.7.0       Replaced by SNABUF      */ 14355700
/* STCCCLASS             OS2.4.0       Replaced by JOBCLASS(STC) */ 14356000
/* TSUCLASS             OS2.4.0       Replaced by JOBCLASS(TSU) */ 14357000
/* TPDEF SESSION         OS1.3.0       Replaced by SESSIONS=(LIMIT=) */ 14358000
/* SPOOLDEF TGLOST       SP5.2.0       No longer required      */ 14360000
/* CKPTDEF CKPTDCON      SP5.1.0       No longer required      */ 14361000
/* MASDEF OWNSID         SP5.1.0       Replaced by OWNMEMB     */ 14361200
/* MASDEF SID            SP5.1.0       Replaced by MEMBER statement */ 14361400
/* SPOOLDEF TGWARN       SP5.1.0       Replaced by TGSPACE=(WARN=) */ 14361600
/* SPOOLDEF TGNUM        SP5.1.0       Replaced by TGSPACE=(MAX=) */ 14361800
/* LOADMOD RMODE         SP4.3.0       Now displayable only    */ 14362000
/* BUFDEF BUFNUM         SP4.1.0       Replaced by LIMIT        */ 14362500
/* BUDEF BUFWARN         SP4.1.0       Replaced by WARN         */ 14363000
/* BUFDEF BUFFREE        SP4.1.0       Replaced by FREE         */ 14364000
/* CONDEF BSPACE         SP4.1.0       No longer supported      */ 14365000
/* JOBCLASS CONDPURG     SP4.1.0       Replaced by JOBCLASS OUTDISP= */ 14365600
/* NJEDEF NATNUM         SP4.1.0       No longer required      */ 14366200
/* OFFn.SR DS=ANY        SP4.1.0       Replaced by OUTDISP=     */ 14366800
/* OFFn.SR DSHOLD=       SP4.1.0       Replaced by MOD=OUTDISP= */ 14367400
/* OFFn.ST DS=           SP4.1.0       Replaced by OUTDISP=     */ 14368000
/* OUTCLASS CONDPURG     SP4.1.0       Replaced by OUTCLASS OUTDISP= */ 14368600
/* OUTCLASS HOLD         SP4.1.0       Replaced by OUTCLASS OUTDISP= */ 14369200
/* OUTCLASS MSGHOLD      SP4.1.0       Replaced by OUTCLASS OUTDISP= */ 14369800
/* PRINTDEF RSEPLINE     SP4.1.0       Replaced by PRINTDEF SEPPAGE= */ 14370400
/* PRINTDEF SEPLINE      SP4.1.0       Replaced by PRINTDEF SEPPAGE= */ 14370600
/* TPDEF BUFNUM          SP4.1.0       Replaced by LIMIT        */ 14370800
/* TPDEF BUFWARN         SP4.1.0       Replaced by WARN         */ 14371000
/* TPDEF BUFSIZE         SP4.1.0       Replaced by SIZE         */ 14371200
/* TPDEF BUFFREE         SP4.1.0       Replaced by FREE         */ 14371400
/* JOBCLASS XBATCH       SP3.1.3       No longer needed for XBM  */ 14371600
/* JOBDEF XBATCH         SP3.1.3       No longer needed for XBM  */ 14372100
/* CONDEF MSGID          SP3.1.1       JES2 Assumes YES         */ 14372400
/* HASPSSSM              SP3.1.1       Use STEPLIB              */ 14373000
/* NODE BSC/SNA          SP3.1.1       No longer differentiate   */ 14373500
/* PRINTRnn              SP3.1.1       Form of PRTnn no longer supported */ 14374000
/* SPOOLDEF RECINCR      SP3.1.1       No longer needed        */ 14375000
/* TPDEF WAIT            SP3.1.1       use RMT(*) WAITIME=       */ 14375500
/* TRACE                 SP3.1.1       Replaced by TRACEDEF and TRACE(n) */ 14376000
/* CKPTDEF DSNAME        SP2.2.0       Replaced by CKPTDEF CKPTn=(DSN=) */ 14380000
/* CKPTDEF DUPLEX        SP2.2.0       Replaced by CKPTDEF MODE=,DUPLEX= */ 14390000
/* CKPTDEF PRIMARY       SP2.2.0       Replaced by CKPTDEF CKPT1=(VOL=) */ 14400000
/* CKPTDEF RECONFIG      SP2.2.0       Cannot be specified in initdeck */ 14405000
/* SPOOLDEF TGBENUM      SP2.2.0       Replaced by SPOOLDEF TGBPERVL */ 14410000
/* TPDEF RMTNUM          SP2.2.0       Determined from highest RMTn Stmt */ 14420000
/*                                     (RMTNUM added back in SP5.2.0) */ 14430000
/*                                     */ 14580000
/* ***** */ 14590000
/*                                     */ 14600000
/*                                     */ 14610000
/* ***** */ 14620000
/*                                     */ 14630000
/* NOTE: Changing ANY of the following parameters will prevent a */ 14640000
/* JES2 Warmstart; they can ONLY be changed on a COLDSTART      */ 14650000
/* ***** */ 14660000
/*                                     */ 14670000
/*                                     */ 14680000
/* NJEDEF OWNNODE=       */ 14700000
/* SPOOLDEF BUFSIZE=, DSNAME=, TRKCELL=, VOLUME=                */ 14720000
/*                                     */ 14740000
/* NOTE: If VOLUME= is a 5 character prefix, it can be changed   */ 14750000
/* to a 4 character prefix using an operator command (for        */ 14760000
/* example it can be changed from SPOOL to SP00). Any other     */ 14770000
/* changes require a COLDSTART.                                   */ 14780000
/* ***** */ 99999999

```

Appendix B. Obsolete keywords

The following shows a list of obsolete keywords for JES2 initialization statements or commands.

<i>Table 100. Obsolete keywords for JES2 initialization statements or commands</i>		
Initialization statement or command	Obsolete keyword	Replacement value
CKPTDEF	APPLCOPY	N/A
INIT(nnnn)	DRAIN	START=NO
INTRDR	RDINUM	N/A
JOBCLASS	STCCCLASS	JOBCLASS(STC)
JOBCLASS	TSUCLASS	JOBCLASS(TSU)
JOBDEF	JCLERR	N/A
MASDEF	SID	MEMBER statement
MASDEF	OWNSID	OWNMEMB
MASDEF	AUTOESYS	AUTOEMEM
NODE(nnn)	SNA	N/A
NODE(nnn)	BSC	N/A
NODE(nnn)	TCPIP	N/A
OUTDEF	BROADCAST	N/A
OUTDEF	LOCALNUM	DESTDEF LOCALNUM
PRT(nnn)	DRAIN	START=NO
PRT(nnn)	NOMARK	MARK=NO
PRT(nnn)	NOPAUSE	PAUSE=NO
PRT(nnn)	NOSEP	SEP=NO
PRT(nnn)	NOSEPDS	SEPDS=NO
PRT(nnn)	SEPDEFLT	SEPCHARS=DEFAULT
PRT(nnn)	SEPEXIST	SEPCHARS=CURRENT
PUN(nnn)	DRAIN	START=NO
PUN(nnn)	NOPAUSE	PAUSE=NO
PUN(nnn)	NOSEP	SEP=NO
PUN(nnn)	NOSEPDS	SEPDS=NO
RDR(nn)	AUTO	START
SPOOLDEF	RELADDR	N/A
SPOOLDEF	TGBPERVL	N/A
SPOOLDEF	TGNUM	TGSPACE=(MAX=)
SPOOLDEF	TGWARN	TGSPACE=(WARN=)

Table 100. Obsolete keywords for JES2 initialization statements or commands (continued)

Initialization statement or command	Obsolete keyword	Replacement value
TPDEF	BELOWBUF	BSCBUF
TPDEF	EXTBUF	SNABUF

Table 101. Obsolete keywords for JES2 commands

Command	Obsolete keyword	Replacement value
\$CO	NDISP and ODISP	OUTDISP and /OUTDISP
\$DO	NDISP and ODISP	OUTDISP and /OUTDISP
\$PO	NDISP and ODISP	OUTDISP and /OUTDISP
\$TO	NDISP and ODISP	OUTDISP and /OUTDISP

Appendix C. Accessibility

Accessible publications for this product are offered through [IBM Documentation for z/OS \(www.ibm.com/docs/en/zos\)](http://www.ibm.com/docs/en/zos).

If you experience difficulty with the accessibility of any z/OS documentation see [How to Send Feedback to IBM](#) to leave documentation feedback.

Notices

This information was developed for products and services that are offered in the USA or elsewhere.

IBM may not offer the products, services, or features discussed in this document in other countries. Consult your local IBM representative for information on the products and services currently available in your area. Any reference to an IBM product, program, or service is not intended to state or imply that only that IBM product, program, or service may be used. Any functionally equivalent product, program, or service that does not infringe any IBM intellectual property right may be used instead. However, it is the user's responsibility to evaluate and verify the operation of any non-IBM product, program, or service.

IBM may have patents or pending patent applications covering subject matter described in this document. The furnishing of this document does not grant you any license to these patents. You can send license inquiries, in writing, to:

*IBM Director of Licensing
IBM Corporation
North Castle Drive, MD-NC119
Armonk, NY 10504-1785
United States of America*

For license inquiries regarding double-byte character set (DBCS) information, contact the IBM Intellectual Property Department in your country or send inquiries, in writing, to:

*Intellectual Property Licensing
Legal and Intellectual Property Law
IBM Japan Ltd.
19-21, Nihonbashi-Hakozakicho, Chuo-ku
Tokyo 103-8510, Japan*

The following paragraph does not apply to the United Kingdom or any other country where such provisions are inconsistent with local law: INTERNATIONAL BUSINESS MACHINES CORPORATION PROVIDES THIS PUBLICATION "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF NON-INFRINGEMENT, MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. Some states do not allow disclaimer of express or implied warranties in certain transactions, therefore, this statement may not apply to you.

This information could include technical inaccuracies or typographical errors. Changes are periodically made to the information herein; these changes will be incorporated in new editions of the publication. IBM may make improvements and/or changes in the product(s) and/or the program(s) described in this publication at any time without notice.

This information could include missing, incorrect, or broken hyperlinks. Hyperlinks are maintained in only the HTML plug-in output for IBM Documentation. Use of hyperlinks in other output formats of this information is at your own risk.

Any references in this information to non-IBM websites are provided for convenience only and do not in any manner serve as an endorsement of those websites. The materials at those websites are not part of the materials for this IBM product and use of those websites is at your own risk.

IBM may use or distribute any of the information you supply in any way it believes appropriate without incurring any obligation to you.

Licensees of this program who wish to have information about it for the purpose of enabling: (i) the exchange of information between independently created programs and other programs (including this one) and (ii) the mutual use of the information which has been exchanged, should contact:

*IBM Corporation
Site Counsel
2455 South Road*

Poughkeepsie, NY 12601-5400
USA

Such information may be available, subject to appropriate terms and conditions, including in some cases, payment of a fee.

The licensed program described in this document and all licensed material available for it are provided by IBM under terms of the IBM Customer Agreement, IBM International Program License Agreement or any equivalent agreement between us.

Any performance data contained herein was determined in a controlled environment. Therefore, the results obtained in other operating environments may vary significantly. Some measurements may have been made on development-level systems and there is no guarantee that these measurements will be the same on generally available systems. Furthermore, some measurements may have been estimated through extrapolation. Actual results may vary. Users of this document should verify the applicable data for their specific environment.

Information concerning non-IBM products was obtained from the suppliers of those products, their published announcements or other publicly available sources. IBM has not tested those products and cannot confirm the accuracy of performance, compatibility or any other claims related to non-IBM products. Questions on the capabilities of non-IBM products should be addressed to the suppliers of those products.

All statements regarding IBM's future direction or intent are subject to change or withdrawal without notice, and represent goals and objectives only.

This information contains examples of data and reports used in daily business operations. To illustrate them as completely as possible, the examples include the names of individuals, companies, brands, and products. All of these names are fictitious and any similarity to the names and addresses used by an actual business enterprise is entirely coincidental.

COPYRIGHT LICENSE:

This information contains sample application programs in source language, which illustrate programming techniques on various operating platforms. You may copy, modify, and distribute these sample programs in any form without payment to IBM, for the purposes of developing, using, marketing or distributing application programs conforming to the application programming interface for the operating platform for which the sample programs are written. These examples have not been thoroughly tested under all conditions. IBM, therefore, cannot guarantee or imply reliability, serviceability, or function of these programs. The sample programs are provided "AS IS", without warranty of any kind. IBM shall not be liable for any damages arising out of your use of the sample programs.

Terms and conditions for product documentation

Permissions for the use of these publications are granted subject to the following terms and conditions.

Applicability

These terms and conditions are in addition to any terms of use for the IBM website.

Personal use

You may reproduce these publications for your personal, noncommercial use provided that all proprietary notices are preserved. You may not distribute, display or make derivative work of these publications, or any portion thereof, without the express consent of IBM.

Commercial use

You may reproduce, distribute and display these publications solely within your enterprise provided that all proprietary notices are preserved. You may not make derivative works of these publications, or

reproduce, distribute or display these publications or any portion thereof outside your enterprise, without the express consent of IBM.

Rights

Except as expressly granted in this permission, no other permissions, licenses or rights are granted, either express or implied, to the publications or any information, data, software or other intellectual property contained therein.

IBM reserves the right to withdraw the permissions granted herein whenever, in its discretion, the use of the publications is detrimental to its interest or, as determined by IBM, the above instructions are not being properly followed.

You may not download, export or re-export this information except in full compliance with all applicable laws and regulations, including all United States export laws and regulations.

IBM MAKES NO GUARANTEE ABOUT THE CONTENT OF THESE PUBLICATIONS. THE PUBLICATIONS ARE PROVIDED "AS-IS" AND WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESSED OR IMPLIED, INCLUDING BUT NOT LIMITED TO IMPLIED WARRANTIES OF MERCHANTABILITY, NON-INFRINGEMENT, AND FITNESS FOR A PARTICULAR PURPOSE.

IBM Online Privacy Statement

IBM Software products, including software as a service solutions, ("Software Offerings") may use cookies or other technologies to collect product usage information, to help improve the end user experience, to tailor interactions with the end user, or for other purposes. In many cases no personally identifiable information is collected by the Software Offerings. Some of our Software Offerings can help enable you to collect personally identifiable information. If this Software Offering uses cookies to collect personally identifiable information, specific information about this offering's use of cookies is set forth below.

Depending upon the configurations deployed, this Software Offering may use session cookies that collect each user's name, email address, phone number, or other personally identifiable information for purposes of enhanced user usability and single sign-on configuration. These cookies can be disabled, but disabling them will also eliminate the functionality they enable.

If the configurations deployed for this Software Offering provide you as customer the ability to collect personally identifiable information from end users via cookies and other technologies, you should seek your own legal advice about any laws applicable to such data collection, including any requirements for notice and consent.

For more information about the use of various technologies, including cookies, for these purposes, see IBM's Privacy Policy at ibm.com/privacy and IBM's Online Privacy Statement at ibm.com/privacy/details in the section entitled "Cookies, Web Beacons and Other Technologies," and the "IBM Software Products and Software-as-a-Service Privacy Statement" at ibm.com/software/info/product-privacy.

Policy for unsupported hardware

Various z/OS elements, such as DFSMSdfp, JES2, and MVS, contain code that supports specific hardware servers or devices. In some cases, this device-related element support remains in the product even after the hardware devices pass their announced End of Service date. z/OS may continue to service element code; however, it will not provide service related to unsupported hardware devices. Software problems related to these devices will not be accepted for service, and current service activity will cease if a problem is determined to be associated with out-of-support devices. In such cases, fixes will not be issued.

Minimum supported hardware

The minimum supported hardware for z/OS releases identified in z/OS announcements can subsequently change when service for particular servers or devices is withdrawn. Likewise, the levels of other software products supported on a particular release of z/OS are subject to the service support lifecycle of those

products. Therefore, z/OS and its product publications (for example, panels, samples, messages, and product documentation) can include references to hardware and software that is no longer supported.

- For information about software support lifecycle, see: [IBM Lifecycle Support for z/OS \(www.ibm.com/software/support/systemsz/lifecycle\)](http://www.ibm.com/software/support/systemsz/lifecycle)
- For information about currently-supported IBM hardware, contact your IBM representative.

Programming Interface Information

This publication documents information that is NOT intended to be used as programming Interfaces of JES2.

Trademarks

IBM, the IBM logo, and ibm.com are trademarks or registered trademarks of International Business Machines Corp., registered in many jurisdictions worldwide. Other product and service names might be trademarks of IBM or other companies. A current list of IBM trademarks is available on the Web at [Copyright and Trademark information \(www.ibm.com/legal/copytrade.shtml\)](http://www.ibm.com/legal/copytrade.shtml).

Microsoft, Windows, Windows NT, and the Windows logo are trademarks of Microsoft Corporation in the United States, other countries, or both.

Java™ and all Java-based trademarks and logos are trademarks or registered trademarks of Oracle and/or its affiliates.

The registered trademark Linux® is used pursuant to a sublicense from the Linux Foundation, the exclusive licensee of Linus Torvalds, owner of the mark on a worldwide basis.

UNIX is a registered trademark of The Open Group in the United States and other countries.

Index

Special Characters

- \$T DESTid command
 - second-level destination [138](#)
 - two-level DESTids [139](#)

Numerics

- 3800 printer
 - burster option for [325](#)
 - character arrangement table [301](#)
 - marking separator page for [318](#)
 - specifying FCB [300](#)
 - specifying FCB for [314](#)

A

- accessibility
 - contact IBM [471](#)
- ADVANCED_FORMAT
 - SPOOLDEF [412](#)
- ALLCKPT subparameter
 - on CKPTDEF statement [108](#)
- AMASPZAP format
 - support for functional subsystem [219](#), [379](#), [432](#)
- APPL initialization statement [91](#)
- assistive technologies [471](#)
- asterisk
 - range
 - asterisk [2](#)
 - JES2 interpretation [2](#)
 - upper limit [2](#)
- AUTH parameter
 - on NODE statement [236](#)
- AUTOCMD on CONDEF [112](#)
- AUTOCMD parameter [112](#)
- AUTOEMEM parameter
 - initialization parameter on MASDEF statement [213](#)
- automatic command [112](#)
- automatic mode
 - specifying for local statement reader [372](#)

B

- BADTRACK statement
 - initialization statement [94](#)
- batch class
 - defining [161](#)
- BELOWBUF parameter
 - on BUFDEF statement [96](#)
- BERTNUM on CKPTSPACE [108](#)
- BERTNUM parameter [108](#)
- BERTWARN parameter
 - initialization parameter on CKPTSPACE [109](#)
- blank truncation
 - specification [287](#)

- BLNKTRNC parameter
 - parameter on OUTCLASS statement [287](#)
- BSC (binary synchronous communication) RJE workstation
 - specify characteristic [389](#)
- BSCBUF parameter
 - on TPDEF statement
 - number required [425](#)
- BUFDEF statement
 - initialization statement [95](#)
- buffer
 - specifying
 - above 16 megabytes in virtual storage [96](#), [425](#)
 - below 16 megabytes in virtual storage [96](#), [425](#)
 - number of console message [113](#)
 - number of teleprocessing [424](#)
 - number required [95](#)
 - size of JES2 [412](#)
 - size of multileaving [426](#)
 - SMF buffer use [406](#)
 - specifying warning message
 - \$HASPO50 [113](#)
 - buffer quantity [405](#)
 - buffering option
 - specifying double
 - local printer [299](#)
 - local statement punch [336](#)
 - remote printer [301](#)
 - remote statement punch [336](#)
- BUFNUM on SMFDEF [405](#)
- BUFNUM parameter
 - initialization parameter on CONDEF [113](#)
- BUFNUM parameter on CONDEF [113](#)
- BUFSIZE on SPOOLDEF statement
 - initialization parameter [412](#)
 - performance consideration [412](#)
- burster-trimmer-stacker option [325](#)

C

- carriage control tape
 - specifying
 - for local printer [319](#)
 - for remote printer [350](#)
 - initial [319](#)
- CCWNUM on PUNCHDEF
 - initialization parameter [336](#)
- CCWNUM parameter on PRINTDEF [299](#)
- channel command word
 - specify [298](#)
 - specifying
 - maximum number for local card punch [336](#)
 - maximum number for local printer [298](#)
- character arrangement table
 - specifying [301](#)
- character set [1](#)
- character specification for initialization statement [1](#)
- checkpoint

- checkpoint (*continued*)
 - specifying
 - space definition [108](#)
- checkpoint data set
 - integrity
 - printer options for [314](#), [344](#)
 - punch options for [330](#), [357](#)
 - recommendation for [103](#)
 - specifying log size [103](#), [104](#)
 - specifying volume containing [103](#)
- checkpoint reconfiguration
 - operator verification [106](#)
- checkpoint space
 - definition [109](#)
- CKPTSPACE statement
 - initialization statement [108](#)
- Class
 - \$D I [154](#), [246](#), [251](#)
 - \$D Init [154](#), [246](#), [251](#)
- CMDNUM on CONDEF
 - initialization parameter [113](#)
- command
 - buffer
 - number [113](#)
 - character [113](#)
 - identifier
 - JES2 [114](#)
 - output
 - REDIRECT initialization statement [376](#)
 - range
 - asterisk [2](#)
 - JES2 interpretation [2](#)
 - upper limit [2](#)
 - syntax diagrams [10](#)
- commands statement
 - conventions used in describing [1](#)
- COMPACT parameter
 - on APPL statement [93](#)
 - on NODE statement [236](#)
- COMPACT statement
 - initialization [109](#)
- compression/expansion feature
 - specifying
 - for BSC RJE workstation [394](#)
 - for SNA remote station [402](#)
- CONCHAR on CONDEF
 - initialization parameter [113](#)
- CONDitional parameter
 - on PROCLIB statement [305](#)
- CONNECT on LINE(nnnnn) statement
 - initialization parameter [195](#), [203](#), [207](#)
- CONNECT on SOCKET statement
 - initialization parameter [409](#)
- CONNECT parameter
 - on APPL statement [94](#)
 - on NJEDEF statement [227](#)
 - on NODE statement [224](#), [236](#)
- CONNect statement
 - initialization statement [115](#)
- connection
 - network
 - defining [115](#)
 - resistance value [115](#)
 - specifying [115](#)
- console
 - redirect display output [376](#)
- console message buffer
 - caution in determining number [113](#)
 - number [113](#)
 - usage [113](#)
- contact
 - z/OS [471](#)
- control offload behavior
 - issue \$dollar.HASP595 [282](#)
- control statement
 - /*DEST [133](#)
 - /*EDS [141](#)
 - /*JOBPARM
 - ESTBYTE relation [141](#)
 - ESTLNCT relation [143](#)
 - line count exceeded [343](#)
 - LINECT on PRINTDEF relation [299](#)
 - RESTART parameter [177](#)
 - /*NETACCT [220](#)
 - /*OUTPUT
 - line count exceeded [343](#)
 - local printer route code [333](#)
 - NIFLASH parameter [300](#)
 - requires NIFLASH parameter [325](#)
 - /*PRIORITY
 - job execution priority [185](#)
 - PRTYJECL parameter on JOBDEF [183](#)
 - /*ROUTE
 - local printer [333](#)
- CTC (channel-to-channel)
 - NJE connection [198](#)

D

- D INITINFO
 - example [118](#)
 - format [118](#)
 - parameter description [118](#)
- D MODule (jxxxxxxx) statement [121](#)
- data set
 - JES2 checkpoint [103](#)
 - JES2 checkpoint log size [103](#), [104](#)
 - JES2 checkpoint, alternate [101](#)
 - JES2 spool [103](#)
 - JES2 spool log size [103](#)
- data sets limit [290](#)
- DBLBUFR on PRINTDEF statement
 - initialization parameter [299](#)
- DBLBUFR on PUNCHDEF
 - initialization parameter [336](#)
- DEBUG statement
 - as a performance factor [131](#)
- dedicated line
 - specifying
 - for SNA NJE session [93](#)
- defective track specification [94](#)
- define general purpose subtask
 - initialization statement for [417](#), [420](#), [423](#)
- define members of a MAS
 - initialization statement for [217](#)
- define NJE header
 - HDRBUF parameter [227](#)
- define NJE trailer

- define NJE trailer (*continued*)
 - HDRBUF parameter [227](#)
- definition [108](#)
- demand setup [289](#)
- description [157](#)
- DESTid initialization statement
 - DESTid subscript [136](#)
 - initialization statement [137](#)
- DESTid subscript
 - DESTid initialization statement [136](#)
- destination identifier [137](#)
- display initialization information [118](#)
- DISPLEN parameter
 - initialization parameter on CONDEF [114](#)
- DISPMAX parameter
 - initialization parameter on CONDEF [114](#)
- DMNDSET on OUTDEF
 - initialization parameter [289](#)
- DORMANCY on MASDEF [213](#)
- DORMANCY parameter
 - initialization parameter on MASDEF [213](#)
- double buffering option
 - specify
 - for remote printer [301](#)
 - specifying
 - for local printer [299](#)
 - for local statement punch [336](#)
 - for remote statement punch [336](#)
- DSLIMIT on OUTDEF
 - initialization parameter [290](#)
- DSNAME on SPOOLDEF
 - initialization parameter [412](#)
- DSName parameter
 - on INCLUDE statement [152](#)
 - on PROCLIB statement [305](#)
- DSNMASK on SPOOLDEF
 - initialization parameter [413](#)
- DUPLEX parameter
 - initialization parameter on CKPTDEF [103](#)

E

- ENDNODE parameter
 - on NODE statement [236](#)
- ESTBYTE initialization statement [141](#)
- estimated spool utilization for output exceeded [141](#)
- ESTIME statement
 - default estimated execution time [142](#)
 - initialization statement [142](#)
- ESTLNCT statement
 - initialization statement [143](#)
- ESTPAGE statement
 - initialization statement [144](#)
- ESTPUN statement
 - initialization statement [145](#)
- event trace
 - initialization parameters for [431](#)
 - initialization statement for [428](#), [430](#)
 - log data set size [431](#)
 - trace table page size [431](#)
- execution
 - associated with priority [185](#)
- execution batch scheduling
 - associated with job class [161](#)

- exit point and exit routine association [146](#)
- EXIT(nnn)
 - initialization statement [146](#)
- EXTBUF parameter
 - on BUFDEF statement [96](#)

F

- FCB (forms control buffer)
 - specifying for 3800 printer [314](#)
 - specifying for local impact printer [314](#)
 - specifying for remote printer [345](#)
- FCB on PRINTDEF statement
 - initialization parameter [299](#)
 - specify initial printer
 - for an impact printer [299](#)
 - specifying initial FCB
 - for a nonimpact printer [300](#)
- FENCE on SPOOLDEF
 - initialization parameter [413](#)
- flash forms ID [300](#)
- Forms parameter
 - specifying for printer [315](#)
- FORMS parameter
 - on PRT(nnnnn) statement [315](#)
- FSS (functional subsystem)
 - definition [149](#)
- FSS initialization statement [149](#)
- Function
 - using
 - parameter ranges [1](#)
- functional subsystem
 - no patching facility support [219](#), [379](#), [432](#)

G

- GDGBIAS parameter [171](#)
- general purpose subtask definition
 - initialization statement for [417](#), [420](#), [423](#)
- group
 - definition
 - initialization statement [151](#)
- GRPDEF statement
 - initialization statement [151](#)

H

- HDRBUF on NJEDEF statement
 - initialization parameter [227](#)
- hold jobs
 - in held class [176](#)
- HOLD parameter
 - initialization parameter on MASDEF [214](#)
 - on NODE statement [237](#)
- HONORLIM parameter
 - initialization parameter on INTRDR [159](#)
- HTTP_NOTIFY
 - \$T JOBDEF [182](#)

I

- I(nnnn) initialization statement [153](#)
- impact printer

- impact printer (*continued*)
 - specifying FCB for [314](#), [345](#)
 - specifying print chain for [302](#)
- INCLUDE statement
 - initialization statement [151](#)
- INITDEF initialization statement [155](#)
- initialization
 - SPOOLDEF statement [410](#)
 - SUBMITRDR statement [422](#)
 - TPDEF statement [423](#)
 - ZAPJOB statement [439](#)
- initialization parameter [213](#)
- initialization parameter on CKPTSPACE [108](#)
- initialization parameter on CONDEF [112](#)
- initialization statement
 - character set [1](#)
 - conventions used in describing [1](#)
 - D OPTsdef [129](#)
 - ESTIME statement [142](#)
 - JES2 initialization
 - APPL statement [91](#)
 - L(nnnnn).JT(n) [186](#)
 - L(nnnnn).ST(n) [187](#)
 - LNE(nnnnn) - BSC [190](#)
 - LNE(nnnnn) - SNA [198](#)
 - LNE(nnnnn) - TCP/IP [205](#)
 - OFF(n).SR [255](#)
 - OFF(n).ST [267](#)
 - OFFLOAD(n) [278](#)
 - OPTsdef statement [283](#)
 - OUTCLASS(v) [285](#)
 - OUTPRTY(n) [292](#)
 - PCEDEF statement [295](#)
 - POLICYLIB(xxxxxxxx) statement [296](#)
 - PRINTDEF statement [298](#)
 - PUNCHDEF statement [336](#)
 - range
 - asterisk [2](#)
 - JES2 interpretation [2](#)
 - upper limit [2](#)
 - REDIRECT statement [376](#)
- initialization statement and parameter summary tables [15](#)
- initiator
 - initialization statement [153](#), [155](#)
 - logical
 - define characteristic [155](#)
 - specify characteristic [153](#), [155](#)
- input
 - definition [156](#), [160](#)
 - initialization statement [156](#), [160](#)
- input definition [156](#), [160](#)
- INPUTDEF initialization statement [156](#), [160](#)
- internal reader [157](#)
- INTRDR statement [157](#)
- IPADDR on SOCKET statement
 - initialization parameter [409](#)

J

- JECL
 - definition [159](#)
 - initialization statement [159](#)
- jecl definition [159](#)
- JECLDEF initialization statement [159](#)

- JES2
 - specifying characteristic [1](#)
- JES2 buffer
 - specifying size [412](#)
- JES2 initialization [108](#), [112](#), [157](#), [405](#)
- JESLOG parameter
 - on REQJOBID statement [387](#)
- job
 - class
 - batch [161](#)
 - journal processing for [173](#)
 - log processing [174](#)
 - parameters to specify processing [161](#)
 - queuing a job [161](#)
 - specify characteristic [161](#)
 - specify number [227](#)
 - SYSOUT class limit [161](#)
 - definition
 - initialization statement [179](#)
 - journal
 - processing for job class [173](#)
 - log
 - printing for job class [174](#)
 - output scheduling priority
 - vs quantity of output [292](#)
 - queuing [182](#), [183](#)
 - receiver [195](#), [203](#), [227](#)
 - specify maximum number [182](#)
 - specifying
 - use [183](#)
 - transmitter
 - network [196](#), [203](#), [207](#), [227](#)
- job entry subsystem
 - command identifier [114](#)
- JOB statement
 - support for PRTY parameter [291](#)
- job transmitter
 - work selection characteristics [186](#)
- JOBCLASS(class) initialization statement [161](#)
- JOBCLASS(STC) initialization statement [161](#)
- JOBCLASS(TSU) initialization statement [161](#)
- JOBDEF statement
 - initialization statement [179](#)
- JOBNUM on JOBDEF
 - as a performance factor [182](#)
- JOBNUM parameter
 - initialization parameter on JOBDEF [182](#), [183](#)
- JOE (job output element)
 - number to be generated [290](#)
 - performance factor [113](#)
 - required for JES2 [290](#)
 - use [290](#)
- JOENUM parameter
 - on OUTDEF statement [290](#)
- JOENUM parameter on OUTDEF
 - as a performance factor [290](#)
- JOEWARN parameter
 - on OUTDEF statement [290](#)
- JRNUM on LINE(nnnnn)
 - initialization parameter [195](#), [203](#)
- JRNUM on NJEDEF
 - initialization parameter [227](#)
- JTNUM on LINE(nnnnn)
 - initialization parameter [196](#), [203](#), [207](#)

JTNUM on NJEDEF

initialization parameter [227](#)

K

keyboard

navigation [471](#)

PF keys [471](#)

shortcut keys [471](#)

L

L(nnnnn).JT(n)

initialization statement [186](#)

L(nnnnn).ST(n)

initialization statement [187](#)

length

message option [114](#)

line

dedicated [395](#), [403](#)

network [195](#), [203](#), [227](#)

network job receiver [195](#), [203](#), [227](#)

network job transmitter [196](#), [203](#), [207](#), [227](#)

NJE (network job entry) [190](#), [198](#)

page limit [190](#), [198](#)

RJE (remote job entry) [190](#), [198](#)

specifying characteristics for BSC RJE workstation [389](#)

specifying characteristics for SNA remote station [403](#)

SYSOUT transmitter characteristics [187](#)

TCP/IP [205](#)

transmitter characteristics [186](#)

line limit

specifying for job transmitters [186](#)

specifying for SYSOUT transmitters [189](#)

LINE on SOCKET statement

initialization parameter [409](#)

LINE parameter

on APPL statement [94](#)

on NODE statement [237](#), [238](#)

LINE(nnnnn) - BSC

initialization statement [190](#)

LINE(nnnnn) - SNA

initialization statement [198](#)

LINE(nnnnn) - TCP/IP

initialization statement [205](#)

LINECCHR parameter

ASCII line control character

LINE initialization statement [196](#)

LINECT on PRINTDEF statement

initialization parameter

LINECT parameter [299](#)

LINENUM on NJEDEF

initialization parameter [228](#)

LNE(nnnnn) - BSC

initialization statement [190](#)

LNE(nnnnn) - SNA

initialization statement [198](#)

LNE(nnnnn) - TCP/IP

initialization statement [205](#)

load installation exit routine [196](#)

LOADmod(jxxxxxx) statement

initialization statement [209](#)

local printer

local printer (*continued*)

LIMIT parameter

selection of output by amount [315](#)

local reader statement

default punch destination

for jobs entered at local reader [404](#)

LOCKOUT on MASDEF

initialization parameter [215](#)

log data set size

specifying [431](#)

logical initiator

specify characteristic [153](#), [155](#)

logical line

defining [190](#), [198](#)

LOGMODE parameter

on NODE statement [238](#)

LOGON(nnn)

initialization statement [210](#)

LOGSIZE parameter

initialization parameter on CKPTDEF [103](#), [104](#)

LRECL (logical record length)

on remote punch [359](#)

M

MAILMSG on NJEDEF

initialization parameter [228](#)

make jobs eligible for restart

RESTART on MASDEF [216](#)

make jobs eligible to restart

AUTOEMEM on MASDEF statement [213](#)

manual mode

specifying

for local statement reader [372](#)

MAS members

sharing initialization statements [12](#)

MAS members definition

initialization statement for [217](#)

MASDEF initialization statement [213](#)

MASMSG parameter

initialization parameter on CONDEF [114](#)

MAXHOP on NJEDEF

initialization parameter [228](#)

maximum dormancy [213](#)

MEMBER initialization statement [217](#)

message

buffer

specifying number [113](#)

usage percentage [113](#)

delay time for a remote console [227](#)

length

specifying [114](#)

specifying maximum length [114](#)

queued for spool [114](#)

specifying length [114](#)

module

display information [118](#)

multi-access spool configuration

lock-out warning time [215](#)

message limit [227](#)

minimum dormancy [213](#)

minimum queue control interval [214](#)

providing balanced member work load [213](#)

N

- NAME parameter
 - on NODE statement [238](#)
 - on PROCLIB statement [306](#)
- NAME patching statement [219](#)
- NAME statement
 - JES2 initialization [219](#)
 - JES2 patching facility [219](#)
 - NAME initialization statement [219](#)
- navigation
 - keyboard [471](#)
- NETACCT statement
 - initialization parameter [220](#)
- NETSRV on SOCKET statement
 - initialization parameter [409](#)
- NETSRV parameter
 - on NODE statement [239](#)
- network
 - JES2 account number [220](#)
 - job receiver quantity [195](#), [203](#), [227](#)
 - job transmitter quantity [196](#), [203](#), [207](#), [227](#)
 - local account number [220](#)
 - node quantity
 - specifying maximum [228](#)
 - SYSOUT receiver quantity [197](#), [204](#), [208](#), [229](#)
 - SYSOUT transmitter quantity [197](#), [204](#), [208](#), [229](#)
- network accounting
 - characteristic [220](#)
 - initialization statement [220](#)
- NIFCB on PRINTDEF
 - initialization parameter [300](#)
- NIFLASH on PRINTDEF
 - initialization parameter [300](#)
- NIUCS on PRINTDEF
 - initialization parameter [301](#)
- NJE
 - considerations when using system symbols [13](#)
- NJE (network job entry)
 - application ID for [210](#)
 - command identifier [114](#)
 - identifying to VTAM [210](#)
 - password for [210](#)
- NJE connection
 - CTC (channel-to-channel) [198](#)
- node
 - JES2 number [228](#)
 - maximum path [228](#)
 - resistance to job flow [229](#)
 - resistance tolerance [229](#)
- NODE on SOCKET statement
 - initialization parameter [409](#)
- NODE(xxxxxxxx)
 - initialization statement [230](#)
- NodeA parameter
 - on CONNect statement [116](#)
- NodeB parameter
 - on CONNect statement [117](#)
- NODENUM on NJEDEF
 - initialization parameter [228](#)
- NODENUM parameter
 - on NJEDEF statement [228](#)
- number of SMF [405](#)

O

- Obsolete keywords
 - JES2 initialization statements
 - JES2 commands [469](#)
- OFF(n).SR
 - initialization statement [255](#)
- OFF(n).ST
 - initialization statement [267](#)
- offload device
 - defining
 - initialization statement [278](#)
- offload SYSOUT receiver
 - defining
 - initialization statement [255](#)
- offload SYSOUT transmitter
 - defining
 - initialization statement [267](#)
- OFFLOAD(n)
 - initialization statement [278](#)
- ONECKPT subparameter
 - on CKPTDEF statement [108](#)
- operator
 - checkpoint reconfiguration verification [106](#)
- operator command
 - identifying in JES2 initialization [113](#)
- operator message suppression SEP [349](#)
- OPVERIFY parameter
 - initialization parameter on CKPTDEF [106](#)
- OUTCLASS statement
 - initialization statement [287](#)
- OUTCLASS(v) (system output class characteristic)
 - initialization statement [285](#)
- OUTDisp parameter
 - on JOBCLASS(class) statement [174](#)
 - on OFF(n).SR statement [263](#)
 - on OFF(n).ST statement [189](#), [273](#)
 - on OUTCLASS statement [287](#)
- OUTPRTY(n)
 - initialization statement [292](#)
- output
 - disposition
 - as a work selection criteria [189](#), [273](#)
 - how to specify [174](#), [287](#)
 - specifying [174](#), [287](#)
 - estimated pages statement [144](#)
 - estimated punched statement [145](#)
 - selection by amount
 - LIMit parameter [346](#), [359](#)
 - LIMIT parameter [315](#), [331](#)
 - specifying SYSOUT class characteristics for [161](#)
- OUTTIME parameter
 - on OUTDEF statement [290](#)
- overcoming held [157](#)
- OWNMEMB on MASDEF
 - initialization parameter [215](#)
- OWNNODE on NJEDEF
 - initialization parameter [228](#)

P

- page limit
 - specifying for SYSOUT transmitters [189](#)
- PAGE on OUTPRTY statement

PAGE on OUTPRTY statement (*continued*)

initialization parameter [293](#)

PAGES= on TRACEDEF

initialization parameter [431](#)

parameter

BLNKTRNC parameter [287](#)

JES2 initialization

BERTWARN on CKPTSPACE [109](#)

BUFNUM on CONDEF [113](#)

BUFSIZE on SPOOLDEF [412](#)

BUFWARN on CONDEF [113](#)

BUFWARN on SMFDEF [406](#)

CCWNUM on PRINTDEF [298](#)

CCWNUM on PUNCHDEF [336](#)

CKPTLOCK on MASDEF [214](#)

CMDNUM on CONDEF [113](#)

CONCHAR on CONDEF [113](#)

CONNECT on SOCKET [409](#)

DBLBUFR on PRINTDEF [299](#)

DBLBUFR on PUNCHDEF [336](#)

DELAY on NJEDEF parameter [227](#)

DISPLEN on CONDEF [114](#)

DISPMAX on CONDEF [114](#)

DMNDSET on OUTDEF [289](#)

DORMANCY on MASDEF [213](#)

DSLIMIT on OUTDEF [290](#)

DSNAME on SPOOLDEF [412](#)

DSNMASK on SPOOLDEF [413](#)

FCB on PRINTDEF statement [299](#)

FENCE on SPOOLDEF [413](#)

HOLD on MASDEF [213](#)

HONORLIM on INTRDR [159](#)

IPADDR on SOCKET parameter [409](#)

JOBNUM on JOBDEF [182](#)

JOBWARN on JOBDEF [183](#)

JRNUM on LINE(nnnnn) [195](#), [203](#)

JRNUM on NJEDEF [227](#)

JTNUM on LINE(nnnnn) [196](#), [203](#), [207](#)

JTNUM on NJEDEF [227](#)

LIMIT on TPDEF [424](#)

LINE on SOCKET [409](#)

LINECT on PRINTDEF statement [299](#)

LINENUM on NJEDEF [228](#)

LOCKOUT on MASDEF [215](#)

LOGMSG on JOBDEF [183](#)

LOGSIZE on CKPTDEF [103](#)

MAILMSG on NJEDEF [228](#)

MASMSG on CONDEF [114](#)

MAXHOP on NJEDEF [228](#)

MBUFSIZE on TPDEF [426](#)

NETSRV on SOCKET [409](#)

NFY_SUBJECT on JOBDEF [183](#)

NIFCB on PRINTDEF statement [300](#)

NIUCS on PRINTDEF [301](#)

NODE on SOCKET [409](#)

NODENUM on NJEDEF [228](#)

OWNMEMB on MASDEF [215](#)

OWNNODE on NJEDEF [228](#)

PAGE on OUTPRTY [293](#)

PAGES on TRACEDEF [431](#)

PATH on NJEDEF [228](#)

PORT on SOCKET [409](#)

PRIORITY on JOBPRTY [185](#)

PRIORITY on OUTPRTY [293](#)

parameter (*continued*)

JES2 initialization (*continued*)

PRTYHIGH on JOBDEF [183](#)

PRTYHIGH on OUTDEF [291](#)

PRTYJECL on JOBDEF [183](#)

PRTYJOB on JOBDEF [183](#)

PRTYLOW on JOBDEF [183](#)

PRTYLOW on OUTDEF [291](#)

PRTYOUT on OUTDEF statement [291](#)

PRTYRATE on JOBDEF [183](#)

RANGE on JOBDEF [184](#)

RDBLBUFR on PRINTDEF [301](#)

RDBLBUFR on PUNCHDEF [336](#)

RDRCHAR on CONDEF [114](#)

REST on SOCKET [409](#)

RESTART on LOGON [197](#), [204](#), [208](#), [212](#)

RESTART on NETSERV [224](#)

RESTMAX on NJEDEF [228](#)

RESTNODE on NJEDEF [229](#)

RESTTOL on NJEDEF [229](#)

RMTMSG on TPDEF [427](#)

RMTNUM on TPDEF [427](#)

SECURE on SOCKET [409](#)

SESSIONS on TPDEF [427](#)

SHARED on MASDEF [216](#)

SIZE= on TRACEDEF [431](#)

SPOOLNUM on SPOOLDEF [413](#)

SRNUM on LINE(nnnnn) [197](#), [204](#), [208](#)

SRNUM on NJEDEF [229](#)

STACK on NETSERV [225](#)

START on LOGON [197](#), [204](#), [208](#), [212](#)

START on NETSERV [225](#)

STNUM on LINE(nnnnn) [197](#), [204](#), [208](#)

STNUM on NJEDEF [229](#)

TGBESIZE on SPOOLDEF [413](#), [414](#)

TIME= on JOBPRTY [185](#)

TRaceio on NETSERV [225](#)

TRANS on PRINTDEF statement [301](#)

TRKCELL on SPOOLDEF [415](#)

UCS on PRINTDEF [302](#)

USERSET on OUTDEF [292](#)

VOLUME on SPOOLDEF [416](#)

XCFGRPNM on MASDEF [216](#)

password

specifying for line [196](#), [204](#), [208](#)

specifying for RJE workstation [404](#)

patch

CKPTname reference [380](#), [433](#)

CSECT reference [380](#), [433](#)

description [219](#), [379](#), [432](#)

dspname reference [380](#), [433](#)

member reference [220](#)

statements

format [220](#), [380](#), [433](#)

patching facility

nonsupport for functional subsystem [219](#), [379](#), [432](#)

PATH on NJEDEF

initialization parameter [228](#)

path resistance

maximum node path [228](#)

maximum tolerance [228](#)

PATHMGR parameter

on CONNect statement [117](#)

on NODE statement [240](#)

- PCDEF statement
 - initialization statement [295](#)
- PENCRYPT parameter
 - on NODE statement [240](#)
- performance
 - consideration
 - BUFSIZE parameter on SPOOLDEF statement [412](#)
 - CCWNUM parameter on PRINTDEF [299](#)
 - JOBNUM parameter on JOBDEF performance [182](#)
 - JOENUM parameter on OUTDEF [290](#)
 - TGFSIZE parameter on SPOOLDEF [414](#)
 - TGSPACE=(MAX=) parameter on SPOOLDEF [415](#)
 - factor
 - DEBUG performance [131](#)
- performance factor
 - BUFNUM parameter on CONDEF [113](#)
 - DEBUG statement [131](#)
- PLIM
 - R(nnnn).PR(m) statement [346](#)
- POLICYLIB
 - format description [296](#)
 - modifications [296](#)
 - parameters [297](#)
 - syntax [296](#)
- POLICYLIB(xxxxxxx) statement
 - initialization statement [296](#)
- PORT on SOCKET statement
 - initialization parameter [409](#)
- print band
 - specifying for local impact printer [302](#)
- print chain
 - specifying for local impact printer [302](#)
 - specifying for remote impact printer [350](#)
- print environment
 - PRINTDEF statement [298](#)
- print line
 - maximum number per page [299](#)
 - specifying estimation of output [142](#)
 - translation [301](#)
- print train
 - specifying for local impact printer [302](#)
 - specifying for remote impact printer [350](#)
- PRINTDEF statement
 - initialization statement [298](#)
- printer
 - channel program limit [298](#)
 - checkpoint data set option [313](#), [314](#)
 - local
 - numbering [306](#)
 - specify characteristic [306](#)
 - remote
 - checkpoint data set option [343](#), [344](#)
 - compaction for [344](#)
 - numbering [336](#)
 - specify characteristic [336](#)
 - specifying logical record size [346](#)
- priority
 - associated with a processing interval [293](#)
 - associated with execution time [185](#)
 - output record count [293](#)
 - specifying
 - for jobs entered at local statement reader [366](#)
 - for jobs entered at remote statement reader [366](#)
 - for priority aging [183](#), [291](#)
- priority aging
 - specify
 - intervals for a job [183](#)
 - specifying for output [291](#)
 - specifying priority for [183](#)
- PRIORITY control statement
 - support for [183](#)
- PRIORITY on JOBPRTY
 - initialization parameter [185](#)
- PRIORITY on OUTPRTY statement
 - initialization parameter [293](#)
- PRIORITY parameter
 - initialization parameter on OUTPRTY [293](#)
- PRIVATE parameter
 - on NODE statement [240](#)
- PRMode parameter
 - R(nnnn).PR(m) statement [347](#)
- PRMODE parameter
 - PRT(nnnn) statement [331](#)
 - PRT(nnnnn) statement [316](#)
 - R(nnnnn).PU(m) statement [359](#)
- process mode
 - parameter on PRT(nnnn) statement [331](#)
 - PRT(nnnnn) statement [316](#)
 - R(nnnn).PR(m) statement [347](#)
 - R(nnnnn).PU(m) statement [359](#)
- processor environment
 - PCDEF statement [295](#)
- PROCLIB statement
 - initialization statement [302](#)
- PRT(nnnnn)
 - initialization statement [306](#)
- PRTYHIGH on JOBDEF
 - initialization parameter [183](#)
- PRTYHIGH on OUTDEF
 - initialization parameter [291](#)
- PRTYJECL parameter
 - initialization parameter on JOBDEF [183](#)
- PRTYJOB on JOBDEF
 - initialization parameter [183](#)
- PRTYLOW on JOBDEF
 - initialization parameter [183](#)
- PRTYLOW on OUTDEF
 - initialization parameter [291](#)
- PRTYOUT on OUTDEF statement
 - initialization parameter [291](#)
- PRTYOUT parameter on OUTDEF statement
 - support [291](#)
- PRTYRATE on JOBDEF
 - initialization parameter [183](#)
- PRYORATE parameter on OUTDEF
 - support for [291](#)
- PUN(nn)
 - initialization statement [326](#)
- punch environment
 - PUNCHDEF statement [336](#)
- PUNCHDEF statement
 - initialization statement [336](#)
- punched statement output
 - specify estimate [143](#)

Q

QHELD parameter

QHELD parameter (*continued*)
on JOBCLASS statement [176](#)

R

R(nnnn).PR(m)
initialization statement [336](#)
R(nnnnn).PU(m)
initialization statement [353](#)
R(nnnnnn).RD(m)
initialization statement [364](#)
RANGE parameter
OFF(n).JR statement
job ID [247](#)
OFF(n).JT statement
job ID [253](#)
OFF(n).SR statement
job ID [263](#)
OFF(n).ST statement
job ID [274](#)
PRT(nnnnn) statement
output job [316](#)
PUN(nn) statement
output job [332](#)
RDBLBUFR on PRINTDEF
initialization parameter [301](#)
RDBLBUFR on PUNCHDEF
initialization parameter [336](#)
RDIRAREA parameter
on CONDEF statement [114](#)
RDR(nn)
initialization statement [367](#)
RDRCHAR parameter
initialization parameter on CONDEF [114](#)
RECEIVE parameter
on NODE statement [241](#)
reconfiguration
operator verification [106](#)
recovery
intervention rate
RECVOPTS statement [373](#)
RECVOPTS statement
initialization statement [373](#)
redirect console output
initialization statement [376](#)
REGION parameter
on JOBCLASS statement [176](#)
region size
defining [176](#)
remote
specifying
characteristics of BSC [389](#)
remote printer
selection of output by amount
LIMit parameter [346](#)
remote punch statement
selection of output by amount
LIMit parameter [359](#)
remote reader statement
default printer destination
jobs entered at reader [367](#)
default punch destination
jobs entered at reader [367](#)
remote statement punch

remote statement punch (*continued*)
selection of output by amount
LIMit parameter [359](#)
remote station
specifying
characteristics of SNA [398](#)
specifying a dedicated line [403](#)
specifying a printer quantity [404](#)
specifying a statement punch quantity [404](#)
specifying a statement reader quantity [404](#)
REP statement
JES2 initialization [379](#)
JES2 patching facility [379](#)
REP initialization statement [379](#)
REPLACE patching statement [380](#)
REQJOBID statement
initialization statement [387](#)
request unit
specifying for SNA remote workstation [402](#)
reset checkpoint lock
AUTOEMEM on MASDEF statement [213](#)
RESTART on MASDEF [216](#)
RESGROUP
Resource Group [388](#)
resistance
maximum
specifying [228](#)
resistance
path, maximum tolerance [228](#)
path, node tolerance [229](#)
RESOURCE parameter [176](#)
REST on SOCKET statement
initialization parameter [409](#)
REST parameter
on NODE statement [241](#)
restart job by job class
RESTART parameter
JOBCLASS statement [177](#)
RESTART on LOGON
initialization parameter [197](#), [204](#), [208](#), [212](#)
RESTART on NETSERV
initialization parameter [224](#)
RESTART parameter
initialization parameter on MASDEF [216](#)
RESTMAX on NJEDEF
initialization parameter [228](#)
RESTMAX parameter
on NJEDEF statement [228](#)
RESTNODE on NJEDEF
initialization parameter [229](#)
RESTTOL on NJEDEF
initialization parameter [229](#)
RJE
considerations when using system symbols [13](#)
RJE (remote job entry)
specify line characteristic [190](#), [198](#)
specifying number of buffers for [424](#)
RJE workstation
numbering [389](#)
specifying
dedicated line [395](#)
specifying a printer quantity [396](#)
specifying a statement punch quantity [396](#)
specifying a statement reader quantity [396](#)

- RMT(nnnnn)
 - initialization statement
 - BSC RJE workstation [389](#)
 - SNA RJE workstation [398](#)
- RMTMSG on TPDEF
 - initialization parameter [427](#)
- RMTNUM on TPDEF
 - initialization parameter [427](#)
- route
 - output [137](#)
- route code
 - caution in use [317](#)
 - specifying
 - for BSC remote station [137](#)
 - for local printer [317](#)
 - for local statement punch [332](#)
 - for remote printer [348](#)
 - for SNA remote station [404](#)
 - specifying for remote statement punch [360](#)
 - symbolic name [137](#)
- Routecde parameter
 - OFF(n).SR statement [264](#)
 - on PRT(nnnnn) statement [317](#)
 - PUN(nnnn) statement [332](#)
 - R(nnnn).PR(m) statement
 - default node destination for print output [348](#)
 - R(nnnnn).PU(m) statement [360](#)

S

- SAPI_OPT
 - \$T OUTDEF [292](#)
- SCHENV parameter, on the JOBCLASS statement [178](#)
- SCOPE parameter
 - on CONDEF statement [115](#)
- second-level destination
 - \$T DESTid command [138](#)
- SECURE on SOCKET
 - initialization parameter [409](#)
- SEGLIM parameter
 - on OUTDEF statement [291](#)
- selection of output by amount
 - remote printer
 - LIMit parameter [346](#)
- separator page
 - marking for 3800 printer [318](#)
 - specify type [301](#)
- SEPPAGE parameter
 - on PRINTDEF statement [301](#)
- SESSIONS on TPDEF
 - initialization parameter [427](#)
- shared DASD
 - for checkpoint device [216](#)
- SHARED on MASDEF
 - initialization parameter [216](#)
- sharing initialization statements
 - using system symbols [12](#)
- shortcut keys [471](#)
- SIGNON parameter
 - on NODE statement [242](#)
- SIZE on TRACEDEF
 - initialization parameter [431](#)
- SMF (system management facilities)
 - buffer usage [406](#)

- SMF (system management facilities) (*continued*)
 - replacing ID for [215](#)
- SMF (system management facility)
 - bypassing IEFUJP exit for job class [172](#)
 - bypassing IEFUSO exit for job class [172](#)
 - omitting type 26 records for job class [178](#)
 - omitting type 6 records for job class [178](#)
 - producing type 26 records for job class [178](#)
 - producing type 6 records for job class [178](#)
- SMFDEF statement
 - initialization [406](#)
- SNA (system network architecture)
 - remote station
 - compaction feature [402](#)
 - compression/expansion feature [402](#)
 - numbering [398](#)
 - password for [404](#)
 - printer quantity [404](#)
 - specify characteristic [398](#)
 - statement punch quantity [404](#)
 - statement reader quantity [404](#)
 - remote station line [403](#)
 - remote workstation
 - largest request unit [402](#)
- SNABUF parameter
 - on TPDEF statement
 - number required [425](#)
- SOCKET on NETSERV statement
 - initialization parameter [224](#)
- specify characteristic [157](#)
- specifying [405](#)
- specifying number of active [112](#)
- spool
 - definition
 - SPOOLDEF statement [410](#)
 - threshold percentage message for [415](#)
 - volume
 - identification [416](#)
 - specifying serial number [416](#)
 - volume number
 - specifying [413](#)
 - volume partitioning
 - specifying [413](#)
- SPOOL statement
 - initialization statement [409](#)
- SPOOLDEF statement
 - initialization [410](#)
- SPOOLNUM on SPOOLDEF
 - initialization parameter [413](#)
- SRNUM on LINE(nnnnn)
 - initialization parameter [197](#), [204](#), [208](#)
- SRNUM on NJEDEF
 - initialization parameter [229](#)
- SSI(nnn)
 - initialization statement [416](#)
- STACK on NETSERV
 - initialization parameter [225](#)
- START on LOGON
 - initialization parameter [197](#), [204](#), [208](#), [212](#)
- START on NETSERV
 - initialization parameter [225](#)
- start option processing
 - defining

- start option processing (*continued*)
 - defining (*continued*)
 - initialization statement [283](#)
- statement
 - DESTDEF statement [133](#)
 - EDS statement [141](#)
 - initialization
 - GRPDEF statement [151](#)
 - JOBDEF statement [179](#)
 - JES2 initialization
 - APPL statement [91](#)
 - CKPT2 on CKPTDEF [101](#)
 - COMPACT statement [109](#)
 - DUPLEX on CKPTDEF [103](#)
 - ESTBYTE statement [141](#)
 - ESTLNCT statement [143](#)
 - ESTPAGE statement [144](#)
 - ESTPUN statement [145](#)
 - FSS statement [149](#)
 - I(nnnn) [153](#)
 - INITDEF statement [155](#)
 - INPUTDEF statement [156](#)
 - JECLDEF statement [159](#)
 - JOBCLASS(class) [161](#)
 - LOGON(nnn) [210](#)
 - MASDEF statement [212](#)
 - MEMBer [217](#)
 - NETACCT statement [220](#)
 - OUTCLASS statement [287](#)
 - PRT(nnnnn) [306](#)
 - PUN(nn) [326](#)
 - R(nnnn).PR(m) [336](#)
 - R(nnnnn).PU(m) [353](#)
 - R(nnnnnn).RD(m) [364](#)
 - RDR(nn) [367](#)
 - RDR(nn) statement [367](#)
 - RMT(nnnnn) (BSC RJE workstation) [389](#)
 - RMT(nnnnn) (SNA RJE workstation) [398](#)
 - SUBMITLIB [417](#)
 - SUBMITRDR [420](#)
 - SUBTDEF [423](#)
 - TRACE(nnn) [428](#)
 - TRACEDEF statement [430](#)
 - JES3 initialization
 - INPUTDEF statement [160](#)
- statement punch
 - (see also local device)
 - checkpoint option [330](#)
 - numbering [326](#)
 - specify characteristic [326](#)
 - remote
 - checkpoint option [357](#)
 - compaction for [358](#)
 - identifying forms for [358](#)
 - numbering [353](#)
 - specify characteristic [353](#)
- statement reader
 - default printer destination
 - for jobs entered at local reader [371](#)
 - local
 - default node destination for punch output [372](#)
 - number [367](#)
 - specify characteristic [367](#)
 - remote

- statement reader (*continued*)
 - remote (*continued*)
 - numbering [364](#)
 - specify characteristic [364](#)
- STDFORM parameter
 - on OUTDEF statement [292](#)
- STNUM on LINE(nnnnn)
 - initialization parameter [197](#), [204](#), [208](#)
- STNUM on NJEDEF
 - initialization parameter [229](#)
- submit reader definition
 - SUBMITRDR statement [422](#)
- SUBMITLIB initialization statement [417](#)
- SUBMITRDR initialization statement [420](#)
- SUBMITRDR statement
 - initialization [422](#)
- SUBnet parameter
 - on NODE statement [241](#)
- subsystem interface definition
 - SSI(nnn) statement [416](#)
- SUBTDEF initialization statement [423](#)
- summary of changes [xxi](#)
- SWA
 - placing SWA (scheduler work area) [178](#)
 - SWA (scheduler work area) [178](#)
 - SWA residency [178](#)
- syntax diagrams
 - how to read [10](#)
- SYS1.HASPCKPT
 - specifying volume containing [103](#)
- SYSOUT (system output) class characteristic
 - OUTCLASS(v) statement [285](#)
- SYSOUT class
 - matching message class [137](#)
 - specifying a separate SYSOUT class characteristic [287](#)
- SYSOUT transmitter
 - work selection characteristics [187](#)
- SYSSYM parameter
 - on JOBCLASS statement [178](#)
- system symbols
 - considerations for NJE and RJE use [13](#)
 - using to share initialization statements [12](#)

T

- teleprocessing buffer
 - minimum requirement for BSC [424](#)
 - minimum requirement for SNA [424](#)
 - specifying [424](#)
- teleprocessing definition
 - TPDEF statement [423](#)
- teleprocessor line
 - specify characteristic [190](#), [198](#)
- TGBESIZE on SPOOLDEF
 - initialization parameter [413](#), [414](#)
- TGFSIZE on SPOOLDEF
 - as a performance factor [414](#)
- TGSPACE=(MAX=) on SPOOLDEF
 - as a performance factor [415](#)
 - initialization parameter [414](#)
- TGSPACE=(WARN=) on SPOOLDEF
 - initialization parameter [415](#)
- TIME parameter
 - on JOBCLASS statement [178](#)

- TIME= on JOBPRTY
 - initialization parameter [185](#)
- TIMEtol parameter
 - on NJEDEF statement [229](#)
- TPDEF statement
 - initialization [423](#)
- TRace parameter
 - on NODE statement [242](#)
- TRACE(n) initialization statement [428](#)
- TRACEDEF initialization statement [430](#)
- TRaceio on NETSERV
 - initialization parameter [225](#)
- track cell
 - method
 - requirements for [415](#)
 - specifying
 - characteristic for SYSOUT class [288](#)
 - size [415](#)
- track group
 - number [414](#)
 - number per volume [414](#)
 - percent usage [415](#)
- trademarks [476](#)
- TRANS on PRINTDEF
 - initialization parameter [301](#)
- TRANSMIT parameter
 - on NODE statement [242](#)
- TRKCELL on SPOOLDEF
 - initialization parameter [415](#)
- truncation
 - blank [287](#)
- two-level DESTids
 - \$T DESTid command [139](#)

U

- UCS on PRINTDEF
 - initialization parameter [302](#)
- UNCONDitional parameter
 - on PROCLIB statement [305](#)
- UNIT parameter
 - on PROCLIB statement [305](#)
- user interface
 - ISPF [471](#)
 - TSO/E [471](#)
- USERSET on OUTDEF
 - initialization parameter [292](#)

V

- VALIDATE parameter
 - on OFFLOAD initialization statement [282](#)
- VERify patching statement [433](#)
- VERIFY statement
 - JES2 initialization [432](#)
 - JES2 patching facility [432](#)
 - VERify initialization statement [432](#)
- VERSIONS parameter
 - on CKPTDEF statement
 - NUMBER subparameter [107](#)
 - WARN subparameter [107](#)
- VOLATILE parameter
 - on CKPTDEF statement [107](#)

- VOLS parameter
 - on OFFLOAD initialization statement [282](#)
- VOLser parameter
 - on PROCLIB statement [305](#)
- volume count
 - specifying
 - for spool offload data set [282](#)
- VOLUME on SPOOLDEF
 - initialization parameter [416](#)

W

- WLM scheduling environment
 - SCHENV [178](#)
- work selection
 - PUN(nn) statement [334](#)
 - R(nnnn).PR(m) statement [351](#)
 - R(nnnnn).PU(m) statement [363](#)
- work selection parameter
 - PRT(nnnnn) statement [321](#)
- WS criteria
 - off.st [187](#), [189](#)
- WS parameter
 - PRT(nnnnn) statement [321](#)
 - PUN(nn) statement [334](#)
 - R(nnnn).PR(m) statement [351](#)
 - R(nnnnn).PU(m) statement [363](#)

X

- XCFGRPNM on MASDEF
 - initialization parameter [216](#)

Z

- ZAPJOB statement
 - initialization [439](#)



Product Number: 5655-ZOS

SA32-0992-60

