

RISC-V Reference

James Zhu <jameszhu@berkeley.edu>

RISC-V Instruction Set

Core Instruction Formats

31	27	26	25	24	20	19	15	14	12	11	7	6	0	
funct7				rs2		rs1		funct3		rd		opcode		R-type
imm[11:0]						rs1		funct3		rd		opcode		I-type
imm[11:5]				rs2		rs1		funct3		imm[4:0]		opcode		S-type
imm[12:10:5]				rs2		rs1		funct3		imm[4:1:11]		opcode		B-type
imm[31:12]										rd		opcode		U-type
imm[20:10:1:11:19:12]										rd		opcode		J-type

RV32I Base Integer Instructions

Inst	Name	FMT	Opcode	funct3	funct7	Description (C)	Note
add	ADD	R	0110011	0x0	0x00	$rd = rs1 + rs2$	
sub	SUB	R	0110011	0x0	0x20	$rd = rs1 - rs2$	
xor	XOR	R	0110011	0x4	0x00	$rd = rs1 \wedge rs2$	
or	OR	R	0110011	0x6	0x00	$rd = rs1 \mid rs2$	
and	AND	R	0110011	0x7	0x00	$rd = rs1 \& rs2$	
sll	Shift Left Logical	R	0110011	0x1	0x00	$rd = rs1 \ll rs2$	
srl	Shift Right Logical	R	0110011	0x5	0x00	$rd = rs1 \gg rs2$	
sra	Shift Right Arith*	R	0110011	0x5	0x20	$rd = rs1 \gg rs2$	msb-extends
slt	Set Less Than	R	0110011	0x2	0x00	$rd = (rs1 < rs2) ? 1 : 0$	
sltu	Set Less Than (U)	R	0110011	0x3	0x00	$rd = (rs1 < rs2) ? 1 : 0$	zero-extends
addi	ADD Immediate	I	0010011	0x0		$rd = rs1 + imm$	
xori	XOR Immediate	I	0010011	0x4		$rd = rs1 \wedge imm$	
ori	OR Immediate	I	0010011	0x6		$rd = rs1 \mid imm$	
andi	AND Immediate	I	0010011	0x7		$rd = rs1 \& imm$	
slli	Shift Left Logical Imm	I	0010011	0x1	imm[5:11]=0x00	$rd = rs1 \ll imm[0:4]$	
srlr	Shift Right Logical Imm	I	0010011	0x5	imm[5:11]=0x00	$rd = rs1 \gg imm[0:4]$	
srai	Shift Right Arith Imm	I	0010011	0x5	imm[5:11]=0x20	$rd = rs1 \gg imm[0:4]$	msb-extends
slti	Set Less Than Imm	I	0010011	0x2		$rd = (rs1 < imm) ? 1 : 0$	
sltiu	Set Less Than Imm (U)	I	0010011	0x3		$rd = (rs1 < imm) ? 1 : 0$	zero-extends
lb	Load Byte	I	0000011	0x0		$rd = M[rs1+imm][0:7]$	
lh	Load Half	I	0000011	0x1		$rd = M[rs1+imm][0:15]$	
lw	Load Word	I	0000011	0x2		$rd = M[rs1+imm][0:31]$	
lbu	Load Byte (U)	I	0000011	0x4		$rd = M[rs1+imm][0:7]$	zero-extends
lhu	Load Half (U)	I	0000011	0x5		$rd = M[rs1+imm][0:15]$	zero-extends
sb	Store Byte	S	0100011	0x0		$M[rs1+imm][0:7] = rs2[0:7]$	
sh	Store Half	S	0100011	0x1		$M[rs1+imm][0:15] = rs2[0:15]$	
sw	Store Word	S	0100011	0x2		$M[rs1+imm][0:31] = rs2[0:31]$	
beq	Branch ==	B	1100011	0x0		$\text{if}(rs1 == rs2) PC += imm$	
bne	Branch !=	B	1100011	0x1		$\text{if}(rs1 != rs2) PC += imm$	
blt	Branch <	B	1100011	0x4		$\text{if}(rs1 < rs2) PC += imm$	
bge	Branch <=	B	1100011	0x5		$\text{if}(rs1 \geq rs2) PC += imm$	
bltu	Branch < (U)	B	1100011	0x6		$\text{if}(rs1 < rs2) PC += imm$	zero-extends
bgeu	Branch >= (U)	B	1100011	0x7		$\text{if}(rs1 \geq rs2) PC += imm$	zero-extends
jal	Jump And Link	J	1101111			$rd = PC+4; PC += imm$	
jalr	Jump And Link Reg	I	1100111	0x0		$rd = PC+4; PC = rs1 + imm$	
lui	Load Upper Imm	U	0110111			$rd = imm \ll 12$	
auipc	Add Upper Imm to PC	U	0010111			$rd = PC + (imm \ll 12)$	
ecall	Environment Call	I	1110011	0x0	imm=0x0	Transfer control to OS	
ebreak	Environment Break	I	1110011	0x0	imm=0x1	Transfer control to debugger	

伪指令

Pseudo Instructions

Pseudoinstruction	Base Instruction(s)	Meaning
la rd, symbol	auipc rd, symbol[31:12] addi rd, rd, symbol[11:0]	Load address
l{b h w d} rd, symbol	auipc rd, symbol[31:12] l{b h w d} rd, symbol[11:0](rd)	Load global
s{b h w d} rd, symbol, rt	auipc rt, symbol[31:12] s{b h w d} rd, symbol[11:0](rt)	Store global
fl{w d} rd, symbol, rt	auipc rt, symbol[31:12] fl{w d} rd, symbol[11:0](rt)	Floating-point load global
fs{w d} rd, symbol, rt	auipc rt, symbol[31:12] fs{w d} rd, symbol[11:0](rt)	Floating-point store global
nop	addi x0, x0, 0	No operation
li rd, immediate	<i>Myriad sequences</i>	Load immediate
mv rd, rs	addi rd, rs, 0	Copy register
not rd, rs	xori rd, rs, -1	One's complement
neg rd, rs	sub rd, x0, rs	Two's complement
negw rd, rs	subw rd, x0, rs	Two's complement word
sext.w rd, rs	addiw rd, rs, 0	Sign extend word
seqz rd, rs	sltiu rd, rs, 1	Set if = zero
snez rd, rs	sltu rd, x0, rs	Set if \neq zero
sltz rd, rs	slt rd, rs, x0	Set if < zero
sgtz rd, rs	slt rd, x0, rs	Set if > zero
fmv.s rd, rs	fsgnj.s rd, rs, rs	Copy single-precision register
fabs.s rd, rs	fsgnjx.s rd, rs, rs	Single-precision absolute value
fneg.s rd, rs	fsgnjn.s rd, rs, rs	Single-precision negate
fmv.d rd, rs	fsgnj.d rd, rs, rs	Copy double-precision register
fabs.d rd, rs	fsgnjx.d rd, rs, rs	Double-precision absolute value
fneg.d rd, rs	fsgnjn.d rd, rs, rs	Double-precision negate
beqz rs, offset	beq rs, x0, offset	Branch if = zero
bnez rs, offset	bne rs, x0, offset	Branch if \neq zero
blez rs, offset	bge x0, rs, offset	Branch if \leq zero
bgez rs, offset	bge rs, x0, offset	Branch if \geq zero
bltz rs, offset	blt rs, x0, offset	Branch if < zero
bgtz rs, offset	blt x0, rs, offset	Branch if > zero
bgt rs, rt, offset	blt rt, rs, offset	Branch if >
ble rs, rt, offset	bge rt, rs, offset	Branch if \leq
bgtu rs, rt, offset	bltu rt, rs, offset	Branch if >, unsigned
bleu rs, rt, offset	bgeu rt, rs, offset	Branch if \leq , unsigned
j offset	jal x0, offset	Jump
jal offset	jal x1, offset	Jump and link
jr rs	jalr x0, rs, 0	Jump register
jalr rs	jalr x1, rs, 0	Jump and link register
ret	jalr x0, x1, 0	Return from subroutine
call offset	auipc x1, offset[31:12] jalr x1, x1, offset[11:0]	Call far-away subroutine
tail offset	auipc x6, offset[31:12] jalr x0, x6, offset[11:0]	Tail call far-away subroutine
fence	fence iorw, iorw	Fence on all memory and I/O

Registers

Register	ABI Name	Description	Saver
x0	zero	Zero constant	—
x1	ra	Return address	Caller
x2	sp	Stack pointer	—
x3	gp	Global pointer	—
x4	tp	Thread pointer	Callee
x5	t0-t2	Temporaries	Caller
x8	s0 / fp	Saved / frame pointer	Callee
x9	s1	Saved register	Callee
x10-x11	a0-a1	Fn args/return values	Caller
x12-x17	a2-a7	Fn args	Caller
x18-x27	s2-s11	Saved registers	Callee
x28-x31	t3-t6	Temporaries	Caller
f0-7	ft0-7	FP temporaries	Caller
f8-9	fs0-1	FP saved registers	Callee
f10-11	fa0-1	FP args/return values	Caller
f12-17	fa2-7	FP args	Caller
f18-27	fs2-11	FP saved registers	Callee
f28-31	ft8-11	FP temporaries	Caller