

DS Style User Guide

A complete guide to setup, everyday use, artwork and personalisation

Compatible with the original EZ-Flash Omega and Omega Definitive Edition

Nintendo DS-inspired. Made for the Game Boy Advance.

Open source kernel for the EZ-Flash Omega family.

Contents

Select any section to jump straight to it. The guide is arranged from first-time setup to advanced personalisation.

Welcome to DS Style	What DS Style is and what it changes.
Before You Begin	Choose the correct cartridge build and prepare your SD card.
Install DS Style	A safe, model-aware installation walkthrough.
Your SD Card	DS Style folder structure and contents.
Feature Overview	A quick tour of the complete experience.
Everyday Navigation	Start screen, file views, favourites, recents and NOR Flash.
Settings Explained	Plain-language explanations of every setting.
Launching Games	Boot modes, addons, cheats, saves and NOR Flash.
Artwork and Thumbnails	Title art, box art and custom artwork.
Thumbnail Scraper	Build packs, preview artwork and create custom overrides.
DS Style Customiser	Create a personal kernel without editing source files.
Languages and Filenames	Interface languages and accented filename support.
Supported Files	Games, emulated systems and media formats.
Care and Safety	Saving, updates and good SD-card habits.
Frequently Asked Questions	Common pitfalls and straightforward fixes.
Uninstall DS Style	Restore the stock SD-card layout and official kernel.
Reporting Bugs	Where to report a problem and what information to include.
Open Source and Community	Sharing, credit, support and further reading.

Welcome to DS Style

A FAMILIAR WAY TO ENJOY YOUR LIBRARY

DS Style is a custom kernel for the EZ-Flash Omega family. It replaces the stock launcher with a clean interface inspired by the Nintendo DS, while keeping the cartridge's core game-loading features close at hand.

Browse games in List, List + Art, Horizontal carousel or Vertical carousel views. Choose title or square box artwork, keep favourites and recently played games nearby, and personalise the interface's look, sound and wording.

A note from the creator

I created DS Style in celebration of the Game Boy Advance's 25th anniversary. I wanted to give the system a front end of its own: something familiar, welcoming and enjoyable to use every day, with thoughtful quality-of-life improvements and useful new features. I hope you enjoy making it your own and, most importantly, playing your games.

FrankieT19

> **TWO CARTRIDGE MODELS** DS Style supports both the original EZ-Flash Omega and the Omega Definitive Edition. Always use the download made for your exact cartridge.

What DS Style does not change

DS Style remains an EZ-Flash kernel. Game compatibility, save behaviour, NOR Flash and addon features still depend on the cartridge hardware and the underlying EZ-Flash system. This guide explains the DS Style interface while preserving the important usage advice supplied by EZ-Flash.

At a glance

Browse your way Choose List, List + Art or either carousel view.	**Make it personal** Select colours, light or dark mode, sounds and languages.
Find games quickly Use favourites, recently played lists and quick-start options.	**Add artwork** Use title images, box art and custom thumbnails.
Customise Use DS Style Customiser and Thumbnail Scraper to make the experience your own.	**A refined interface** Enjoy a fresh, carefully polished experience designed for clear and comfortable browsing.

Before You Begin

Choose the correct download

Cartridge	Correct DS Style build
Original Omega	Use the original Omega release. Its update file is ezkernel.bin.
Omega DE	Use the Omega Definitive Edition release. Its update file is ezkernelnew.bin.

Official foundation

Each edition of DS Style is built on the official EZ-Flash kernel and firmware listed below.

Cartridge	Official foundation
Original Omega	Official Kernel 1.10 and Firmware 9.0
Omega DE	Official Kernel 1.06; Firmware 5.0 for Rev.A and Firmware 7.0 for Rev.B

What you need

- An EZ-Flash Omega or EZ-Flash Omega Definitive Edition.
- A microSD card and a reliable card reader.
- The DS Style release made for your cartridge.
- A backup of your saves and any other files you want to keep before making changes.
- The latest official EZ-Flash kernel installed first.

Prepare the microSD card

Always back up the files you want to keep before installing DS Style. Make sure the microSD card is formatted according to the table below.

Card capacity	EZ-Flash guidance
Up to 2 GB	FAT or FAT16, 32 KB allocation unit
Up to 32 GB	FAT32, 32 KB allocation unit
Above 32 GB	exFAT, 32 KB or larger allocation unit

Install DS Style

A CAREFUL FIRST INSTALLATION TAKES ONLY A FEW MINUTES

1. Back up SAVER, RTS and any other folders or files you want to keep to your computer.
2. Update the cartridge with the latest official EZ-Flash kernel, then confirm it starts normally.
3. Open the DS Style download made for your cartridge.
4. Copy the SYSTEM folder and the correct kernel file to the root of the microSD card.
5. Move any existing IMGS, SAVER, RTS, CHEAT, PATCH and BACKUP folders into SYSTEM. Merge folders when asked; do not place one SYSTEM folder inside another.
6. Artwork and cheats are included in SYSTEM. Copy the complete folder; allow the transfer to finish.
7. Optionally edit SYSTEM/NAME.TXT. The top bar displays up to 11 characters.
8. Safely eject the microSD card and return it to the cartridge.
9. Hold R while powering on the Game Boy Advance. Keep the console powered until the update has completed.

KEEP THE ROOT CLEAN When extracting a release, avoid creating an extra folder layer. The SYSTEM folder and the correct kernel file should be visible directly at the root of the card.

Video installation guide

Follow the complete installation process on screen.

Watch the DS Style tutorial on YouTube

DURING THE UPDATE Never switch off the console while the kernel is being written. Wait for the process to finish.

Updating an existing DS Style installation

Back up the card, then merge the new release with the existing installation. Keep your NAME.TXT, SETTINGS.TXT, saves and personal artwork. The Manager's Update DS Style button replaces only the kernel.

After the update

After DS Style has finished installing, you may remove ezkernel.bin or ezkernelnew.bin using your computer. The root update file is hidden from normal browsing.

Your SD Card

DS Style keeps its support files together inside SYSTEM. Your game folders may be organised elsewhere on the card in any way that makes sense to you.

```
microSD root
|-- ezkernel.bin              Original Omega update file
|-- ezkernelnew.bin           Omega DE update file
|-- SYSTEM
|   |-- NAME.TXT              Optional top-bar name
|   |-- SETTINGS.TXT          Created and maintained by DS Style
|   |-- SAVER                 Game saves
|   |-- BACKUP                Optional save backups
|   |-- RTS                   Save states
|   |-- PATCH                 Addon patch data
|   |-- PLUG                  File and emulator plug-ins
|   |-- CHEAT                 Included cheat library
|   |-- KERNELS               Optional styles and custom kernels
|   |-- IMGS                  Included 120 x 80 title artwork
|   |   `-- CUSTOM            Custom title artwork
|   `-- IMGS2                 Included 80 x 80 box artwork
|       `-- CUSTOM            Custom box artwork
`-- Games                     Your own folders and files
```

> **ONLY ONE KERNEL FILE APPLIES** The diagram shows both model filenames for reference. Place only the file made for your cartridge on the card.

Files you may edit

NAME.TXT	Enter the name shown in the top-left corner. Only the first 11 characters are displayed.
SETTINGS.TXT	A readable record of DS Style settings. The file includes comments and valid choices.
CUSTOM artwork	Add BMP artwork for any file or folder. See Artwork and Thumbnails.

Folders DS Style maintains

Save, backup, patch and save-state folders should be left in place. Deleting or reorganising them can make saves, addons or save states appear to be missing.

Feature Overview

Core experience	Nintendo DS-inspired interface; faithful animated Start screen; List, List + Art, Horizontal carousel and Vertical carousel views; and quality-of-life refinements throughout.
Appearance & artwork	All 16 Nintendo DS colour options; light and dark mode; 120 x 80 title artwork packs; 80 x 80 box-art packs; local and Libretro sources; and custom artwork for every game, file or folder.
Start screen	Feature favourite games or the last played game, with quick access to SD Card, NOR Flash and Settings.
Boot & launch	Choose a default Clean, Add-on or Menu launch mode; resume the last SD position; or use a quick-start hotkey to launch the last played game.
Personalisation & sound	Toggle interface sounds, set a top-bar name and create a personal edition with DS Style Customiser.
Kernel features	Includes Simple theme features, PogoShell plug-in support, save backups and the functionality of the official EZ-Flash kernel.
Languages	English (UK), English (US), Spanish, French, Portuguese, German, Turkish, Italian, Dutch, Swedish, Finnish, Chinese and Thai.

Everyday Navigation

Start screen

A	Open the selected game, SD Card, NOR Flash or Settings.
D-pad	Move between the visible options. Left and Right also move between favourites.
L / R	Move between favourites when Favourites is selected.
Select	Switch the featured game between Last Played and Favourites.

The Start screen is always available. Use Boot to under Interface to choose your first screen; B can still return to the Start screen.

SD Card screen

A	Enter a folder, open a file, launch a game or accept.
B	Go back one folder or cancel.
Start	Open Recently Played; press again to switch between Recently Played and Favourites.
Hold Start	Delete the selected file after confirmation.
Select	Cycle through List, List + Art, Horizontal and Vertical views.
Double-tap Select	Add or remove the selected game as a favourite.
L / R	Move between screens; inside recents or favourites, switch between those lists.

Movement by view

Horizontal	Left/Right moves one item. Up/Down jumps ten items.
Vertical	Up/Down moves one item. Left/Right jumps ten items.
List / List + Art	Up/Down moves one item. Left/Right jumps ten items.

Recently Played and Favourites

Press Start from the SD Card screen to open Recently Played. Press Start again, or use L and R, to switch to Favourites. Press B from either list to return to the SD Card position you left.

Double-tap Select on the SD Card screen or in the Favourites view to add or remove the selected game from your favourites.

NOR Flash

A	Open the selected NOR game's boot menu.
B	Return to the previous screen.
Select	Cycle the view mode.
L / R	Move between screens.

Settings

Settings controls

Up / Down	Move through the settings list.
A or Left / Right	Change the selected setting.
A on >	Open the setting's pop-up menu.
B	Close a pop-up menu.
L / R	Move between screens, including while a settings category is open.

The built-in Help pages cover the same everyday controls.

Settings explained

Settings is grouped into Interface, Games, Hardware, Open SYSTEM and Help. Open SYSTEM lets you manage support files and returns to Settings with B. List names are always simplified; file extensions and sizes are hidden.

Interface

Time	Set the cartridge clock.
Clock format	Choose a 12-hour or 24-hour clock for the top bar.
Language	Choose the interface language.
Sounds	Turn menu sounds on or off.
Theme	Choose Light, Dark or Auto (dark from 20:00 to 08:00). DE custom builds may add Custom.
Colour	Choose the accent colour. Omega DE custom builds may add a Custom colour.
Load style	Prepare an alternative .bin kernel from SYSTEM/KERNELS, then restart while holding R to install it.
View mode	Choose List, List + Art, Horizontal carousel or Vertical carousel.
View options	Open artwork and animation settings for the current view.
Wrap around	Loop browsers and menus past either end. On by default; turn Off for fixed ends.
Boot to	Choose Start screen, SD, NOR, Last game, Recents or Favourites as the startup destination.
Featured game	Choose Last played or Favourites for the Start screen. Select also switches between them on that screen.

Interface view options

List folders	Use List view in folders without games, then your chosen view in game folders. On by default. SYSTEM always uses List view.
Thumbnails	Choose the included 120 x 80 title artwork or 80 x 80 box artwork.
Art position	Align side artwork Top, Centre or Bottom in the horizontal carousel; Left, Centre or Right in the vertical carousel. In List + Art, position the thumbnail at the Top, Centre or Bottom.
Art border	Choose Off, Accent, Black, Grey or White. Accent highlights the selected carousel artwork; neighbouring artwork uses grey.
Round corners	Round artwork corners, keep only Start screen artwork square, or turn rounding Off. Borders follow the selected outline.
Animations	Slide smoothly between carousel games, with a brief pulse on direct launch. On by default; Off retains the static presentation.
Side size	With animations On, Small previews grow as they move into focus; Equal keeps side artwork the same size as the selection.

Games

Boot engine	Use the fast patch engine normally; use manual patching for modified games that need it.
Auto save	Automatically back up the previous game's save when DS Style starts.
Quick start	Choose the boot hotkey that immediately starts the last played game.
Addon settings	Choose which in-game addon features are available.
Boot mode	Choose the default way GBA games are launched.
Sleep hotkey	Choose the in-game sleep command.
Addon hotkey	Choose the in-game menu command.
Enable BIOS	Choose whether GBA games use the full GBA startup BIOS.
Back up saves	Choose whether save copies are written to BACKUP.

Hardware

Mode B	Omega DE only. Choose rumble, RAM expansion or DS-GBA link behaviour when the cartridge switch is set appropriately.
In-game RTC	Enable the cartridge RTC module for games that need a real-time clock.
LED settings	Omega DE only. Configure the cartridge LEDs.

The About page may reward a little curiosity.

> **OMEGA DE ONLY** Mode B and LED settings appear only on the Omega Definitive Edition. Mode B can provide rumble, memory expansion or DS-GBA link behaviour when the cartridge switch is set appropriately.

Launching Games

Choosing a launch method

The Boot mode setting chooses what happens when you open a GBA game. Clean launches immediately without add-on features. Add-on launches immediately with the features selected in Addon settings. Menu opens the standard EZ-Flash boot menu each time, allowing you to choose manually.

The boot menu

The standard boot menu provides the familiar EZ-Flash choices for clean boot, add-on boot and writing a game to NOR Flash.

> **MODIFIED GAMES** If a translation, ROM hack or homebrew title does not start correctly, set Boot mode to Menu, select the manual patch engine and confirm the save type.

Addon features

Addon features are selected in Settings and used only when a game is launched with addon support. The in-game menu is opened with the configured addon hotkey. Available items may include reset, save state, load state, sleep and cheat controls.

Cheats

Cheat choices appear only when the cheat library contains a matching entry and cheat support is enabled. Select the desired cheats, launch with add-on support, then enable them from the in-game menu when needed.

> **SAVE CAREFULLY** Cheats can interfere with save data in some games. Turn cheats off before saving or loading progress whenever possible.

Writing to NOR Flash

NOR Flash keeps games on the cartridge for fast access. Use the clean or addon write option from a game’s launch menu, then use the NOR Flash screen to start or manage written games.

On the Omega Definitive Edition, NOR Flash is not noticeably faster than launching from the SD card. Its main purpose is supporting Mode B features.

Do not switch off the console while writing, deleting or formatting NOR Flash. Formatting the complete NOR area can take several minutes.

Omega DE standalone and Mode B features

On the Omega DE, Mode B can expose cartridge functions to Nintendo DS software. Link mode presents the first NOR game as though it were a standalone GBA cartridge. Before and after a Mode B session, the save transfer commands copy that game's save between SD storage and the cartridge so progress remains available in both modes.

Artwork and Thumbnails

Two artwork formats

Style	Location
Title artwork	120 x 80 pixels, stored in SYSTEM/IMGS.
Box artwork	80 x 80 pixels, stored in SYSTEM/IMGS2.

The Thumbnails setting chooses which collection is shown. Both collections are included in the standard installation. Standard GBA artwork is organised by the game's internal code; the Thumbnail Scraper creates this structure automatically.

Both artwork formats can be used in the horizontal carousel, vertical carousel and List + Art view.

Custom artwork for any file or folder

CUSTOM folders provide artwork for ROM hacks, homebrew, translations, emulated games, media, documents, folders or any item whose normal artwork is missing or undesired.

Name the BMP exactly after the file without its extension, or after the folder as it appears on the SD card.

Ready-made wide and square console folder artwork is included in the CUSTOM folders. Rename a supplied image if needed to match the name of your console folder.

```
Pokemon Emerald Rogue.gba
  -> SYSTEM/IMGS/CUSTOM/Pokemon Emerald Rogue.bmp
  -> SYSTEM/IMGS2/CUSTOM/Pokemon Emerald Rogue.bmp

Game Boy Advance  (folder)
  -> SYSTEM/IMGS/CUSTOM/Game Boy Advance.bmp
  -> SYSTEM/IMGS2/CUSTOM/Game Boy Advance.bmp
```

- File artwork uses the filename without its extension.
- Folder artwork uses the folder name exactly as it appears on the card.
- Matching is not case-sensitive.
- Files with the same base name and different extensions share artwork.
- Names such as Game (1) and Game (2) remain separate.
- Each CUSTOM folder supports up to 256 images because of the GBA's memory limits.

> **CUSTOM ART TAKES PRIORITY** When a matching image exists in CUSTOM, DS Style uses it before the normal game-code artwork. Removing the custom image restores the normal fallback.

Thumbnail Scraper



DS Style Thumbnail Scraper creates correctly formatted artwork without requiring you to rename or modify games. It can build a complete pack or create a small collection of custom images.

Build Pack

Use Build Pack when you want a broad GBA artwork collection. Choose the thumbnail size, then choose an artwork source.

Libretro	Downloads artwork from the public Libretro library. Choose box art, gameplay screenshots or title screens.
Local Pack	Converts an unzipped artwork collection already stored on your computer.

Choose the game regions to include and arrange the regional artwork priority. If the first choice is unavailable, the next enabled region is tried. Global crop and zoom settings apply to the pack.

Search, preview and exceptions

Search & Preview lets you choose a supported system and inspect individual Libretro results before building. Exceptions preserve a different crop, zoom, position or image choice for a particular GBA game while the rest of the pack uses the global settings.

Custom Art

Use Custom Art for any file or folder you want to give artwork. Select a file to capture its exact name, choose a folder name, or enter the name manually. Each entry can keep its own crop and zoom settings, and can be created in either artwork size.

Scan SD Card checks the games already on your card and adds matching artwork for supported emulated systems. GBA games are excluded by default because Build Pack is the more efficient way to create a regular GBA collection. The scanner keeps existing custom entries and respects the 256-image limit for each CUSTOM folder.

Output and cache

Finished packs are placed in a dated folder inside DS Style Thumbnail Scraper output, beside the program. Open that dated folder when you are ready to copy IMGS or IMGS2 to your microSD card. A clearly named cache folder may also appear; it stores downloaded index information so later searches and builds can start more quickly.

> **NO GAME DOWNLOADS** The scraper works entirely with artwork. It does not download games, and your ROM files do not need to be edited.

DS Style Customiser



DS Style Customiser is an easy-to-use Windows program for creating a personal kernel. Each project is a private working copy, so the supplied DS Style source remains untouched and you can return to the project later.

Before opening the Customiser

- Install devkitPro in C:\devkitPro.
- Keep the Customiser executable, Templates folder and supplied DS Style source folders together.
- Choose the correct cartridge model when creating the project.
- Use GIMP or another image editor for template artwork; XCF templates are intended for GIMP.

devkitPro	GIMP
Required to build a finished kernel. Install it in C:\devkitPro.	Recommended for editing the supplied XCF artwork templates.
Download devkitPro	Download GIMP

A simple project workflow

1. Create a project and choose Original Omega or Omega Definitive Edition.
2. Adjust colours, images, sounds and interface text.
3. Use the Start, Horizontal and Vertical pages to preview or edit supported layout choices.
4. Save each section as you work.
5. Open Build and create the cartridge's kernel file.
6. Place the kernel file on the root of the microSD card and hold R while the cartridge boots.

Updating or converting a project

Use Import / Convert to bring an older project onto the current DS Style source, or to create a copy for the other cartridge model. Choose the destination cartridge first, then select either the project

folder or its DS Style Source folder. The Customiser creates a new project and carries over its artwork, colours, sounds, text and supported layout choices; the original project is not changed.

> **OMEGA DE-ONLY CUSTOM SLOTS** When a project is converted to the original Omega, separate Custom Theme and Custom Colour assets are preserved inside the new project but are not included in its kernel build.

What can be changed

Colours Edit GBA colour values with RGB controls, HTML colour values and a picker.	**Images** Replace light and dark backgrounds, top bars, icons and the splash image.
Sounds Preview or replace interface and boot sounds with WAV files within the shown limits.	**Text** Edit interface wording and use language presets as a starting point.
Start screen Choose supported layouts, indicators, alignment and navigation presets.	**Carousel views** Adjust supported title, artwork, heart and navigation positions with live previews.

Images and templates

PNG, JPG and BMP files are accepted for image replacements. Larger images are resized to the required canvas. For the cleanest result, start with the recommended size displayed beside each asset and keep baked interface elements aligned with the template.

When using a supplied template, place your background on a layer below the existing interface elements. You may restyle those elements, but keep them in the same positions so they continue to align with text, artwork and selection areas in the kernel.

Replacing sounds

Replacement sounds must use WAV format and remain within the limits shown by the Customiser. Trim unnecessary silence from the beginning and end so each sound responds promptly and finishes cleanly.

Custom Theme and Custom Colour

On the Omega Definitive Edition, the Custom columns add a new selectable option only when every required asset or colour has been supplied. If a custom set is incomplete, the Customiser explains what is missing and can build without that unfinished option.

MODEL DIFFERENCE The original Omega does not add separate Custom Theme or Custom Colour slots because its kernel has a smaller size limit. Edit any built-in colour and its top bar and icons instead; images, sounds and text remain customisable.

Loading styles from SYSTEM/KERNELS

On either cartridge model, custom kernels created with the Customiser can be kept in SYSTEM/KERNELS. Any .bin kernel placed there may be given a clear name of your choice, making it easy to keep several designs together.

Consider keeping a copy of the standard DS Style kernel in the same folder. This gives you a simple way to return to the default design whenever you wish.

To install a style, open Settings, choose Interface, then choose Load Style. Select the style you want to prepare, then restart the console while holding R to install it.

Undo and Default

Undo restores the value or asset that was present when the project was opened. Default restores the original DS Style source asset.

Languages and Filenames

Included interface languages

DS Style includes English (UK), English (US), Spanish, French, Portuguese, German, Turkish, Italian, Dutch, Swedish, Finnish, Chinese and Thai. The Customiser can edit the wording stored in the Latin-script language slots. Chinese and Thai are built in.

Interface text and filename text are different

The DS Style interface includes an extended character set for its built-in translations. Filenames arrive through the cartridge's SD-card filesystem, which can provide a smaller set of accented characters.

ACCENTED FILENAMES Lowercase filename support includes: à á è é ê ì í ò ó ù ú ü. Other supported interface accents may not display correctly when they appear in a filename.

If a filename displays question marks, rename the file with unaccented Latin characters.

Supported Files

DS Style can open GBA games directly and uses the supplied plug-ins for a range of emulated systems and media formats. Compatibility still depends on the individual game, plug-in and GBA hardware limits.

Game and emulator formats

Extension	Handled as
.gba, .bin, .agb	Game Boy Advance ROM
.mb	GBA multiboot ROM
.gb, .gbc	Game Boy / Game Boy Color through Goomba Color
.nes	NES through PocketNES
.gg, .sms, .sg	Game Gear / Master System / SG-1000 through SMSAdvance
.ngp, .ngc, .ngpc	Neo Geo Pocket / Color through NGPAdvance
.pce	PC Engine through PCEAdvance
.ws, .wsc	WonderSwan / Color through SwanAdvance

Additional emulator formats

Extension	Handled as
.rom	MSX cartridge through MSXAdvance
.z80	48K ZX Spectrum through ZXAdvance
.col	ColecoVision through Cologne; user-prepared Cologne build required
.c8	CHIP-8 through Chip8Adv
.arc	Emerson Arcadia 2001 ROM
.sv	Watara Supervision through Wasabi

Emulator requirements

MSXAdvance uses C-BIOS. ColecoVision support requires a user-prepared Cologne build containing a legally obtained ColecoVision BIOS; place the completed col.gba plug-in in SYSTEM/PLUG. Refer to the emulator's own documentation when preparing either component.

Media and document formats

Extension	Handled as
.jpg, .jpeg, .bmp, .pcx	Images
.lz, .raw, .ap	GBA image formats
.txt, .md, .markdown	Text and Markdown documents
.wav, .mod, .mid, .nsf	Audio and music
.vgm, .vga, .vgl	SMS / Game Gear music
.k3m, .sb, .bgf, .mda, .cwz	Additional supported audio formats

The supplied DS Style viewer presents text in a clean light or dark layout. Markdown files support headings, bold text and horizontal dividers. Use Up and Down to move one line, Left and Right or L and R to move one page, Select to change theme, Start to show controls, and B to return to DS Style.

Care and Safety

Give saves time to finish

On the original Omega, wait a few seconds after saving in a game, using a save state, or triggering an emulator's save action before switching off or resetting. The Omega Definitive Edition does not require the same waiting habit for normal GBA saves.

> **A SIMPLE HABIT** On the original Omega, count slowly to five after saving before switching off. It is a small pause that can prevent lost saves and filesystem damage.

Emulated GB, GBC and NES games

Press L + R to open the emulator menu.

Kernel updates

Keep the console on throughout every kernel update. Stay on the latest DS Style release, and update before reporting an issue if you are using an older version.

NOR Flash operations

Never remove power while a game is being written to NOR Flash or while NOR is being formatted. Use delete and format commands carefully and keep backups of important saves.

Cheats and save states

> **WARNING** Cheats and save states alter or capture a running game in ways the original software did not expect. Some games may show graphical or audio issues after loading a state, and poorly matched cheats can cause crashes or save problems.

Frequently Asked Questions

Holding R does not start the update.

Check the filename and location. The original Omega uses ezkernel.bin; the Omega DE uses ezkernelnew.bin. The file must be on the microSD root.

My saves are not loading.

Make sure the SAVER folder is inside SYSTEM. DS Style expects saves at SYSTEM/SAVER; a SAVER folder left at the microSD root will not be used.

My files or folders are not appearing.

Check that the microSD card is formatted correctly and safely ejected after copying files. See **Prepare the microSD card** for the recommended filesystem and allocation-unit settings.

My filenames contain question marks.

The SD-card filesystem supports a smaller character set than DS Style's internal interface text. Rename the affected file with supported or unaccented Latin characters, and see **Languages and Filenames** for the supported accented characters.

Does DS Style support other flashcarts?

DS Style supports only the EZ-Flash Omega and the original EZ-Flash Omega Definitive Edition. It does not currently support the EZ-Flash Omega Definitive Edition B, released on 26 May 2026.

> **OMEGA DEFINITIVE EDITION B** This is not the earlier Rev B of the original Omega Definitive Edition. The new model has a blue PCB marked EZODE-B on the rear and uses a different kernel. EZ-Flash has not yet published its source code, so DS Style cannot be ported to it until that source is available. Owners may contact EZ-Flash to request its publication.

Artwork is missing.

Check the selected Thumbnails setting and confirm that the artwork is in SYSTEM/IMGS or SYSTEM/IMGS2. Custom artwork belongs in the relevant CUSTOM folder. See **Artwork and Thumbnails** for sizes, locations and naming guidance.

The Customiser cannot find devkitPro.

Install devkitPro at exactly C:\devkitPro. A different drive, renamed folder or nested installation will not be detected by the Customiser.

Can I remove the kernel update file afterwards?

Yes. After confirming that DS Style starts correctly, remove ezkernel.bin or ezkernelnew.bin from the card using your computer.

How do I uninstall DS Style?

Restore the stock SD-card layout by referring to the backup made before installation, remove DS Style-only files and flash the official kernel for your cartridge. Follow **Uninstall DS Style** for the complete process.

Uninstall DS Style

RETURN THE CARTRIDGE TO THE OFFICIAL EZ-FLASH LAYOUT

The simplest method is to restore the stock microSD-card layout, referring to the backup made before installing DS Style. Back up any newer saves first, then compare the card with that original copy.

Reference stock layout

```
microSD root
|-- ezkernel.bin              Original Omega update file, temporarily
|-- ezkernelnew.bin           Omega DE update file, temporarily
|-- SAVER                     Game saves
|-- RTS                       Save states
|-- CHEAT                     Cheat library
|-- PATCH                     Addon patch data
`-- IMGS                      Artwork, if used by the official kernel
```

> **USE YOUR BACKUP AS THE AUTHORITY** The exact folders present depend on the features you use. Refer to your own backup when restoring the layout, and do not delete unfamiliar personal files.

1. Back up the current SYSTEM/SAVER folder and any other newer files you want to keep.
2. Download the latest official kernel for your exact cartridge from EZ-Flash.

3. Restore the stock folder layout by referring to your pre-installation backup. Move saves and other stock folders back to their original locations.
4. Remove DS Style-only settings, custom artwork and support files after confirming that anything important has been backed up.
5. Place the official kernel update file on the microSD root.
6. Hold R while powering on, and keep the console powered until the official kernel has finished installing.

Reporting Bugs

Before reporting a problem, update to the latest DS Style release, restart the cartridge and try to reproduce the issue once more. This helps separate a current bug from an older fixed issue or a one-time SD-card problem.

What to include

- Your cartridge model and hardware revision.
- The DS Style release you are using.
- The selected language, view mode and thumbnail style.
- Clear steps that reproduce the problem.
- Optionally, a photograph or short video. This is especially helpful when the issue is visual or produces unusual sound.
- Whether the same action still occurs after restarting the cartridge.

Report the issue on GBAtemp

Use the main DS Style thread so the report, follow-up questions and fix remain visible to other users.

Open the GBAtemp thread

Open Source and Community

DS Style is open source. You are welcome to modify it, create themes and share personal builds or related tools. No permission is required.

> **CREDIT IS APPRECIATED** When sharing a modified build, theme or derivative tool, please credit DS Style and its original contributors (for example, FrankieT19 and the credited upstream authors).

Source code

Omega DE kernel

Source for the Omega Definitive Edition release.

Open repository

Original Omega kernel

Source for the original Omega release.

Open repository

DS Style Customiser
Source for the personalisation and build tool.
Open repository

Thumbnail Scraper
Source for the artwork and thumbnail tool.
Open repository

Community and guides

DS Style on GBAtemp
Release discussion, community support and updates.
Open the GBAtemp thread

Video showcase and tutorial
A walkthrough of DS Style and installation.
Watch on YouTube

Official EZ-Flash reference

EZ-Flash downloads
Official kernels, firmware, manuals, artwork and cheat libraries.
Open downloads

Original Omega manual
SD setup, saving, add-ons and NOR Flash.
Read manual

Omega DE manual
Mode B, firmware updates and everyday use.
Read manual

Credits

DS Style was created and developed by FrankieT19.

- EZ-Flash team: original Omega and Omega Definitive Edition hardware, firmware and kernel source.
- Sterophonick: the Simple theme and guide from which the project originally began.
- PogoShell: Sasq (PogoShell and plug-ins), Kuwanger (modifications), Moonlight (plug-ins).
- aidiadayo: Thai language support.
- Merkin: refreshed splash screens, system icons and contributions to defensive file handling.
- timdmackey: contributions.
- Kekun: case-sensitive HZK12.h include fix.
- ChaN: FatFs, as used by the upstream EZ-Flash kernel.
- Artwork: damageinc86 (box art), Shenske (PAL template and shadow), shonasof (GBA logo).

Special thanks to the GBAtemp and Reddit communities, everyone who has tested DS Style or reported an issue, and every user who has created artwork, themes or other additions for the project.

Enjoy your games
FrankieT19