FSL Community BSP Release Notes Documentation

Release 2.2

FSL Community BSP Team

CONTENTS

| 1 | 1 Defining the FSL C 1.1 Motivation | | | | | | | 3 3 |
|---|--|-----------------|------|------|------|------|-------|---------------|
| | 1.2 What the FSL (| | | | | | | 3 |
| | 1.3 What you can e | | | | | | | 4 |
| | 1.4 What the comm | - | | | | | | 4 |
| 2 | 2 Upstreaming | | | | | | | 5 |
| | 2.1 Main branch na | mes | | | | | | 5 |
| | 2.2 Upstream cycle | | | | | | • | 5 |
| 3 | | | | | | | | 7 |
| | 3.1 Freescale Officia | | | | | | | 7 |
| | 3.2 FSL Community | y BSP | | | | | • | 7 |
| 4 | | | | | | | | 9 |
| | 4.1 Meta-freescale | | | | | | | 9 |
| | 4.2 License \dots | | | | | | | 9 |
| | 4.3 Kernel Release l | Notes | | | | | | 10 |
| | 4.4 Different Produc | ct SoC Families | | | | | | 10 |
| | 4.5 Supported Boar | d List | | | | | • | 11 |
| 5 | 5 Software Architect | ure | | | | | | 17 |
| | 5.1 SoC Hierarchy | | | | | | | 17 |
| | 5.2 Linux Kernel . | | | | | | | 17 |
| | 5.3 Bootloaders | | | | | | | 20 |
| | 5.4 User Space Pack | _ | | | | | | 23 |
| | 5.5 PackageGroups | and Images | | | | | • | 26 |
| 6 | 6 Test results | | | | | | | 29 |
| 7 | 8 | | | | | | | 31 |
| | 7.1 Morty Source C | ode | | | | | • | 31 |
| Q | 8 Known Issues | | | | | | | 33 |

This document is the release notes for the FSL Community BSP 2.2, which is the result of a community effort to improve Freescale's SoC support for OpenEmbedded and Yocto Project.

This document is released under Creative Commons 4.0 (CC BY-SA 4.0)

If you want to make part of FSL Community BSP access http://freescale.github.io and find links to this document, how to contribute, and how to download both the source code and several pre-built images.

CONTENTS 1

2 CONTENTS

DEFINING THE FSL COMMUNITY BSP

The FSL Community BSP is a community-driven project to provide and maintain Board Support Package (BSP) metadata layers for use in OpenEmbedded and Yocto Project with Freescale's SoCs.

The FSL Community BSP follows Yorto Project's release schedule and branch naming (since release 1.3, denzil).

See the Yocto Project Release for details on the Yocto Project.

1.1 Motivation

The FSL Community BSP started with the goal of easing the use of OpenEmbedded and Yocto Project with Freescale's SoCs and providing an example of how to assemble an easy-to-use platform as the basis for future products.

The FSL Community BSP provides:

- common environment configuration;
- multiple download layers with the use of repo;
- common location for discussing Freescale SoCs, kernels, bootloaders, user space packages, (BSP in general), bugs, how-tos, and so on

1.2 What the FSL Community BSP is not

The FSL Community BSP does not have a paid support team. The members of this community have full-time jobs and work on the project in their spare time. Most of them are working with Freescale SoCs in their full-time job, so it means some of them can provide paid support if requested.

The provided source code is not intended to be a product in itself. It is a reference platform for people to build products with. Because of this, plan to have a development and test cycle for your product if you decide to base it on the FSL Community BSP.

The project is community-driven work, and it is NOT an official Freescale support channel.

1.3 What you can expect

- You can expect help when you post a question, but please be patient. Wait for at least two days for a response. Most of the time, people do reply when they know an answer or have advice to offer. If you don't receive a reply, then it may be due to no one in the community having an adequate response.
- The stable branch is supported for six months after the release date (following the Yocto Project's release schedule);
- The upstreaming takes place as quickly as possible and any needed adjustment is going to be made accordingly.

1.4 What the community expects from you

The community does expect that you contribute back by:

- replying when you know the answer to a question in the mailing list;
- reviewing the patches sent to mailing list;
- testing new patches that affect you directly or indirectly;
- reporting bugs you may find;
- upstreaming bug fixes;
- upstreaming features that may be good for the community.

UPSTREAMING

The FSL Community BSP provides test images and demos in addition to the base BSP for Freescale reference boards and third-party boards. In addition to the BSP, a Linux-based operating system typically requires several other packages, such as ssh client/server, window managers, applications, and so on. These packages are not part of the BSP. In other words, the FSL Community BSP is used with applications, tools and metadata from other projects, such as OpenEmbedded and Poky.

The FSL Community BSP always offers a stable version and a development version. You may face errors that are not caused by FSL Community BSP's layers but instead by OpenEmbedded's or Poky's metadata. In this case, the error must be fixed in its layer.

The following image shows the upstream levels:

2.1 Main branch names

- master-next: this branch is used to keep the patches to be built by the autobuilder for the very first test build. Do not expect to have a clear merging schedule, or to have a stable project when working with the master-next branch;
- master: this is the branch where development takes place. Any new feature or bug fix must be merged here first. This is the development of the next stable branch;
- morty: the latest stable branch. This branch only accepts bug fixes, and is supported for 6 months after the release date.

There are other branches available, and they are the previous stable branches. They are kept online for users' convenience, and you should not expect backports or bug fixes.

2.2 Upstream cycle

In addition to the normal Yocto Project upstream process, there is also a BSP upstream cycle.

The BSP upstream cycle starts just after a Freescale Official Release is published in git.freescale.com. The patches to adapt the recipes from **meta-fsl-bsp-release** are sent out for review to the **meta-freescale** mailing list and are merged in the **meta-freescale**, **meta-freescale-3rdparty** or **meta-freescale-distro** layers or upstreamed to Yocto Project accordingly.

A more detailed step-by-step process is shown below:

1. New Freescale Official Release is published;

- 2. The patches are sent to **meta-freescale**;
- 3. After the review process, the patches are merged in the proper layer's master-next branch;
- 4. Source code is built by the autobuilder;
- 5. After one week in *master-next*, it is merged in *master*;
- 6. Freescale internally bases the next Freescale Official Release from the community source code;
- 7. Back to step 1.

The result is that Freescale uses the FSL Community BSP source code with its bug fixes, improvements, and any new features to create the next Freescale Official Release.

Freescale uses the latest stable branch from Yocto Project to base the *next* Freescale Official Release. When this release is published, it is rebased and reworked to be merged in the current development branch.

THE DIFFERENCES BETWEEN FSL COMMUNITY BSP AND FREESCALE OFFICIAL RELEASE

The goal for each project is different. See below for the main points of divergence.

3.1 Freescale Official Release

The Freescale Official Release is intended to provide a static base for Freescale to test and validate the BSP modules with Freescale evaluation boards, and it is developed internally by Freescale. The set of supported boards vary from release to release and is listed in the Freescale Official Release notes for the specific version. The release points to a static revision of every included layer. Therefore, the release does not receive updates and bug fixes.

3.2 FSL Community BSP

The FSL Community BSP is a reference system that can be used as a base for products and is an open project that accepts contributions from the community. It supports a wide range of boards which range from Freescale evaluation boards (**meta-freescale** layer) to third-party boards (**meta-freescale-3rdparty**). The release is a "moving target", so there are updates on top of the released source code, such as the addition of new features and bug fixes.

Table 3.1: Comparative between Freescale Official Release and FSL Community BSP

| | Freescale Official Release | FSL Community BSP | | |
|--------------------------|-------------------------------|-------------------------------|--|--|
| Intended use | Reference system for BSP | Reference system for use as | | |
| | modules test and validation | base for any project for all | | |
| | on Freescale Reference Boards | supported boards | | |
| Code | Static. Only include any bug | Updates. Receives bug fixes | | |
| | fixes on the upcoming release | and has security issues fixed | | |
| | | often | | |
| Contribution | Indirect contribution via FSL | Open, everyone is welcome to | | |
| | Community BSP. After re- | contribute to the project | | |
| | vision, contribution may be | | | |
| | merged in upcoming release | | | |
| Board Support | Limited, as it supports just | Extended, as it supports both | | |
| | the Freescale evaluation | Freescale evaluation boards | | |
| | boards listed in the Release | and 3rd party boards. See | | |
| | Notes | Supported Board List | | |
| Yocto Project Compatible | No | Yes | | |
| Support | i.MX Community | meta-freescale | | |
| Repository | git.freescale.com | github.com/Freescale | | |

FSL COMMUNITY BSP SCOPE

The scope of the FSL Community BSP includes the meta layers:

- meta-freescale: provides the base support and Freescale ARM and PPC reference boards;
- meta-freescale-3rdparty: provides support for 3rd party and partner boards;
- meta-freescale-distro: provides distros support, images recipes, demo recipes, and packagegroups used to ease the development with Yocto Project.
- Documentation: provides the source code for FSL Community BSP Release Notes (RN) and User Guide (UG).

4.1 Meta-freescale

Since the Yocto Project release 2.2 (Morty) the FSL Community BSP changed the meta layers names. You can see the announcement here.

The following table show the renaming upgrade path:

| Krogoth | Morty |
|--------------------|-------------------------|
| meta-fsl-arm | meta-freescale |
| meta-fsl-ppc | meta-freescale |
| meta-fsl-arm-extra | meta-freescale-3rdparty |
| meta-fsl-demos | meta-freescale-distros |

The **meta-fsl-arm** and **meta-fsl-ppc** meta layers are deprecated. The last release for these meta layers is **krogoth**. Do not expect any update to the layer other than critical bug-fixes. **Meta-fsl-arm** and **meta-fsl-ppc** must be replaced by **meta-freescale**.

The **meta-freescale** meta layer goal is to integrate the ARM and PPC SoC based source code from Freescale, it includes **i.MX**, **Vybrid**, **QorIQ** and **Layerscape** BSPs.

The **meta-fsl-arm-extra** now is **meta-freescale-3rdparty**, any local copy should work as there is a mirror set.

The **meta-fsl-demos** now is **meta-freescale-distros**, any local copy should work as there is a mirror set.

4.2 License

The FSL Community BSP is a project with the same licensing of most Yocto Project layers. It means the recipe file is under a certain license, and the source code used by that recipe is under

another certain license (being it equal or not).

Most of FSL Community BSP's metadata is under MIT license, however the extensive and accurate list of package's license provided by the Yocto Project's metadata can be generated with few commands, for detailed information on how license is handled by Yocto Project see the Reference Manual.

4.2.1 End User License Agreement (EULA)

Freescale releases basically two kind of packages, the open sourced packages use regular open source licenses (GPLv2 for example).

The close sourced packages are released under the Freescale License (known as EULA). Each package has a copy of EULA inside itself and a copy of the EULA text is also included inside meta-freescale root dir (sources/meta-freescale/EULA).

The FSL Community BSP handles the EULA acceptance by prompting user to read and accept EULA text at the very first environment setup. It is user's duty to read and understand it before accepting it. After it is accepted the first time, it is assumed accepted in any other build.

4.3 Kernel Release Notes

The FSL Community BSP includes support for several kernel providers. Each machine may have a different Linux Kernel provider.

The FSL Community BSP is not responsible for the content of those kernels. Although we *as* community should feel empowered to submit bug fixes and new features for those projects.

See the respective Linux Kernel provider for your machine in section Linux Kernel.

4.4 Different Product SoC Families

Currently, the FSL Community BSP includes the following Product SoC Families:

- i.MX Application Processors (imx): Regarding the i.MX Freescale Page: i.MX applications processors are multicore ARM®-based solutions for multimedia and display applications with scalability, high performance, and low power capabilities.
- Vybrid Controller Solutions based on ARM® Cores (vybrid): Regarding the Vybrid Freescale Page: Vybrid controller solutions are built on an asymmetrical-multiprocessing architecture using ARM® cores as the anchor for the platform, and are ideal for many industrial applications.
- Layerscape Architecture (ls): Regarding the Layerscape Freescale Page: delivers unprecedented efficiency and scale for the smarter, more capable networks of tomorrow.

Freescale groups a set of SoCs which target different markets in product families. Those are grouped according to their SoC features and internal hardware capabilities.

The Yocto Project's tools have the required capabilities to differentiate the architectures and BSP components for the different SoC families. In this perspective, the FSL Community BSP can support a wide range of architectures and product lines which go across several markets.

For the FSL Community BSP, the different SoCs, from all product lines manufactured by Freescale, can be seen as different machines, thus easing the use of same architecture across different markets.

4.5 Supported Board List

Please, see the next table for the complete supported board list.

Table 4.1: Supported machines in FSL Community BSP

| Machine | Name | SoC | Layer |
|------------------------|--------------------------------|-------------------------|------------------------|
| apalis-imx6 | Toradex Apalis iMX6Q/D | i.MX6 | meta-freescale-3rdpar |
| b4420qds | NXP B4420QDS | b4420 | meta-freescale |
| b4420qds-64b | NXP B4420QDS-64B | b4420 | meta-freescale |
| b4860qds | NXP B4860QDS | b4860 | meta-freescale |
| b4860qds-64b | NXP B4860QDS-64B | b4860 | meta-freescale |
| c293pcie | NXP C293PCIE | c293pcie | meta-freescale |
| cfa10036 | Crystalfontz CFA-10036 | i.MX28 | meta-freescale-3rdpar |
| cfa10037 | Crystalfontz CFA-10037 | i.MX28 | meta-freescale-3rdpar |
| cfa10049 | Crystalfontz CFA-10049 | i.MX28 | meta-freescale-3rdpar |
| cfa10055 | Crystalfontz CFA-10055 | i.MX28 | meta-freescale-3rdpar |
| cfa10056 | Crystalfontz CFA-10056 | i.MX28 | meta-freescale-3rdpart |
| cfa10057 | Crystalfontz CFA-10057 | i.MX28 | meta-freescale-3rdpart |
| cfa10058 | Crystalfontz CFA-10058 | i.MX28 | meta-freescale-3rdpart |
| cgtqmx6 | Congatec QMX6 Evaluation board | i.MX6 Q/DL | meta-freescale-3rdpart |
| cm-fx6 | CompuLab CM-FX6 | i.MX6 Q/DL | meta-freescale-3rdpart |
| colibri-imx6 | Toradex Colibri iMX6DL/S | i.MX6 DL/S | meta-freescale-3rdpart |
| colibri-imx7 | Toradex Colibri iMX7D/S | i.MX 7Dual / i.MX 7Solo | meta-freescale-3rdpart |
| colibri-vf | Toradex Colibri VF50/VF61 | VF500/VF610 | meta-freescale-3rdpart |
| cubox-i | SolidRun CuBox-i and Hum- | i.MX6 Q/DL | meta-freescale-3rdpart |
| | mingBoard | -, | _ |
| imx233-olinuxino-maxi | OLIMEX iMX233- | i.MX23 | meta-freescale-3rdpar |
| | OLinuXino-Maxi | | |
| imx233-olinuxino-micro | OLIMEX iMX233- | i.MX23 | meta-freescale-3rdpar |
| | OLinuXino-Micro | | |
| imx233-olinuxino-mini | OLIMEX iMX233- | i.MX23 | meta-freescale-3rdpart |
| | OLinuXino-Mini | | |
| imx233-olinuxino-nano | OLIMEX iMX233- | i.MX23 | meta-freescale-3rdpar |
| | OLinuXino-Nano | | |
| imx23evk | NXP i.MX23 Evaluation Kit | i.MX23 | meta-freescale |
| imx28evk | NXP i.MX28 Evaluation Kit | i.MX28 | meta-freescale |
| imx51evk | NXP i.MX51 Evaluation Kit | i.MX51 | meta-freescale |
| imx53ard | NXP i.MX53 SABRE Auto- | i.MX53 | meta-freescale |
| | motive Board | | |
| imx53qsb | NXP i.MX53 Quick Start | i.MX53 | meta-freescale |
| | Board | | |
| imx6dl-riotboard | RIoTboard | i.MX6S | meta-freescale-3rdpart |
| | | | Continued on next pag |
| | | | |

Table 4.1 – continued from previous page

| | Table 4.1 – continued from | om previous page | |
|---------------------------------------|---------------------------------------|------------------|---------------------------------------|
| Machine | Name | SoC | Layer |
| imx6dlsabreauto | NXP i.MX6DL SABRE Automotive | i.MX6DL | meta-freescale |
| imx6dlsabresd | NXP i.MX6DL SABRE Smart Device | i.MX6DL | meta-freescale |
| imx6q-dms-ba16 | Advantech DMS BA16 | i.MX6Q | meta-freescale-3rdpar |
| imx6qdl-variscite-som | Variscite i.MX6Q/DL VAR- SOM-MX6 | i.MX6Q/DL | meta-freescale-3rdpar |
| imx6qpsabreauto | NXP i.MX6Q Plus SABRE Automotive | i.MX6QP | meta-freescale |
| imx6qpsabresd | NXP i.MX6Q Plus SABRE Smart Device | i.MX6QP | meta-freescale |
| imx6qsabreauto | NXP i.MX6Q SABRE Automotive | i.MX6Q | meta-freescale |
| imx6qsabrelite | Boundary Devices i.MX6Q SABRE Lite | i.MX6Q | meta-freescale-3rdpar |
| imx6qsabresd | NXP i.MX6Q SABRE Smart Device | i.MX6Q | meta-freescale |
| imx6sl-warp | WaRP | i.MX6SL | meta-freescale-3rdpar |
| imx6slevk | NXP i.MX6SL Evaluation Kit | i.MX6SL | meta-freescale |
| ${ m imx} 6 { m solos} { m abreauto}$ | NXP i.MX6Solo SABRE Automotive | i.MX6S | meta-freescale |
| imx6solosabresd | NXP i.MX6Solo SABRE Smart Device | i.MX6S | meta-freescale |
| imx6sxsabreauto | NXP i.MX6SoloX Sabre Automotive | i.MX6SX | meta-freescale |
| imx6sxsabresd | NXP i.MX6SoloX SabreSD | i.MX6SX | meta-freescale |
| imx6ul-pico-hobbit | Hobbitboard (PICO- IMX6UL) | i.MX6UL | meta-freescale-3rdpar |
| imx6ulevk | NXP i.MX6UL Evaluation Kit | i.MX6UL | meta-freescale |
| imx7dsabresd | NXP i.MX7D SABRE Smart Device | i.MX7D | meta-freescale |
| imx7s-warp | WaRP7 | i.MX7S | meta-freescale-3rdpar |
| ls1021atwr | NXP LS1021ATWR board | ls102xa | meta-freescale |
| ls1043ardb | NXP LS1043ARDB board | LSCH2 | meta-freescale |
| ls1043ardb-32b | NXP LS1043ARDB-32B | LSCH2 | meta-freescale |
| ls1046ardb | NXP LS1046ARDB | LSCH2 | meta-freescale |
| ls1046ardb-32b | NXP LS1046ARDB | LSCH2 | meta-freescale |
| ls2080ardb | NXP LS2080ARDB board | LSCH3 | meta-freescale |
| ${ m m28evk}$ | DENX M28 SoM Evaluation Kit | i.MX28 | meta-freescale-3rdpar |
| ${ m m53evk}$ | DENX M53 SoM Evaluation Kit | i.MX53 | meta-freescale-3rdpar |
| nitrogen6sx | Boundary Devices Nitrogen6SX | i.MX6SX | meta-freescale-3rdpar |
| nitrogen6x | Boundary Devices Nitrogen6X | i.MX6 Q/DL | meta-freescale-3rdpar |
| | | | Continued on next pag |
| | · | | · · · · · · · · · · · · · · · · · · · |

Table 4.1 – continued from previous page

| | rable III continued | o p. cv.ous pubc | |
|-----------------|----------------------------|------------------|-----------------------|
| Machine | Name | SoC | Layer |
| nitrogen6x-lite | Boundary Devices Nitro- | i.MX6S | meta-freescale-3rdpar |
| | gen6X Lite | | |
| nitrogen7 | Boundary Devices Nitrogen7 | i.MX7D | meta-freescale-3rdpar |
| p2041rdb | NXP P2041RDB | p2041 | meta-freescale |
| p3041ds | NXP P3041DS | p3041 | meta-freescale |
| p4080ds | NXP P4080DS | p4080 | meta-freescale |
| p5020ds | NXP P5020DS | p5020 | meta-freescale |
| p5020ds-64b | NXP P5020DS-64B | p5020 | meta-freescale |
| p5040ds | NXP P5040DS | p5040 | meta-freescale |
| p5040ds-64b | NXP P5040DS-64B | p5040 | meta-freescale |
| pcm052 | Phytec phyCORE Vybrid De- | vf60 | meta-freescale-3rdpar |
| | velopment Kit | | |
| t1023rdb | NXP T1023RDB | t1023 | meta-freescale |
| t1023rdb-64b | NXP T1023RDB | t1023 | meta-freescale |
| t1024rdb | NXP T1024RDB | t1024 | meta-freescale |
| t1024rdb-64b | NXP T1024RDB | t1024 | meta-freescale |
| t1040d4rdb | NXP T1040D4RDB | t1040 | meta-freescale |
| t1040d4rdb-64b | NXP T1040D4RDB | t1040 | meta-freescale |
| t1042d4rdb | NXP T1042D4RDB | t1042 | meta-freescale |
| t1042d4rdb-64b | NXP T1042D4RDB | t1042 | meta-freescale |
| t2080qds | NXP T2080QDS | t2080 | meta-freescale |
| t2080qds-64b | NXP T2080QDS-64B | t2080 | meta-freescale |
| t2080rdb | NXP T2080RDB | t2080 | meta-freescale |
| t2080rdb-64b | NXP T2080RDB | t2080 | meta-freescale |
| t4160qds | NXP T4160QDS | t4160 | meta-freescale |
| t4160qds-64b | NXP T4160QDS-64B | t4160 | meta-freescale |
| t4240qds | NXP T4240QDS | t4240 | meta-freescale |
| t4240qds-64b | NXP T4240QDS-64B | t4240 | meta-freescale |
| t4240rdb | NXP T4240RDB | t4240 | meta-freescale |
| t4240rdb-64b | NXP T4240RDB | t4240 | meta-freescale |
| twr-vf65gs10 | NXP Vybrid TWR- | VF610 | meta-freescale |
| | VF65GS10 | | |
| tx6q-10x0 | Ka-Ro electronics i.MX6Q | i.MX6Q | meta-freescale-3rdpar |
| | TX6Q Computer-On-Module | | |
| tx6q-11x0 | Ka-Ro electronics i.MX6Q | i.MX6Q | meta-freescale-3rdpar |
| | TX6Q Computer-On-Module | | |
| tx6s-8034 | Ka-Ro electronics i.MX6S | i.MX6S | meta-freescale-3rdpar |
| | TX6S Computer-On-Module | | |
| tx6s-8035 | Ka-Ro electronics i.MX6S | i.MX6S | meta-freescale-3rdpar |
| | TX6S Computer-On-Module | | |
| tx6u-8033 | Ka-Ro electronics i.MX6DL | i.MX6DL | meta-freescale-3rdpar |
| | TX6DL Computer-On- | | |
| | Module | | |
| tx6u-80x0 | Ka-Ro electronics i.MX6DL | i.MX6DL | meta-freescale-3rdpar |
| | TX6DL Computer-On- | | |
| | Module | | |
| | | | Continued on next pa |
| | | | |

Table 4.1 – continued from previous page

| Machine | Name | SoC | Layer |
|-----------|---------------------------|-----------|------------------------|
| tx6u-81x0 | Ka-Ro electronics i.MX6DL | i.MX6DL | meta-freescale-3rdpart |
| | TX6DL Computer-On- | | |
| | Module | | |
| ventana | i.MX6Q/DL Ventana Plat- | i.MX6Q/DL | meta-freescale-3rdpart |
| | form | | |
| wandboard | Wandboard i.MX6 Wand- | i.MX6Q/DL | meta-freescale-3rdpart |
| | board Quad/Dual/Solo | | |

4.5.1 Machine Maintainers

Since FSL Community BSP Release 1.6 (Daisy), the maintainer field in machine configuration files of **meta-freescale** and **meta-freescale-3rdparty** is mandatory for any new board to be added.

So now on, every new board must have someone assigned as maintainer. This ensures, in long term, all boards with a maintainer assigned. Current orphan boards are not going to be removed unless it causes maintenance problem and the fix is not straightforward.

The maintainer duties:

- The one with casting vote when a deadlock is faced.
- Responsible to keep that machine working (that means, booting and with some stability) Keep kernel, u-boot updated/tested/working.
- Keep release notes updated
- Keep test cycle updated
- Keep the most usual images building and booting

When a build error is detected, the maintainer will "fix" it. For those maintainers with kernel control (meta-freescale-3rdparty), it is expected that they properly fix the kernel issue (when it's a kernel issue). However, anything out of community control should be worked around anyway.

Machines with maintainers

Table 4.2: Machines with maintainers

| Machine | Name |
|--------------|------------------------|
| apalis-imx6 | Toradex Apalis iMX6Q/D |
| b4420qds | NXP B4420QDS |
| b4420qds-64b | NXP B4420QDS-64B |
| b4860qds | NXP B4860QDS |
| b4860qds-64b | NXP B4860QDS-64B |
| c293pcie | NXP C293PCIE |
| cfa10036 | Crystalfontz CFA-10036 |
| cfa10037 | Crystalfontz CFA-10037 |
| cfa10049 | Crystalfontz CFA-10049 |
| | Continued on next page |

Table 4.2 – continued from previous page

| Machine | le 4.2 – Continued from previous page |
|-----------------------|---------------------------------------|
| | Name |
| cfa10055 | Crystalfontz CFA-10055 |
| cfa10056 | Crystalfontz CFA-10056 |
| cfa10057 | Crystalfontz CFA-10057 |
| cfa10058 | Crystalfontz CFA-10058 |
| cgtqmx6 | Congatec QMX6 Evaluation board |
| cm-fx6 | CompuLab CM-FX6 |
| colibri-imx6 | Toradex Colibri iMX6DL/S |
| colibri-imx7 | Toradex Colibri iMX7D/S |
| colibri-vf | Toradex Colibri VF50/VF61 |
| cubox-i | SolidRun CuBox-i and HummingBoard |
| imx23evk | NXP i.MX23 Evaluation Kit |
| imx28evk | NXP i.MX28 Evaluation Kit |
| imx51evk | NXP i.MX51 Evaluation Kit |
| imx53ard | NXP i.MX53 SABRE Automotive Board |
| imx53qsb | NXP i.MX53 Quick Start Board |
| imx6dl-riotboard | RIoTboard |
| imx6dlsabreauto | NXP i.MX6DL SABRE Automotive |
| imx6dlsabresd | NXP i.MX6DL SABRE Smart Device |
| imx6q-dms-ba16 | Advantech DMS BA16 |
| imx6qdl-variscite-som | Variscite i.MX6Q/DL VAR-SOM-MX6 |
| imx6qpsabreauto | NXP i.MX6Q Plus SABRE Automotive |
| imx6qpsabresd | NXP i.MX6Q Plus SABRE Smart Device |
| imx6qsabreauto | NXP i.MX6Q SABRE Automotive |
| imx6qsabrelite | Boundary Devices i.MX6Q SABRE Lite |
| imx6qsabresd | NXP i.MX6Q SABRE Smart Device |
| imx6sl-warp | WaRP |
| imx6slevk | NXP i.MX6SL Evaluation Kit |
| imx6solosabresd | NXP i.MX6Solo SABRE Smart Device |
| imx6sxsabreauto | NXP i.MX6SoloX Sabre Automotive |
| imx6sxsabresd | NXP i.MX6SoloX SabreSD |
| imx6ul-pico-hobbit | Hobbitboard (PICO-IMX6UL) |
| imx6ulevk | NXP i.MX6UL Evaluation Kit |
| imx7dsabresd | NXP i.MX7D SABRE Smart Device |
| imx7s-warp | WaRP7 |
| ls1021atwr | NXP LS1021ATWR board |
| ls1043ardb | NXP LS1043ARDB board |
| ls1043ardb-32b | NXP LS1043ARDB-32B |
| ls1046ardb | NXP LS1046ARDB |
| ls2080ardb | NXP LS2080ARDB board |
| nitrogen6sx | Boundary Devices Nitrogen6SX |
| nitrogen6x | Boundary Devices Nitrogen6X |
| nitrogen6x-lite | Boundary Devices Nitrogen6X Lite |
| nitrogen7 | Boundary Devices Nitrogen7 |
| p2041rdb | NXP P2041RDB |
| | NXP P3041DS |
| p3041ds | NXP P4080DS |
| p4080ds | |
| p5020ds | NXP P5020DS |
| | Continued on next page |

Table 4.2 – continued from previous page

| Machine | Name |
|----------------|--|
| p5020ds-64b | NXP P5020DS-64B |
| p5040ds | NXP P5040DS |
| p5040ds-64b | NXP P5040DS-64B |
| pcm052 | Phytec phyCORE Vybrid Development Kit |
| t1023rdb | NXP T1023RDB |
| t1024rdb-64b | NXP T1024RDB |
| t1040d4rdb | NXP T1040D4RDB |
| t1042d4rdb-64b | NXP T1042D4RDB |
| t2080qds | NXP T2080QDS |
| t2080qds-64b | NXP T2080QDS-64B |
| t2080rdb | NXP T2080RDB |
| t4160qds | NXP T4160QDS |
| t4160qds-64b | NXP T4160QDS-64B |
| t4240qds | NXP T4240QDS |
| t4240qds-64b | NXP T4240QDS-64B |
| t4240rdb | NXP T4240RDB |
| twr-vf65gs10 | NXP Vybrid TWR-VF65GS10 |
| tx6q-11x0 | Ka-Ro electronics i.MX6Q TX6Q Computer-On- |
| | Module |
| tx6s-8035 | Ka-Ro electronics i.MX6S TX6S Computer-On- |
| | Module |
| tx6u-8033 | Ka-Ro electronics i.MX6DL TX6DL Computer-On- |
| | Module |
| ventana | i.MX6Q/DL Ventana Platform |
| wandboard | Wandboard i.MX6 Wandboard Quad/Dual/Solo |

Machines without a maintainer

Table 4.3: Machines without a maintainer

| Machine | Name |
|------------------------|--------------------------------|
| imx233-olinuxino-maxi | OLIMEX iMX233-OLinuXino-Maxi |
| imx233-olinuxino-micro | OLIMEX iMX233-OLinuXino-Micro |
| imx233-olinuxino-mini | OLIMEX iMX233-OLinuXino-Mini |
| imx233-olinuxino-nano | OLIMEX iMX233-OLinuXino-Nano |
| imx6solosabreauto | NXP i.MX6Solo SABRE Automotive |
| m28evk | DENX M28 SoM Evaluation Kit |
| m53evk | DENX M53 SoM Evaluation Kit |

SOFTWARE ARCHITECTURE

5.1 SoC Hierarchy

The following tree shows the SoC hierarchy:

5.2 Linux Kernel

FSL Community BSP supports the following sources for Linux Kernel:

- linux-advantech: linux-advantech version 4.1-r0.
- linux-boundary: Linux kernel for Boundary Devices boards.
- linux-cfa: Linux kernel for Crystalfontz boards.
- linux-compulab: Linux kernel for CompuLab cm-fx6 boards.
- linux-congatec: linux-congatec version 4.1.15-r0.
- linux-denx: DENX mainline based Linux kernel.
- linux-fslc: Linux kernel based on mainline kernel used by FSL Community BSP in order to provide support for some backported features and fixes, or because it was applied in linux-next and takes some time to become part of a stable version, or because it is not applicable for upstreaming.
- linux-fslc-imx: Linux kernel based on NXP 4.1.15-1.2.0 GA release, used by FSL Community BSP in order to provide support for i.MX based platforms and include official Linux kernel stable updates, backported features and fixes coming from the vendors, kernel community or FSL Community itself.
- linux-gateworks-imx: linux-gateworks-imx version 3.14-r0.
- linux-imx: Linux Kernel provided and supported by Freescale with focus on i.MX Family Reference Boards. It includes support for many IPs such as GPU, VPU and IPU.
- linux-karo: Linux Kernel for Ka-Ro electronics TX Computer-On-Modules.
- linux-qoriq: Linux Kernel for Freescale QorIQ platforms.
- linux-timesys: Linux Kernel with added drivers and board support for Vybrid-based platforms.
- linux-toradex: Linux kernel for Toradex Freescale i.MX based modules.
- linux-variscite: linux-variscite version 4.1.15-r0.

- linux-wandboard: Linux kernel for Wandboard.
- linux-warp7: Linux kernel based on linux-fsl-imx branch 4.1-1.0.x-imx from FSL Community BSP with additional patches to cover devices specific on WaRP7 board.

As stated in *Kernel Release Notes*, FSL Community BSP is not responsible for the Linux Kernel content in any kernel provider. If you are looking for the feature list, supported devices, official way to get a support channel or how to report bug, please, see above where to get help, for each kernel provider.

• linux-imx: provider, Freescale has a release notes document for each version released. This document has a list of known issues, new features, list of kernel arguments, and the linux-imx kernel scope for each Freescale Reference Board. This document is present into the Document Bundle provided by Freescale.

5.2.1 Default Linux Providers

The following table shows the default version of Linux Kernel provided by FSL Community BSP for each supported machine.

Table 5.1: Default Linux kernel version for each supported machine

| Board | Kernel Provider | Kernel Version |
|------------------------|-----------------|------------------------|
| apalis-imx6 | linux-toradex | 3.14.52-v2.6b2.1 |
| b4420qds | linux-qoriq | 4.1 |
| b4420qds-64b | linux-qoriq | 4.1 |
| b4860qds | linux-qoriq | 4.1 |
| b4860qds-64b | linux-qoriq | 4.1 |
| c293pcie | linux-qoriq | 4.1 |
| cfa10036 | linux-cfa | 4.1.13 |
| cfa10037 | linux-cfa | 4.1.13 |
| cfa10049 | linux-cfa | 4.1.13 |
| cfa10055 | linux-cfa | 4.1.13 |
| cfa10056 | linux-cfa | 4.1.13 |
| cfa10057 | linux-cfa | 4.1.13 |
| cfa10058 | linux-cfa | 4.1.13 |
| cgtqmx6 | linux-congatec | 4.1.15 |
| cm-fx6 | linux-compulab | 3.14.28-cm-fx6 |
| colibri-imx6 | linux-toradex | 3.14.52-v2.6b2.1 |
| colibri-imx7 | linux-toradex | 4.1.15-v2.6b2.1 |
| colibri-vf | linux-toradex | 4.4-v2.6b2 |
| cubox-i | linux-fslc | 4.8+git |
| imx233-olinuxino-maxi | linux-fslc | 4.8+git |
| imx233-olinuxino-micro | linux-fslc | 4.8+git |
| imx233-olinuxino-mini | linux-fslc | 4.8+git |
| imx233-olinuxino-nano | linux-fslc | 4.8+git |
| imx23evk | linux-fslc | 4.8+git |
| imx28evk | linux-fslc | 4.8+git |
| imx51evk | linux-fslc | 4.8+git |
| imx53ard | linux-fslc | 4.8+git |
| | | Continued on next page |

Table 5.1 – continued from previous page

| | Board | Kernel Provider | Kernel Version |
|--|--------------------|---------------------------------------|------------------------|
| imx6dl-riotboard linux-fslc-imx 4.8+git imx6dlsabreauto linux-fslc-imx 4.1-2.0.x+git imx6q-dms-ba16 linux-advantech 4.1-4.1-1.0.x-imx-dms-ba16 imx6qdl-variscite-som linux-advantech 4.1-4.1-1.0.x-imx-dms-ba16 imx6qpsabreauto linux-fslc-imx 4.1.15-2.0.0 imx6qpsabreauto linux-fslc-imx 4.1-2.0.x+git imx6qsabreauto linux-fslc-imx 4.1-2.0.x+git imx6qsabreauto linux-fslc-imx 4.1-2.0.x+git imx6qsabreauto linux-fslc-imx 4.1-2.0.x+git imx6qsabresd linux-fslc-imx 4.1-2.0.x+git imx6selosabreauto linux-fslc-imx 4.1-2.0.x+git imx6solosabreauto linux-fslc-imx 4.1-2.0.x+git imx6solosabreauto linux-fslc-imx 4.1-2.0.x+git imx6solosabreauto linux-fslc-imx 4.1-2.0.x+git imx6svabresd linux-fslc-imx 4.1-2.0.x+git imx6susabresd linux-fslc-imx 4.1-2.0.x+git imx7s-warp linux-fslc-imx 4.1-2.0.x+git imx7s-warp linux-qoriq | | | |
| imx6dlsabread linux-fslc-imx 4.1-2.0.x+git imx6dclsabresd linux-sklc-imx 4.1-2.0.x+git imx6qcd-ms-ba16 linux-advantech 4.1-4.1-1.0.x-imx-dms-ba16 imx6qcd-wariscite-som linux-variscite 4.1.15-1.0 imx6qpsabreauto linux-fslc-imx 4.1-2.0.x+git imx6qsabreauto linux-fslc-imx 4.1-2.0.x+git imx6qsabrelite linux-fslc-imx 4.1-2.0.x+git imx6gsabresd linux-fslc-imx 4.1-2.0.x+git imx6sl-warp linux-fslc-imx 4.1-2.0.x+git imx6sl-warp linux-fslc-imx 4.1-2.0.x+git imx6sl-warp linux-fslc-imx 4.1-2.0.x+git imx6solosabreauto linux-fslc-imx 4.1-2.0.x+git imx6ssabread linux-fslc-imx 4.1-2.0.x+git imx6ul-pic-hobbit linux-fslc-imx 4.1-2.0.x+git imx6ul-pic-hobbit linux-fslc-imx 4.1-2.0.x+git imx7dsabread linux-fslc-imx 4.1-2.0.x+git imx7dsabread linux-fslc-imx 4.1-2.0.x+git imx7s-warp linux-fslc-imx 4.1-2.0.x+git | | | |
| imx6q-dms-ba16 linux-advantech 4.1-2.0.x+git imx6q-dl-variscite-som linux-advantech 4.1-4.1-1.0.x-imx-dms-ba16 imx6qpsabreauto linux-imx 4.1.15-2.0.0 imx6qpsabresd linux-fslc-imx 4.1-2.0.x+git imx6qsabreauto linux-fslc-imx 4.1-2.0.x+git imx6qsabresd linux-fslc-imx 4.1-2.0.x+git imx6gsabresd linux-fslc-imx 4.1-2.0.x+git imx6sl-warp linux-fslc-imx 4.1-2.0.x+git imx6sl-warp linux-fslc-imx 4.1-2.0.x+git imx6sl-warp linux-fslc-imx 4.1-2.0.x+git imx6sl-warp linux-fslc-imx 4.1-2.0.x+git imx6solosabreauto linux-fslc-imx 4.1-2.0.x+git imx6sosabreauto linux-fslc-imx 4.1-2.0.x+git imx6sxsabreauto linux-fslc-imx 4.1-2.0.x+git imx6u-pico-hobbit linux-fslc-imx 4.1-2.0.x+git imx6u-pico-hobbit linux-fslc-imx 4.1-2.0.x+git imx7dsabresd linux-fslc-imx 4.1-2.0.x+git imx7dsabresd linux-fslc-imx 4.1-2.0.x+git | | | _ |
| imx6q-dms-ba16 linux-advantech 4.1-4.1-1.0.x-imx-dms-ba16 imx6qdp-variscite-som linux-variscite 4.1.15-1.1.0 imx6qpsabreauto linux-imx 4.1.15-2.0.0 imx6qpsabresed linux-fslc-imx 4.1-2.0.x+git imx6qsabreauto linux-fslc-imx 4.1-2.0.x+git imx6qsabreauto linux-fslc-imx 4.1-2.0.x+git imx6qsabread linux-fslc-imx 4.1-2.0.x+git imx6slevk linux-fslc-imx 4.1-2.0.x+git imx6solosabreauto linux-fslc-imx 4.1-2.0.x+git imx6solosabread linux-fslc-imx 4.1-2.0.x+git imx6solosabread linux-fslc-imx 4.1-2.0.x+git imx6solosabread linux-fslc-imx 4.1-2.0.x+git imx6sosabread linux-fslc-imx 4.1-2.0.x+git imx6sosabread linux-fslc-imx 4.1-2.0.x+git imx6ul-pico-hobbit linux-fslc-imx 4.1-2.0.x+git imx6ul-pico-hobbit linux-fslc-imx 4.1-2.0.x+git imx7s-warp linux-fslc-imx 4.1-2.0.x+git imx7s-warp linux-fslc-imx 4.1-2.0. | | | |
| imx6qdl-variscite-som linux-variscite 4.1.15-1.1.0 imx6qpsabreauto linux-file-imx 4.1.2.0.x+git imx6qpsabreauto linux-fsle-imx 4.1-2.0.x+git imx6qsabreauto linux-fsle-imx 4.1-2.0.x+git imx6qsabresd linux-fsle-imx 4.1-2.0.x+git imx6sl-warp linux-fsle-imx 4.1-2.0.x+git imx6solosabread linux-fsle-imx 4.1-2.0.x+git imx6sosabread linux-fsle-imx 4.1-2.0.x+git imx6sxsabread linux-fsle-imx 4.1-2.0.x+git imx6uelw linux-fsle-imx 4.1-2.0.x+git imx6uelw </td <td></td> <td></td> <td>_</td> | | | _ |
| imx6qpsabreauto linux-fislc-imx 4.1-2.0.x+git imx6qsabresd linux-fslc-imx 4.1-2.0.x+git imx6qsabrelite linux-fslc-imx 4.1-2.0.x+git imx6qsabresd linux-fslc-imx 4.1-2.0.x+git imx6sl-warp linux-fslc-imx 4.1-2.0.x+git imx6slevk linux-fslc-imx 4.1-2.0.x+git imx6solosabreauto linux-fslc-imx 4.1-2.0.x+git imx6solosabread linux-fslc-imx 4.1-2.0.x+git imx6sxsabreauto linux-fslc-imx 4.1-2.0.x+git imx6sxsabread linux-fslc-imx 4.1-2.0.x+git imx6ul-pico-hobbit linux-fslc-imx 4.1-2.0.x+git imx7dsabresd linux-fslc-imx 4.1-2.0.x+git imx7dsabresd linux-fslc-imx 4.1-2.0.x+git imx7-warp linux-fslc-imx 4.1-2.0.x+git imx7dsabresd linux-fslc-imx 4.1-2.0.x+git imx7dsabresd linux-fslc-imx 4.1-2.0.x+git imx7dsabresd linux-fslc-imx 4.1-2.0.x+git imx7dsabresd linux-fslc-imx 4.1-2.0.x+git | | | |
| imx6qsabreadto linux-fslc-imx 4.1-2.0.x+git imx6qsabreauto linux-fslc-imx 4.1-2.0.x+git imx6qsabresd linux-fslc-imx 4.1.5-2.0.0-ga+yocto imx6sl-warp linux-fslc-imx 4.1-2.0.x+git imx6slevk linux-fslc-imx 4.1-2.0.x+git imx6solosabreauto linux-fslc-imx 4.1-2.0.x+git imx6solosabreauto linux-fslc-imx 4.1-2.0.x+git imx6sosabreauto linux-fslc-imx 4.1-2.0.x+git imx6sxsabreauto linux-fslc-imx 4.1-2.0.x+git imx6sxsabread linux-fslc-imx 4.1-2.0.x+git imx6ul-pico-hobbit linux-fslc-imx <td></td> <td></td> <td></td> | | | |
| imx6qsabreauto linux-fslc-imx 4.1-2.0.x+git imx6qsabresd linux-boundary 4.1.15-2.0.0-ga+yocto imx6qsabresd linux-fslc-imx 4.1-2.0.x+git imx6sl-warp linux-fslc-imx 4.1-2.0.x+git imx6slevk linux-fslc-imx 4.1-2.0.x+git imx6solosabreauto linux-fslc-imx 4.1-2.0.x+git imx6sosabreauto linux-fslc-imx 4.1-2.0.x+git imx6sxsabread linux-fslc-imx 4.1-2.0.x+git imx6sxsabread linux-fslc-imx 4.1-2.0.x+git imx6ul-pico-hobbit linux-fslc-imx 4.1-2.0.x+git imx7dsabresd linux-fslc-imx 4.1-2.0.x+git imx7dsabresd linux-fslc-imx 4.1-2.0.x+git imx7s-warp linux-warp7 4.1-4.1-1.0.x-imx-warp7 ls1043ardb linux-qoriq 4.1 ls1043ardb linux-qoriq 4.1 ls1046ardb linux-qoriq 4.1 ls2046ardb linux-qoriq 4.1 ls2046ardb linux-qoriq 4.1 ls2046ardb linux-boundary | ** | | |
| imx6qsabrelite linux-boundary 4.1.15-2.0.0-ga+yocto imx6qsabresd linux-fslc-imx 4.1-2.0.x+git imx6sl-warp linux-fslc-imx 4.1-2.0.x+git imx6slevk linux-fslc-imx 4.1-2.0.x+git imx6slosabreauto linux-fslc-imx 4.1-2.0.x+git imx6solosabreauto linux-fslc-imx 4.1-2.0.x+git imx6sxsabread linux-fslc-imx 4.1-2.0.x+git imx6sxsabresd linux-fslc-imx 4.1-2.0.x+git imx6sxsabresd linux-fslc 4.8+git imx6ul-pico-hobbit linux-fslc 4.8+git imx7s-warp linux-dali 4.1-2.0.x+git linux7qoriq 4.1 4.1 ls1045ardb linux-qoriq 4.1 ls1043ardb-32b linux-qoriq 4.1 </td <td></td> <td></td> <td></td> | | | |
| imx6qsabresd linux-fslc-imx 4.1-2.0.x+git imx6sl-warp linux-fslc-imx 4.1-2.0.x+git imx6slevk linux-fslc-imx 4.1-2.0.x+git imx6solosabreauto linux-fslc-imx 4.1-2.0.x+git imx6solosabresd linux-fslc-imx 4.1-2.0.x+git imx6sxsabreauto linux-fslc-imx 4.1-2.0.x+git imx6sexsabresd linux-fslc-imx 4.1-2.0.x+git imx6ul-pico-hobbit linux-fslc-imx 4.1-2.0.x+git imx6ul-pico-hobbit linux-fslc-imx 4.1-2.0.x+git imx7dsabresd linux-fslc-imx 4.1-2.0.x+git imx6ul-pico-hobbit linux-fslc-imx 4.1-2.0.x+git imx7dsabresd linux-fslc-imx 4.1-2.0.x-git imx7dsabresd linux-qoriq 4.1 ls1021atr linux-qoriq 4.1 ls1024ard | | | |
| imx6sl-warp linux-fslc-imx 4.1-2.0.x+git imx6solevk linux-fslc-imx 4.1-2.0.x+git imx6solosabreauto linux-fslc-imx 4.1-2.0.x+git imx6solosabresd linux-fslc-imx 4.1-2.0.x+git imx6sxsabreauto linux-fslc-imx 4.1-2.0.x+git imx6svsabresd linux-fslc-imx 4.1-2.0.x+git imx6ul-pico-hobbit linux-fslc-imx 4.1-2.0.x+git imx6ul-pico-hobbit linux-fslc-imx 4.1-2.0.x+git imx7dsabresd linux-fslc-imx 4.1-2.0.x+git imx7dsabresd linux-fslc-imx 4.1-2.0.x+git imx7dsabresd linux-fslc-imx 4.1-2.0.x+git imx6ul-pico-hobbit linux-qoriq 4.1 ls1024ab linux-qoriq 4.1 | | _ | 4.1.15-2.0.0-ga+yocto |
| imx6slevk linux-fslc-imx 4.1-2.0.x+git imx6solosabreauto linux-fslc-imx 4.1-2.0.x+git imx6solosabresd linux-fslc-imx 4.1-2.0.x+git imx6sxsabreauto linux-fslc-imx 4.1-2.0.x+git imx6sxsabresd linux-fslc-imx 4.1-2.0.x+git imx6ul-pico-hobbit linux-fslc-imx 4.1-2.0.x+git imx7dsabresd linux-derimx 4.1-2.0.x+git imx7dsabresd linux-derimx 4.1-2.0.x+git imx7dsabresd linux-deriq 4.1 ls1046ardb linux-qoriq 4.1 ls1043ardb linux-qoriq 4.1 ls1046ardb linux-qoriq 4.1 ls2080ardb linux-qoriq 4.1 m2508uardb linux-qoriq 4.1 | imx6qsabresd | | 4.1-2.0.x+git |
| imx6solosabreauto linux-fslc-imx 4.1-2.0.x+git imx6solosabresd linux-fslc-imx 4.1-2.0.x+git imx6sxsabreauto linux-fslc-imx 4.1-2.0.x+git imx6sxsabresd linux-fslc-imx 4.1-2.0.x+git imx6ul-pico-hobbit linux-fslc-imx 4.1-2.0.x+git imx7dsabresd linux-fslc-imx 4.1-2.0.x+git imx7dsabresd linux-fslc-imx 4.1-2.0.x+git imx7s-warp linux-qoriq 4.1 ls1021atwr linux-qoriq 4.1 ls1043ardb linux-qoriq 4.1 ls1043ardb-32b linux-qoriq 4.1 ls1046ardb linux-qoriq 4.1 ls2080ardb linux-qoriq 4.1 ls2080ardb linux-qoriq 4.1 m28evk linux-denx 3.9-master nitrogen6sx linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6sx linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6s-lite linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6s-lite linux-doriq 4.1 <td>imx6sl-warp</td> <td></td> <td>4.1-2.0.x+git</td> | imx6sl-warp | | 4.1-2.0.x+git |
| imx6solosabresd linux-fslc-imx 4.1-2.0.x+git imx6sxsabreauto linux-fslc-imx 4.1-2.0.x+git imx6sxsabresd linux-fslc-imx 4.1-2.0.x+git imx6sul-pico-hobbit linux-fslc-imx 4.1-2.0.x+git imx6sulevk linux-fslc-imx 4.1-2.0.x+git imx7dsabresd linux-fslc-imx 4.1-2.0.x+git imx7s-warp linux-warp7 4.1-4.1-1.0.x-imx-warp7 ls1021atwr linux-qoriq 4.1 ls1043ardb linux-qoriq 4.1 ls1046ardb linux-qoriq 4.1 ls1046ardb linux-qoriq 4.1 ls2080ardb linux-qoriq 4.1 ls2080ardb linux-qoriq 4.1 m53evk linux-denx 3.9-master nitrogen6sx linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6x-lite linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen7 linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6 linux-qoriq 4.1 p5020ds-64b linux-qoriq 4.1 | imx6slevk | linux-fslc-imx | 4.1-2.0.x+git |
| imx6sxsabreauto linux-fslc-imx 4.1-2.0.x+git imx6sxsabresd linux-fslc-imx 4.1-2.0.x+git imx6ul-pico-hobbit linux-fslc-imx 4.1-2.0.x+git imx7dsabresd linux-fslc-imx 4.1-2.0.x+git imx7dsabresd linux-fslc-imx 4.1-2.0.x+git imx7s-warp linux-warp7 4.1-4.1-1.0.x-imx-warp7 ls1021atwr linux-qoriq 4.1 ls1043ardb linux-qoriq 4.1 ls1043ardb linux-qoriq 4.1 ls1046ardb linux-qoriq 4.1 ls1046ardb linux-qoriq 4.1 ls2080ardb linux-qoriq 4.1 ls2080ardb linux-qoriq 4.1 m28evk linux-denx 3.9-master nitrogen6sx linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6sx linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6x-lite linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6x-lite linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen7 linux-doriq 4.1 | imx6solosabreauto | linux-fslc-imx | 4.1-2.0.x+git |
| imx6sxsabresd linux-fslc-imx 4.1-2.0.x+git imx6ul-pico-hobbit linux-fslc 4.8+git imx6ulevk linux-fslc-imx 4.1-2.0.x+git imx7dsabresd linux-slc-imx 4.1-2.0.x+git imx7s-warp linux-qoriq 4.1-4.1-1.0.x-imx-warp7 ls1021atwr linux-qoriq 4.1 ls1043ardb linux-qoriq 4.1 ls1043ardb-32b linux-qoriq 4.1 ls1046ardb linux-qoriq 4.1 ls1046ardb linux-qoriq 4.1 ls2080ardb linux-qoriq 4.1 ls2080ardb linux-qoriq 4.1 m28evk linux-denx 3.9-master nitrogen6sx linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6x linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6x-lite linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen7 linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen7 linux-qoriq 4.1 p3041ds linux-qoriq 4.1 p5020ds | imx6solosabresd | linux-fslc-imx | 4.1-2.0.x+git |
| imx6sxsabresd linux-fslc-imx 4.1-2.0.x+git imx6ul-pico-hobbit linux-fslc 4.8+git imx6ulevk linux-fslc-imx 4.1-2.0.x+git imx7dsabresd linux-warp7 4.1-4.1-1.0.x-imx-warp7 ls1021atwr linux-qoriq 4.1 ls1043ardb linux-qoriq 4.1 ls1043ardb linux-qoriq 4.1 ls1046ardb linux-qoriq 4.1 ls1046ardb linux-qoriq 4.1 ls1046ardb linux-qoriq 4.1 ls2080ardb linux-qoriq 4.1 ls2080ardb linux-qoriq 4.1 m28evk linux-denx 3.9-master nitrogen6sx linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6sx linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6x-lite linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6x-lite linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen7 linux-boundary 4.1.15-2.0.0-ga+yocto p2041rdb linux-qoriq 4.1 p40 | imx6sxsabreauto | linux-fslc-imx | 4.1-2.0.x+git |
| imx6ulevk linux-fslc-imx 4.1-2.0.x+git imx7dsabresd linux-fslc-imx 4.1-2.0.x+git imx7s-warp linux-warp7 4.1-4.1-1.0.x-imx-warp7 ls1021atwr linux-qoriq 4.1 ls1043ardb linux-qoriq 4.1 ls1043ardb-32b linux-qoriq 4.1 ls1046ardb linux-qoriq 4.1 ls1046ardb-32b linux-qoriq 4.1 ls2080ardb linux-qoriq 4.1 ls2080ardb linux-qoriq 4.1 m28evk linux-qoriq 4.1 m28evk linux-denx 3.9-master nitrogen6sx linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6x linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6x-lite linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6x-lite linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen7 linux-qoriq 4.1 p3041ds linux-qoriq 4.1 p5020ds linux-qoriq 4.1 p5020ds linux-qoriq <td>imx6sxsabresd</td> <td>linux-fslc-imx</td> <td></td> | imx6sxsabresd | linux-fslc-imx | |
| imx6ulevk limux-fslc-imx 4.1-2.0.x+git imx7dsabresd limux-fslc-imx 4.1-2.0.x+git imx7s-warp limux-warp7 4.1-4.1-1.0.x-imx-warp7 ls1021atwr limux-qoriq 4.1 ls1043ardb limux-qoriq 4.1 ls1043ardb-32b limux-qoriq 4.1 ls1046ardb limux-qoriq 4.1 ls2080ardb limux-qoriq 4.1 ls2080ardb limux-qoriq 4.1 ls2080ardb limux-qoriq 4.1 m28evk limux-qoriq 4.1 m53evk limux-denx 3.9-master nitrogen6sx limux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6x limux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6x-lite limux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6x-lite limux-boundary 4.1.15-2.0.0-ga+yocto nitrogen7 limux-doriq 4.1 p3041ds limux-qoriq 4.1 p5020ds limux-qoriq 4.1 p5020ds limux-qoriq | imx6ul-pico-hobbit | linux-fslc | 4.8+git |
| imx7dsabresd linux-fslc-imx 4.1-2.0.x+git imx7s-warp linux-warp7 4.1-4.1-1.0.x-imx-warp7 ls1021atwr linux-qoriq 4.1 ls1043ardb linux-qoriq 4.1 ls1043ardb-32b linux-qoriq 4.1 ls1046ardb linux-qoriq 4.1 ls1046ardb-32b linux-qoriq 4.1 ls2080ardb linux-qoriq 4.1 m28evk linux-denx 3.9-master nitrogen6sx linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6x linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6x-lite linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6x-lite linux-boundary 4.1.15-2.0.0-ga+yocto p2041rdb linux-qoriq 4.1 p3041ds linux-qoriq 4.1 p4080ds linux-qoriq 4.1 p5020ds linux-qoriq 4.1 p5020ds-64b linux-qoriq 4.1 p5040ds linux-qoriq 4.1 p5040ds-64b linux-qoriq | | linux-fslc-imx | _ |
| imx7s-warp linux-warp7 4.1-4.1-1.0.x-imx-warp7 ls1021atwr linux-qoriq 4.1 ls1043ardb linux-qoriq 4.1 ls1043ardb-32b linux-qoriq 4.1 ls1046ardb linux-qoriq 4.1 ls1046ardb-32b linux-qoriq 4.1 ls2080ardb linux-qoriq 4.1 m28evk linux-fslc 4.8+git m53evk linux-denx 3.9-master nitrogen6sx linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6x-lite linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen7 linux-boundary 4.1.15-2.0.0-ga+yocto p2041rdb linux-qoriq 4.1 p3041ds linux-qoriq 4.1 p4080ds linux-qoriq 4.1 p5020ds linux-qoriq 4.1 p5020ds linux-qoriq 4.1 p5040ds linux-qoriq 4.1 p5040ds-64b linux-qoriq 4.1 pc023rdb linux-qoriq 4.1 t102 | imx7dsabresd | linux-fslc-imx | _ |
| ls1021atwr linux-qoriq 4.1 ls1043ardb linux-qoriq 4.1 ls1043ardb-32b linux-qoriq 4.1 ls1046ardb linux-qoriq 4.1 ls1046ardb-32b linux-qoriq 4.1 ls2080ardb linux-qoriq 4.1 m28evk linux-fslc 4.8+git m53evk linux-denx 3.9-master nitrogen6sx linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6x-lite linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen7 linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen7 linux-boundary 4.1.15-2.0.0-ga+yocto p2041rdb linux-qoriq 4.1 p3041ds linux-qoriq 4.1 p4080ds linux-qoriq 4.1 p5020ds linux-qoriq 4.1 p5020ds-64b linux-qoriq 4.1 p5040ds-64b linux-qoriq 4.1 pcm052 linux-timesys 3.13 t1023rdb linux-qoriq 4.1 <t< td=""><td></td><td></td><td>_</td></t<> | | | _ |
| Isi043ardb Iinux-qoriq 4.1 Isi043ardb-32b Iinux-qoriq 4.1 Isi046ardb Iinux-qoriq 4.1 Isi046ardb-32b Iinux-qoriq 4.1 Isi046ardb-32b Iinux-qoriq 4.1 Isi2080ardb Iinux-qoriq 4.1 Imix-gevk Iinux-fislc 4.8+git Imix-gen6sx Iinux-boundary 4.1.15-2.0.0-ga+yocto Initrogen6sx Iinux-boundary 4.1.15-2.0.0-ga+yocto Initrogen6x-lite Iinux-boundary 4.1.15-2.0.0-ga+yocto Initrogen7 Iinux-boundary 4.1.15-2.0.0-ga+yocto Initrogen7 Iinux-qoriq 4.1 Ipix-qoriq 4.1 Ipix-qoriq 4.1 possible Iinux-qoriq 4.1 tossible Iinux-qori | | _ | _ |
| Isi043ardb-32b Iinux-qoriq 4.1 Isi046ardb Iinux-qoriq 4.1 Isi046ardb Iinux-qoriq 4.1 Isi046ardb-32b Iinux-qoriq 4.1 Isi046ardb-32b Iinux-qoriq 4.1 Iinux-qoriq 4.1 Iinux-qoriq 4.1 Iinux-denx 3.9-master Iinux-boundary 4.1.15-2.0.0-ga+yocto Iinux-qoriq 4.1 Iinux-qoriq | | | |
| Isi046ardb Iinux-qoriq 4.1 Isi046ardb-32b Iinux-qoriq 4.1 Isi046ardb-32b Iinux-qoriq 4.1 Isi080ardb Iinux-qoriq 4.1 m28evk Iinux-fslc 4.8+git m53evk Iinux-denx 3.9-master mitrogen6sx Iinux-boundary 4.1.15-2.0.0-ga+yocto mitrogen6x Iinux-boundary 4.1.15-2.0.0-ga+yocto mitrogen6x-lite Iinux-boundary 4.1.15-2.0.0-ga+yocto mitrogen7 Iinux-boundary 4.1.15-2.0.0-ga+yocto mitrogen7 Iinux-boundary 4.1.15-2.0.0-ga+yocto p2041rdb Iinux-qoriq 4.1 p3041ds Iinux-qoriq 4.1 p4080ds Iinux-qoriq 4.1 p5020ds Iinux-qoriq 4.1 p5020ds-64b Iinux-qoriq 4.1 p5040ds Iinux-qoriq 4.1 p5040ds-64b Iinux-qoriq 4.1 pcm052 Iinux-timesys 3.13 t1023rdb Iinux-qoriq 4.1 t1023rdb-64b Iinux-qoriq 4.1 t1024rdb Iinux-qoriq 4.1 t1024rdb Iinux-qoriq 4.1 t1024rdb-64b Iinux-qoriq 4.1 t1040d4rdb Iinux-qoriq 4.1 t1040d4rdb Iinux-qoriq 4.1 t1040d4rdb Iinux-qoriq 4.1 t1040d4rdb Iinux-qoriq 4.1 t1040d4rdb-64b Iinux-qo | | | |
| Isi046ardb-32b Iinux-qoriq 4.1 | | | |
| Inux-qoriq 4.1 | | | |
| m28evk linux-fslc 4.8+git m53evk linux-denx 3.9-master nitrogen6sx linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6x linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen7 linux-boundary 4.1.15-2.0.0-ga+yocto p2041rdb linux-qoriq 4.1 p3041ds linux-qoriq 4.1 p4080ds linux-qoriq 4.1 p5020ds linux-qoriq 4.1 p5020ds-64b linux-qoriq 4.1 p5040ds linux-qoriq 4.1 p5040ds-64b linux-qoriq 4.1 pcm052 linux-timesys 3.13 t1023rdb linux-qoriq 4.1 t1023rdb linux-qoriq 4.1 t1024rdb linux-qoriq 4.1 t1040d4rdb linux-qoriq 4.1 t1040d4rdb linux-qoriq 4.1 | | | |
| m53evk linux-denx 3.9-master nitrogen6sx linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6x linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6x-lite linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen7 linux-boundary 4.1.15-2.0.0-ga+yocto p2041rdb linux-qoriq 4.1 p3041ds linux-qoriq 4.1 p4080ds linux-qoriq 4.1 p5020ds linux-qoriq 4.1 p5020ds-64b linux-qoriq 4.1 p5040ds linux-qoriq 4.1 pcm052 linux-qoriq 4.1 t1023rdb linux-qoriq 4.1 t1023rdb linux-qoriq 4.1 t1024rdb linux-qoriq 4.1 t1024rdb linux-qoriq 4.1 t1040d4rdb linux-qoriq 4.1 t1040d4rdb linux-qoriq 4.1 | | | |
| nitrogen6sx linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6x linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6x-lite linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen7 linux-boundary 4.1.15-2.0.0-ga+yocto p2041rdb linux-qoriq 4.1 p3041ds linux-qoriq 4.1 p4080ds linux-qoriq 4.1 p5020ds linux-qoriq 4.1 p5020ds-64b linux-qoriq 4.1 p5040ds linux-qoriq 4.1 p5040ds-64b linux-qoriq 4.1 t1023rdb linux-qoriq 4.1 t1023rdb linux-qoriq 4.1 t1024rdb linux-qoriq 4.1 t1024rdb linux-qoriq 4.1 t1040d4rdb linux-qoriq 4.1 t1040d4rdb linux-qoriq 4.1 | | | |
| nitrogen6x linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen6x-lite linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen7 linux-boundary 4.1.15-2.0.0-ga+yocto p2041rdb linux-doriq 4.1 p3041ds linux-qoriq 4.1 p4080ds linux-qoriq 4.1 p5020ds linux-qoriq 4.1 p5020ds-64b linux-qoriq 4.1 p5040ds linux-qoriq 4.1 p5040ds-64b linux-qoriq 4.1 pcm052 linux-timesys 3.13 t1023rdb linux-qoriq 4.1 t1024rdb linux-qoriq 4.1 t1024rdb linux-qoriq 4.1 t1040d4rdb linux-qoriq 4.1 t1040d4rdb linux-qoriq 4.1 | | | |
| nitrogen6x-lite linux-boundary 4.1.15-2.0.0-ga+yocto nitrogen7 linux-boundary 4.1.15-2.0.0-ga+yocto p2041rdb linux-qoriq 4.1 p3041ds linux-qoriq 4.1 p4080ds linux-qoriq 4.1 p5020ds linux-qoriq 4.1 p5020ds-64b linux-qoriq 4.1 p5040ds linux-qoriq 4.1 p5040ds-64b linux-qoriq 4.1 pcm052 linux-timesys 3.13 t1023rdb linux-qoriq 4.1 t1023rdb-64b linux-qoriq 4.1 t1024rdb linux-qoriq 4.1 t1040d4rdb linux-qoriq 4.1 t1040d4rdb linux-qoriq 4.1 | | | |
| nitrogen7 linux-boundary 4.1.15-2.0.0-ga+yocto p2041rdb linux-qoriq 4.1 p3041ds linux-qoriq 4.1 p4080ds linux-qoriq 4.1 p5020ds linux-qoriq 4.1 p5020ds-64b linux-qoriq 4.1 p5040ds linux-qoriq 4.1 p5040ds-64b linux-qoriq 4.1 pcm052 linux-timesys 3.13 t1023rdb linux-qoriq 4.1 t1023rdb-64b linux-qoriq 4.1 t1024rdb linux-qoriq 4.1 t1040d4rdb linux-qoriq 4.1 t1040d4rdb linux-qoriq 4.1 | | · · · · · · · · · · · · · · · · · · · | |
| p2041rdb linux-qoriq 4.1 p3041ds linux-qoriq 4.1 p4080ds linux-qoriq 4.1 p5020ds linux-qoriq 4.1 p5020ds-64b linux-qoriq 4.1 p5040ds linux-qoriq 4.1 p5040ds-64b linux-qoriq 4.1 pcm052 linux-timesys 3.13 t1023rdb linux-qoriq 4.1 t1023rdb-64b linux-qoriq 4.1 t1024rdb linux-qoriq 4.1 t1024rdb-64b linux-qoriq 4.1 t1040d4rdb linux-qoriq 4.1 t1040d4rdb-64b linux-qoriq 4.1 | | | |
| p3041ds linux-qoriq 4.1 p4080ds linux-qoriq 4.1 p5020ds linux-qoriq 4.1 p5020ds-64b linux-qoriq 4.1 p5040ds linux-qoriq 4.1 p5040ds-64b linux-qoriq 4.1 pcm052 linux-timesys 3.13 t1023rdb linux-qoriq 4.1 t1023rdb-64b linux-qoriq 4.1 t1024rdb linux-qoriq 4.1 t1024rdb-64b linux-qoriq 4.1 t1040d4rdb linux-qoriq 4.1 t1040d4rdb-64b linux-qoriq 4.1 | | | - 0 0 |
| p4080ds linux-qoriq 4.1 p5020ds linux-qoriq 4.1 p5020ds-64b linux-qoriq 4.1 p5040ds linux-qoriq 4.1 p5040ds-64b linux-qoriq 4.1 pcm052 linux-timesys 3.13 t1023rdb linux-qoriq 4.1 t1023rdb-64b linux-qoriq 4.1 t1024rdb linux-qoriq 4.1 t1024rdb-64b linux-qoriq 4.1 t1040d4rdb linux-qoriq 4.1 t1040d4rdb-64b linux-qoriq 4.1 | | | |
| p5020ds linux-qoriq 4.1 p5020ds-64b linux-qoriq 4.1 p5040ds linux-qoriq 4.1 p5040ds-64b linux-qoriq 4.1 pcm052 linux-timesys 3.13 t1023rdb linux-qoriq 4.1 t1023rdb-64b linux-qoriq 4.1 t1024rdb linux-qoriq 4.1 t1024rdb-64b linux-qoriq 4.1 t1040d4rdb linux-qoriq 4.1 t1040d4rdb-64b linux-qoriq 4.1 | | | |
| p5020ds-64b linux-qoriq 4.1 p5040ds linux-qoriq 4.1 p5040ds-64b linux-qoriq 4.1 pcm052 linux-timesys 3.13 t1023rdb linux-qoriq 4.1 t1023rdb-64b linux-qoriq 4.1 t1024rdb linux-qoriq 4.1 t1024rdb-64b linux-qoriq 4.1 t1040d4rdb linux-qoriq 4.1 t1040d4rdb-64b linux-qoriq 4.1 | | * * | |
| p5040ds linux-qoriq 4.1 p5040ds-64b linux-qoriq 4.1 pcm052 linux-timesys 3.13 t1023rdb linux-qoriq 4.1 t1023rdb-64b linux-qoriq 4.1 t1024rdb linux-qoriq 4.1 t1024rdb-64b linux-qoriq 4.1 t1040d4rdb linux-qoriq 4.1 t1040d4rdb-64b linux-qoriq 4.1 | | | |
| p5040ds-64b linux-qoriq 4.1 pcm052 linux-timesys 3.13 t1023rdb linux-qoriq 4.1 t1023rdb-64b linux-qoriq 4.1 t1024rdb linux-qoriq 4.1 t1024rdb-64b linux-qoriq 4.1 t1040d4rdb linux-qoriq 4.1 t1040d4rdb-64b linux-qoriq 4.1 | | | |
| pcm052 linux-timesys 3.13 t1023rdb linux-qoriq 4.1 t1023rdb-64b linux-qoriq 4.1 t1024rdb linux-qoriq 4.1 t1024rdb-64b linux-qoriq 4.1 t1040d4rdb linux-qoriq 4.1 t1040d4rdb-64b linux-qoriq 4.1 | | * * | |
| t1023rdb linux-qoriq 4.1 t1023rdb-64b linux-qoriq 4.1 t1024rdb linux-qoriq 4.1 t1024rdb-64b linux-qoriq 4.1 t1040d4rdb linux-qoriq 4.1 t1040d4rdb-64b linux-qoriq 4.1 | | | |
| t1023rdb-64b linux-qoriq 4.1 t1024rdb linux-qoriq 4.1 t1024rdb-64b linux-qoriq 4.1 t1040d4rdb linux-qoriq 4.1 t1040d4rdb-64b linux-qoriq 4.1 | | | |
| t1024rdb linux-qoriq 4.1 t1024rdb-64b linux-qoriq 4.1 t1040d4rdb linux-qoriq 4.1 t1040d4rdb-64b linux-qoriq 4.1 | | | |
| t1024rdb-64b linux-qoriq 4.1 t1040d4rdb linux-qoriq 4.1 t1040d4rdb-64b linux-qoriq 4.1 | | | |
| t1040d4rdb linux-qoriq 4.1 t1040d4rdb-64b linux-qoriq 4.1 | | linux-qoriq | 4.1 |
| t1040d4rdb-64b linux-qoriq 4.1 | | linux-qoriq | 4.1 |
| | t1040d4rdb | linux-qoriq | 4.1 |
| Continued on next page | t1040d4rdb-64b | linux-qoriq | 4.1 |
| | | | Continued on next page |

5.2. Linux Kernel 19

Table 5.1 – continued from previous page

| Board | Kernel Provider | Kernel Version |
|----------------|---------------------|---------------------------|
| t1042d4rdb | linux-qoriq | 4.1 |
| t1042d4rdb-64b | linux-qoriq | 4.1 |
| t2080qds | linux-qoriq | 4.1 |
| t2080qds-64b | linux-qoriq | 4.1 |
| t2080rdb | linux-qoriq | 4.1 |
| t2080rdb-64b | linux-qoriq | 4.1 |
| t4160qds | linux-qoriq | 4.1 |
| t4160qds-64b | linux-qoriq | 4.1 |
| t4240qds | linux-qoriq | 4.1 |
| t4240qds-64b | linux-qoriq | 4.1 |
| t4240rdb | linux-qoriq | 4.1 |
| t4240rdb-64b | linux-qoriq | 4.1 |
| twr-vf65gs10 | linux-fslc | 4.8+git |
| tx6q-10x0 | linux-karo | 3.16-2015-09-18 |
| tx6q-11x0 | linux-karo | 3.16-2015-09-18 |
| tx6s-8034 | linux-karo | 3.16-2015-09-18 |
| tx6s-8035 | linux-karo | 3.16-2015-09-18 |
| tx6u-8033 | linux-karo | 3.16-2015-09-18 |
| tx6u-80x0 | linux-karo | 3.16-2015-09-18 |
| tx6u-81x0 | linux-karo | 3.16-2015-09-18 |
| ventana | linux-gateworks-imx | 3.14-1.0.x_ga+yocto |
| wandboard | linux-wandboard | 4.1.15_1.1.0_ga-wandboard |

5.3 Bootloaders

FSL Community BSP supports barebox and u-boot as bootloaders.

- barebox: Barebox a bootloader that inherits the best of U-Boot and the Linux kernel
- **u-boot-boundary**: **u-boot** for Boundary Devices boards.
- **u-boot-fslc**: U-Boot based on mainline U-Boot used by FSL Community BSP in order to provide support for some backported features and fixes, or because it was submitted for revision and it takes some time to become part of a stable version, or because it is not applicable for upstreaming.
- u-boot-imx: U-Boot provided by Freescale with focus on i.MX reference boards.
- u-boot-karo: u-boot for Ka-Ro electronics TX Computer-On-Modules.
- u-boot-qoriq: U-Boot provided by Freescale with focus on QorIQ boards
- u-boot-toradex: U-Boot bootloader with support for Toradex Computer on Modules.
- **u-boot-variscite**: U-Boot for Variscite i.MX6Q/DL VAR-SOM-MX6.

The following table shows the default bootloaders (and their versions) for the supported boards.

Table 5.2: Default bootloader version for each supported machine $\,$

| Board | Bootloader | Bootloader version | | | |
|------------------------|------------------|--|--|--|--|
| apalis-imx6 | u-boot-toradex | v2015.04-v2.6b2.1+git | | | |
| b4420qds | u-boot-qoriq | 2016.09+fslgit+fsl | | | |
| b4420qds-64b | u-boot-qoriq | 2016.09+fslgit+fsl | | | |
| b4860qds | u-boot-qoriq | 2016.09+fslgit+fsl | | | |
| b4860qds-64b | u-boot-qoriq | 2016.09+fslgit+fsl | | | |
| c293pcie | u-boot-qoriq | 2016.09+fslgit+fsl | | | |
| cfa10036 | barebox | 2015.10.0 | | | |
| cfa10037 | barebox | 2015.10.0 | | | |
| cfa10049 | barebox | 2015.10.0 | | | |
| cfa10055 | barebox | 2015.10.0 | | | |
| cfa10056 | barebox | 2015.10.0 | | | |
| cfa10057 | barebox | 2015.10.0 | | | |
| cfa10058 | barebox | 2015.10.0 | | | |
| cgtqmx6 | u-boot-fslc | v2016.11+git | | | |
| cm-fx6 | u-boot-fslc | v2016.11+git | | | |
| colibri-imx6 | u-boot-toradex | v2015.04-v2.6b2.1+git | | | |
| colibri-imx7 | u-boot-toradex | v2015.04-v2.6b2.1+git | | | |
| colibri-vf | u-boot-toradex | v2015.04-v2.6b2.1+git | | | |
| cubox-i | u-boot-fslc | v2016.11+git | | | |
| imx233-olinuxino-maxi | u-boot-fslc | v2016.11+git | | | |
| imx233-olinuxino-micro | u-boot-fslc | v2016.11+git | | | |
| imx233-olinuxino-mini | u-boot-fslc | v2016.11+git | | | |
| imx233-olinuxino-nano | u-boot-fslc | v2016.11+git | | | |
| imx23evk | u-boot-fslc | v2016.11+git | | | |
| imx28evk | u-boot-fslc | v2016.11+git | | | |
| imx51evk | u-boot-fslc | v2016.11+git | | | |
| imx53ard | u-boot-fslc | v2016.11+git | | | |
| imx53qsb | u-boot-fslc | v2016.11+git | | | |
| imx6dl-riotboard | u-boot-fslc | v2016.11+git | | | |
| imx6dlsabreauto | u-boot-fslc | v2016.11+git | | | |
| imx6dlsabresd | u-boot-fslc | v2016.11+git | | | |
| imx6q-dms-ba16 | u-boot-fslc | v2016.11+git | | | |
| imx6qdl-variscite-som | u-boot-variscite | 2015.04 | | | |
| imx6qpsabreauto | u-boot-imx | 2016.03-imx_v2016.03_4.1.15_2.0.0_ga | | | |
| imx6qpsabresd | u-boot-imx | 2016.03-imx_v2016.03_4.1.15_2.0.0_ga | | | |
| imx6qsabreauto | u-boot-fslc | v2016.11+git | | | |
| imx6qsabrelite | u-boot-boundary | v2016.03+git | | | |
| imx6qsabresd | u-boot-fslc | v2016.11+git | | | |
| imx6sl-warp | u-boot-fslc | v2016.11+git | | | |
| imx6slevk | u-boot-fslc | v2016.11+git | | | |
| imx6solosabreauto | u-boot-imx | | | | |
| imx6solosabresd | u-boot-imx | | | | |
| imx6sxsabreauto | u-boot-imx | | | | |
| imx6sxsabresd | u-boot-fslc | 2016.03-imx_v2016.03_4.1.15_2.0.0_ga v2016.11+git | | | |
| imx6ul-pico-hobbit | u-boot-fslc | v2016.11+git v2016.11+git | | | |
| ппхош-рісо-порыі | u-000t-181C | Continued on next page | | | |

5.3. Bootloaders 21

Table 5.2 – continued from previous page

| | Table 3.2 – Continued | |
|--|----------------------------|--------------------------------------|
| Board | Bootloader | Bootloader version |
| imx6ulevk | u-boot-fslc | v2016.11+git |
| imx7dsabresd | u-boot-fslc | v2016.11+git |
| imx7s-warp | u-boot-fslc | v2016.11+git |
| ls1021atwr | u-boot-qoriq | 2016.09 + fslgit + fsl |
| ls1043ardb | u-boot-qoriq | 2016.09 + fslgit + fsl |
| ls1043ardb-32b | u-boot-qoriq | 2016.09+fslgit+fsl |
| ls1046ardb | u-boot-qoriq | 2016.09+fslgit+fsl |
| ls1046ardb-32b | u-boot-qoriq | 2016.09+fslgit+fsl |
| ls2080ardb | u-boot-qoriq | 2016.09+fslgit+fsl |
| m28evk | u-boot-fslc | v2016.11+git |
| m53evk | u-boot-fslc | v2016.11+git |
| nitrogen6sx | u-boot-boundary | v2016.03+git |
| nitrogen6x | u-boot-boundary | v2016.03+git |
| nitrogen6x-lite | u-boot-boundary | v2016.03+git |
| nitrogen7 | u-boot-boundary | v2016.03+git |
| p2041rdb | u-boot-gorig | 2016.09+fslgit+fsl |
| p3041ds | u-boot-qoriq | 2016.09+fslgit+fsl |
| p4080ds | u-boot-qoriq | 2016.09+fslgit+fsl |
| p5020ds | u-boot-qoriq | 2016.09+fslgit+fsl |
| p5020ds-64b | u-boot-gorig | 2016.09+fslgit+fsl |
| p5040ds | u-boot-gorig | 2016.09+fslgit+fsl |
| p5040ds-64b | u-boot-gorig | 2016.09+fslgit+fsl |
| pcm052 | u-boot-fslc | v2016.11+git |
| t1023rdb | u-boot-gorig | 2016.09+fslgit+fsl |
| t1023rdb-64b | u-boot-qoriq | 2016.09+fslgit+fsl |
| t1024rdb | u-boot-gorig | 2016.09+fslgit+fsl |
| t1024rdb-64b | u-boot-gorig | 2016.09+fslgit+fsl |
| t1040d4rdb | u-boot-gorig | 2016.09+fslgit+fsl |
| t1040d4rdb-64b | u-boot-qoriq | 2016.09+fslgit+fsl |
| t1042d4rdb | u-boot-qoriq | 2016.09+fslgit+fsl |
| t1042d4rdb-64b | u-boot-qoriq | 2016.09+fslgit+fsl |
| t2080qds | u-boot-qoriq | 2016.09+fslgit+fsl |
| t2080qds-64b | u-boot-qoriq | 2016.09+fslgit+fsl |
| t2080rdb | u-boot-qoriq | 2016.09+fslgit+fsl |
| t2080rdb-64b | u-boot-qoriq | 2016.09+fslgit+fsl |
| t4160qds | u-boot-qoriq | 2016.09+fslgit+fsl |
| t4160qds-64b | u-boot-qoriq | 2016.09+fslgit+fsl |
| t4240qds | u-boot-qoriq | 2016.09+fslgit+fsl |
| t4240qds-64b | u-boot-qoriq | 2016.09+fslgit+fsl |
| t4240rdb | u-boot-qoriq | 2016.09+fslgit+fsl |
| t4240rdb-64b | u-boot-qoriq | 2016.09+fslgit+fsl |
| twr-vf65gs10 | u-boot-fslc | v2016.11+git |
| $\frac{\text{twi-viosgsto}}{\text{tx6q-10x0}}$ | u-boot-karo | v2015.10-rc2+git |
| tx6q-11x0 | u-boot-karo | v2015.10-rc2+git v2015.10-rc2+git |
| tx6s-8034 | u-boot-karo | v2015.10-rc2+git v2015.10-rc2+git |
| $\frac{\text{tx6s-8034}}{\text{tx6s-8035}}$ | u-boot-karo u-boot-karo | v2015.10-rc2+git v2015.10-rc2+git |
| tx6u-8033 | u-boot-karo | v2015.10-rc2+git v2015.10-rc2+git |
| 0600-n0x0 | u-boot-karo | 9 |
| | | Continued on next page |

Table 5.2 – continued from previous page

| Board | Bootloader | Bootloader version |
|-----------|----------------------|--------------------|
| tx6u-80x0 | u-boot-karo | v2015.10-rc2+git |
| tx6u-81x0 | u-boot-karo | v2015.10-rc2+git |
| ventana | u-boot-gateworks-imx | v2015.04+git |
| wandboard | u-boot-fslc | v2016.11+git |

5.4 User Space Packages

There is a huge number of user space packages provided by the Yocto Project. The following table shows some version for few highlighted packages.

Table 5.3: Main user space package versions

| Package | Board/SoC Family | Version |
|--------------|------------------|---------|
| gstreamer1.0 | All | 1.8.3 |
| udev | All | 3.2 |

5.4.1 Freescale User Space Packages

This section shows the version package for each board. Those packages provide hardware acceleration for GPU or VPU, hardware optimization or some hardware test tools.

- Hardware acceleration is achieved using a different core for processing some specific task. In this case, GPU or VPU.
- Hardware optimization is achieved with some changes in source code in order to get a better performance for a specific task on a specific hardware. For example, audio decode made by software, but with optimizations for ARM.
- Hardware-specific is applicable when the package was designed to be executed on a specific hardware, and it does not make sense on other hardware. For example, imx-test is a test package for imx boards. It can be cross-compiled for any other core, although it will only behave as expect if executed on imx boards.

The package version and variety varies on *SoC Hierarchy*. For example, machines with i.MX28 SoC does not have VPU, the recipe imx-vpu is not needed. There are differences, as well, in GPU support recipes.

Version by SoC Hierarchy

The following table shows the version of each package depending on the SoC Hierarchy.

Table 5.4: User space package version by SoC hierarchy

| Package name | ls102xa | mx28 | m×5 | mx6q / mx6dl | mxбsl | vf60 |
|-----------------|-------------|-------------|-------------|-----------------|-------------|-----------------------|
| apptrk | git | _ | _ | _ | _ | _ |
| cst | git | git | git | git | git | git |
| devregs | 1.0+AU- | 1.0+AU- | 1.0+AU- | 1.0+AU- | 1.0+AU- | 1.0+AU- |
| | · · | | | | | d 402692 +34ed |
| directfb | 1.7.7 | 1.7.7 | 1.7.7 | 1.7.7 | 1.7.7 | 1.7.7 |
| directfb- | 1.7.0 | 1.7.0 | 1.7.0 | 1.7.0 | 1.7.0 | 1.7.0 |
| examples | | | | | | |
| elftosb | 10.12.01 | 10.12.01 | 10.12.01 | 10.12.01 | 10.12.01 | 10.12.01 |
| firmware- | _ | _ | 5.4 | 5.4 | 5.4 | _ |
| imx | | | | | | |
| fsl-alsa- | _ | _ | _ | 1.0.26 | 1.0.26 | _ |
| plugins | | | | | | |
| gpu-viv- | _ | _ | _ | _ | _ | _ |
| bin-mx6q | | | | | | |
| gpu-viv- | _ | _ | | | | _ |
| g2d | | | | | | |
| gst1.0-fsl- | _ | _ | | | _ | |
| plugin | | | | | | |
| gstreamer1 | .0- – | | _ | 0.12.2 | 0.12.2 | _ |
| plugins- | | | | | | |
| imx | | | | | | |
| imx-kobs | _ | 5.5+git | 5.5 + git | 5.5+git | 5.5+git | 5.5+git |
| imx-lib | _ | _ | _ | 5.4 | 5.4 | _ |
| imx-test | _ | 00.00.00 | 00.00.00 | 5.7 | 5.7 | 00.00.00 |
| imx-uuc | 0.5.1 + git | 0.5.1 + git | 0.5.1 + git | 0.5.1 + git | 0.5.1 + git | 0.5.1+git |
| imx-vpu | _ | _ | _ | 5.4.35 | 5.4.35 | _ |
| libf- | _ | _ | _ | 4.1.4 | 4.1.4 | _ |
| slcodec | | | | | | |
| libf- | _ | _ | _ | 4.1.4 | 4.1.4 | _ |
| slparser | | | | | | |
| libfs- | _ | _ | _ | 1.0.68 | _ | _ |
| lvpuwrap | | | | | | |
| libmcc | _ | _ | _ | _ | _ | 1.05.1 |
| mqxboot | _ | _ | _ | _ | _ | 2.0.1 |
| mxsldr | 0.0.0+git | 0.0.0+git | 0.0.0 + git | 0.0.0+git | 0.0.0+git | 0.0.0+git |
| qe-ucode | git | _ | _ | _ | _ | _ |
| qemu-fsl | _ | _ | _ | _ | _ | _ |
| rcw | git | _ | _ | _ | _ | _ |
| xf86- | _ | _ | _ | _ | _ | _ |
| video- | | | | | | |
| imxfb | | | | | | |
| xf86- | _ | _ | _ | _ | _ | _ |
| video- | | | | | | |
| imxfb- | | | | | | |
| vivante | | | | | | |

Hardware relation by SoC Hierarchy

The following table shows how packages interact with hardware depending on the $SoC\ Hierarchy$

Table 5.5: Hardware dependent packages

| Package Name | mx28 | mx5 | mx6 | vf60 |
|-----------------------|--------------|--------------|--------------|----------|
| imx-test | HW-specific | HW-specific | HW-specific | _ |
| gst-fsl-plugin | HW-specific | HW-specific | HW-specific | _ |
| libfslcodec | HW | HW | HW | _ |
| | optimization | acceleration | acceleration | |
| libfslparser | HW | HW | HW | _ |
| | optimization | optimization | optimization | |
| imx-vpu | _ | HW | HW | _ |
| | | acceleration | acceleration | |
| imx-lib | _ | HW | HW | _ |
| | | acceleration | acceleration | |
| firmware-imx | _ | HW-specific | HW-specific | _ |
| mxsldr | HW-specific | _ | _ | _ |
| gpu-viv-g2d | _ | _ | HW | _ |
| | | | acceleration | |
| xf86-video-imxfb- | _ | _ | HW | _ |
| vivante | | | acceleration | |
| gpu-viv-bin-mx6q | _ | _ | HW | _ |
| | | | acceleration | |
| directfb | _ | _ | HW | _ |
| | | | acceleration | |
| directfb-examples | _ | _ | HW | _ |
| | | | acceleration | |
| xf86-video-imxfb | _ | $_{ m HW}$ | _ | _ |
| | | acceleration | | |
| amd-gpu-bin-mx51 | _ | HW | _ | _ |
| | | acceleration | | |
| libz160 | _ | HW | _ | _ |
| | | acceleration | | |
| amd-gpu-x11-bin- | _ | HW | _ | _ |
| mx51 | | acceleration | | |
| libfslvpuwrap | _ | _ | HW | _ |
| | | | acceleration | |
| fsl-alsa-plugins | _ | | HW-specific | _ |
| gstreamer1.0-plugins- | _ | _ | HW | _ |
| imx | | | acceleration | |
| imx-uuc | HW-specific | HW-specific | HW-specific | _ |
| libmcc | _ | _ | _ | |
| mqxboot | _ | _ | _ | HW- |
| | | | | specific |

5.5 PackageGroups and Images

The FSL Community BSP provides a list of PACKAGEGROUPS and images intended to ease the initial development of custom applications.

The main goal is not to provide a production solution, on the contrary, it should be seen as an example of package set for a specific IP development, and an example of initial generic development and test images.

5.5.1 PACKAGEGROUPS

The following list shows the current PACKAGEGROUPs available in Morty when using FSL Community BSP.

You can understand what a PACKAGEGROUPS is and learn how to use it in Yocto Project Development Manual

- packagegroup-fsl-gstreamer 1.0: Package group used by FSL Community to provide audio, video, networking and debug GStreamer plugins with the required hardware acceleration (if supported by the SoC).
- packagegroup-fsl-gstreamer 1.0-full: Package group used by FSL Community to provide all GStreamer plugins from the base, good, and bad packages, as well as the ugly and libary ones if commercial packages are whitelisted, and plugins for the required hardware acceleration (if supported by the SoC).
- packagegroup-fsl-mfgtool: Freescale Manufacturing Tool requirements.
- packagegroup-fsl-tools-benchmark: Package group used by FSL Community to provide a set of benchmark applications.
- packagegroup-fsl-tools-gpu: Package group used by FSL Community to add the packages which provide GPU support.
- packagegroup-fsl-tools-gpu-external: Package group used by FSL Community to provide graphic packages used to test the several hardware accelerated graphics APIs including packages not provided by Freescale.
- packagegroup-fsl-tools-testapps: Packagegroup used by FSL Community to provide a set of packages and utilities for hardware test.
- packagegroup-imx-tools-audio: Set of audio tools for inclusion on images.

5.5.2 Images

The following images are provided by FSL Community BSP only. See the list of Yocto Project's reference images in Yocto Project Reference Manual

- fsl-image-machine-test: A console-only image that includes gstreamer packages, Freescale's multimedia packages (VPU and GPU) when available, and test and benchmark applications.
- **fsl-image-mfgtool-initramfs**: Small image to be used with Manufacturing Tool (mfgtool) in a production environment.

- **fsl-image-multimedia**: A console-only image that includes gstreamer packages and Freescale's multimedia packages (VPU and GPU) when available for the specific machine.
- **fsl-image-multimedia-full**: A console-only image that includes gstreamer packages and Freescale's multimedia packages (VPU and GPU) when available for the specific machine.

5.5.3 Distros

The following distros are supported by FSL Community BSP.

- **fslc-framebuffer**: Distro for Framebuffer graphical backend. This distro doesn't include x11 and wayland features.
- **fslc-wayland**: Distro for Wayland without X11. This distro include wayland feature but doesn't has x11 support.
- **fslc-x11**: Distro for X11 without wayland. This distro include x11 feature and doesn' has wayland support.
- **fslc-xwayland**: Distro for Wayland with X11. This distro include both wayland and x11 features.

NOTE: Poky's distros are still available to use.

CHAPTER

SIX

TEST RESULTS

Freescale has a complete test cycle for the BSP released. It includes tests for Linux Kernel for the GPU package and for the VPU package (and all other package needed by the BSP, such as imx-lib).

The results and known issues, from Linux Kernel, GPU and VPU packages can be found in the Freescale Release Notes (Download tab of freescale.com/imx).

For boards from meta-freescale-3rdparty, the test cycle is performed by each mantainer.

CHAPTER

SEVEN

ACKNOWLEDGEMENTS

The FSL BSP Community is a community effort of keeping and mantaining a Freescale boards/chips layer for the Yocto Project.

7.1 Morty Source Code

The statistics can be seen at the FSL Community BSP website. It has not been included here as it changes every time bug fixes are included during the maintenance cycle of the release and it would be outdated most of time.

CHAPTER

EIGHT

KNOWN ISSUES

The list of known issues for the FSL Community BSP can be seen at the following URL:

https://bugzilla.yoctoproject.org/buglist.cgi?quicksearch=meta-freescale

It has not been included here as it changes every time bug fixes are included during the maintenance cycle of the release and it would be outdated most of time.