

Connection Setup



Connection

Serial Port



OK

Cancel

Serial Settings

USB-SERIAL CH340 (COM21)



9600 Baud



8 Data bits



None Parity



1 Stop Bit



Advanced...

Mode



RTU



ASCII

Response Timeout

2000

[ms]

Delay Between Polls

10

[ms]

Remote Server

IP Address

127.0.0.1

Port

502

Connect Timeout

3000

[ms]

Read/Write Definition



Slave ID:

2

OK

Function:

03 Read Holding Registers (4x) ▾

Cancel

Address:

0

Apply

Quantity:

7

Scan Rate:

1000

ms



Read/Write Enabled

Read/Write Once

View

Rows



10



20



50



100



Hide Alias Columns



Address in Cell



PLC Addresses (Base 1)

Display:

Signed ▾

Modbus RTU protocol

Read status registers, read function code: 0x30					
Register address (Hex)	PLC Address (decimal)	meaning	Number of bytes	content	remark
0000	40001	Humidity	2	0.1%RH	read
0001	40002	Temperature	2	0.1℃	read
0002	40003	Illuminance high 16 byte	2	Works for 0-200000 Lux (1 Lux) sensor	read
0003	40004	Illuminance low 16 byte	2		read
0006	40007	Illuminance	2	Works for 0-65535 Lux (1 Lux) and 0-200000 Lux (0.01 Lux) sensor	read