


KALLISTE Quick Start Guide

Version 2.0.1



- K-ARP -

The K-ARP user interface



K-ARP is an interactive harmonic sequencer combining two independent sequencers:

- a **Chord Sequencer**
- a **Visual Arpeggio Matrix**

Unlike conventional arpeggiators, every chord and every arpeggio is completely and easily defined by the user. Nothing is generated randomly.

Each chord may have its own:

- Root note
- Chord quality (Major, Minor, Sus2, Sus4, Diminished or Augmented)
- Octave

The Visual Arpeggio Matrix lets you build arpeggios simply by clicking the notes you want to hear (from 0 to 6 notes per step).

Every modification is heard immediately.

Understanding the Visual Arpeggio Matrix



Each row of the Visual Arpeggio Matrix represents one note of the current chord:

- **R** = Root
- **3** = Third
- **5** = Fifth
- **↑R** = Root one octave higher
- **↑3** = Third one octave higher
- **↑5** = Fifth one octave higher

Click the desired cells to build your arpeggio.

Multiple notes may be selected in the same column to create polyphonic arpeggios.



Tip: Hold **Ctrl** and click a matrix cell to display the note corresponding to the programmed chord in that column.

Creating your first sequence

- Set the desired **CHORD LEN** using the CHORD LEN knob.
- Enter the chord roots using the vertical Chord sliders.
- Select the chord quality for each step using the corresponding Chord Type button.
- Set the octave of the selected chord using the **OCT** knob, if required.
- Set the desired **ARP LEN** using the ARP LEN knob.
- Build the arpeggio by clicking the desired notes in the Visual Arpeggio Matrix.
- Set the desired tempo using the Clock Tempo knob.
- Press **RUN**.

Your sequence starts immediately.

Editing while listening

K-ARP is designed for real-time composition. While RUN is active, you may freely modify:

- Chord roots
- Chord qualities
- Octaves
- Arpeggio pattern
- Tempo
- CHORD LEN
- ARP LEN



Every modification is heard immediately.

Synchronization and Context Menu

K-ARP can easily be integrated into larger modular systems.

Inputs

- **RUN:** Starts or stops K-ARP from an external trigger.
- **RST SEQ:** Resets the current sequence from an external trigger.

Outputs


- **OUT CLK:** Sends a trigger on each chord step.
- **ROOT V/OCT:** Chord root CV output.
- **CHORD V/OCT / GATE:** Chord CV and Gate outputs.
- **ARP V/OCT / GATE:** Arpeggio CV and Gate outputs.

When several notes are active in the same arpeggio step, the Arpeggio CV and Gate outputs automatically become polyphonic.

Additional functions are available from the context menu:

- **Clear Chords** — Clears the current chord sequence.
- **Clear ARP Matrix** — Clears all notes from the Visual Arpeggio Matrix.
- **User Presets** — Allows the current K-ARP configuration to be saved as a user preset and recalled later.

K-ARP – CONTROLS & MOUSE ACTIONS



This infographic summarizes the interactions with the sliders, buttons, and matrix, as well as the module's inputs and outputs.

- K-SCENE -



K-SCENE is an expander for K-ARP. Simply place it immediately to the right of K-ARP.

No patch cables are required between the two modules.

K-SCENE extends K-ARP by storing complete K-ARP configurations as Scenes.

Unlike traditional scene memories, K-SCENE lets you hear a Scene while you are building it, before deciding to store it.

Each Scene stores:

- Tempo
- Chord progression
- Chord qualities
- Octaves
- Visual Arpeggio Matrix
- CHORD LEN
- ARP LEN

Up to **16 Scenes** can be stored.

1 - K-SCENE PLAY Mode

K-SCENE starts in **PLAY / AUTO** mode.

► **PLAY + AUTO mode :**

Stored Scenes are played automatically in sequence.

Playback behavior after the last stored Scene depends on the **Loop Auto** setting in the context menu:

- **Loop Auto ON:** playback returns to Scene 1 after the last stored Scene and continues looping through the stored Scenes.
- **Loop Auto OFF:** the last stored Scene continues playing in a loop.

RUN OFF automatically resets playback to Scene 1.

Scene selection with the mouse is disabled while AUTO playback is active.

► **PLAY + MANUAL mode :**

The active Scene plays continuously.

To select the Scene that will play next, **Ctrl + Click** the desired stored Scene slot.

The selected Scene becomes active when the current Scene reaches its end.



►► **Tip — Start AUTO playback from a specific Scene**

To continue AUTO playback from a specific point without restarting from Scene 1, stay in PLAY mode and select the desired Scene in MANUAL mode using **Ctrl + Click**. Once that Scene becomes active, switch to **AUTO** without stopping RUN. AUTO playback will continue from that Scene onward.



Tip — Switch between AUTO and MANUAL during playback

You can switch freely between **AUTO** and **MANUAL** while playback is running. This makes it possible to alter the Scene progression in real time — for example, to repeat a scene or temporarily change the playback path in MANUAL mode, then switch back to AUTO to resume automatic sequencing.

2 - K-SCENE STORE Mode

Selecting **STORE** automatically switches playback to **MANUAL** mode.

STORE mode allows Scenes to be created, edited and organized.

► **Recall a stored Scene**

Ctrl + Click a stored Scene slot.

⇒ The selected Scene becomes the active editing Scene.

► **Store the current Scene**

Build or modify a sequence in K-ARP.

- Click the destination Scene slot once.
- The selected Scene slot is armed for storage and its LED starts blinking.
- Click the same Scene slot again.

⇒ The current K-ARP configuration is stored in the selected Scene slot.

Tip: A **double-click** on the destination slot performs the same operation directly.

Note: Scenes can only be stored while K-ARP is stopped (**RUN OFF**).

This prevents accidental overwriting during playback.

► Delete a Scene

- Press and hold the Scene slot you want to delete.
- The selected Scene slot and its LED start blinking, indicating that the Scene is armed for deletion.
- Click the same Scene slot again.

⇒ The Scene is deleted.

► Cancel an armed action

Click anywhere to cancel a pending **Store** or **Delete** operation.

EOC output

EOC sends a trigger at the end of each Scene.

If **EOC on RUN/RST** is enabled, an additional trigger is sent when RUN is activated.

This initial trigger can be disabled when the external module must remain on its current step at playback start.

Typical workflow :

- Create a sequence in K-ARP.
- Switch K-SCENE to STORE.
- Store the first Scene.
- Modify chords, arpeggios or tempo.
- Store the new version in another Scene.
- Repeat until your composition is complete.
- Switch to PLAY.
- Select AUTO or MANUAL.
- Press RUN on K-ARP.

One of K-SCENE's most distinctive features is that every modification made while editing is heard immediately, allowing musical ideas to be refined naturally before they are stored.

Context Menu

- **Loop AUTO** — Controls playback behavior after the last stored Scene:
 - **Enabled:** playback returns to Scene 1 and continues looping through the stored Scenes.
 - **Disabled:** the last stored Scene continues playing in a loop.
- **EOC on RUN/RST** — When enabled, EOC also sends a trigger when RUN is activated. Disable this option if the external module should not receive this initial trigger and should only advance on subsequent end-of-scene triggers.
- **Clear all scenes** — Deletes all stored Scenes.

SCENE CONTROL & MOUSE ACTIONS

This infographic provides a visual summary of STORE and PLAY modes, the Ctrl + Click, Double Click, and Press and Hold + Click Again actions, as well as the different slot states.

