

Automated Irrigation System Documentation

Head unit board v 0.1

Automated Irrigation system is a fully automated modular system to smart home gardening. A central control unit controls multiple head units, which are to measure the plants condition, and based on the instructions given by the main control, irrigate the plant as needed.

This documentation contains information ONLY about the alpha version of the head units board.

Board Features:

1. Measure soil moisture
2. Measure temperature
3. Measure light
4. Drive Irrigation pump

Realization:

- Moisture: 555 timer RC capacity measure
- Temperature: in box measurement
- Light: in box measurement
- Watering pump: common source motor drive circuit

Controller: EFM32GG Giant Gecko Starter Kit


PCB editor: KiCAD

Basic Head unit functionality:

The microcontroller drives the sensors, and reads temperature, moisture and light data. Based on measured data, the controller drives an external pump, to irrigate the plants soil. The connection between the controller and the board is happening through the pin array.


Temperature sensor:

The used IC for temperature measurement is an LM75C. The chip uses I2C bus to communicate with the controller, therefore connected to the on board I2C bus.



Moisture sensor:



Moisture measuring method is based on capacity measurement. The measurement is based on a TLC555 timer IC in astable mode. The measured capacity controls the frequency of the timer, which is connected to the PD0 pin on the microcontroller. This pin can be configured as an external clock for pulse counter unit.



RA and RB is to be measured with the probe capacity in mind.

Light sensor:

Light measurement is done via VEML7700 IC. This chip is communicating with the microcontroller on I2C protocol, therefore connected to the I2C bus on the board.




Package:

Project is packaged in an IP67 plastic case. The case has to protect the device from water, and dust, that may be common at the area of application and may damage the unprotected board. Without casing, only indoor use is possible.

-Pump:


The control element of the system is one 12V pump, a Barwig 0333. The pump requires 12V power supply, that must be connected to the board externally.



The pump is driven by a simple common source circuit.

-Power Supply:


The device is powered with an LPV-35-12 power supply unit, which provides 12V DC for the pump. Alternatively a barrel jack input is supported if 12V DC input is available. When the barrel jack is in use, LPV power supply is out of use.




-Connectors:

The board has five connectors.


1. Pin array to connect to the giant gecko controller. (2x10 pin array female)
2. screw terminal for capacity measure device
3. screw terminal for pump drive
4. screw terminal for 12V DC input
5. barrel jack, for 12V DC input



-Schematic:



-PCB layout:



-Prototype Hardware (kiCAD 3D model):

