

DataWedge Time Measurement Methodology

This document describes how Activation Time and Data Received Time are measured for both RFID and barcode workflows in the application.

Quick Validation

1. **Monotonic Timing:** Using `SystemClock.elapsedRealtime()` is the correct choice. It keeps measurements immune to system clock jumps (e.g., NTP synchronization events) and captures true elapsed duration, including deep sleep time.
2. **Activation Logic:** Measuring from `onStart()` is robust because it captures elapsed time from initial UI visibility to DataWedge profile and hardware readiness.
3. **State Mapping:**
 - **RFID:** Uses `RESULT_GET_ACTIVE_PROFILE` and checks for the "RWDemo" profile.
 - **Barcode:** Uses the `WAITING` scanner status, which is the most accurate indicator that scanner hardware is powered and ready.
4. **Trigger-to-Data Latency:** Resetting the timer on the button `onClick` event and stopping it at the first `handleDecodeData` event provides a clear user-perceived response metric.

1. Activation Time (App Startup to Hardware Ready)

Activation Time measures the delay between the application entering the foreground and the DataWedge hardware (RFID sled and barcode scanner) reaching a ready state.

Measurement Flow

1. **Baseline (T0):** The measurement starts in the `onStart()` lifecycle method of `RWDemoActivity` using `SystemClock.elapsedRealtime()`.
 - *Code:* `activationTimerStartMs = SystemClock.elapsedRealtime();`
2. **RFID Activation:** The time is recorded when the application receives a DataWedge broadcast confirming that the "RWDemo" profile is now active.
 - *Condition:* `RESULT_GET_ACTIVE_PROFILE` extra matches "RWDemo".
 - *Calculation:* `Elapsed = CurrentTime - activationTimerStartMs`
3. **Barcode Activation:** The time is recorded when the application receives a DataWedge status notification indicating the scanner is in the "WAITING" state.
 - *Condition:* `RESULT_SCANNER_STATUS` extra equals "WAITING".
 - *Calculation:* `Elapsed = CurrentTime - activationTimerStartMs`

Summary Dialog

Once both hardware components report a ready state for the first time after startup, an Activation Time Summary dialog is shown with precise millisecond values.

2. Data Received Time (Trigger to First Data)

Data Received Time measures latency from user interaction (tapping a scan button) to the first captured data returned via intent.

Measurement Flow

1. **Trigger Point:** The measurement starts immediately when the user clicks the “Soft Scan” (RFID) or “Barcode Scan” button.
 - *RFID Code:* `rfidDataTimerStartMs = SystemClock.elapsedRealtime();`
 - *Barcode Code:* `barcodeDataTimerStartMs = SystemClock.elapsedRealtime();`
 2. **Data Capture:** The time is recorded in `handleDecodeData` when the first valid payload arrives for that specific source.
 - *RFID Condition:* First occurrence where `source` is `RFID` and payload is non-empty.
 - *Barcode Condition:* First occurrence where `source` is `scanner` and payload is non-empty.
 3. **Calculation:**
 - `Data Latency = CurrentTime - TriggerPoint`
-

3. Implementation Details

- **Precision:** All measurements use `SystemClock.elapsedRealtime()`, which provides a monotonic clock that includes sleep time, making it ideal for interval timing.
- **Display Format:** Times are formatted as `S.mmm` seconds (e.g., `1.234s`).
- **Reset Logic:**
 - Activation timers reset on every `onStart()`.
 - Data latency timers reset every time a new scan is initiated via the UI buttons.

4. Why These Metrics Matter

- **Activation Time** helps identify delays in DataWedge profile switching or hardware initialization (e.g., Bluetooth handshake for RFID sleds).
- **Data Received Time** quantifies scanning responsiveness from a user perspective.