

Assembly Instructions: Model X-12 Ergonomic Desk Monitor Mount

Document Overview

This document provides step-by-step instructions for assembling and mounting the Model X-12 Ergonomic Desk Monitor Mount.

 **WARNING:** Exceeding the specified weight capacity (20 lbs / 9 kg) may result in equipment damage or personal injury. Ensure your desk surface is stable enough to support the combined weight of the mount and monitor.

Specifications & Requirements

Estimated Time

- **Assembly:** 15–20 minutes
- **Difficulty:** Easy (1 person required)

Tools Required

- 4mm Allen Wrench (Included)
- 6mm Allen Wrench (Included)
- Phillips-head Screwdriver (Not included)

Hardware Components

Before beginning, verify that you have received all the components listed below.

Item	Component Name	Qty
A	Desk Clamp Assembly	1
B	Support Pole	1
C	Articulating Monitor Arm	1
D	VESA Plate	1
E	M4x12mm Screws (for monitor)	4

Assembly Steps

Step 1: Attach the Clamp to the Desk

1. Loosen the clamp bolt on the **Desk Clamp Assembly (A)** until the opening is wider than your desktop thickness.
2. Slide the clamp completely onto the edge of the desk.
3. Tighten the clamp bolt clockwise by hand until the mount is securely fastened to the desk.

Step 2: Install the Support Pole

1. Thread the **Support Pole (B)** clockwise into the base of the **Desk Clamp Assembly (A)**.
2. Use the 4mm Allen wrench to tighten the safety set screw located at the back of the clamp base.

 **NOTE:** Do not overtighten the set screw; tighten just until it is flush with the metal base to prevent the pole from rotating.

Step 3: Attach the Articulating Arm

1. Slide the **Articulating Monitor Arm (C)** down onto the **Support Pole (B)** to your desired height.
2. Tighten the collar clamp on the arm using the 6mm Allen wrench to lock it into position.

Step 4: Secure the VESA Plate to the Monitor

1. Lay your monitor face down on a flat, soft surface (like a towel or foam packaging) to prevent scratching the screen.
2. Align the **VESA Plate (D)** with the mounting holes on the back of your monitor.
3. Use a Phillips-head screwdriver to secure the plate using four **M4x12mm Screws (E)**.

Step 5: Mount and Adjust the Monitor

1. Carefully lift the monitor and slide the **VESA Plate (D)** into the receiving slot at the end of the **Articulating Monitor Arm (C)**.
2. Listen for an audible "click," which indicates the quick-release tab has locked into place.
3. Adjust the tilt and tension of the arm using the 6mm Allen wrench until the monitor hovers in place without drifting.

Troubleshooting & Maintenance

- **Problem:** The monitor sinks or droops downwards.
 - **Solution:** Locate the tension adjustment screw on top of the articulating arm joint. Turn it clockwise (+) using the 6mm Allen wrench to increase the gas-spring tension.
- **Maintenance:** Check the tightness of the desk clamp and arm collar every six months to ensure continued stability.