

Troubleshooting: Resetting a Frozen SmartHub

If your SmartHub becomes unresponsive, the status LED will turn **solid red**, and connected devices will show as "Offline" in your app. Follow these steps to perform a hard reset.

Before You Begin

Important: A hard reset will not delete your saved devices or network configurations. Do not unplug the power cable during this process.

Step-by-Step Reset Procedure

1. **Locate the Reset Button:** Find the pinhole button labeled **RESET** on the back panel of the SmartHub, located just above the power port.
2. **Trigger the Reset:** Insert a straightened paperclip or SIM ejector tool into the pinhole. Press and hold the button down for **10 seconds**.
3. **Monitor the LED:** Release the button when the status LED begins to **flash amber**. This indicates the reboot cycle has started.
4. **Verify Connection:** Wait approximately 2 minutes. The reset is complete when the LED turns **solid blue**, signaling the hub has reconnected to your Wi-Fi network.

Status LED Reference

If the LED does not turn blue, use this table to diagnose the issue:

LED Color / Pattern	Meaning	Next Action
Flashing Red	No internet connection detected.	Reboot your internet router.
Solid Amber	Firmware update in progress.	Wait 5 minutes; do not disrupt power.
Off	No power to the device.	Check that the power adapter is secure.