

Open19 Server Specification

Yuval Bachar
LinkedIn

Document Number: O19-1000-0002



Version Tracking

Author	Date	Version	Change details
Yuval Bachar	3/11/2019	1.0	Release version

Legal Disclaimer

THIS DOCUMENT WAS DEVELOPED UNDER THE OPEN19 FOUNDATION INTELLECTUAL PROPERTY POLICY DATED 31 MAR 2017 AS PART OF A "SINGLE SOURCE PROJECT" LED LINKEDIN INC. IN CONNECTION WITH THIS PROJECT, "INCLUDED CLAIMS," AS DEFINED UNDER THE OPEN19 FOUNDATION INTELLECTUAL PROPERTY POLICY, SHALL BE LIMITED IN SCOPE TO HARDWARE SPECIFICATIONS (SUCH AS FORM FACTOR, WHERE PROVIDED) AND HARDWARE DESIGN FILES FOR THE FOLLOWING, AS APPLICABLE: OPEN19 CAGES, OPEN19 BOLT SWITCH, OPEN19 POWER SHELF (EXTERNAL ONLY), AND OPEN19 CABLES. EXCEPT FOR THE REQUIRED BINARIES AND PROGRAMMING FILES, ALL SOFTWARE, APPLICATION RELATED INFORMATION, AND CHIP TECHNOLOGY (INCLUDING FPGA CODE) SHALL BE EXCLUDED FROM THE SCOPE OF "INCLUDED CLAIMS."

Table of Content

OPEN19 SERVER SPECIFICATION	1
TABLE OF CONTENT	2
TABLE OF FIGURES.....	3
1 OPEN19 PLATFORM OVERVIEW	5
1.1 GENERAL.....	5
1.2 OPEN19 PLATFORM BACKGROUND.....	5
1.3 OPEN19 DESCRIPTION.....	6
1 BRICK (HALF WIDTH 1RU) SPECIFICATIONS	8
1.1 BRICK DIMENSIONS	8
1.2 MAIN PCBA	8
1.2.1 <i>PCB Dimensions</i>	9
1.3 INTERCONNECT	10
1.4 CONNECTORS PINOUT	12
1.4.1 <i>Data Connector</i>	12
1.4.2 <i>Power Connector</i>	12
1.5 BRICK RETENTION	13
1.6 DESIGN REQUIREMENTS	13
1.6.1 <i>Brick Keying</i>	14
1.7 MATERIALS.....	16
1.8 WEIGHT	16
2 DOUBLE WIDE BRICK (FULL WIDTH 1RU) SPECIFICATIONS	17
2.1 BRICK DIMENSIONS	17
2.2 MAIN PCBA	18
2.2.1 <i>PCB Dimensions</i>	18
2.3 INTERCONNECT	19
2.4 CONNECTOR PINOUT	21
2.5 CONNECTORS PINOUT	21
2.5.1 <i>Data Connector</i>	21
2.5.2 <i>Data Connector</i>	21
2.5.3 <i>Power Connector</i>	22
2.6 BRICK RETENTION	23
2.7 DESIGN REQUIREMENTS	23
2.8 MATERIALS.....	26
2.9 WEIGHT	26
3 DOUBLE HIGH HALF WIDTH BRICK (HALF WIDTH 2RU) SPECIFICATIONS	27
3.1 BRICK DIMENSIONS	27
3.2 MAIN PCBA	28
3.2.1 <i>PCB Dimensions</i>	28
3.3 INTERCONNECT	29
3.4 CONNECTOR PINOUT	30
3.4.1 <i>Data Connector</i>	31
3.4.2 <i>Power Connector</i>	31

3.5	BRICK RETENTION	32
3.6	DESIGN REQUIREMENTS	32
3.7	MATERIALS.....	36
3.8	WEIGHT	36
4	DOUBLE HIGH BRICK (FULL WIDTH 2RU) SPECIFICATIONS.....	37
4.1	BRICK DIMENSIONS	37
4.2	MAIN PCBA	38
4.3	INTERCONNECT	40
4.4	CONNECTOR PINOUT	42
4.4.1	<i>Data Connector</i>	42
4.4.2	<i>Power Connector</i>	43
4.5	BRICK RETENTION	44
4.6	DESIGN REQUIREMENTS	44
4.7	MATERIALS.....	47
4.8	WEIGHT	47

Table of Figures

FIGURE 1 : RACK LEVEL OPEN19 PLATFORM OVERVIEW	7
FIGURE 2 : BRICK DIMENSIONS	8
FIGURE 3 : BRICK MAIN PCBA	9
FIGURE 4 : BRICK PCB DIMENSIONS	10
FIGURE 5 : PCB CONNECTORS.....	10
FIGURE 6 : BRICK PCB OVERALL DIMENSIONS	11
FIGURE 7 : BRICK PCBA PINOUT DEFINITION	11
FIGURE 8 : BRICK RETENTION	13
FIGURE 9 : BRICK DESIGN CONSIDERATION	13
FIGURE 10 : DESIGN CONSIDERATION 3D	14
FIGURE 11 : BRICK FACEPLATE.....	14
FIGURE 12 : KEYING DIMENSIONS	15
FIGURE 13 : SAFETY BACK PANEL PERFORATION	15
FIGURE 14 : 3D BRICK KEYING.....	16
FIGURE 15 : DOUBLE WIDE BRICK DIMENSIONS	17
FIGURE 16 : DW BRICK MAIN PCBA (SHOWING ONLY ONE CONNECTOR SET).....	18
FIGURE 17 : DOUBLE WIDE BRICK PCB DIMENSIONS	19
FIGURE 18 : PCB CONNECTORS	20
FIGURE 19 : DOUBLE WIDE BRICK PCB OVERALL DIMENSIONS	21
FIGURE 20 : DOUBLE WIDE BRICK PCBA PINOUT DEFINITION	21
FIGURE 21 : DOUBLE WIDE BRICK RETENTION	23
FIGURE 22 : DOUBLE WIDE BRICK DESIGN CONSIDERATION	23
FIGURE 23 : DOUBLE WIDE BRICK DESIGN CONSIDERATION 3D	24
FIGURE 24 : DOUBLE WIDE BRICK FACEPLATE	24
FIGURE 25 : KEYING DIMENSIONS	25
FIGURE 26 : FULL WIDTH BRICK SAFETY BACK PANEL PERFORATION	25
FIGURE 27 : FULL WIDTH BRICK KEYING LOCATION.....	26
FIGURE 28 : DOUBLE HIGH HALF WIDTH BRICK DIMENSIONS	27
FIGURE 29 : DWHW BRICK MAIN PCBA	28
FIGURE 30 : DOUBLE WIDE HALF WIDTH BRICK PCB DIMENSIONS	29
FIGURE 31 : PCB CONNECTORS	30

FIGURE 32 : DOUBLE WIDE HALF WIDTH BRICK PCB OVERALL DIMENSIONS	30
FIGURE 33 : DOUBLE WIDE BRICK PCBA PINOUT DEFINITION	31
FIGURE 34 : DOUBLE HIGH HALF WIDTH BRICK RETENTION.....	32
FIGURE 35 : DOUBLE HIGH HALF WIDTH BRICK FACEPLATE1.....	33
FIGURE 36 : DOUBLE HIGH HALF WIDTH BRICK FACEPLATE2.....	33
FIGURE 37 : HALF WIDTH DOUBLE HIGH BRICK KEYING DIMENSIONS	34
FIGURE 38 : HALF WIDTH DOUBLE HIGH BRICK SAFETY BACK PANEL PERFORATION.....	35
FIGURE 39 : FULL WIDTH BRICK KEYING LOCATION.....	35
FIGURE 40 : DOUBLE HIGH DOUBLE WIDE BRICK DIMENSIONS.....	37
FIGURE 41 : DOUBLE WIDE DOUBLE HIGH BRICK DIMENSIONS.....	38
FIGURE 42 : DOUBLE WIDE DOUBLE HIGH BRICK PCB DIMENSIONS (SHOWING ONE SET OF TWO)	39
FIGURE 43 : PCB CONNECTORS	40
FIGURE 44 : DOUBLE WIDE DOUBLE HIGH BRICK PCB OVERALL DIMENSIONS.....	41
FIGURE 45 : DOUBLE WIDE DOUBLE HIGH BRICK PCBA PINOUT DEFINITION	42
FIGURE 46 : DOUBLE HIGH DOUBLE WIDE BRICK RETENTION	44
FIGURE 47 : DOUBLE HIGH DOUBLE WIDE BRICK FACEPLATE 1	45
FIGURE 48 : DOUBLE HIGH DOUBLE WIDE BRICK FACEPLATE 2	45
FIGURE 49 : DOUBLE WIDTH DOUBLE HIGH BRICK KEYING DIMENSIONS	46
FIGURE 50 : DOUBLE WIDTH DOUBLE HIGH BRICK SAFETY BACK PANEL PERFORATION.....	47
FIGURE 51 : DOUBLE HIGH DOUBLE WIDE BRICK DESIGN CONSIDERATION 3D.....	47

1 Open19 Platform Overview

1.1 General

The purpose of this document is to fully describe the Open19 platform and the components of its infrastructure. The specification will use a single instance of the platform as an example, which includes:

- Two 12RU cages
- One power shelf
- One Open19 switch
- 12RU power and data cabling solutions

While we'll focus on the above configuration in this document, we want to be clear that the Open19 platform can be configured per site and per specific adoption requirement. For example, some implementations will integrate two aforementioned items per rack, and some will go for a dual 8RU solution in a rack. We will mention different options that are currently available for buildout. The current solution needs to be fit into a 19-inch rack with 36 to 52 rack units and a minimum depth of 1000 mm, which is the only requirement for installing the Open19 platform.

Refer to the server specification for detailed description of different servers' form factors for the Open19 platform.

1.2 Open19 Platform Background

The Open19 platform is an open standard to define a new server form factor. It is a standard that also defines data and power distribution but not the internal design of the servers to enable server design partners to innovate and build their own servers to create a competitive landscape.

The Open19 platform has the following key goals:

- Create an open standard for 19-inch rack environment for server, storage, and networking.
- Optimize rack deployment cost.
 - Reduce common infrastructure cost by 30% to 40%
 - Reduce server cost by 15% to 20%
- Enable faster rack integration.
 - 7 to 10 times faster
- Build an ecosystem that can consolidate requirements and volumes with a high adoption level.
- Accommodate with different sizes of data centers and edge solutions.

1.3 Open19 Description

The Open19 project offers operators of data centers and edge solutions an optimized open platform. This platform is meant to be installed to any existing or new 19-inch rack and targeted to operate as a standalone disaggregated platform that only requires a 19-inch rack and 10°C to 40°C operating environment.

The Open19 platform has four main building blocks and two optional ones:

- Any 19-inch 4-post rack – The Open19 standard does not specify the rack. Any rack that is EIA compatible and at least 1000mm deep can be used.
- Brick cage – A structure that creates the common, cross supplier, and form factor.
- Data cable, and power cable for the servers creating blind mate connectivity with predefined pinouts.
- Bricks – The Open19 platform defines four form factors:
 - Brick- 1RU half width
 - Double Wide Brick (DW) – 1RU full width
 - Double High Brick (DH) – 2RU full width
 - Double High Half Width Brick (DHHW) – 2RU half width
- Power shelf – There are two types. One is up to 19.2KW in 1RU, the other is up to 38.4KW in a 2RU.
- Network switch – Eliminate the need for server DAC (Direct Attach Cable). The switch is optional but highly recommended. Standard switch can be used with the appropriate data cable.
- Battery backup unit (BBU) – This is optional.

The following diagram shows the components of the Open19 platform in a rack.




Figure 1 :Rack Level Open19 Platform Overview

The following sections describe the specification of a server's form factors. Refer to the Open19 system level specification for additional information.

1 Brick (Half Width 1RU) Specifications

1.1 Brick Dimensions

The brick is designed to be constructed to the overall dimensions shown below:




Figure 2 : Brick Dimensions

1.2 Main PCBA

The main PCBA (Printed Circuit Board Assembly) provides blind mate connections for 12V input power and up to up to 4x25G data signals.

The PCBA is adequately supported on chassis standoffs, with the top surface of the PCB specified as a reference surface. It is located $6.5\text{mm} \pm 0.5\text{mm}$ ($0.256'' \pm 0.020$) above the bottom surface of the sheet metal chassis.




Figure 3 : Brick Main PCBA

1.2.1 PCB Dimensions

Width – $209.55\text{mm} \pm 0.25$ ($8.25'' \pm 0.010$) with two clearance notches as shown. The PCB may be narrower, depending on the server vendor's requirements.

Length – As required by the server vendor.

Thickness – Nominal 2.5mm ($0.097''$), with the use of 4.0mm tall chassis standoffs. Thickness may vary from 1.6mm ($0.063''$) to 3.2mm ($0.125''$), given the length of the supporting standoff may be adjusted to locate the PCB top surface at the 6.5mm reference height.




Figure 4 : **Brick PCB Dimensions**

1.3 Interconnect

The brick is equipped with blind mate connectors for receiving 12V power from the power shelf and transferring data with the switch. The blind mate connectors mate with the cable connectors projected from the rear wall of the cage.

- Power connector – Amphenol DWR-L2P-BP200-101
- Data connector – Molex 171320-9032 4pr x 2, Right Angle with Guide Receptacle

The rating of power and data connectors is described below:

- Power connector – Not-To-Exceed (NTE) 35A at 12v
- Data connector – 4 Channels of 25G; refer to the platform channel description for more details.




Figure 5 : **PCB Connectors**

The connectors are positioned within the brick as shown below:




Figure 6 : Brick PCB Overall Dimensions




Figure 7 :Brick PCBA Pinout Definition

1.4 Connectors Pinout

1.4.1 Data Connector

We have two type of pinout definitions, one for the fully specialized Open19 switch and the other for general purpose switches. Please note different cables are used for the two options.

Open19 Backplane Data connector					
Signal Description	Net name	Pin Number		Net Name	Signal Description
Optional Console port	Console TX	B1	B2	Console RX	Optional Console port
	SPARE (NC)	A1	A2	SPARE (NC)	
Switch to Server (1G)	GE_SWITCH_BP_TX_N	D1	D2	GE_SWITCH_BP_RX_N	Server to Switch OOB (1G)
	GE_SWITCH_BP_TX_P	C1	C2	GE_SWITCH_BP_RX_P	
Server to Switch port1 (25G TX)	SERV1_TX_P	F1	F2	SERV2_TX_P	Server to Switch port2 (25G TX)
	SERV1_TX_N	E1	E2	SERV2_TX_N	
Switch to Server port1 (25G RX)	SERV1_RX_P	H1	H2	SERV1_RX_P	Switch to Server port2 (25G RX)
	SERV1_RX_N	G1	G2	SERV1_RX_N	
Ground Pin	GND	GND1...GND18		GND	Ground Pin

Table 1: Data Connector Pinout for Specialty Switch

Open19 Backplane Data connector					
Signal Description	Net name	Pin Number		Net Name	Signal Description
Server to Switch port3 (25G TX)	SERV3_TX_P	B1	B2	SERV4_TX_P	Server to Switch port4 (25G TX)
	SERV3_TX_N	A1	A2	SERV4_TX_N	
Server to Switch port3 (25G RX)	SERV3_RX_P	D1	D2	SERV4_RX_P	Switch to Server port4 (25G RX)
	SERV3_RX_N	C1	C2	SERV4_RX_N	
Server to Switch port1 (25G TX)	SERV1_TX_P	F1	F2	SERV2_TX_P	Server to Switch port2 (25G TX)
	SERV1_TX_N	E1	E2	SERV2_TX_N	
Switch to Server port1 (25G RX)	SERV1_RX_P	H1	H2	SERV1_RX_P	Switch to Server port2 (25G RX)
	SERV1_RX_N	G1	G2	SERV1_RX_N	
Ground Pin	GND	GND1...GND18		GND	Ground Pin

Table 2: Data Connector Pinout for Standard Switch

1.4.2 Power Connector

Open19 Backplane Power connector					
Signal Description	Net name	Pin No		Net Name	Signal Description
12V Backplane power	VDD12V_BP	A1	G1	GND	Ground

Table 3: Power Connector Pinout

1.5 Brick Retention

The brick is secured into the cage with a single Southco D9-47-1302-K quarter-turn fastener, located on the right side of the faceplate. It is positioned as shown below:




Figure 8 : **Brick Retention**

1.6 Design Requirements

Clearance channels are required along the top edges of the brick, extending forward from the rear panel to the back of the faceplate.




Figure 9 : **Brick Design Consideration**



Figure 10 : **Design Consideration 3D**

The faceplate is notched above and below the fastener (See Figure 11). Note that the faceplate can accommodate any type of ports or drives as needed and is not required to be fully perforated.




Figure 11 : **Brick Faceplate**

Screws and/or rivets used to secure the top cover are flush to under-flush. The vertical edges on the rear of the brick chassis base are coined to break sharp edges.

1.6.1 Brick Keying

Two keying notches are positioned in the left and right corners of the sheet metal enclosure as shown below. All dimensions below are critical.




Figure 12 : **Keying Dimensions**

See below for typical dimensions of the airflow perforation. All dimensions below are critical.




Figure 13 : **Safety Back Panel Perforation**

Screws and/or rivets used to secure the top cover are flush to under-flush.
The vertical edges on the rear of the brick chassis base are coined to break sharp edges.




Figure 14 : **3D Brick Keying**

1.7 Materials

The brick enclosure is constructed of sheet metal with adequate strength and rigidity. Suggested material is 0.8mm SGCC for the chassis base and 0.6mm SGCC for the top cover.

1.8 Weight

The maximum weight of the brick, when equipped with all drives and/or accessories, is 25lbs (11.4kg).

2 Double Wide Brick (Full Width 1RU) Specifications

2.1 Brick Dimensions

The Double Wide (DW) brick is designed to be constructed to the overall dimensions shown below:




Figure 15 : Double Wide Brick Dimensions

2.2 Main PCBA

The main PCBA provides blind mate connections for two 12V input power connectors and two 4x25G data signals connectors.

Note that it is optional to connect to all four connectors. Connect to all four connectors for maximum performance.

The PCBA is adequately supported on chassis base, with the top surface of the PCB specified as a reference surface. It is located 6.5mm+/-0.5mm (0.256" +/-0.020) above the bottom surface of the sheet metal chassis.




Figure 16 : DW Brick Main PCBA (showing only one connector set)

2.2.1 PCB Dimensions

Width – The DW brick can accommodate a board that is up to 438.33mm+/- 0.25 (17.257" +/-0.010) wide with two clearance notches as shown.

Length – As required by the server vendor.

Thickness – Nominal 2.5mm (0.097"), with the use of 4.0mm tall chassis standoffs. Thickness may vary from 1.6mm (0.063") to 3.2mm (0.125"), given the length of the supporting standoff may be adjusted to locate the PCB top surface at the 6.5mm reference height.




Figure 17 : Double Wide Brick PCB Dimensions

2.3 Interconnect

The Double Wide brick is equipped with at least one set of blind mate connectors for receiving 12V power from the power shelf and transferring data with the switch. A second set of connectors may be populated, if required.

- Power connector – Amphenol DWR-L2P-BP200-101
- Signal connector – Molex 171320-9032 4pr x 2, Right Angle with Guide Receptacle

The rating of power and data connectors is described below:

- Power connector – Not-To-Exceed (NTE) 35A at 12v
- Data connector – 4 Channels of 25G; refer to the platform channel description for more details.




Figure 18 : **PCB Connectors**

Note that the picture above shows only one set of connectors, which is the minimum for a Double Wide brick. The following section describes a Double Wide brick with two sets of connectors.

The connectors are positioned within the DW brick as shown below:




Figure 19 : Double Wide Brick PCB Overall Dimensions

2.4 Connector Pinout




Figure 20 : Double Wide Brick PCBA Pinout Definition

2.5 Connectors Pinout

2.5.1 Data Connector

2.5.2 Data Connector

Open19 Backplane Data connector					
Signal Description	Net name	Pin Number		Net Name	Signal Description
Optional Console port	Console TX	B1	B2	Console RX	Optional Console port
	SPARE (NC)	A1	A2	SPARE (NC)	
Switch to Server (1G)	GE_SWITCH_BP_TX_N	D1	D2	GE_SWITCH_BP_RX_N	Server to Switch OOB (1G)
	GE_SWITCH_BP_TX_P	C1	C2	GE_SWITCH_BP_RX_P	
Server to Switch port1 (25G TX)	SERV1_TX_P	F1	F2	SERV2_TX_P	Server to Switch port2 (25G TX)
	SERV1_TX_N	E1	E2	SERV2_TX_N	
Switch to Server port1 (25G RX)	SERV1_RX_P	H1	H2	SERV1_RX_P	Switch to Server port2 (25G RX)
	SERV1_RX_N	G1	G2	SERV1_RX_N	
Ground Pin	GND	GND1...GND18		GND	Ground Pin

Table 4: Data Connector Pinout for Specialty Switch

Open19 Backplane Data connector					
Signal Description	Net name	Pin Number		Net Name	Signal Description
Server to Switch port3 (25G TX)	SERV3_TX_P	B1	B2	SERV4_TX_P	Server to Switch port4 (25G TX)
	SERV3_TX_N	A1	A2	SERV4_TX_N	
Server to Switch port3 (25G RX)	SERV3_RX_P	D1	D2	SERV4_RX_P	Switch to Server port4 (25G RX)
	SERV3_RX_N	C1	C2	SERV4_RX_N	
Server to Switch port1 (25G TX)	SERV1_TX_P	F1	F2	SERV2_TX_P	Server to Switch port2 (25G TX)
	SERV1_TX_N	E1	E2	SERV2_TX_N	
Switch to Server port1 (25G RX)	SERV1_RX_P	H1	H2	SERV1_RX_P	Switch to Server port2 (25G RX)
	SERV1_RX_N	G1	G2	SERV1_RX_N	
Ground Pin	GND	GND1...GND18		GND	Ground Pin

Table 5: Data Connector Pinout for Standard Switch

2.5.3 Power Connector

Open19 Backplane Power connector					
Signal Description	Net name	Pin No		Net Name	Signal Description
12V Backplane power	VDD12V_BP	A1	G1	GND	Ground

Table 6: Power Connector Pinout

2.6 Brick Retention

The DW brick is secured into the cage with two Southco D9-47-1302-K quarter-turn fasteners, one located on each side of the faceplate. They are positioned as shown below:




Figure 21 : **Double Wide Brick Retention**

2.7 Design Requirements

Clearance channels are required along the top edges of the DW brick, extending forward from the rear panel to the back of the faceplate.




Figure 22 : **Double Wide Brick Design Consideration**



Figure 23 : **Double Wide Brick Design Consideration 3D**

The faceplate is notched above and below the Southco fasteners.




Figure 24 : **Double Wide Brick Faceplate**

Two keying notches are positioned in the left and right corners of the sheet metal enclosure as shown below. All dimensions below are critical.




Figure 25 : **Keying Dimensions**

See below for typical dimensions of the airflow perforation. All dimensions below are critical.




Figure 26 : **Full Width Brick Safety Back Panel Perforation**

Screws and/or rivets used to secure the top cover are flush to under-flush.
The vertical edges on the rear of the brick chassis base are coined to break sharp edges.




Figure 27 : **Full Width Brick Keying Location**

2.8 Materials

The DW brick enclosure is constructed of sheet metal with adequate strength and rigidity. Suggested material is 0.8mm SGCC for the chassis base and 0.6mm SGCC for the top cover.

2.9 Weight

The maximum weight of the DW brick, when equipped with all drives and/or accessories, is 50 lbs (22.7kg).

3 Double High Half Width Brick (Half Width 2RU) Specifications

3.1 Brick Dimensions

The DH Brick is designed to be constructed to the overall dimensions shown below:




Figure 28 : Double High Half Width Brick Dimensions

3.2 Main PCBA

The main PCBA provides blind mate connections for 12V input power and up to 4x25G data signals.

The PCBA is adequately supported on chassis standoffs, with the top surface of the PCB specified as a reference surface. It is located $6.50\text{mm} \pm 0.50\text{mm}$ ($0.256'' \pm 0.020''$) above the bottom surface of the sheet metal chassis. A second PCBA may be installed at a reference surface height of $48.55\text{mm} \pm 0.50\text{mm}$ ($1.911'' \pm 0.020''$) above the bottom surface of the chassis.




Figure 29 : DWHW Brick Main PCBA

3.2.1 PCB Dimensions

Width – $209.55\text{mm} \pm 0.25$ ($8.25'' \pm 0.010$) with two clearance notches as shown. PCB may be narrower, depending on the server vendor's requirements.

Length – As required by the server vendor.

Thickness – Nominal 2.5mm ($0.097''$), with the use of 4.0mm tall chassis standoffs. Thickness may vary from 1.6mm ($0.063''$) to 3.2mm ($0.125''$), given the length of the supporting standoff may be adjusted to locate the PCB top surface at the 6.5mm reference height.




Figure 30 : **Double Wide Half Width Brick PCB Dimensions**

3.3 Interconnect

The brick is equipped with blind mate connectors for receiving 12V power from the power shelf and transferring data with the switch. The blind mate connectors mate with the cable connectors projected from the rear wall of the cage. The server can connect to up to two connectors from each side as needed.

- Power Connector – Amphenol DWR-L2P-BP200-101
- Signal Connector – Molex 171320-9032 4pr x 2, Right Angle with Guide Receptacle




Figure 31 : **PCB Connectors**

The connectors are positioned within the brick as shown below:




Figure 32 : **Double Wide Half Width Brick PCB Overall Dimensions**

3.4 Connector Pinout




Figure 33 : Double Wide Brick PCBA Pinout Definition

3.4.1 Data Connector

Open19 Backplane Data connector					
Signal Description	Net name	Pin Number		Net Name	Signal Description
Optional Console port	Console TX	B1	B2	Console RX	Optional Console port
	SPARE (NC)	A1	A2	SPARE (NC)	
Switch to Server (1G)	GE_SWITCH_BP_TX_N	D1	D2	GE_SWITCH_BP_RX_N	Server to Switch OOB (1G)
	GE_SWITCH_BP_TX_P	C1	C2	GE_SWITCH_BP_RX_P	
Server to Switch port1 (25G TX)	SERV1_TX_P	F1	F2	SERV2_TX_P	Server to Switch port2 (25G TX)
	SERV1_TX_N	E1	E2	SERV2_TX_N	
Switch to Server port1 (25G RX)	SERV1_RX_P	H1	H2	SERV1_RX_P	Switch to Server port2 (25G RX)
	SERV1_RX_N	G1	G2	SERV1_RX_N	
Ground Pin	GND	GND1...GND18		GND	Ground Pin

Table 7: Data Connector Pinout for Specialty Switch

Open19 Backplane Data connector					
Signal Description	Net name	Pin Number		Net Name	Signal Description
Server to Switch port3 (25G TX)	SERV3_TX_P	B1	B2	SERV4_TX_P	Server to Switch port4 (25G TX)
	SERV3_TX_N	A1	A2	SERV4_TX_N	
Server to Switch port3 (25G RX)	SERV3_RX_P	D1	D2	SERV4_RX_P	Switch to Server port4 (25G RX)
	SERV3_RX_N	C1	C2	SERV4_RX_N	
Server to Switch port1 (25G TX)	SERV1_TX_P	F1	F2	SERV2_TX_P	Server to Switch port2 (25G TX)
	SERV1_TX_N	E1	E2	SERV2_TX_N	
Switch to Server port1 (25G RX)	SERV1_RX_P	H1	H2	SERV1_RX_P	Switch to Server port2 (25G RX)
	SERV1_RX_N	G1	G2	SERV1_RX_N	
Ground Pin	GND	GND1...GND18		GND	Ground Pin

Table 8: Data Connector Pinout for Standard Switch

3.4.2 Power Connector

Open19 Backplane Power connector					
Signal Description	Net name	Pin No		Net Name	Signal Description
12V Backplane power	VDD12V_BP	A1	G1	GND	Ground

Table 9: Power Connector Pinout

3.5 Brick Retention

The brick is secured into the cage with a single Southco D9-47-1302-K quarter-turn fastener, located on the right side of the faceplate. It is positioned as shown below:




Figure 34 : **Double High Half Width Brick Retention**

3.6 Design Requirements

Clearance channels are required along the top edges and side walls of the DHHW brick, extending forward from the rear panel to the back of the faceplate.




Figure 35 : **Double High Half Width Brick Faceplate1**

The faceplate is notched above and below the fastener.




Figure 36 : **Double High Half Width Brick Faceplate2**

Four keying notches are provided in the top left/right and the bottom left/right corners of the sheet metal enclosure as shown below. All dimensions below are critical.




Figure 37 : **Half Width Double High Brick Keying Dimensions**

See below for typical dimensions of the airflow perforation. All dimensions below are critical.




Figure 38 : **Half Width Double High Brick Safety Back Panel Perforation**

Screws and/or rivets used to secure the top cover are flush to under-flush.
The vertical edges on the rear of the brick chassis base are coined to break sharp edges.




Figure 39 : **Full Width Brick Keying Location**

3.7 Materials

The DH brick enclosure is constructed of sheet metal with adequate strength and rigidity. Suggested material is 0.8mm SGCC for the chassis base and 0.6mm SGCC for the top cover.

3.8 Weight

The maximum weight of the DH brick, when equipped with all drives and/or accessories, is 50 lbs (22.7kg).

4 Double High Brick (Full Width 2RU) Specifications

4.1 Brick Dimensions

The 2W2H brick is designed to be constructed to the overall dimensions shown below:




Figure 40 : Double High Double Wide Brick Dimensions

4.2 Main PCBA

The main PCBA provides blind-mate connections for 12V input power and up to 4x25G data signals.

The PCBA is adequately supported on chassis standoff, with the top surface of the PCB specified as a reference surface. It is located 6.50mm+/-0.50mm (0.256" +/-0.020) above the bottom surface of the sheet metal chassis. A second PCBA may be installed at a reference surface height of 48.55mm+/-0.5mm (1.911" +/-0.020") above the bottom surface of the chassis.




Figure 41 : **Double Wide Double High Brick Dimensions**

5.2.1 PCB Dimensions

Width – The 2W2H brick can accommodate a board that is up to 438.33mm+/- 0.25 (17.257" +/-0.010) wide with two clearance notches as shown.

Length – As required by the server vendor.

Thickness – Nominal 2.5mm (0.097"), with the use of 4.0mm tall chassis standoffs. Thickness may vary from 1.6mm (0.063") to 3.2mm (0.125"), given the length of the supporting standoff may be adjusted to locate the PCB top surface at the 6.50mm and 48.55mm reference heights.




Figure 42 : **Double Wide Double High Brick PCB Dimensions (showing one set of two)**

4.3 Interconnect

The 2W2H brick is equipped with at least one set of blind mate connectors for receiving 12V power from the power shelf and transferring data with the switch. All four sets of connectors may be populated, if required.

- Power Connector – Amphenol DWR-L2P-BP200-101
- Signal Connector – Molex 171320-9032 4pr x 2, Right Angle with Guide Receptacle




Figure 43 : **PCB Connectors**

The connectors are positioned within the 2W2H brick as shown below:




Figure 44 : Double Wide Double High Brick PCB Overall Dimensions

4.4 Connector Pinout




Figure 45 :Double Wide Double High Brick PCBA Pinout Definition

4.4.1 Data Connector

Open19 Backplane Data connector					
Signal Description	Net name	Pin Number		Net Name	Signal Description
Optional Console port	Console TX	B1	B2	Console RX	Optional Console port
	SPARE (NC)	A1	A2	SPARE (NC)	
Switch to Server (1G)	GE_SWITCH_BP_TX_N	D1	D2	GE_SWITCH_BP_RX_N	Server to Switch OOB (1G)
	GE_SWITCH_BP_TX_P	C1	C2	GE_SWITCH_BP_RX_P	
Server to Switch port1 (25G TX)	SERV1_TX_P	F1	F2	SERV2_TX_P	Server to Switch port2 (25G TX)
	SERV1_TX_N	E1	E2	SERV2_TX_N	
Switch to Server port1 (25G RX)	SERV1_RX_P	H1	H2	SERV1_RX_P	Switch to Server port2 (25G RX)
	SERV1_RX_N	G1	G2	SERV1_RX_N	
Ground Pin	GND	GND1...GND18		GND	Ground Pin

Table 10: Data Connector Pinout for Specialty Switch

Open19 Backplane Data connector					
Signal Description	Net name	Pin Number		Net Name	Signal Description
Server to Switch port3 (25G TX)	SERV3_TX_P	B1	B2	SERV4_TX_P	Server to Switch port4 (25G TX)
	SERV3_TX_N	A1	A2	SERV4_TX_N	
Server to Switch port3 (25G RX)	SERV3_RX_P	D1	D2	SERV4_RX_P	Switch to Server port4 (25G RX)
	SERV3_RX_N	C1	C2	SERV4_RX_N	
Server to Switch port1 (25G TX)	SERV1_TX_P	F1	F2	SERV2_TX_P	Server to Switch port2 (25G TX)
	SERV1_TX_N	E1	E2	SERV2_TX_N	
Switch to Server port1 (25G RX)	SERV1_RX_P	H1	H2	SERV1_RX_P	Switch to Server port2 (25G RX)
	SERV1_RX_N	G1	G2	SERV1_RX_N	
Ground Pin	GND	GND1...GND18		GND	Ground Pin

Table 11: Data Connector Pinout for Standard Switch

4.4.2 Power Connector

Open19 Backplane Power connector					
Signal Description	Net name	Pin No		Net Name	Signal Description
12V Backplane power	VDD12V_BP	A1	G1	GND	Ground

Table 12: Power Connector Pinout

4.5 Brick Retention

The 2W2H brick is secured into the cage with two Southco D9-47-1302-K quarter-turn fasteners, one located on each side of the faceplate. They are positioned as shown below:




Figure 46 : **Double High Double Wide Brick Retention**

4.6 Design Requirements

Clearance channels are required along the top edges and the side walls of the 2W2H brick, extending forward from the rear panel to the back of the faceplate.




Figure 47 : **Double High Double Wide Brick Faceplate 1**

The faceplate is notched above and below the Southco fasteners. The thumbscrew is attached to sheet metal with a minimum thickness of 1.2mm.




Figure 48 : **Double High Double Wide Brick Faceplate 2**

Four keying notches are provided in the top left/right and the bottom left/right corners of the sheet metal enclosure as shown below. All dimensions below are critical.




Figure 49 : **Double Width Double High Brick Keying Dimensions**

See below for typical dimensions of the airflow perforation. All dimensions below are critical.




Figure 50 : **Double Width Double High Brick Safety Back Panel Perforation**

Screws and/or rivets used to secure the top cover are flush to under-flush.
The vertical edges on the rear of the brick chassis base are coined to break sharp edges.




Figure 51 : **Double High Double Wide Brick Design Consideration 3D**

4.7 Materials

The 2W2H brick enclosure is constructed of sheet metal with adequate strength and rigidity. Suggested material is 0.8mm SGCC for the chassis base and 0.6mm SGCC for the top cover.

4.8 Weight

The maximum weight of the 2W2H brick, when equipped with all drives and/or accessories, is 100 lbs (45.4 kg).