GRONY 2 – STATION SHEET

Date: _____ Checked by: _____

Use only at Grony 2 • Tick when done • Fix it or tell Joe • Red tags = p2 • Easy methods = p3 • Drivers, inventory = p4 • Info stickers = p5 • Not for customers' view

1. OPENING – at Grony 2

Before the first customer.

1. Grony 2 laptop on; wallpaper solid black; I'm in **my own Chrome profile**.
2. **UPS** (TOP EDGE) on with its green light showing; Epson printers **B, D, F, G** on power.
3. Every printer here is on **power and USB** to this computer – even the ones not in use.
   How: Never unplug a printer to free a socket or cable.
4. Each printer's **letter** matches its name on the screen.
   How: Settings → Printers & scanners → printer → Printer properties → General → type the name from the table on page 4 exactly, e.g. "B - Epson ET-2860", then print a test page.
5. Extension boards are **off the floor**; no board plugged into another; **no cable across the walkway** (wires may pass under the printers). **(G2-1)**
6. Laminator is off and cool; nothing rests on or beside it. **(G2-4)**
7. Floor swept; printers dusted with rag and brush; ink tank and tubes dry. **(G2-3)**
8. **Pen on a rope** is set up on the customers' table, the pen writes and the rope is secure.
   How: Tie the pen to the table edge with a short rope so customers can write but cannot take it. Pen dry? Replace it.

2. DURING THE DAY

Ask yourself these all day, not once.

9. I used printers B, D, F and G first. The **HP M880m (C, E)** stay reserved – extreme cases only, and Joe told.
   How: Log the date, job and pages. Afterwards leave it on standby, plugged in, on USB.
10. I chose the right **letter** on screen for every job.
11. Test and spoilt prints go in **WASTE PAPERS** only. A full document or customer paper is torn into the **BIN**. **(G2-6)**
12. **PRINTING PAPERS** hold clean A4, 4×6, 5×7 only; the ream stays in its wrapper, upright. A3 flat – **never folded**. **(G2-7)**
13. Finished jobs wait in **CUSTOMERS' WORK TO BE COLLECTED**, each in an envelope marked with the GM number and name; collected jobs removed. **(G2-8)**
14. No notes, papers or bags on printer lids or tops; instructions pasted on a label board.
15. Staplers, cutter, tapes, pens and scissors back in their place after use.
16. Faulty machine or item: on the lower shelf of the Boys' showcase with a note (item, fault, date, name); Joe told the same day.
17. Customer details private; files only in their GM-number folder. Replies, receipts and payments go in the customer's **WhatsApp chat**; no personal numbers given.
18. **Complaints** (customer or staff) are written on the log on the **left of the glass showcase**, with date and details.
19. Many files or copies: I checked the **quality and size of the first printout** before printing the rest.
20. **Power cut:** UPS off when there is no work, on only when needed; back on charge when power returns.

3. CLOSING – at Grony 2

Before locking up.

21. **Laminator** off, unplugged and cooled. **(G2-4)**
22. **Bin** emptied; WASTE PAPERS sorted – no full documents left. **(G2-5, G2-6)**
23. Desktop, Documents and Downloads empty on the Grony 2 laptop.
24. Printers off at their button but **still plugged in and on USB**; UPS charging.
25. No socket overloaded; no loose paper near the wall socket or boards. **(G2-1, G2-2)**
26. Pen drives, cards and routers back in the showcase or Grony 3/4.
27. Everything needed for printing within reach; anything missing reported to Joe.

4. GRONY 2 SHOWCASE LIST

Check all are available (as printed on the sticker).

28. Cellotapes
29. Brown envelopes
30. Polythene bags – in a brown envelope
31. Stapler
32. Staple pins – in a brown envelope
33. Cuttings – in a brown envelope; a few ready, kept with rubber bands
34. Online forms – in a brown envelope
35. Scissors
36. Passport cutter
37. Passport envelopes – in a brown envelope

5. COMPANY NUMBER STICKER

On the back of the Grony 2 monitor – customers send their work on WhatsApp to this number.

38. Sticker is on the back of the monitor, **flat, clean and facing customers**; the number reads clearly from the customer side.
    How: Torn, faded or peeling? Print a new one (Grony_Company_Number_Sticker.pdf), laminate, tape all four edges. **(G2-13)**
39. **Weekly:** I scanned the QR with my phone camera and it opened a WhatsApp chat with the company number.
    How: Camera app → point at the QR → tap the link → WhatsApp opens.
40. A customer who asks where to send work is shown the sticker and asked to send files on WhatsApp.

GRONY 2 – STATION SHEET

Date: _____ Checked by: _____

Use only at Grony 2 • Tick when done • Fix it or tell Joe • Red tags = p2 • Easy methods = p3 • Drivers, inventory = p4 • Info stickers = p5 • Not for customers' view

GRONY 2 AT A GLANCE – draft from photos, not to scale. Red numbers = RED MARKERS list below.



RED MARKERS – GRONY 2

Numbers match the red circles. Fix, then tick.

G2-1 Extension boards and cables on the floor by printers C, E and the shelf units. ☐
How: One board per station, fixed off the floor, plugged straight into the wall. No board into another. Cables bundled off the walkway.

G2-2 Wall socket on the wooden unit, cables dangling right above the stationery. ☐
How: Electrician secures socket and cables; keep paper and tapes away from it.

G2-3 External ink tank (CISS) and tubes loose beside the UPS. ☐
How: Tanks in a tray away from the UPS; secure the tubes; wipe any spill.

G2-4 Hot laminator on the shelf directly above the bin. ☐
How: Off and unplugged at closing; cool before leaving; keep paper and bin away.

G2-5 Bin is an open cardboard box of plastic and paper, with a second box under it. ☐
How: Proper lidded bin, emptied daily at closing.

G2-6 WASTE PAPERS slot overflowing, with full printed documents inside. ☐
How: Empty daily; tear documents into the BIN; test prints only.

G2-7 PRINTING PAPERS slot: ream torn open, wrapper crumpled, sheets spilling. ☐
How: Keep the ream in its wrapper, upright and flat.

G2-8 CUSTOMERS' WORK slot: prints and posters stuffed in loose. ☐
How: Each job in an envelope marked with GM number and name; remove collected jobs daily; never fold A3.

G2-9 Printers D, F and G stacked on one thin shelf. ☐
How: Keep vents uncovered and tops clear; check the shelf takes the weight.

G2-10 Glass showcase: stock mixed with loose tools and wires; film still on the glass. ☐
How: Sort stock by type; tools into a toolbox; peel the film.

G2-11 Showcase sticker lists work items, but they sit on the wooden unit. ☐
How: Move the sticker to the unit, or the items into the showcase.

G2-12 Faded tape labels and torn sticker residue on the HP printers. ☐
How: Clean off; one permanent info sticker per printer (letter, model, rule).

G2-13 Paper company-number sticker is taped across the top vent slots of the Philips monitor. ☐
How: Fix the new sticker on the flat back panel below the vents; tape all four edges; keep vents clear.

PRINTERS AT GRONY 2

Tick when its information sticker is written and a snapshot sent to the owner.

B Epson EcoTank ET-2860 – Wi-Fi + USB – top of the wooden unit. ☐

C HP Color LaserJet Managed flow MFP M880m ("HP COLOUR 1") – aisle, on castors. **Reserved** – owner to confirm which M880. Service sticker: D.A.L Divine Anchor Ltd. ☐

D Epson photo printer (Wi-Fi/Ethernet) – top of the white shelf, beside the UPS. ☐

E HP Color LaserJet Managed flow MFP M880m ("HP COLOUR 2") – aisle. **Reserved** – owner to confirm which M880. ☐

F Epson (cream) with external ink tank – middle shelf. ☐

G Epson EcoTank L8050 – bottom shelf. ☐

A Not yet seen – tell Claude where it is. ☐

LABELLED PLACES

What each place holds – only that.

- **BIN (ALL RUBBISH)** – lower-left shelf. Rubbish and unusable paper; official documents torn first.
- **WASTE PAPERS (for test prints)** – test and spoilt prints only.
- **PRINTING PAPERS (A4 sheet, 4×6, 5×7, etc.)** – clean paper only.
- **CUSTOMERS' WORK TO BE COLLECTED** – finished jobs in marked envelopes.
- **Tools shelf** – tapes, staplers, correction pens, markers, cutter, stamp.
- **Glass showcase** – stock for sale; tools do not belong here.

NOTES – new problems seen at Grony 2

Write the date, what you saw and your name. Send a photo to the owner so it becomes a red marker.

_____

_____

_____

_____

_____

_____

_____

_____

_____

_____

_____

_____

_

_____

_

_____

_

GRONY 2 – STATION SHEET

Date: _____ Checked by: _____

Use only at Grony 2 • Tick when done • Fix it or tell Joe • Red tags = p2 • Easy methods = p3 • Drivers, inventory = p4 • Info stickers = p5 • Not for customers' view

EASY WAYS TO DO EVERY SERVICE AT GRONY 2 – DRAFT: owner to confirm each method before it is posted. Claude chat names are in quotes.

BEFORE EVERY JOB

1. New customer? Make sure they are registered and have a **GM number**; open their GM folder.
2. Save every file in that GM folder – never on the Desktop or Downloads.
3. Choose the printer by its **letter** (see "Which printer?").
4. Quote from the price list; record the sale in **Live Sale** (WIC on) before handing over. Replies, receipts and payments go in the customer's WhatsApp chat – company number only.

WHICH PRINTER?

1. **B** – scanning, copying, quick A4 colour.
2. **G** (or **D**) – photos and passport photos.
3. **HP black-and-white MFP** – black-and-white copies and documents.
4. A3, or anything else: ask Joe first – the **HP M880m (C, E)** is reserved for extreme cases.
5. Large format, binding, stickers: **Grony 5**.

TYPING – from handwriting

1. Lay the pages flat on printer **B** and scan them (Epson Scan 2, 300 dpi) into the customer's GM folder.
2. Open the Claude chat **"Handwritten transcript"**, upload the scan and ask for a **Word document**.
3. Check every name, date and number against the handwriting; ask the customer about words you cannot read.
4. Open it in Word, fix the layout, save it in the GM folder.
5. Print by letter and hand over with the original.

Tip: straight, flat scans transcribe best.

TYPING – from a file or message

1. Save the customer's file in the GM folder; **Save As** a new name – never change the original.
2. Edit in Word (PDF: open it in Word, or ask Claude to convert it).
3. Check, print by letter, save.

CV · LETTER · FORM · INVITATION

1. Get the customer's details (WhatsApp or in person); ask for anything missing.
2. Paste them into the matching Claude chat and ask for a **Word document** in a clean layout.
3. Check spelling, names, dates and phone numbers with the customer.
4. Print on B (colour) or the HP black-and-white MFP; save the Word file in the GM folder.

SCAN

1. Place the document flat on **B**; scan to PDF (Epson Scan 2).
2. Name it with the GM number and what it is, e.g. "GM24 – results slip".
3. Send on WhatsApp or email if asked; keep a copy in the GM folder.

PHOTOCOPY

1. Few or colour copies: copy on **B**. Many black-and-white copies: the HP black-and-white MFP.
2. Make one copy and check its **quality and size**, then the rest. Spoilt copies go in WASTE PAPERS.
3. Staple or sort; hand over with the original.

PRINT A CUSTOMER'S FILE

1. WhatsApp file: save it from the company WhatsApp on the laptop into the GM folder. Pen drive: scan it with Windows Security, copy the file in, give the drive back.
2. Open it; check page size, orientation and page count.
3. Print preview, pick the printer by letter; print the **first page** and check its quality and size before the rest.
4. Put the job in a marked envelope in CUSTOMERS' WORK.

PHOTO PRINTS

1. Photo paper in **G** (or D); make sure the paper size on screen matches (4×6, 5×7…).
2. Open the photo and print at best photo quality, no scaling.
3. Let it dry before touching; hand over in an envelope.

PASSPORT PHOTOS

1. Plain background, face straight, shoulders level; stand to snap.
2. Size and crop with the shop's passport photo editor.
3. Print on 4×6 photo paper (G or D).
4. Cut with the **passport cutter**; hand over in a passport envelope.

LAMINATION

1. Switch the laminator **ON**, set the heater and wait for the ready light.
2. Put the document inside the right-size pouch; feed the sealed edge first.
3. Catch it and lay it flat to cool.
4. At closing: switch off, unplug, let it cool.

DESIGN – poster, flyer, invitation, ID card

1. In Claude (design chat) say what it is, the size, the exact wording and colours; ask for it in Canva.
2. Review it and ask for changes in plain words until it is right.
3. Download the PDF; print a test on B; check spelling and numbers with the customer.
4. Bigger than A3: take it to **Grony 5**.

ONLINE ADMISSION APPLICATION

1. Check the portal is open and what it needs (documents, photo, results).
2. Scan the applicant's documents on **B** into their GM folder.
3. Fill the form with the applicant beside you; they check every detail **before** you submit. Never save their password in the browser.
4. Print the confirmation or payment slip; record the sale in Live Sale.

LARGE FORMAT · BINDING · STICKERS

1. Go to Grony 5 with the file – the assisting staff covers your counter and fetches what you cannot reach.
2. Bring the finished job back to the customer's envelope or hand it over.

A PRINTER FAILS MID-JOB

1. Stop sending the job; clear a simple jam.
2. Open that printer's **Claude chat** (instructions + drivers) and follow it. No chat? Flag it to the owner.
3. Send it again on another letter (not the M880m unless extreme).
4. Faulty machine: lower shelf of the Boys' showcase with a note; tell Joe.

6. PRINTER DRIVERS, CLAUDE CHATS & INFORMATION STICKERS

Every printer needs: **(1)** its correct **driver** installed on the Grony 2 computer; **(2)** its own **Claude chat** that gives the instructions and drivers for that printer – write its name; **if a printer has NO chat, tick FLAG and tell the owner**; **(3)** an **information sticker** on it (page 5). **GM app:** printer properties use other names (e.g. "HP 880 A3 PRINTER B" at Grony 2) – rename them to these letters.

LTR	PRINTER / DEVICE	NAME ON SCREEN (type exactly)	DRIVER INSTALLED	CLAUDE CHAT NAME (write it)	NO CHAT – FLAG	INFO STICKER ON IT	POWER + USB ON
B	Epson EcoTank ET-2860 – A4 colour, scan/copy, Wi-Fi	**B - Epson ET-2860**	☐		☐	☐	☐
C	HP Color LaserJet MFP M880m – RESERVED	**C - HP M880m RESERVED**	☐		☐	☐	☐
D	Epson photo printer (Wi-Fi/Ethernet)	**D - Epson Photo**	☐		☐	☐	☐
E	HP Color LaserJet MFP M880m – RESERVED	**E - HP M880m RESERVED**	☐		☐	☐	☐
F	Epson (cream) with external ink tank	**F - Epson Cream**	☐		☐	☐	☐
G	Epson EcoTank L8050 – A4 photo, 6 colours	**G - Epson L8050**	☐		☐	☐	☐
?	HP black-and-white MFP (desk) – letter to confirm	**(letter to confirm)**	☐		☐	☐	☐
–	Laminator (device – no driver)	**n/a**	n/a		☐	☐	☐

7. GRONY 2 INVENTORY – properties, tools and materials

Count each item, write the number, tick when it is present and in good condition; report anything missing to Joe. The GM app gives most properties no location (190 of 197) – when this list is checked, set each item's location to Grony 2 in the app.

COMPUTER & POWER

- ☐ Grony 2 laptop + charger
- ☐ Philips monitor + power and video cables
- ☐ Mouse, mouse pad (and keyboard if separate)
- ☐ UPS (TOP EDGE) + its cable
- ☐ Extension boards (qty ___) – none on the floor
- ☐ USB cable for every printer (qty ___)
- ☐ Power cable for every printer (qty ___)
- ☐ USB hub / adapters on the desk
- ☐ Wall socket on the wooden unit – secure

PRINTERS & MACHINES

Each with its letter sticker and information sticker.

- ☐ B Epson EcoTank ET-2860
- ☐ C HP M880m ("HP COLOUR 1")
- ☐ D Epson photo printer
- ☐ E HP M880m ("HP COLOUR 2")
- ☐ F Epson (cream) + external ink tank + tubes
- ☐ G Epson EcoTank L8050
- ☐ HP black-and-white MFP (desk)
- ☐ Laminator
- ☐ Printer covers (qty ___)

FURNITURE & FIXTURES

- ☐ Desk with printed mat; chairs (qty ___)
- ☐ White shelf unit (laminator + bin); white shelf unit (D, F, G)
- ☐ Wooden unit: 3 slots + tools shelf
- ☐ Glass showcase
- ☐ Lidded bin (replaces the cardboard box)
- ☐ **Pen on a rope** on the customers' table
- ☐ Light bulb(s) working (qty ___)
- ☐ Window banners and posters in good condition – none from other companies
- ☐ Stickers in place: BIN, WASTE PAPERS, PRINTING PAPERS, CUSTOMERS' WORK, showcase list, company number, staff note, printer letters and info stickers

TOOLS

- ☐ Staplers (qty ___) (incl. giant / long-arm if kept here)
- ☐ Scissors (qty ___)
- ☐ Passport cutter
- ☐ Cutter / knife (qty ___)
- ☐ A3 paper cutter (if kept here)
- ☐ Correction pens (qty ___)
- ☐ Pens and markers incl. permanent marker (qty ___)
- ☐ Date stamp
- ☐ Cellotapes (qty ___)
- ☐ Pins / thumbtacks
- ☐ Rubber bands (in a wallet)
- ☐ Rags and brush
- ☐ Mop / broom
- ☐ Toolbox with screwdrivers – out of the showcase

MATERIALS

- ☐ A4 paper (qty ___) reams
- ☐ A3 paper (qty ___) – flat
- ☐ 4×6 photo paper
- ☐ 5×7 photo paper
- ☐ A4 photo paper
- ☐ Brown envelopes (qty ___)
- ☐ Passport envelopes (qty ___)
- ☐ Polythene bags (in a brown envelope)
- ☐ Staple pins (in a brown envelope)
- ☐ Laminating pouches A4 / A3 (qty ___)
- ☐ Ink bottles for B, G, F/D – every colour (qty ___)
- ☐ Spare toner for the HP printers (qty ___)
- ☐ Cuttings – a few ready, rubber-banded
- ☐ Online forms (in a brown envelope)
- ☐ Company cards / flyers in the yellow wallet
- ☐ Customer jobs in marked envelopes in CUSTOMERS' WORK

STOCK IN THE GLASS SHOWCASE

Count against the item list in the GM app.

- ☐ Game pads / controllers (qty ___)
- ☐ Wireless mice (qty ___)
- ☐ 4G Wi-Fi router (qty ___)
- ☐ Laptop batteries, adapters and chargers (qty ___)
- ☐ Other accessories as on the item list

PRINTER & DEVICE INFORMATION STICKERS – GRONY 2

Print at 100%, cut on the dashed lines and stick each one on its printer where it can be read without moving the machine. Fill in the blanks (serial number, Claude chat name, technician). Safe-use lines are general – the owner confirms them for each model.

B — Epson EcoTank ET-2860

Grony 2 • A4 colour printer, scanner, copier • Wi-Fi + USB

USE FOR: Scanning, copying, quick A4 colour prints.

SAFE USE

- Switch off with the power button – leave it plugged in and on USB.
- Refill only the matching colour; bottles upright; fill to the upper line; wipe spills at once.
- Keep it level – never tilt it or carry it with ink in the tanks.
- No food or drink near it; keep vents and top clear.
- Lift the scanner lid gently; wipe the glass with a soft dry cloth only.

Driver & help – Claude chat: "_____"

Serial no.: _____ **Bought:** _____ **Technician:** _____

Keep on power + USB • Fault: lower shelf of the Boys' showcase + note, tell Joe

C — HP Color LaserJet Managed flow MFP M880m

"HP COLOUR 1" • aisle • on castors • service sticker on front

USE FOR: **RESERVED** – A3 / extreme cases only. Tell Joe first; log date, job and pages.

SAFE USE

- The fuser inside is HOT – never touch it; let it cool before clearing a deep jam.
- Feed A3 flat, never folded; right tray and paper size.
- Not on the small UPS. Vents clear; nothing on top; no liquids.
- Correct toner cartridge only.
- Heavy, on castors – do not move it alone.

Driver & help – Claude chat: "_____"

Serial no.: _____ **Bought:** _____ **Technician:** _____

Keep on power + USB • Fault: lower shelf of the Boys' showcase + note, tell Joe

D — Epson photo printer

Grony 2 • top of the white shelf, beside the UPS

USE FOR: Colour and photo prints (owner to confirm paper sizes).

SAFE USE

- Switch off with the power button – leave it plugged in and on USB.
- Use the correct ink only; wipe spills at once.
- No notes or papers on the lid; remove memory cards after use.
- Shares a shelf with F and G – keep vents uncovered.

Driver & help – Claude chat: "_____"

Serial no.: _____ **Bought:** _____ **Technician:** _____

Keep on power + USB • Fault: lower shelf of the Boys' showcase + note, tell Joe

E — HP Color LaserJet Managed flow MFP M880m

"HP COLOUR 2" • aisle

USE FOR: **RESERVED** – A3 / extreme cases only. Tell Joe first; log date, job and pages.

SAFE USE

- The fuser inside is HOT – never touch it; let it cool before clearing a deep jam.
- Feed A3 flat, never folded; right tray and paper size.
- Not on the small UPS. Vents clear; nothing on top; no liquids.
- Correct toner cartridge only.
- Heavy – do not move it alone.

Driver & help – Claude chat: "_____"

Serial no.: _____ **Bought:** _____ **Technician:** _____

Keep on power + USB • Fault: lower shelf of the Boys' showcase + note, tell Joe

F — Epson (cream) with external ink tank

Grony 2 • middle shelf

USE FOR: Colour and photo prints (owner to confirm paper sizes).

SAFE USE

- External ink tank stays upright, in a tray, away from the UPS and sockets.
- Never pull or kink the ink tubes – do not move this printer without telling Joe.
- Wipe ink spills at once; keep ink bottles closed.
- Switch off with the power button – leave it plugged in and on USB.

Driver & help – Claude chat: "_____"

Serial no.: _____ **Bought:** _____ **Technician:** _____

Keep on power + USB • Fault: lower shelf of the Boys' showcase + note, tell Joe

G — Epson EcoTank L8050

Grony 2 • bottom shelf • A4 photo, 6 colours • Wi-Fi + USB

USE FOR: Photos, passport photos and photo prints (4×6, 5×7, A4).

SAFE USE

- Photo paper: print side up, one sheet at a time; let prints dry before touching.
- Switch off with the power button – leave it plugged in and on USB.
- Refill only the matching colour; bottles upright; fill to the upper line; wipe spills at once.
- Keep it level – never tilt it or carry it with ink in the tanks.
- No food or drink; keep vents and top clear.

Driver & help – Claude chat: "_____"

Serial no.: _____ **Bought:** _____ **Technician:** _____

Keep on power + USB • Fault: lower shelf of the Boys' showcase + note, tell Joe

? — HP black-and-white MFP

Grony 2 desk • letter to confirm

USE FOR: Black-and-white copies and documents (many pages).

SAFE USE

- The fuser inside is HOT – let it cool before clearing a deep jam; clear jams gently.
- No staples or paper clips in the document feeder.
- Do not plug it into the small UPS. Keep vents clear; nothing on top; no liquids.

Driver & help – Claude chat: "_____"

Serial no.: _____ **Bought:** _____ **Technician:** _____

Keep on power + USB • Fault: lower shelf of the Boys' showcase + note, tell Joe

– — Laminator

Grony 2 • top of the white shelf

USE FOR: Laminating documents and ID cards in pouches (A4 / A3).

SAFE USE

- The rollers are HOT – never touch them or push metal inside.
- Switch ON, set the heater and wait for the ready light before feeding.
- Feed the sealed edge first; never force a jam – switch off and let it cool.
- Switch OFF and unplug at closing; keep paper, plastic and the bin away from it.

Driver & help – Claude chat: "_____"

Serial no.: _____ **Bought:** _____ **Technician:** _____

Off and unplugged at closing • Fault: lower shelf of the Boys' showcase, tell Joe