

ARGUS Quick Start

Every command, labelled PI or LAPTOP

ARGUS quick start

Every block says which machine it runs on. **PI** is a Raspberry Pi Connect shell; **LAPTOP** is PowerShell on Windows.

1 · PI — start the node

```
cd ~/argus
git pull
./scripts/run_node.sh
```

It prints the address to open and then stays running. Leave the window alone.

Want	Command
Classify subjects that hold still	<code>./scripts/run_node.sh --every-frame</code>
Bigger detector	<code>./scripts/run_node.sh --model yolov8s</code>
Run against a recording, no camera	<code>./scripts/run_node.sh --video media/vtest.avi</code>
Add the dangerous-person stage	<code>./scripts/run_node.sh --threat</code>

First run only, to get the fast CPU path:

```
python scripts/export_cpu_models.py --format ncnn
```

2 · Watch it

Open `http://<pi-address>:8000/dashboard` in any browser that can reach the Pi. Live feed with boxes, detection FPS every second, what is in frame, and events with the still saved for each.

Or from a shell:

PI

```
cd ~/argus && ./scripts/node_status.sh
```

One line per second:

```
fps= 9.9 ms= 27 cap= 10.0 | tracks= 2 events= 14 motion= 3 stills= 14 | cpu-ncnn yolov8n
gate=True rate=0.98 | fl-r2
```

`tracks` rises when something is in frame; `events` rises once it leaves.

3 • PI — check what the camera sees

```
cd ~/argus && source .venv/bin/activate
python scripts/check_classes.py --camera --save /tmp/seen.jpg
```

Prints the ARGUS classes and the raw COCO labels behind them, and writes an annotated copy you can open. Point it at a file instead to test without the camera:

```
python scripts/check_classes.py media/vtest.avi
```

The four classes: person · vehicle (bicycle, car, motorcycle, bus, train, truck) · animal (bird, cat, dog, horse, sheep, cow) · package (backpack, handbag, suitcase). COCO has no parcel class, so a cardboard box detects as nothing — use a backpack.

4 • PI — a federated round

Node running in shell 1, then:

```
cd ~/argus && ./scripts/fl_trial.sh
```

It starts the aggregator, seeds samples, trains locally, joins the round, and reports the gate's decision. Watch `detect_fps` while it runs — training is a separate process on one core, so detection keeps going.

`model_version` moves to `fl-r1`, `fl-r2` ... only when the gate **accepts** the averaged model. A rejection means it scored worse on this node's own held-out samples, and the node kept the model it had. That is the gate working.

The seeded samples are synthetic and never appear in the event list. Say so when presenting: the pipeline captures and trains on real events, demonstrated alongside a corpus large enough to train on.

5 · LAPTOP — the product dashboard (optional)

```
cd $HOME\Documents\argus\argus
.\scripts\run_dashboard.ps1 -Node 10.0.0.140
```

Then open `http://localhost:3000` (or `:3001`) and log in as `admin`.

Set the password on the PI:

```
python scripts/set_password.py --user admin
```

If it says **SYSTEM OFFLINE**, your laptop cannot reach the Pi, or the port Next.js chose is missing from `CORS_ORIGINS`. The node's own page at `http://<pi>:8000/dashboard` has no such dependency.

If it breaks

Symptom	Fix
Only <code>person</code> detected	Subject is holding still → <code>--every-frame</code> ; or it is too small in frame
Nothing detected at all	<code>python scripts/check_classes.py --camera</code> — separates model from scene
<code>camera_error</code> in status	<code>python -c "from picamera2 import Picamera2"</code> ; if it mentions numpy → <code>pip install "numpy>=1.26,<2"</code>
People look blue	<code>CAMERA_SWAP_RB=true ./scripts/run_node.sh</code>
Round returns 409	Fewer than 200 labelled samples — let <code>fl_trial.sh</code> seed them
Dashboard offline, curl works	Wrong port in <code>CORS_ORIGINS</code> (Next.js often uses 3001)
<code>backend: cpu</code> on the Pi	<code>python scripts/export_cpu_models.py --format ncnn</code>