

Date 88.04.13		Norsk Data A.S PROGRAM DESCRIPTION		Page 1 of 5	
Product	Name COSMOS X.25 Program Access		ND-no. 211197A		Category SPEC
Reason	X New version				
Documen- tation	Title COSMOS X.25 Option Programmer Guide COSMOS X.25 Option Operator Guide			ND-no. 60.227.1 EN 30.034.1 EN	
Purpose	Libraries to allow the access to COSMOS X.25 Option from programs written in PLANC.				
Prerequi- sites	Computer	Type	Floating format	Op. system	Version
	ND-100	Any	Any	SINTRAN III	>= J
	ND-110	Any	Any	----- "	-----
	ND-120	Any	Any	----- "	-----
	ND-500	Any	Any	----- "	-----
	ND-5000	Any	Any	----- "	-----
	ND-no.	Product name			Version
	210373	X-MESSAGE (Inter System)			>=J
	Access to one of the following products:				
	210570	COSMOS X.25 Option for PIOC			>=A
	210573	COSMOS X.25 Option (HDLC)			>=C
	ND-no.	File Name		Type Containing	
	210609A	XMP-B02		DEFS XM-LIB PLANC def.	
	210609A	XMP-B02		IMPT XM-LIB PLANC imp.	
	210609A	XMP-100-1-B02		BRF XM-LIB PLANC/1bank	
210609A	XMP-100-2-B02		BRF XM-LIB PLANC/2bank		
210609A	XMP-500-B02		NRF XM-LIB PLANC/ND500		
Minimum mass storage resources for installation					
User	Userspace		Number of files		
UTILITY	60 pages on		10 files		
(any user may be used)					
Minimum permanent mass storage resources					
User	Userspace		Number of files		
UTILITY	60 pages on		10 files		
(any user may be used)					
Space requirement on seg file(s) is 0 pages					
			ND.no. for Source 250238A		

Date 88.04.13		Norsk Data A.S PROGRAM DESCRIPTION	Page 2 of 5
Product	Name COSMOS X.25 Program Access	ND-no. 211197A	Category SPEC
File Name	Type	Containing	
INST-X25PA-A<rev>	MCRO	PERFORM installation program	
X25PA-100-1-A<rev>	BRF	X.25 Library 1-Bank	
X25PA-100-2-A<rev>	BRF	X.25 Library 2-Bank	
X25PA-500-A<rev>	NRF	X.25 Library 500/5000	
X25PA-LIBR-A<rev>	DEFS	New X.25 Lib def. file	
X25PA-LIBR-A<rev>	IMPT	New X.25 Lib import file	
X25PA-INITEX-A<rev>	PLNC	Example, Initiator program	
X25PA-LISTEX-A<rev>	PLNC	Example, Listener program	
X25PA-LOADEX-A<rev>	MCRO	Example, Loading the library	

NOTE: <rev> is to be replaced by the current revision of the DIRECTORY or FILE. The revision level is found on the preceding "ND SOFTWARE LIBRARY DISKETTE" pages.

Date 88.04.13		Norsk Data A.S PROGRAM DESCRIPTION		Page 3 of 5
Product	Name COSMOS X.25 Program Access	ND-no. 211197A	Category SPEC	

1 INTRODUCTION

COSMOS X.25 Program Access is offered to ease the use of the message interface for the COSMOS X.25 Options, for both PIOC and HDLC. Intended users are software houses and ND departments with a good knowledge of COSMOS/XMSG programming.

The product consists of a set of library routines which format the messages going to the X.25 Packet Level module, and react to events stemming from the X.25 Packet Level. The library resides in the user address space, and acts as a part of the RT-process or Background program.

The COSMOS X.25 Program Access was delivered as an intrinsic part of the COSMOS X.25 Option (for HDLC), 210573C. For later versions of that product it will be separate. This is because it is a common part for both the COSMOS X.25 Options (ND no. 210570 and ND no. 210573), and because the XMSG programming involved here is too complicated to be categorized as a Standard Product.

2 SYSTEM PREREQUISITES

The following are prerequisites for the installation of the product COSMOS X.25 Program Access:

SOFTWARE:

COSMOS X.25 Option: The libraries may be used with both
COSMOS X.25 Option (HDLC-based version) -
ND no. 210573C, and the COSMOS X.25 Option
for PIOC - ND no. 210570A.

Operating System: SINTRAN III version J or later.

X-MESSAGE: Version J or later with a minimum of 15 ports.

3 SYSTEM OVERVIEW

The system consists of the three library files, definition and import files necessary for compilation, and examples of use. The examples may be used both as an extension of the documentation, and as a base for building one's own programs.

Date 88.04.13		Norsk Data A.S PROGRAM DESCRIPTION	Page 4 of 5
Product	Name COSMOS X.25 Program Access	ND-no. 211197A	Category SPEC

4 INSTALLATION PROCEDURE

4.1 Copying the files from the diskettes

In the following instructions, replace <rev> with the current revision number.

- Log in as the user which should contain the library files.
- Make sure that this user has at least 60 pages of disk space available.
- Insert the diskette with the directory name 211197A<rev>-XX-01D (double density diskette) or 211197A<rev>-XX-01S (single density diskette).
- Execute the following commands (operator input is underlined):

@ENTER-DIRECTORY,211197A<rev>-XX-01,FLOPPY-DISC-1,0↵

@PERFORM (211197A<rev>-XX-01:FLOPPY-USER)INST-X25PA-A:MCRO↵

PERFORM 2412F

Macro name (Default = INSTALL-X25) : ↵

The installation procedure will then start. It will perform the following tasks:

- Check the user specified.
- Delete old product files if of the same version.
- Copy the new files to the given user.

A remote copy mechanism is available, using COSMOS File Transfer. It can be started by the command sequence:

@ENTER-DIRECTORY,211197A<rev>-XX-01,FLOPPY-DISC-1,0↵

@PERFORM (211197A-XX-01:FLOPPY-USER)INST-X25PA-A:MCRO↵

PERFORM 2412F

Macro name (Default = INSTALL-X25) : REMOTE-I-X25↵

4.2 Loading

When you have installed the new COSMOS X.25 Program Access files, you can load your program as shown in the file X25PA-LOADEX-A:MCRO.

Date 88.04.13				Norsk Data A.S		Page 5 of 5	
PROGRAM DESCRIPTION							
Product	Name COSMOS X.25 Program Access				ND-no. 211197A		Category SPEC

4.3 Before starting the program.

Before starting your program, make sure that the port *X25GATE is defined on your machine.

5 MISCELLANEOUS

The following are inconsistencies between this implementation, and the currently available documentation.

5.1 Facility negotiation.

To provide for compatability between the A-version of X.25 and later versions, facility negotiation is done after a special scheme. This applies to the Connect Accept command in the four-step connect procedure.

If no facilities are given here, (Fac. length = 0), the X.25 Packet Level will choose Standard Default Values for Window and Packet Sizes (W.S.=2 and P.S.=128 Bytes). If facilities are given, these are of course used by the X.25 Packet Level, and a corresponding Connect Accept Packet will be sent if values are correct.

The X.25 Packet Level will always negotiate the Packet Size to its Standard Default Value, which is 128 Bytes.

ND SOFTWARE LIBRARY DISKETTE

PAGE 1

Containing :
COSMOS X.25 Program Access

Directory Name :
211197A01-XX-01D

User Name : FLOPPY-USER

[illegible]