

## Capture

```
0x00  ff ff ff 7f  ff ff ff 7f  ff ff ff 7f  ff ff ff 7f
0x10  03 00 02 00  00 00 00 00  00 00 00 00  00 00 80 02
0x20  00 05 00 00  04 83 0a 12  00 08 00 f7  96 fc 10 81
```

*128 bytes from the device, preceded by the host's 16-byte barrier, nine frames in all*

deformat

## Frames

frame 0 four frame-synchronization patterns, the barrier  
frame 1 trace identifier 1, then alignment synchronization  
frame 2 trace info, trace on, address, atom

recover packets

## Packets

```
0x10  I_NOT_SYNC
0x12  I_ASYNC
0x20  I_TRACE_INFO
0x24  I_TRACE_ON
0x25  I_ADDR_CTXT_L_32IS1  0x08001214
0x2b  I_ATOM_F1  E
```

expand into elements

## Elements

```
0x10  no-sync
0x24  trace on
0x2b  instruction range  0x08001214 to 0x0800121c, 3 instructions
```