

Roll#-----

Quiz#3

Section: C

Total Marks 10

Question1: [marks 3]

<pre> Mov ax, -2 Mov bx, -1 Cmp ax,bx Jle exit Add ax,1 Exit: Mov ax,0x4c00 Int 21h </pre>	What would be the value of SF and OF after execution of cmp instruction. Tell whether jump is taken or not? Solution: CF= OF= Jump= SF=
--	--

Question2: What would be the output (values of array) after execution of the code given below? Which mode of addressing is used? [marks 4]

<pre> [org 0x0100] Jmp start arr: dw 0, 2, 4, 6, 8 ,10 start: mov si, 0 Mov di,10 loop1: Mov ax, [arr + si] Mov bx, [arr + di] Mov [arr+si], bx Mov [arr +di],ax Add si,2 Sub di,2 Cmp si,di Jbe loop1 Mov ax, 0x4c00 Int 0x21 </pre>	Solution: arr: Type of addressing=
---	--

Question3 [marks 3]

[org 0x0100]

Mov Byte [mem], 1

Mov Word [mem+1], 2

Mov bl,[mem+2]

exit:

Mov ax, 0x4c00

Int 0x21

mem :dw 0

Below memory is given each box represents single Byte. Update memory contents and tell what would be the value stored in bl register? What type of addressing is used?

Solution:

bl =

