

THANK YOU
FOR CHOOSING
RUMI.



RUMI

RUMI61S User Manual



Dual Mode: Wired + Bluetooth 3.0/5.0
Dimensions: L*W*H: 291.1*101.1*38.72mm
Weight :630g
19 Different RGB Backlights
ABS Double Injection Keycaps
Built in Lithium Ion Battery (2500mAh)
1.6M Type C Cable
Hot Swappable
5 pin PCB
Voltage/Current = 5V 150mA
Operating System: WinXP, Win7, Win8, Win10, MacOS, iOS, Android

Charging:

- 1. The "Fn" key LED color indicates the status of the battery when you are in Bluetooth mode. Battery power from high to low: White -> Blue -> Green -> Yellow -> Red.
- 2. The LED will flash red repeatedly when keyboard battery power is low.
- White LED means the battery is full.
- 3. Backlight will automatically turn off after 8 minutes without use.
- 4. The keyboard will enter sleep mode and automatically disconnect from Bluetooth after 30 minutes without use. Press any key to wake the keyboard.

Bluetooth Pairing:

- 1. Turn on the Bluetooth switch located on the top part of the keyboard.
- 2. Press and hold Fn + TAB to enter Bluetooth mode. The LED color of the TAB key indicates which mode you are currently using. Blue = Bluetooth, Red = Wired.
- 3. Press and hold Fn + Q/W/E for 3 seconds. The Q/W/E key LED will begin flashing repeatedly to indicate that the keyboard is ready to pair with a new device.
- 4. On your device, select "RUMI61 3.0/5.0."
- 5. Once the keyboard has connected to the device, the Q/W/E key will stop flashing to indicate successful Bluetooth pairing.
- 6. The keyboard can support up to 3 devices. Press and hold Fn + Q/W/E to set up a connection to a new device. Short press Q/W/E to connect a previously paired device that is associated with a particular profile.

Fn Combination Keys:

[{	Decrease Backlight speed
}]	Increase Backlight speed
::	Decrease backlight brightness
""	Increase backlight brightness
\	Switch RGB backlight mode
TAB	Toggle between Bluetooth/wired
Right Shift	Reset keyboard
WIN	Windows lock /unlock
Left Ctrl	Function mode switching
Q	Bluetooth device #1
W	Bluetooth device #2
E	Bluetooth device #3
Space Key	Switch backlight color
Y	Print Screen
U	Scroll Lock
I	Pause
H	Insert
J	Home
K	Page Up
N	Delete
M	End
,<	Page Down
Right Alt	←
App	↓
Right Ctrl	→
/?	↑