helix_code_services.md — Services Guide

Revision: 1 **Last modified:** 2026-07-17T00:00:00Z

Overview

HelixCode service management wrappers: install, boot, stop, health-check, and status for the HelixCode / HelixLLM / HelixAgent service fleet.

Prerequisites

- `helix_code_home.sh` sourced first (provides `hc_home()`)
- bash ≥ 4.0
- Docker or Podman (for compose-based services)
- Network access to `github.com:HelixDevelopment/HelixCode.git`

Quick Start

```bash
source constitution/scripts/helix_code/helix_code_home.sh
source constitution/scripts/helix_code/helix_code_services.sh

# Install binaries
hc_install

# Boot the coder (multi-track live sink)
hc_boot_coder

# Check status
hc_status

# Verify all binaries on PATH
hc_verify_binaries
```

Functions

Function	Purpose
`hc_install [--flags]`	Install HelixCode binaries via `install_helix_path.sh`
`hc_boot_service <name>`	Boot a service via the Containers submodule compose
`hc_boot_coder`	Boot the HelixLLM coder on `:18434` (with health wait)
`hc_stop_service <name>`	Stop a service
`hc_status`	Print health status of all 4 HelixCode services
`hc_verify_binaries`	Verify all 6 binaries are on PATH
`hc_health [host] [port] [path]`	Health check (from `helix_code_home.sh`)

Service Ports

Service	Port	Health Endpoint
HelixCode server	`:8080`	`/health`
HelixLLM coder	`:18434`	`/health`
HelixLLM gateway	`:8443`	`/internal/health`
HelixAgent	`:8100`	`/health`

Safety

- §11.4.161: uses rootless podman via the Containers submodule
- §11.4.119: single-owner GPU — only one track boots the coder
- §12.6: 60% memory ceiling applies to service boot

Cross-references

- `docs/helix_code/INTEGRATION_PLAN.md` §3 Tasks 1.2-4
- `docs/helix_code/CLAUDE_TOOLKIT_EXTENSION.md` §1
- `docs/helix_code/RISK_ANALYSIS.md` — port collisions, GPU contention