

fx_section_AIAK

AI/AK. Phase 39.AW (2026-05-14) — D3 wired touch panel + UI scaling closure cycle

AI. D3 wired touch panel non-functional — Phase 39.AW + 39.AY closure, 2026-05-14

Status: Fixed (→ Fixed.md) **Type:** Bug

- **Closure cycle:** Phase 39.AW source-side + Phase 39.AY captured-evidence verification (1.1.5-dev, between 0.0.11 and pre-Sonos tag).
- **Closure commits:** source 011fcd5b15b (Phase 39.AW source-side fix); Phase 4 verification qa-results/d3_phase4_postflash_20260514_1649/PHASE_4_VERDICT.md.
- **Discovery:** D3's primary touch panel was reconnected via wired-direct HDMI + 2 USB ports (operator hardware change). Touch input did NOT work despite the panel being functional via the previous wireless connection. Phase 1 captured-evidence (qa-results/d3_phase1_forensics_20260514_1453/d3_touch_forensics_*) via live ADB revealed the panel is wch.cn USB2IIC_CTP_CONTROL (USB VID 32d7 PID 0001) — a THIRD vendor not in atmosphere-touch-config.sh's hardcoded list of Nuvoton V5000 (222a:0002) and QDtech MPI7009 (0712:0009). The bridge presents 3 USB-HID interfaces (event8 mouse, event7 keyboard, event6 touch); without an IDC file at /vendor/usr/idc/Vendor_32d7_Product_0001.idc, Android InputManager could not reliably classify event6 as a touchscreen.
- **Source-side fix:** new device/rockchip/rk3588/idc/Vendor_32d7_Product_0001.idc declaring touch.deviceType=touchScreen + touch.orientationAware=1 + device.internal=1 + cursor.mode=navigation. device/rockchip/rk3588/device.mk PRODUCT_COPY_FILES entry deploys to /vendor/usr/idc/. device/rockchip/rk3588/bin/atmosphere-touch-config.sh extended with the new VID:PID dispatch to HDMI1/HDMI2 displays.
- **Phase 4 captured-evidence (post-flash, firmware UTC 1778 764554):** getevent -lp on event6 now reports input props: INPUT_PROP_DIRECT ← Android NOW classifies as direct-touch

(touchscreen). Full multitouch protocol exposed: ABS_MT_SLOT (max 9 = 10-finger MT), ABS_MT_POSITION_X, ABS_MT_POSITION_Y, ABS_MT_TRACKING_ID, MSC_TIMESTAMP. Pre-fix baseline had input props: <none> and only ABS_X/Y non-MT.

- **Regression-protection:** CM-AI-WIRED-TOUCH-FORENSICS pre-build gate (Phase 39.AP, 8 invariants) + paired mutation in meta_test_false_positive_proof.sh strips systematic-debugging Phase 1 citation literal → gate FAILs. On-device test_d3_wired_touch_forensics.sh runs per topology dispatch via test_all_fixes.sh.
- **Why this matters:** Without this fix, a fleet-wide hardware variation (different OEM touch panel) silently broke touch input — the failure mode the §11.4 covenant exists to catch. Phase 1 captured-evidence ADB probe (§11.4.21 path #1) re-wrote my original hypothesis triplet (a/b/c) to reveal an unanticipated (b) variant: a third vendor that the existing config infrastructure never knew about.
- **Cross-references:** Builds on the existing IDC infrastructure pattern + Fix #43 / #47 (input device classification policy). Uses §11.4.21 self-resolution exhaustion mandate (path #1 ADB) for the entire 4-phase cycle.

AK. D3 touch display UI rendered too large (per-display density fix) — Phase 39.AW + 39.AY closure, 2026-05-14

Status: Fixed (→ Fixed.md) **Type:** Bug

- **Closure cycle:** Phase 39.AW + 39.AY (1.1.5-dev, between 0.0.11 and pre-Sonos tag).
- **Closure commits:** source 011fcd5b15b; Phase 4 verification qa-results/d3_phase4_postflash_20260514_1649/PHASE_4_VERDICT.md.
- **Discovery:** Operator reported "icons, everything, the whole UI is too big" on D3's wired touch display. Phase 1 captured-evidence (d3_ui_scaling_forensics_*) revealed the panel reports DRM modes 2560x1440 / 1920x1200 / 1920x1080 (NOT MPI7009's 1024x600 — a DIFFERENT higher-resolution panel) and was rendering at xxhdpi bucket (ro.sf.lcd_density=320). UI assets designed for a smaller HDPI screen were rendering oversized on this physically-modest higher-resolution panel.
- **Source-side fix:** device/rockchip/common/display_settings.xml ADDED forcedDensity="213" (tvdpi bucket) to the local:0 block only. local:1 (TV pass-through) and local:2 (4K monitor) UN-CHANGED at forcedDensity="320" — non-regression mandate satisfied per User-explicit instruction: *"Not a single other display configuration and resolution can be affected, only this particular touch display when connected!"*.
- **Phase 4 captured-evidence (post-flash):** wm density -d 0 reports Physical density: 320 / Override density: 213 (was 320 with NO override pre-fix). wm density -d 2 still reports Physical

density: 213 / Override density: 320 (TV pass-through UNCHANGED). Display 1 unaffected. Non-regression PASS.

- **Regression-protection:** CM-AK-UI-SCALING-FORENSICS pre-build gate (Phase 39.AS, 8 invariants — wm-density-per-display + DRM-EDID-probe + runtime-display-settings-probe + non-regression-baseline + screencap-evidence + decision-guide-section).
- **Why this matters:** Per-display density override is the rare case where a config-level fix produces user-visible quality-of-life improvement without any source-code change. The captured-evidence cycle proved the change is precisely scoped — display 0 affected, others UNCHANGED, as the user mandated.
- **Cross-references:** Builds on Fix #80 (HDMI dual-display detection). Uses §11.4.5 captured-evidence per-display probe pattern.

AQ. test_all_fixes.sh orchestrator — ANDROID_SERIAL inheritance gap caused 107 SKIPS in Phase 2 — Phase 39.BQ closure, 2026-05-16

Status: Completed (→ Fixed.md) **Type:** Task

- **Closure cycle:** Phase 39.BQ (User mandate 2026-05-15, §11.4.1 script-bug).
- **Discovery:** Phase 39.BM test_all_fixes.sh cycle on D3 reported Phase 2 (After Reboot) summary: Suites run: 114 / Suites passed: 6 / Suites failed: 2 / Suites skipped: 107. All 107 SKIPS traced to sub-test scripts hard-failing on missing ANDROID_SERIAL env var.
- **Root cause (captured-evidence from orchestrator + sub-test source audit 2026-05-16):** 22 sub-test scripts (test_streaming_kinopoisk.sh, test_streaming_rutube.sh, test_streaming_ivi.sh, test_streaming_smarttube.sh, test_streaming_stress_visual.sh, test_visual_coverage_all_apps.sh, test_launcher_titles.sh, test_audio_coverage_all_outputs.sh, test_audio_stress_capture.sh, test_netflix_tv_ui_visual.sh, test_orientation_d9_steady_state.sh, test_lampa_qa.sh, test_video_routing_bug21_mirror_surface.sh, et al for Bug #22 / #23) read ANDROID_SERIAL from their host env. The orchestrator's run_device_test helper invoked them via adb shell sh test.sh — but adb shell does NOT propagate host env vars to the device shell. The on-device sh invocation had no ANDROID_SERIAL → hard-fail SKIP at each sub-test's top guard.
- **Source-side fix:** device/rockchip/rk3588/tests/test_all_fixes.sh:346 adds run_host_test() helper that uses host bash (not adb shell sh) with ANDROID_SERIAL propagated. Five mis-dispatched invocations (Bug #13 / #21 / #22 / #23 / D9 orientation) migrated from run_device_test to run_host_test.

- **Captured-evidence (Phase 39.BP cycle after fix):** Phase 2 PASS rate jumped from 5% → 75% — direct §11.4.5 captured-evidence proof the dispatch table fix lifted real PASSes that had been masked behind ANDROID_SERIAL-related SKIPS.
- **Regression-protection:** CM-ANDROID-SERIAL-PROPAGATION planned (gate asserts the run_host_test helper exists in test_all_fixes.sh AND ≥ 5 sub-tests are invoked via it). Currently deferred — the dispatch is a test-orchestrator script rather than a shipping artifact, so a paired-mutation gate would only assert the orchestrator's structure (still valuable per §11.4.1 — to land in next cycle).
- **Why this matters:** This is the exact §11.4 failure mode the covenant exists to catch — 107 sub-tests SKIPPed is invisible "all green" reporting when the underlying tests never ran. Skipped-count is mechanically distinguishable from PASS-count per §11.4.1, but the fix unmaskes the actual PASS/FAIL signal on a major fraction of the suite.
- **Cross-references:** Companion to §AP (host adb-server resilience — Phase 39.BT). Same root-class as §AT (test-side stale assertions). Both demonstrate the §11.4.1 "FAIL-bluffs equally forbidden" principle: a SKIP-bluff (script-bug masking real signal) and a FAIL-bluff (stale assertion against removed control) are equally damaging — both must be fixed at the test layer, not patched in call sites.

AW. D9 orientation watchdog losing race — Phase 39.BV closure, end-to-end validated on D4 Phase 39.CJ, 2026-05-16

Status: Fixed (→ Fixed.md) **Type:** Bug

- **Closure cycle:** Phase 39.BV source-side fix + Phase 39.CJ D4 end-to-end captured-evidence (User mandate 2026-05-15 Pavel #4 forensic anchor).
- **Discovery:** Phase 39.BP D3 cycle 30/30 readings = 1 despite watchdog running at 1Hz polling — deterministic race-loss against synchronous framework writers.
- **Root cause (CONFIRMED via subagent agentId a8d-d6a0ac86c82908):**
 DeviceStateRotationLockSettingController.readPersistedSetting()
 at frameworks/base/packages/SystemUI/.../
 DeviceStateRotationLockSettingController.java:141-166 →
 mRotationPolicyWrapper.setRotationLock() →
 WindowManagerService.thawRotation() →
 DisplayRotation.setUserRotation() (writes ACCELEROMETER_ROTATION=1) on every DeviceState change. D9's dual-display topology triggers DeviceState changes far more frequently than D1/D2. Polling at 1Hz cannot win this race.
- **Source-side fix (Phase 39.BV Option B):** Created device/rockchip/atmosphere/presenter/Presenter/src/main/java/com/atmosphere/presenter/RotationLockObserver.kt (~190 lines) —

Kotlin ContentObserver on

Settings.System.ACCELEROMETER_ROTATION URI; reacts within ~50ms of any write; preserves Phase 39.BG §AN Layer 3 Netflix bypass via ROTATION_OWNER_PACKAGES set; uses ActivityManager.getRunningAppProcesses() for foreground detection (no shell exec). Wired into PresenterService.kt onCreate + onDestroy. atmosphere-orientation-watchdog.sh INTERVAL_SEC reduced from 1 to 60 — now serves as a safety-net heartbeat in case Presenter is killed.

- **Pre-build gates:** CM-AW-ROTATION-OBSERVER-PRESENT (8 invariants: ContentObserver registration, ACCELEROMETER_ROTATION URI literal, TARGET_VALUE=0, Netflix bypass preserved, Phase 39.BV citation, PresenterService onCreate start, PresenterService onDestroy stop, watchdog cadence ≥ 30 s) + CM-D9-WATCHDOG-FAST-INTERVAL amended to accept observer-primary topology (legacy INTERVAL_SEC=1 OR observer-primary INTERVAL_SEC ≥ 30).
- **Paired mutation:** strips registerContentObserver(URI → gate FAILs with content-observer-not-registered.
- **Phase 39.CJ D4 captured-evidence 2026-05-16T19:32Z (build v2 MD5 519e32e8465b28c02845c1b3eae31094):** test injected foreign write settings put system accelerometer_rotation 1, read back at 300ms / 600ms / 900ms intervals — **ALL THREE READS returned 0**. RotationLock-Observer caught the write and reverted within the first 300ms read window. Pre-fix shell watchdog at 1000ms polling could not have caught this in 300ms — direct empirical proof the observer is the primary correction surface as designed.
- **Why this matters:** D9 dual-display rotation glitches were end-user-visible (Pavel #4 user-mandate forensic anchor). The polling-only approach was a §11.4.7 demotion-evidence violation — claiming "INTERVAL_SEC=1 closes the <5s aggressor race window" without acknowledging the underlying race is event-driven and polling has a fundamental floor. Event-driven ContentObserver is the architecturally-correct surface per AOSP 15 frameworks/base/core/java/android/database/ContentObserver.java documentation.
- **Cross-references:** Fix #65 always-portrait mandate (the original specification that the watchdog enforces), Phase 39.BG §AN Layer 3 Netflix bypass (preserved in the observer), §11.4.7 demotion-evidence rule (the rule the original watchdog-only approach silently violated).

**AX. tap-undim AccessibilityService not observing
TYPE_TOUCH_INTERACTION_START — Phase 39.BW
closure, end-to-end validated on D4 Phase 39.CJ,
2026-05-16**

Status: Fixed (→ Fixed.md) **Type:** Bug

- **Closure cycle:** Phase 39.BW source-side fix + Phase 39.CJ D4 end-to-end captured-evidence (User mandate 2026-05-15 Phase 39.AZ regression).
- **Discovery:** Phase 39.BP D3 cycle: brightness dimmed correctly (102→10 in 6s), but input tap 200 400 followed by 1.2s wait did NOT restore brightness — tap-undim broken.
- **Root cause (CONFIRMED via subagent agentId a0c94d28bafb49485):** architectural decoupling between TWO parallel dimming paths — (1) PrimaryDisplayDimController.kt (Kotlin, in-Presenter) has working tap-undim via PresenterAccessibilityService TYPE_TOUCH_INTERACTION_START forwarding, (2) atmosphere-idle-dim-daemon.sh (Fix #132 shell daemon) was 100% polling-based at **5000ms** default with NO touch hook at all. The \$AX test exercises path #2; a 1.2s test window cannot observe a state transition that requires 5s polling — design contradiction.
- **Source-side fix (Phase 39.BW Option A):** dropped IDLE_DIM_POLL_MS default 5000 → 1000 at device/rockchip/rk3588/bin/atmosphere-idle-dim-daemon.sh:127. Source inline citation: Phase 39.BW \$AX captured-evidence + 1.2s test-window justification.
- **Pre-build gate:** CM-AX-IDLE-DIM-POLL-1S (4 invariants — default==1000 literal, no legacy 5000, Phase 39.BW citation, \$AX rationale literal).
- **Paired mutation:** flip IDLE_DIM_POLL_MS: -1000 → IDLE_DIM_POLL_MS: -5000 → gate FAILs with default-not-1000ms + legacy-5000-default-still-present.
- **Phase 39.CJ D4 captured-evidence 2026-05-16T19:34Z (build v2 MD5 519e32e8465b28c02845c1b3eae31094):** D4 brightness baseline = 10 (idle-dim state observed); input tap 200 400 injected; sleep 2; brightness re-read = **102 (RE-STORED)**. Daemon
persist.atmosphere.idle_dim.last_action=restore + last_action_epoch_ms=959310. Phase 39.BW
IDLE_DIM_POLL_MS=1000 default + idle-dim daemon properly detected tap-induced mLastUserActivityTime update and restored brightness to operator's preferred value within 2 seconds. Pre-fix this would have stayed at 10 for up to 5s.
- **Why this matters:** Pre-fix, end-users saw a "dead screen" for up to 5s after touching it from idle. Subjectively this looks like the device is broken — exactly the kind of user-visible defect the §11.4 covenant exists to prevent. Option C (extend PresenterAccessibilityService to forward

TYPE_TOUCH_INTERACTION_START to the shell daemon via setprop atmosphere.idle_dim.touch_epoch_ms) remains queued as Phase 39.BW.2 for sub-50ms reaction — Option A alone closes the user-visible defect.

- **Cross-references:** Phase 39.AZ idle-dim daemon (Fix #132) — the original implementation that §AX patched. §AJ idle-dim mandate (User mandate 2026-05-14). Phase 39.U-α screen_off_timeout=60000 design.