

FFI surface (Dart $\rightleftharpoons$ Rust)

FFI surface (Dart $\rightleftharpoons$ Rust)

Revision: 1 Last modified: 2026-06-25T00:00:00Z

Master technical specification — Volume 4 (Clients), nano-detail deep-dive. This document **deepens** the *FFI surface — Dart $\rightleftharpoons$ helix-core* section of the pass-1 client overview [04_CLIENT §3] into an implementation-ready specification of the **helix-ffi exported surface**: the two binding generators (flutter_rust_bridge v2 primary, UniFFI native-shim fallback), the exact Rust/Dart/Swift/Kotlin/C signatures of start/stop/status_stream/exits/ set_exit/ set_shields/advertise/attach_tun, the mirrored TunnelStatus enum and its projection from the orchestrator's canonical enum, StreamSink event delivery, the tokio threading model, error propagation, the codegen + drift-gate pipeline, memory budgets, edge cases, and test points tied to the §11.4.169 closed test-type vocabulary.

SPEC-ONLY. It describes *what to build* — signatures, state machines, memory ceilings, error taxonomy, edge cases, test points — not the shipping product.

Boundary with sibling docs. This document **owns** only the *exported* FFI surface of helix-core. It **consumes**: the orchestrator's canonical TunnelStatus broadcast enum and Orchestrator:: {start, stop, subscribe, apply_map, set_pin} API [02_ORCH §2.1, §4.1]; the Transport/TransportKind labels [02_TRANS §2, §3.3]; the TunnelPlatform MethodChannel/EventChannel shim contract [04_CLIENT §4]; the per-platform tunnel mechanisms (NEPacketTunnelProvider, VpnService) [04_CLIENT §5, research-ios_android]. The orchestrator *internals* (three loops, kill-switch coupling, reconciler) are doc 02's; this doc owns only how that core is *exposed across the language boundary*.

Evidence base. Citations inline by id: [04_CLIENT §N] = final/03-client-core-and-ui.md; [04_ARCH §5] = 04_VPN_CLD/HelixVPN-Architecture-Refined.md §5; [04_UI] = 04_VPN_CLD/HelixVPN-

helix-ui-Flutter.md; [02_ORCH §N] = final/v02-data-plane/orchestrator-and-state.md; [02_TRANS §N] = final/v02-data-plane/transport-trait.md; [research-flutter_ffi] / [research-ios_android] = the cited research digests; [10_QA §N] = final/10-testing-acceptance-and-qa.md (§11.4.169 taxonomy). Any claim not grounded in the evidence base is tagged UNVERIFIED per constitution §11.4.6 — never fabricated.

Table of contents

- 0. Position, ownership, and the load-bearing seam
 - 1. Two generators, two consumption modes
 - 2. The Rust source of truth (helix-ffi/src/api.rs)
 - 3. The TunnelStatus enum — mirror + projection
 - 4. StreamSink event delivery & the threading model
 - 5. The Dart-facing surface (helix_core.dart)
 - 6. UniFFI native-shim surface (Swift / Kotlin / C)
 - 7. The TunnelPlatform $\rightleftharpoons$ FFI division of labor
 - 8. Error propagation across the boundary
 - 9. Lifecycle, idempotence, and attach_tun fd ownership
 - 10. Codegen + drift-gate pipeline
 - 11. Memory & performance budgets
 - 12. Edge cases & failure modes
 - 13. Test points — §11.4.169 closed vocabulary
 - 14. Surfaced decisions & cross-doc contracts
 - Sources verified
-

0. Position, ownership, and the load-bearing seam

helix-ffi is the **single hand-authored Rust crate** that both binding generators read; it is the only place the core's surface crosses a language boundary [04_CLIENT §3.1]. It is decoupled and project-agnostic (vasic-digital/helix_core workspace, snake_case flat submodule per §11.4.28/.29/.74): it depends *up* on helix-core (orchestrator, status enum) and exposes *down* a stable Dart/Swift/ Kotlin/C surface, but contains no project-specific UI glue.

0.1 What this document owns

#	Owned artifact	Where
F1	The exact Rust API of <code>helix-ffi</code> (<code>start/stop/status_stream/exits/set_exit/set_shields/advertise/apply_map/attach_tun/detach_tun</code>) + the mirrored DTO types (<code>ClientConfig</code> , <code>CoreMode</code> , <code>Shields</code> , <code>ExitOption</code> , <code>AdvertiseResult</code> , <code>MapApplied</code> , <code>CoreError</code>)	§2
F2	The Dart-facing <code>TunnelStatus</code> (7-variant) and its deterministic projection from the orchestrator's canonical 5-variant <code>core::TunnelStatus</code>	§3
F3	The <code>StreamSink<TunnelStatus></code> delivery mechanism + the tokio runtime / forwarding-task threading model + the pause/resume re-emit rule	§4
F4	The idiomatic Dart wrapper (<code>helix_core.dart</code>) and the UniFFI Swift/Kotlin/C surface	§5, §6
F5	Error propagation (<code>frb exception</code> $\Leftrightarrow$ UniFFI typed error $\Leftrightarrow$ C error code)	§8
F6	The codegen + drift-gate (a generated-Dart/Rust mismatch is a build-blocking finding)	§10

0.2 What this document does NOT own

- The orchestrator loops / kill-switch / DNS / reconciler — doc 02 [02_ORCH §3–§9]; this doc consumes `Orchestrator::subscribe()` and the broadcast enum.
- The Transport trait and its impls — doc 02 [02_TRANS]; this doc surfaces only the `kind()` label string inside `Connected.transport`.
- The OS tunnel lifecycle (TUN creation, permission, packet pump) — the `TunnelPlatform` shim [04_CLIENT §4–§5]; this doc owns only the `attach_tun/detach_tun` handoff and the in-process-vs-native-shim consumption split (§7).
- The Riverpod data layer / widgets — [04_CLIENT §7–§8]; this doc stops at the `Stream<TunnelStatus>` the providers watch.

0.3 The load-bearing invariant (CI1 + CI2, restated at the FFI layer)

`helix-ffi` owns *logic and status*; it does NOT own the OS tunnel lifecycle. Lifecycle commands flow **UI** $\rightarrow$ **shim** $\rightarrow$ **core** (the OS owns the tunnel process); status events flow **core** $\rightarrow$ **FFI** $\rightarrow$ **UI** (the core owns truth about protection state). `set_shields/set_exit/exits` are

pure logic and go straight UI → FFI without touching the OS tunnel.
The UI *only* ever believes the core's status stream, never its own
intent. [04_CLIENT §0.1 CI1/CI2, §3.3]

This is the seam that mechanically prevents the classic "UI says connected while the OS tunnel is actually down" bug — the FFI never *reports* a state the orchestrator did not *emit* (§3, §4.5).

1. Two generators, two consumption modes


Two binding generators read **one** Rust surface — the canonical Mullvad/WARP pattern [04_CLIENT §3, 04_ARCH §5.1, research-flutter_ffi §7]:

- **flutter_rust_bridge (frb) v2 — 2.12.0** (Flutter Favorite; StreamSink support; arbitrary/async Rust types; new SSE codec) [research-flutter_ffi §1]. The **primary** generator: emits the Dart⇌Rust glue (frb_generated.dart + a Rust wrapper) for the UI process.
- **UniFFI (Mozilla)** — first-party **Kotlin / Swift** output [research-flutter_ffi §2]. The **native-shim fallback**: emits the typed Swift/Kotlin bindings a platform tunnel *extension* (NEPacketTunnelProvider, VpnService, HarmonyOS ArkTS→NAPI) uses when it links the core **directly** rather than through Dart. uniffi-dart is NOT production-ready and is NOT used for the Dart surface (frb owns Dart) [research-flutter_ffi §2].
- **cbindgen C header** — the **raw-C fallback** where UniFFI's language support is thin (HarmonyOS NAPI shim, Aurora Qt/C++ backend) [04_CLIENT §5.5/§5.6, D-CLIENT-3].

These map onto **two distinct consumption modes**, and *which mode a platform uses decides where each TunnelStatus originates*:

Mode	Where the core runs	Generator	Status path	Platforms
(A) In-process frb	the Dart/UI process (same process as Flutter)	frb v2	core → StreamSink → frb port → Dart isolate	Linux desktop (core in-process); Windows app side talks to the privileged service over a pipe but the Dart-facing surface is still frb

Mode	Where the core runs	Generator	Status path	Platforms
(B) Native-shim UniFFI/ C	a separate OS tunnel extension process	UniFFI (Swift/Kotlin) / cbindgen (C)	core → shim → EventChannel → Dart (the TunnelPlatform event stream, §7)	iOS/macOS NE, Android VpnService, HarmonyOS, Aurora



Honest boundary (§11.4.6). In Mode B the **core never runs in the Dart isolate** — it runs inside the OS extension process (the memory-constrained one, §11). The frb runtime + tokio threads of Mode A are therefore **NOT** part of the iOS NE footprint; the NE links the UniFFI/cbindgen staticlib only [research-ios_android §1 "applies to the process as a whole"]. This is why the iOS memory ceiling (§11) is a *native-shim* constraint, not an frb constraint.

2. The Rust source of truth (helix-ffi/src/api.rs)

This is the **only** hand-authored FFI source; both generators read it. It promotes the pass-1 sketch [04_CLIENT §3.1] to the production surface; the lean Phase-0 subset (start/stop/status_stream) is the G5 gate [04_CLIENT §13 T0.1].

```
// helix-ffi/src/api.rs
// frb + UniFFI generate Dart / Swift / Kotlin / C bindings from
//   THIS file.
// The transport/WG/orchestrator internals are doc 02's; this is
//   purely the EXPORTED surface.
use flutter_rust_bridge::frb;
use flutter_rust_bridge::StreamSink;

// ----- construction inputs
pub struct ClientConfig {
    /// Phase 0: filesystem path to a static map.json. Phase 1+:
    ///   an opaque control-plane
    /// session token (handed straight to the orchestrator; the
    ///   FFI never parses it).
    pub map_path_or_session: String,
    /// Ladder seed: "auto" | "plain" | "masque" | "shadowsocks" |
    ///   "uot" | "lwo".
    /// "auto" => the coordinator-pushed TransportPolicy.order
    ///   decides [02_TRANS §6.2].
    pub transport: String,
    pub mode: CoreMode,
}

#[frb(mirror(CoreMode))] // re-export helix_core::CoreMode's
//   Dart mirror
pub enum CoreMode { Client, Connector }

// ----- lifecycle (LOGIC only – NOT the OS
//   tunnel, CI1) -----
/// Construct + start the orchestrator (doc 02
///   Orchestrator::start). Idempotent guard:
/// a second start while already running returns
///   Err(CoreError::AlreadyStarted) (§9.2).
pub async fn start(cfg: ClientConfig) -> Result<(), CoreError>;

/// Graceful stop (doc 02 Orchestrator::stop). Idempotent: stop-
///   when-stopped => Ok(()).
pub async fn stop() -> Result<(), CoreError>;

// ----- the live status stream (§3, §4)
/// Register a sink; the FFI forwarding task projects
///   core::TunnelStatus -> ffi::TunnelStatus
```

```

/// (§3.3) and pushes each onto `sink`. Returns once the sink is
    registered; events arrive
/// asynchronously. The CURRENT status is re-emitted immediately
    on (re)registration (§4.5).
pub fn status_stream(sink: StreamSink<TunnelStatus>) ->
    Result<(), CoreError>;

// ----- exits / routing (Phase 1+)


---


pub async fn exits() -> Result<Vec<ExitOption>, CoreError>;
pub async fn set_exit(id: String, multi_hop_chain:
    Option<Vec<String>>) -> Result<(), CoreError>;

// ----- privacy shields -----
pub async fn set_shields(s: Shields) -> Result<(), CoreError>;

// ----- connector mode only -----


---


pub async fn advertise(cidrs: Vec<String>) ->
    Result<AdvertiseResult, CoreError>;

// ----- desired-state push (Phase 1 bridges WatchNetworkMap;
    Phase 0 file-watch) -----
/// Push a fresh RouteMap into the running orchestrator (doc 02
    Orchestrator::apply_map).
/// Malformed JSON => Err(CoreError::Config); the last-applied map
    stays live (fail-static).
/// `MapApplied` reports the diff (peers added/removed/changed)
    for the Connector/Console UI.
pub async fn apply_map(map_json: String) -> Result<MapApplied,
    CoreError>;

// ----- shim handoff (called by the platform
    shim, NOT the UI) -----
/// The core never opens the TUN; the shim hands it a packet fd.
    Ownership of `fd` transfers
/// to the core on Ok (the core close()s it on detach/stop) -
    §9.3. Synchronous (no await):
/// it only stores the fd + wakes loop A/B.
pub fn attach_tun(fd: i32) -> Result<(), CoreError>;
pub fn detach_tun() -> Result<(), CoreError>;

// ----- DTOs (mirrored byte-for-byte into Dart/
    Swift/Kotlin) -----


---


pub struct Shields {
    pub kill_switch: bool,
    pub dns_protection: bool,
    pub daita: bool,
    pub post_quantum: bool,
    pub split_tunnel: Vec<String>, // per-route bypass CIDRs; per-
    APP split is shim-layer
}

pub struct ExitOption {
    pub id: String,
    pub kind: String, // "privacy_exit" | "network"

```

```

pub label: String,
pub country: Option<String>,
pub rtt_ms: Option<u32>,
pub jurisdiction: Option<String>, // multi-hop labels
}

pub struct AdvertiseResult {
pub accepted: Vec<String>,
pub conflicts: Vec<String>, // overlapping-CIDR conflicts
                             surfaced to the Connector UI
}

```

#[frb(mirror(T))] **semantics.** CoreMode/TunnelStatus are defined in helix-core (so the orchestrator and the FFI share one definition — no parallel hand-written enum). **#[frb(mirror(T))]** tells frb to generate the Dart mirror for a type owned by another crate [research-flutter_ffi §1, frb V2 "mirror" facility]. DTOs defined *in* helix-ffi (ClientConfig, Shields, ExitOption, AdvertiseResult, CoreError) need no mirror — frb auto-mirrors them. This is the corrected, precise form of the [04_CLIENT §3.1] sketch (which annotated own types with bare **#[frb(mirror)]**).

Result<T, CoreError> vs anyhow::Result. The [04_CLIENT §3.1] sketch used `anyhow::Result<>`; the production surface uses a **typed CoreError enum** (§8) so UniFFI (which needs a concrete error type, not `anyhow::Error`) and frb both surface a *classified* failure to the UI — a typed error drives an honest, specific UI message instead of an opaque string (§11.4.6). *anyhow* may remain *internal* to the orchestrator; the FFI boundary converts to CoreError.

3. The TunnelStatus enum — mirror + projection

3.1 The canonical (core-owned) enum — consumed, not redefined

The orchestrator owns the **canonical 5-variant** enum and broadcasts it on a `tokio::sync::broadcast` channel [02_ORCH §4.1]:

```

// helix-core/src/status.rs (OWNED by doc 02 – this doc CONSUMES
                             it)
pub enum TunnelStatus {                                           //
    Connecting,
    Handshaking,
    Connected { transport: String, rtt_ms: u32 }, // transport
    = Transport::kind() [02_TRANS §3.3]

```



```

Reconnecting,
Down { reason: String }, // stable-
    prefix vocabulary [02_ORCH §4.4]
}

```

3.2 The Dart-facing (FFI-owned) enum — the 7-variant surface

The FFI exposes the **extended 7-variant** enum the UI's color/announce logic switches on [04_CLIENT §3.1, §7.1]. It is the Dart-facing canonical and is what the StreamSink carries:

```

// helix-ffi re-exports + extends – the Dart-facing surface
pub enum TunnelStatus { //
    ffi::TunnelStatus

    Disconnected, // clean
    idle – DISTINCT from Down
    Connecting,
    Handshaking,
    Connected { transport: String, path: String, rtt_ms:
        u32 }, // path = "direct" | "relay"
    Reconnecting,
    Down { reason:
        String }, // unexpected drop
        (reason & danger-class)
    Danger { kind: String }, // "leak" |
        "killswitch_tripped" – red palette
}

```

The three FFI extensions over the core enum [04_CLIENT §3.1 status-enum note]:

1. **Disconnected** — clean user-idle (never started / cleanly stopped), distinct from Down (an *unexpected* drop). Drives the neutral-grey stateDisconnected token [04_CLIENT §7.1].
2. **path** on Connected — "direct" (P2P/NAT-traversal) vs "relay" (DERP-style), surfaced by the StatusChip [04_CLIENT §7.2].
3. **Danger { kind }** — leak / kill-switch-tripped, drives the red stateDanger palette and **overrides any user intent** [04_CLIENT §8.4].

3.3 The projection — StatusProjector (the only place the extension happens)

The helix-ffi forwarding task (§4) runs a **pure deterministic projector** from core::TunnelStatus (+ two side snapshots the core exposes) to ffi::TunnelStatus. This is the single, testable seam where the extension is computed — never ad-hoc in the UI:


```

// helix-ffi/src/project.rs
pub struct ProjCtx {
    pub last_stop_was_user: bool, // distinguishes clean idle
                                  // from drop (from Orchestrator)
    pub active_path: Option<String>, // "direct"|"relay" from the
                                  // active route/transport (§14 C3)
    pub shields_tripped: Option<String>, // Some("leak")|
                                  // Some("killswitch_tripped") | None
}


pub fn project(s: &core::TunnelStatus, cx: &ProjCtx) ->
    ffi::TunnelStatus {
    use core::TunnelStatus as C;
    // Danger overrides everything (§8.4): a live leak / tripped
    // kill-switch always paints red.
    if let Some(kind) = &cx.shields_tripped { return
        ffi::TunnelStatus::Danger { kind: kind.clone() }; }
    match s {
        C::Connecting => ffi::TunnelStatus::Connecting,
        C::Handshaking => ffi::TunnelStatus::Handshaking,
        C::Connected { transport, rtt_ms } =>
            ffi::TunnelStatus::Connected {
                transport: transport.clone(),
                path: cx.active_path.clone().unwrap_or_else(||
                    "direct".into()), // §14 C3 default
                rtt_ms: *rtt_ms,
            },
        C::Reconnecting => ffi::TunnelStatus::Reconnecting,
        // The clean-idle vs drop split: orchestrator emits
        // Down{reason:"stopped"} on a USER
        // stop [02_ORCH §2.4 step 6] → Disconnected; every other
        // Down is an unexpected drop.
        C::Down { reason } => match classify(reason) {
            DownClass::UserStop =>
                ffi::TunnelStatus::Disconnected,
            DownClass::Danger(k) => ffi::TunnelStatus::Danger {
                kind: k },
            DownClass::Drop => ffi::TunnelStatus::Down {
                reason: reason.clone() },
        },
    }
}

/// Classify on the orchestrator's STABLE reason prefix [02_ORCH
/// §4.4] – no prose parsing (§11.4.6).
fn classify(reason: &str) -> DownClass {
    match reason {
        "stopped" =>
            DownClass::UserStop,
        "auth-failed" =>
            DownClass::Danger("killswitch_tripped".into()),
        _ /* ladder-exhausted | host-fatal | ... */ =>
            DownClass::Drop,
    }
}

```



3.4 The Dart-facing state diagram (what the UI switches on)



3.5 What the stream MUST NOT carry (I5 at the FFI layer)

The FFI re-emits exactly what the orchestrator broadcasts: ephemeral state, never durable per-connection records [02_ORCH §4.5].

`Connected.transport` is a *kind* label; path is "direct"|"relay"; `rtt_ms` is an aggregate EWMA. No SSID, no gateway IP, no per-packet data ever crosses the `StreamSink` (§11.4.10, [02_ORCH §4.5]). The projector is pure and holds no buffer beyond the single cached latest value (§4.5).

4. StreamSink event delivery & the threading model

4.1 Why StreamSink

`frb v2` **explicitly supports StreamSink**: a Rust fn takes a `StreamSink<T>` argument and Dart receives a `Stream<T>` it can `listen()` — the canonical way to push continuous events from a long-lived Rust task to Dart (`frb` issue #347, solved by `StreamSink`) [research-flutter_ffi §1]. This `Stream<TunnelStatus>` is exactly what the Riverpod `StreamProvider` watches [04_CLIENT §8.2, research-flutter_ffi §6].

4.2 The tokio runtime (Mode A, in-process)

`helix-ffi` owns **one** `tokio::runtime::Runtime`, created lazily on the first `start()` and reused for the process lifetime (re-created only if fully torn down):

```
// helix-ffi/src/runtime.rs
static RT: OnceCell<tokio::runtime::Runtime> = OnceCell::new();
static ORCH: tokio::sync::Mutex<Option<helix_core::Orchestrator>>
    = /* ... */;

fn rt() -> &'static tokio::runtime::Runtime {
    RT.get_or_init(|| tokio::runtime::Builder::new_multi_thread()
        .worker_threads(2) // small: the
        .orchestrator's loops are I/O-bound (§11)
        .thread_name("helix-core")
        .enable_all()
        .build()
        .expect("tokio runtime"))
}
```

- **frb already drives Rust on its own worker thread(s)** off the Dart isolate [research-flutter_ffi §1]; the FFI additionally owns a tokio runtime so the orchestrator's three async loops + reconciler + re-dial driver run on dedicated worker threads [02_ORCH §2.2]. async fn FFI calls (start/stop/exits/...) are `rt().spawn`-ed and their result awaited by frb, so the Dart await never blocks the UI isolate.
- **Bridge-version pinning (mandatory).** The `flutter_rust_bridge` crate version MUST equal the `flutter_rust_bridge` Dart-dep version, else the generated glue mismatches [research-flutter_ffi §1 caveat]. Enforced by the drift gate (§10).

4.3 The forwarding task


`status_stream(sink)` registers the sink with a long-lived forwarding task that drains the orchestrator broadcast receiver and pushes projected events:

```
pub fn status_stream(sink: StreamSink<TunnelStatus>) ->
    Result<(), CoreError> {
    let orch = ORCH.blocking_lock();
    let mut rx =
        orch.as_ref().ok_or(CoreError::NotStarted)?.subscribe(); //
        broadcast::Receiver
    let projector_ctx = ctx_handle(); // shared ProjCtx
        (updated by the orchestrator)
    sink.add(project(&last_status(),
        &projector_ctx.snapshot())).ok(); // §4.5 re-emit
        latest
    rt().spawn(async move {
        loop {
            match rx.recv().await {
                Ok(core_s) => { let _ = sink.add(project(&core_s,
                    &projector_ctx.snapshot())); }
                Err(broadcast::error::RecvError::Lagged(_)) =>
                    continue, // skip-to-latest (§4.6)
                Err(broadcast::error::RecvError::Closed) => {
                    sink.close_sink(); break; }
            }
        }
    })
}
```

```

    }
  });
  Ok(())
}

```



4.4 Emit discipline (coalesce, inherited from the orchestrator)

The orchestrator already coalesces: one emit per `OrchState` transition; `Connected` is re-emitted only when `rtt_ms` drifts $> rtt_emit_delta_ms$ (default 5 ms) [02_ORCH §4.3]. The FFI projector adds **one** extra coalescing rule: if `project()` yields a value *byte-identical* to the last forwarded `ffi::TunnelStatus`, the forward is suppressed (so a core-side re-emit that does not change the projected value — e.g. an rtt drift below the UI's threshold — does not wake the UI). A path change *does* re-emit `Connected` (the `StatusChip` updates).

4.5 Pause / resume + the "current truth" guarantee

Riverpod 3.0 **pauses** a `StreamProvider`'s subscription when no widget listens, and `StreamProvider.autoDispose` tears the underlying stream down when unwatched [research-flutter_ffi §6]. Two FFI obligations follow:

1. **The forwarding task NEVER stops on Dart pause.** It holds the broadcast receiver independent of Dart listen-state, because the *kill-switch / protection truth* must not be lost while the UI is backgrounded. A paused Dart subscription only stops *delivery* to the isolate; the orchestrator keeps running (Mode A) or the extension keeps running (Mode B).
2. **On (re)subscribe, the FFI re-emits the cached latest status immediately** (§4.3 first `sink.add`), so a resumed `StreamProvider` renders *current truth*, never a stale gap or an empty `AsyncLoading` that misrepresents protection state (§11.4.6, [04_CLIENT §8.4]). `helix-ffi`

keeps exactly **one** cached `ffi::TunnelStatus` (the last forwarded value) — not a history (I5, §3.5).

Recommendation (D-FFI-1, §14). Use `@riverpod / StreamProvider.autoDispose` for the tunnel-status provider so a paused subscription is cheap, BUT rely on the §4.5(2) re-emit for correctness on resume — do NOT make the kill-switch UI depend on a non-`autoDispose` "always alive" provider, which "is almost never destroyed" [research-flutter_ffi §6].

4.6 Lagged is NOT an error

`tokio::broadcast` is a bounded ring (cap 64) [02_ORCH §4.2]: a slow receiver that falls behind gets `RecvError::Lagged(n)` and is fast-forwarded. For a *status* stream the receiver only ever needs the **latest** state, so the forwarding task treats `Lagged` as "continue → next `recv()` yields the newest" and never surfaces it to Dart as an error (§4.3). This mirrors the orchestrator's documented receiver contract [02_ORCH §4.6].

5. The Dart-facing surface (`helix_core.dart`)

`frb` mirrors every type, so the Dart `TunnelStatus` is the **generated** mirror of `ffi::TunnelStatus` (never a hand-written parallel). The thin wrapper adds ergonomics only [04_CLIENT §3.2]:

```
// helix_core_ffi/lib/helix_core.dart – idiomatic wrapper over
// frb_generated.dart
abstract class HelixCore {
  Future<void> start({required String transport, String?
    mapPathOrSession,
    CoreMode mode = CoreMode.client});
  Future<void> stop();

  /// frb StreamSink → Dart broadcast Stream. NO polling (CI2).
  /// The first event is the
  /// current status (§4.5); subsequent events are coalesced state
  /// changes (§4.4).
  Stream<TunnelStatus> statusStream();

  Future<List<ExitOption>> exits();
  Future<void> setExit(String id, {List<String>? multiHopChain});
  Future<void> setShields(Shields s);

  // connector mode:
  Future<AdvertiseResult> advertise(List<String> cidrs);

  // shim handoff (called by the platform shim, NOT the UI):
  Future<void> attachTun(int fd);
```

```

    Future<void> detachTun();
}

/// Console (no Capability.tunnel) gets this null impl – never
    links the Rust staticlib (CI3).
class NoCore implements HelixCore {
    @override Stream<TunnelStatus> statusStream() => const
        Stream.empty();
    // every method throws StateError('Console has no tunnel core')
        – compile-gated out anyway.
    // ...
}

// the entire happy path a client app drives (the Phase-0 G5 demo,
    [04_CLIENT §13 T0.1]):
await core.start(transport: 'auto', mapPathOrSession:
    session.token);
core.statusStream().listen((s) => /* Riverpod fold →
        ConnectButton, [04_CLIENT §8] */);
// ...later:
await core.stop();

```

5.1 Dart-side error surface

Every Future-returning method may throw a CoreException (the Dart mirror of CoreError, §8). The wrapper does NOT swallow it — the controller surfaces it as an honest UI message (§8.3). statusStream() never throws on Lagged (§4.6); it closes only when the core is torn down (RecvError::Closed).

6. UniFFI native-shim surface (Swift / Kotlin / C)

In Mode B the core runs inside the OS tunnel extension; UniFFI generates the typed binding the extension calls. The **same api.rs** produces it; the surface is the same verbs, named in each language's idiom. The status flows out via the platform EventChannel (§7), not via frb.

6.1 Swift (iOS / macOS NEPacketTunnelProvider)

```

// generated by UniFFI from helix-ffi (HelixCore.swift) – used
    inside the NE extension
import HelixCore

final class PacketTunnelProvider: NEPacketTunnelProvider {
    override func startTunnel(options: [String:NSObject]?,
                               completionHandler: @escaping (Error?)
-> Void) {

```



```

let cfg = decodeTunnelConfig(options) //
    overlay IP, routes, DNS, session
let settings = makeNetworkSettings(cfg) //
    NEPacketTunnelNetworkSettings
setTunnelNetworkSettings(settings) { [weak self] err in
    guard err == nil, let self else { return
        completionHandler(err) }
    do {
        try helixCoreStart(cfg: ClientConfig(mapPathOrSession:
            cfg.sessionToken,
            transport: "auto",
            mode: .client)) // typed throw
        let fd =
            self.packetFlowFd() // the NE
            packet fd (Mode B handoff)
        try helixAttachTun(fd: fd) //
            §9.3 ownership transfer
        self.relayStatus() //
            subscribe → EventChannel (§7)
        completionHandler(nil)
    } catch let e as CoreError {
        completionHandler(coreErrorToNSError(e)) // §8.2
    } catch { completionHandler(error) }
}
}
}
override func stopTunnel(with r: NEProviderStopReason,
    completionHandler: @escaping () → Void) {
    try? helixDetachTun(); try? helixCoreStop();
    completionHandler() // 04 quiescent
}
}

```

helixCoreStart/helixAttachTun/helixCoreStop are UniFFI-generated Swift throwing functions; CoreError is a UniFFI error enum (§8.2). The Swift side reads/writes the packet fd handed to the core (Layer-3 IP packets) [research-ios_android §1, §3].

6.2 Kotlin (Android VpnService + JNI)

```

// generated by UniFFI from helix-ffi (HelixCore.kt) – used inside
// the foreground VpnService
class HelixVpnService : VpnService() {
    override fun onStartCommand(intent: Intent?, flags: Int,
        startId: Int): Int {
        val cfg = TunnelConfig.from(intent)
        val builder = Builder().addAddress(cfg.overlayIp,
            32).setMtu(cfg.mtu)
        cfg.routes.forEach { builder.addRoute(it.addr,
            it.prefix) } // AllowedIPs
        cfg.dnsServers.forEach {
            builder.addDnsServer(it) } // tunnel DNS
        cfg.splitExcludeApps.forEach {
            builder.addDisallowedApplication(it) }
    }
}

```

```

    val pfd: ParcelFileDescriptor =
        builder.establish()!! // OS creates TUN
    startForeground(NOTIF_ID,
        persistentNotification()) // required for
        bg tunnel
    HelixCore.start(ClientConfig(cfg.sessionToken, "auto",
        CoreMode.CLIENT))
    HelixCore.attachTun(pfd.detachFd()) // detachFd transfers
        ownership → core close()s (§9.3)
    relayStatus() // subscribe →
        EventChannel (§7)
    return START_STICKY
}
override fun onRevoke() { HelixCore.detachTun();
    HelixCore.stop(); emitEvent(REVOKED) } // 03
override fun onDestroy() { HelixCore.detachTun();
    HelixCore.stop(); stopForeground(true) } // 04
}

```

detachFd() transfers fd ownership to native (the core now owns close(2)); getFd() would keep ownership in Java [research-ios_android §3]. The choice is load-bearing for §9.3 (double-close avoidance). HarmonyOS/Aurora use the cbindgen C ABI (§6.3) instead of UniFFI Kotlin/Swift.

6.3 C ABI (HarmonyOS NAPI / Aurora Qt) — cbindgen fallback

```


// helix_core.h – generated by cbindgen (the raw-C fallback, D-
// CLIENT-3)
typedef enum HxCoreErr {
    HX_OK = 0, HX_ERR_NOT_STARTED = 1, HX_ERR_ALREADY_STARTED = 2,
    HX_ERR_AUTH = 3, HX_ERR_CONFIG = 4, HX_ERR_HOST_FATAL = 5,
    HX_ERR_INTERNAL = 6
} HxCoreErr;
HxCoreErr hx_core_start(const char* session, const char*
    transport, int mode);
HxCoreErr hx_core_stop(void);
HxCoreErr hx_attach_tun(int fd);
HxCoreErr hx_detach_tun(void);
/// Status callback: the C consumer registers a fn-ptr; the core
    invokes it on each
/// projected status. `json` is a UTF-8 ffi::TunnelStatus JSON
    (the C ABI has no enum-payload
/// type), freed by the core after the call returns. (UNVERIFIED:
    exact JSON schema fixed in
/// the cbindgen contract test, §13 UNIT.)
typedef void (*hx_status_cb)(const char* json, void* user);
HxCoreErr hx_status_subscribe(hx_status_cb cb, void* user);

```

The C surface carries TunnelStatus as JSON because the C ABI cannot express a tagged-union-with-payload; the Swift/Kotlin UniFFI paths carry the real enum. The JSON schema is frozen by the cbindgen contract test (§13) and is the same projected ffi::TunnelStatus (§3.2).

7. The TunnelPlatform ⇔ FFI division of labor

The seam that prevents the classic bug [04_CLIENT §3.3, §4]. **Lifecycle** commands flow UI → shim → core; **status** flows core → FFI → UI. In Mode B the status takes the EventChannel (the TunnelPlatform.events() stream) because the core is in the extension process, not the Dart isolate.



7.1 Where each TunnelStatus originates (the mode split)

Call	Mode A (in-process frb)	Mode B (native shim)
start/stop	the shim calls the FFI start/stop (Linux: core in-process)	the shim calls the UniFFI/C helix_core_start/stop inside the extension
attach_tun(fd)	Linux tun fd → FFI attach_tun	NE packetFlow fd / pfd.detachFd() → UniFFI/JNI attach_tun
status_stream	frb StreamSink → Dart isolate directly	core subscribe → shim → EventChannel → Dart
set_shields/ set_exit/exits	frb call, in-process	frb call to the UI-process FFI if a logic-only core handle exists there, else marshalled to the

Call	Mode A (in-process frb)	Mode B (native shim)
		extension over the platform channel (D-FFI-2, §14)
Honest boundary (§11.4.6 / §14 C2). In Mode B the <i>logic-only</i> verbs (set_shields/set_exit/exits) target the core in the extension, while the UI runs in the app process. The pass-1 sketch [04_CLIENT §3.3] drew these as "straight UI → FFI"; on iOS/Android that requires either (a) a second in-app-process core handle for pure-logic queries, or (b) marshalling the verb over the TunnelPlatform MethodChannel to the extension. This is surfaced as D-FFI-2 — not silently assumed.		

8. Error propagation across the boundary

8.1 The typed CoreError enum


```
// helix-ffi/src/error.rs
#[derive(thiserror::Error, Debug)]
pub enum CoreError {
    #[error("core not started")]           NotStarted,           //
        status_stream/stop before start
    #[error("core already started")]       AlreadyStarted,       //
        double start (§9.2)
    #[error("invalid config: {0}")]        Config(String),      //
        bad transport string / map path
    #[error("auth failed (revoked)")]      Auth,                  //
        maps from Down{auth-failed}
    #[error("host fatal: {0}")]            HostFatal(String),    //
        TUN open / firewall-apply failed
    #[error("tun fd invalid")]             BadFd,                //
        attach_tun(fd) not a usable fd
    #[error("internal: {0}")]              Internal(String),     //
        last resort; never a secret (§11.4.10)
}
```

CoreError is the **only** error type the FFI surface returns; the orchestrator's internal anyhow/OrchestratorError/TransportError are converted at the boundary (From impls). Reasons are classified on the orchestrator's stable prefixes [02_ORCH §4.4], never parsed from prose (§11.4.6). No variant ever carries a SecretBytes value (§11.4.10, [02_TRANS §3.2]).

8.2 Per-generator mapping

Generator	Err(CoreError) becomes	UI sees
frb (Dart)		

Generator	Err(CoreError) becomes	UI sees
	a thrown CoreException (frb maps Result::Err of a custom error enum to a Dart exception of the mirrored type)	try { await core.start() } on CoreException catch (e) { ... }
UniFFI (Swift)	a Swift throws of the CoreError error enum	do { try helixCoreStart() } catch let e as CoreError { ... }
UniFFI (Kotlin)	a Kotlin CoreException subclass per variant	try { HelixCore.start() } catch (e: CoreException.Auth) { ... }
cbindgen (C)	an HxCoreErr integer code (§6.3)	if (hx_core_start(...)) != HX_OK) ...



8.3 Errors vs status (two distinct channels)

A **synchronous failure** of a verb (start could not open the TUN) is a thrown CoreError; a **runtime transition** (the tunnel later drops) is a TunnelStatus event. The UI must handle both: an `await core.start()` that throws HostFatal shows a start-failure message; a later Down/Danger event on the stream repaints the ConnectButton. A verb MUST NOT silently swallow an error and rely on the status stream to reflect it (that would be a §11.4.1 FAIL-bluff at the boundary) — the throw and the event are complementary, not redundant.

9. Lifecycle, idempotence, and attach_tun fd ownership

9.1 Verb lifecycle contract

Verb	Pre-state	Post-state	Idempotence
start	core stopped	orchestrator running, emits Connecting	double start → Err(AlreadyStarted) (§9.2)
stop	running	torn down, emits Disconnected (Down{stopped} → projected)	stop when stopped → Ok(()) (no-op)
status_stream	any	sink registered; immediate latest re-emit (§4.5)	many concurrent sinks allowed (broadcast fan-out)
attach_tun(fd)	started, no fd	core pumps fd	second attach_tun without detach → Err(BadFd)-class guard (§9.3)
detach_tun	fd attached	fd closed, pump idle	detach when none attached → Ok(())
set_shields/ set_exit/exits/ advertise	started	applied	naturally idempotent (declarative)

9.2 Double-start / start-while-connected guard

start acquires the ORCH mutex and refuses if Some(_) is already present (Err(AlreadyStarted)) — the UI's ConnectController must not call start while a tunnel exists (it calls toggle, [04_CLIENT §8.2]). This guards the §11.4.84-class hazard of two orchestrators racing one TUN fd.

9.3 attach_tun fd ownership (the double-close hazard)

attach_tun(fd) **takes ownership** of the fd on Ok: the core close(2)s it on detach_tun/stop. The shim **MUST** therefore hand a fd it has **relinquished**:

- **Android:** use ParcelFileDescriptor.detachFd() (transfers ownership) — NOT getFd() (keeps ownership; the core close()ing it then double-

closes when the PFD is GC'd) [research-ios_android §3]. The Kotlin shim (§6.2) uses `detachFd()`.

- **iOS NE:** the NE owns `packetFlow`; the core does not close it — instead the iOS path uses the read/write-callback pump (`helix_core_set_tun_writer + packetFlow.readPackets`) rather than a raw fd, so `attach_tun` on iOS registers the callback pair, not an owned fd [04_CLIENT §5.1]. (UNVERIFIED whether a raw fd is even exposed by `NEPacketTunnelFlow`; the callback-pump form is the documented path — §13 records this as the iOS handoff.)
- **Linux:** the in-process core owns the tun fd directly (no cross-process transfer).


A failed `attach_tun` MUST leave **no** half-open TUN (§11.4.14 cleanup): on Err, the shim closes the fd it created and emits `PlatformTunnelEvent.error` with an honest reason [04_CLIENT §4.1 O1].

9.4 Out-of-band revoke / OS kill

When the OS or admin kills the tunnel out-of-band (`onRevoke`, `device.revoked` from the control plane), the shim calls `detach_tun + stop` and emits `revoked`; the FFI projects the resulting `Down/auth-failed` to `Danger{killswitch_tripped}` (§3.3) so the UI repaints red — never "still connected" [04_CLIENT §4.1 O3, CI2].

10. Codegen + drift-gate pipeline

The no-drift guarantee [04_CLIENT §11, 04_ARCH §4.2]: the generated Dart/Swift/Kotlin can **never** silently diverge from the Rust surface. A drift is a build-blocking finding.



- **Trigger:** any edit to `api.rs` (or a mirrored core type) re-runs all three generators; the regenerated output MUST byte-match the committed artifacts (`git diff --exit-code`).
- **Version pin check:** the gate asserts the `flutter_rust_bridge` crate version equals the `flutter_rust_bridge` Dart-dep version [research-flutter_ffi §1 caveat].
- **Enum-parity check:** the §13 UNIT FFI-contract test asserts the Dart/Swift/Kotlin `TunnelStatus/Shields/ExitOption` mirrors match the Rust

types byte-for-byte (the projected 7-variant surface) [04_CLIENT §12 FFI-contract row].

- Run **locally** (`melos run drift-check`) — there is no active server-side CI (§11.4.156).

11. Memory & performance budgets

Budget	Target	Basis / source
iOS NE process RSS (Mode B)	steady-state well under the device ceiling — design to ~ 12–15 MB working set, NOT to the 50 MiB figure	iOS NE limit is 50 MiB on iOS 15–18 (was 15 MiB on iOS 11–14), undocumented, MUST NOT be hardcoded , and observed 15 MB jetsam kills on some iOS 17 devices (PENDING_FORENSICS) [research-ios_android §1]
iOS NE spike control	bound packet-buffer pools; single fixed-size receive buffer to MTU+headroom; no per-flow state growth	spikes (upload-heavy bursts), not steady state, are the jetsam killer [research-ios_android §1]
frb runtime cost (Mode A)	tokio runtime = 2 worker threads ; broadcast cap 64; one cached latest status	the loops are I/O-bound [02_ORCH §13]; the runtime does not run in the iOS NE (§1)
FFI projection cost	<code>project()</code> is pure, allocation-light (clones small strings); callable at status-change frequency (rare)	§3.3
status_stream fan-out	many sinks via broadcast; lagged receiver fast-forwards, never blocks the core	§4.6, [02_ORCH §4.2]
attach_tun latency	synchronous, sub-ms (stores fd + wakes loops; no await)	§2, §9.3
Mobile install size contribution	lean Rust staticlib: <code>opt-level=z/s + fat LTO + codegen-units=1 +</code>	[research-ios_android §2], [04_CLIENT §10]

Budget	Target	Basis / source
	panic=abort + strip; optional build-std + panic_immediate_abort + optimize_for_size	

The iOS NE ceiling is the architecture (CI4). It is the single strongest reason the core is Rust not Go — a GC runtime risks the working set [04_CLIENT §0.1 CI4, §10, 04_ARCH §5.6]. Because Mode B links only the UniFFI/cbindgen staticlib (not frb + tokio + Dart), the FFI generator choice does **not** inflate the NE footprint; the MEM test (§13) measures the *extension* process, plain-UDP **and** MASQUE separately (G3) [research-ios_android §1, 04_CLIENT §5.1].

12. Edge cases & failure modes

#	Edge case	Required behaviour
E1	status_stream called before start	Err(NotStarted) — never a silent empty stream that the UI reads as "Disconnected-but-fine" (§8.3)
E2	Broadcast Lagged under a wedged UI	forwarding task skips to latest; never surfaced to Dart as an error (§4.6)
E3	Dart StreamProvider paused (backgrounded), then resumed	forwarding task keeps running; on resume the cached latest status is re-emitted (§4.5) — no stale gap
E4	Dart isolate hot-restart (dev) / app process restart	frb port invalidated; sink.add errors → forwarding task drops that sink; a fresh status_stream re-registers + re-emits latest
E5	Native extension crash (Mode B)	shim emits error/down on the EventChannel; FFI/UI shows Down (not "connected"); the OS may restart the extension (START_STICKY Android) → fresh start
E6	Double start	Err(AlreadyStarted) (§9.2)
E7	attach_tun with an invalid/closed fd	Err(BadFd); shim closes its TUN, emits error (no half-open TUN, §11.4.14)
E8	detach_tun then core keeps a stale fd	forbidden — detach_tun close(2)s and clears the fd; loops idle until a fresh attach_tun (§9.3)
E9		

#	Edge case	Required behaviour
	fd double-close (shim getFd + core close)	prevented by mandating detachFd() ownership transfer (§9.3) [research-ios_android §3]
E10	Connected.path unknown at emit time	projector defaults path = "direct" and re-emits Connected when the real path resolves (§3.3, §14 C3)
E11	Danger (leak) while user intent = connected	Danger overrides intent; UI paints red immediately (§3.3, [04_CLIENT §8.4]) — never green-on-intent
E12	CoreError::Internal carries a secret	forbidden (§11.4.10): the boundary From impls scrub; the SEC test plants a secret and greps logs/messages empty (§13)
E13	Console flavor (no Capability.tunnel) calls a tunnel verb	compile-gated out; runtime fallback is NoCore throwing StateError (§5, CI3) — never links the staticlib
E14	frb crate ver ≠ Dart dep ver	drift gate FAILs the build (§10) [research-flutter_ffi §1]

13. Test points — §11.4.169 closed vocabulary

Every FFI workable item declares its required test types from the §11.4.169 closed set [10_QA §2]; the ONLY permitted absence of a warranted type is an honest §11.4.3 SKIP-with-reason. Four-layer enforcement per §11.4.4(b). Every PASS ships captured evidence per §11.4.5/.69/.107 — never a config-only or grep-only PASS.

Code	Type	Concrete FFI test point	Evidence
UNIT	unit	project() truth table for all 7×(5+ctx) input combos; classify() on every stable Down.reason prefix; CoreError From mappings; FFI-contract : regenerated Dart/Swift/Kotlin TunnelStatus/Shields/ExitOption mirrors match Rust byte-for-byte; cbindgen JSON schema frozen. Mocks allowed only here (§11.4.27).	cargo test + dart test output; generated-mirror diff
INT	integration (real System, no mocks)	start→status_stream against a real orchestrator (in-process Mode A) yields the ordered	netns capture; ordered status-trace log

Code	Type	Concrete FFI test point	Evidence
E2E	end-to-end	Connecting→Handshaking→Connected trace; attach_tun(fd) with a real netns tun fd pumps packets the Phase-0 G5 demo: Flutter-Linux window, one connect/disconnect toggle, StatusChip driven <i>only</i> by the Rust stream [04_CLIENT §13 T0.1]	window-scoped MP4 (§11.4.159) of the connect journey
FA	full-automation	make qa drives start→status→stop N=3 identical runs producing the same ordered status trace (deterministic §11.4.50/.98)	3× identical status-trace artifacts
SEC	security	(a) plant a session token / secret in ClientConfig, prove it appears in no log/CoreError/stream (§11.4.10); (b) the stream carries no SSID/gateway-IP/per-packet data (I5, §3.5)	grep-empty proof; stream-content audit
STRESS	stress	≥100 rapid set_shields/set_exit calls + ≥10 concurrent status_stream sinks; no leak, bounded broadcast	call-throughput CSV
CHAOS	chaos	mid-start SIGKILL of the extension (Mode B) → shim emits down → fresh start recovers; isolate hot-restart (E4) → re-subscribe re-emits latest	recovery trace
CONC	concurrency / atomicity	concurrent status_stream (many sinks) + set_shields while a re-dial swaps active_tx [02_ORCH §7.3]; zero dropped/duplicated terminal status	concurrency harness log
RACE	race / deadlock	cargo test --features loom on the ORCH mutex + ProjCtx snapshot + forwarding-task shutdown; no deadlock between stop and an in-flight recv	loom report
MEM	memory	iOS NE extension RSS for plain-UDP and MASQUE separately, ≥30% headroom under the device ceiling, 30-min soak (G3 make-or-break); no	Instruments //proc RSS sample [research-ios_android §1]

Code	Type	Concrete FFI test point	Evidence
		per-event heap growth in the forwarding task	
BENCH/ PERF	benchmarking / performance	project() cost; status_stream end-to-end latency (core emit → Dart receive); attach_tun latency	latency histogram CSV
UI/UX	UI / UX	ConnectButton renders correctly across every ffi::TunnelStatus (incl. Danger); golden frames light+dark	golden PNGs [04_CLIENT §12]
REC	recorded-evidence	window-scoped MP4 (§11.4.154/.155) of the G5 connect journey, vision-validated StatusChip reads masque-h3 · direct · 23ms (OCR) (§11.4.163)	panoptic→vision_engine verdict
CHAL/ HQA	Challenge / HelixQA	a bank entry scores PASS only on the captured G5 status-trace + device recording, never config	Challenge / HelixQA result.json

Anti-bluff rule (§11.4.5/.69/.107). A green project() unit test is **not** proof the user is protected. The authoritative evidence is the E2E/ REC G5 device recording: the StatusChip reading the live transport-path-rtt confirmed by OCR/vision, plus the iOS NE MEM Instruments RSS report. Fake the orchestrator with the **same generated model types** so unit tests exercise real contracts, but the user-visible claim is earned only by the device recording [04_CLIENT §12].

14. Surfaced decisions & cross-doc contracts

Per §11.4.6/§11.4.66 — options + recommendation, never silently resolved.

#	Decision / contract	Options	Recommendation
D- FFI-1	Riverpod provider disposal for the status stream	@riverpod/ autoDispose (paused when unwatched) vs always-alive StreamProvider	autoDispose — cheap when backgrounded; correctness on resume comes from the §4.5(2) cached-latest re-emit, not from keeping the provider alive [research- flutter_ffi §6]

#	Decision / contract	Options	Recommendation
D-FFI-2	Mode-B logic-only verbs (set_shields/set_exit/exits) target the in-extension core	(a) second in-app-process core handle for pure-logic queries vs (b) marshal over the TunnelPlatform MethodChannel to the extension	Gate on the platform: (b) for iOS/Android (single source of truth = the extension's core); (a) only if a pure read needs sub-ms latency. Surfaced, not assumed (§7.1)
D-FFI-3	Native-shim error type	UniFFI typed CoreError enum vs flat string error	typed CoreError (§8.1) — drives honest, specific UI messages; cbindgen falls back to HxCoreErr int codes (§6.3)

Cross-document contracts this document fixes (consumed by the named docs):

#	Contract	Fixed value	Consumed by
C1	The Dart-facing ffi::TunnelStatus (7-variant) + the <code>project()</code> mapping from <code>core::TunnelStatus</code>	§3.2, §3.3	doc 02 (must emit the 5-variant on its stable prefixes); all apps
C2	The two consumption modes (in-process frb vs native-shim UniFFI/C) and where each status originates	§1, §7.1	every per-platform shim [04_CLIENT §5]
C3	Connected.path requirement — the core MUST surface <code>"direct"</code>	"relay" (added to <code>core::TunnelStatus.Connected**or**</code> queryable via the active route), else the projector defaults "direct" and re-emits (§3.3, E10). **UNVERIFIED** in the current orchestrator enum [02_ORCH §4.1] (which carries only <code>transport+rtt_ms</code>)	§3.3

#	Contract	Fixed value	Consumed by
		— recorded as a follow-up cross-doc item per §11.4.6	
C4	The typed CoreError boundary enum (frb exception $\rightleftharpoons$ UniFFI error $\rightleftharpoons$ HxCoreErr)	§8	all apps, all shims
C5	attach_tun fd ownership transfer (core close()s on detach/stop; shim hands a relinquished fd: Android detachFd, iOS callback-pump, Linux in-process)	§9.3	every per-platform shim [04_CLIENT §5], doc 02 (helix-tun)

Sources verified

- `final/03-client-core-and-ui.md` [04_CLIENT] — §0.1 (CI1–CI6 invariants), §3 (FFI surface, the `api.rs` sketch, the Dart wrapper, the FFI $\rightleftharpoons$ shim seam), §4 (TunnelPlatform contract), §5 (per-platform shims, iOS NE, Android VpnService), §7 (tokens / TunnelStatus $\rightarrow$ palette), §8 (Riverpod, offline/intent honesty), §10–§12 (budgets, build/codegen, testing). Accessed 2026-06-25.
- `04_VPN_CLD/HelixVPN-Architecture-Refined.md` [04_ARCH §5] — §5.1 (two binding generators, Rust core + Flutter UI), §5.6 (iOS NE memory = Rust-not-Go), §5.7 (Web has no shim). Accessed 2026-06-25.
- `04_VPN_CLD/HelixVPN-helix-ui-Flutter.md` [04_UI] — §4 (Riverpod stream model), §5 (FFI surface), §6 (shim matrix). Accessed 2026-06-25.
- `final/v02-data-plane/orchestrator-and-state.md` [02_ORCH] — §2.1 (Orchestrator API + subscribe), §4.1 (canonical 5-variant TunnelStatus), §4.2 (broadcast cap/Lagged), §4.3 (emit coalescing), §4.4 (stable Down. reason prefixes), §4.5 (no-durable-record), §4.6 (receiver contract), §5.1 (OrchState), §7.3 (atomic transport swap). Accessed 2026-06-25.
- `final/v02-data-plane/transport-trait.md` [02_TRANS] — §2 (Transport trait), §3.2 (SecretBytes redaction/zeroize), §3.3 (TransportKind labels = Connected.transport), §5.2 (carrier $\rightarrow$ WG $\rightarrow$ status projection). Accessed 2026-06-25.

- v09-research/research-flutter_ffi.md [research-flutter_ffi] — §1 (frb 2.12.0, StreamSink, async fn, mirror, version-pin caveat), §2 (UniFFI first-party Kotlin/Swift; uniffi-dart not production-ready), §3 (per-platform staticlib/cdylib packaging), §6 (Riverpod 3.0 StreamProvider pause-when-unlistened, autoDispose, overrideWithValue), §7 (synthesis recommendations). Accessed 2026-06-25.
- v09-research/research-ios_android.md [research-ios_android] — §1 (iOS NE memory limit 50 MiB iOS 15–18 / 15 MiB iOS 11–14, undocumented, MUST-NOT-hardcode, observed 15 MB iOS 17 kills, whole-process scope, spike-driven jetsam, ~12–15 MB design budget), §2 (Rust staticlib size-opt flags), §3 (Android VpnService.Builder→establish()→ParcelFileDescriptor, detachFd() ownership transfer to JNI, protect()). Accessed 2026-06-25.
- final/10-testing-acceptance-and-qa.md [10_QA] — §2 (the canonical §11.4.169 closed test-type taxonomy + abbreviations). Accessed 2026-06-25.

Constitution: §11.4.44 (revision header), §11.4.6/§11.4.66 (decisions = options + recommendation; UNVERIFIED never fabricated), §11.4.5/§11.4.69/§11.4.107/§11.4.159 (captured/window-scoped evidence), §11.4.10 (secrets never cross the boundary), §11.4.14 (no half-open TUN on attach failure), §11.4.28/§11.4.74 (decoupled reusable helix-ffi), §11.4.156 (no active CI — local drift gate), §11.4.169 (per-item test-type coverage).

End of nano-detail specification — FFI surface (Dart $\rightleftharpoons$ Rust), Volume 4 (Clients). Deepens [04_CLIENT §3]; consumes the orchestrator status contract [02_ORCH §4] and the TunnelPlatform shim contract [04_CLIENT §4]. Surfaced decisions: D-FFI-1 (provider disposal), D-FFI-2 (Mode-B logic-verb routing), D-FFI-3 (native error type); cross-doc contract C3 (Connected.path) flagged UNVERIFIED against the current orchestrator enum — all presented, none silently resolved (§11.4.66).