

CS230, Fall 20xx
Data Lab: Manipulating Bits
Assigned: Sept. 15, Due: Mon., Sept. 28, 11:59PM

Daehyeon Baek is the lead person for this assignment. If you have question, please make questions to piazza or e-mail to (cs230_ta@kaist.ac.kr).

1 Introduction

The purpose of this assignment is to become more familiar with bit-level representations of integers and floating point numbers. You'll do this by solving a series of programming "puzzles." Many of these puzzles are quite artificial, but you'll find yourself thinking much more about bits in working your way through them.

2 Logistics

This is an individual project. All handins are electronic. Clarifications and corrections will be posted on the course Web page.

3 Handout Instructions

First make sure you fork the CS230/LAB2 repository to your private namespace! If you don't, you won't be able to submit your work. Once you have your private repo, you may clone your private repo. Also, make sure you have added your SSH key to the GitLab Web UI. To check SSH key settings and how to fork and clone, please see previous announcements and Lab 1 README.

```
unix> git clone ssh://git@cs230.kaist.ac.kr:10022/cs[your_student_id]
/lab2.git
```

The only file you will be modifying and turning in is `bits.c`.

The `bits.c` file contains a skeleton for each of the 15 programming puzzles. Your assignment is to complete each function skeleton using only *straightline* code for the integer puzzles (i.e., no loops or conditionals) and a limited number of C arithmetic and logical operators. Specifically, you are *only* allowed to use the following eight operators:

`! ~ & ^ | + << >>`

A few of the functions further restrict this list. Also, you are not allowed to use any constants longer than 8 bits. See the comments in `bits.c` for detailed rules and a discussion of the desired coding style.

4 The Puzzles

This section describes the puzzles that you will be solving in `bits.c`.

4.1 Bit Manipulations

Table 1 describes a set of functions that manipulate and test sets of bits. The “Rating” field gives the difficulty rating (the number of points) for the puzzle, and the “Max ops” field gives the maximum number of operators you are allowed to use to implement each function. See the comments in `bits.c` for more details on the desired behavior of the functions. You may also refer to the test functions in `tests.c`. These are used as reference functions to express the correct behavior of your functions, although they don’t satisfy the coding rules for your functions.

Name	Description	Rating	Max Ops
<code>bitXor(x, y)</code>	$x \oplus y$ using only <code>~</code> and <code>&</code>	1	14
<code>byteSwap(x, n, m)</code>	Swaps the <i>n</i> th and the <i>m</i> th byte	2	25
<code>rotateLeft(x, n)</code>	Rotate <i>x</i> to the left by <i>n</i>	3	25
<code>leftBitCount(x)</code>	Returns count of number of consecutive 1’s in left-hand (most significant) end of word. <i>x</i> .	4	50
<code>absVal(x)</code>	Absolute value of <i>x</i>	4	10

Table 1: Bit-Level Manipulation Functions.

4.2 Two’s Complement Arithmetic

Table 2 describes a set of functions that make use of the two’s complement representation of integers. Again, refer to the comments in `bits.c` and the reference versions in `tests.c` for more information.

4.3 Floating-Point Operations

For this part of the assignment, you will implement some common single-precision floating-point operations. In this section, you are allowed to use standard control structures (conditionals, loops), and you may

Name	Description	Rating	Max Ops
<code>tmax()</code>	Return maximum two's complement integer	1	4
<code>fitsShort(x)</code>	Return 1 if <code>x</code> can be represented as a 16-bit, two's complement integer.	1	8
<code>rempwr2(x, n)</code>	Compute $x \times 2^n$, for $0 \leq x \leq 30$	3	20
<code>sign(x)</code>	Return 1 if positive, 0 if zero, and -1 if negative	2	10
<code>isNonNegative(x)</code>	Return 1 if <code>x</code> ≥ 0 , return 0 otherwise	3	6
<code>isGreater(x, y)</code>	If <code>x</code> $>$ <code>y</code> then return 1, else return 0	3	24
<code>howManyBits(x)</code>	Return the minimum number of bits required to represent <code>x</code> in two's complement	4	90

Table 2: Arithmetic Functions

use both `int` and `unsigned` data types, including arbitrary unsigned and integer constants. You may not use any unions, structs, or arrays. Most significantly, you may not use any floating point data types, operations, or constants. Instead, any floating-point operand will be passed to the function as having type `unsigned`, and any returned floating-point value will be of type `unsigned`. Your code should perform the bit manipulations that implement the specified floating point operations.

Table 3 describes a set of functions that operate on the bit-level representations of floating-point numbers. Refer to the comments in `bits.c` and the reference versions in `tests.c` for more information.

Name	Description	Rating	Max Ops
<code>float_abs(uf)</code>	Compute $ uf $	2	10
<code>float_f2i(uf)</code>	Compute $(int) uf$	4	30
<code>float_half(uf)</code>	Compute $0.5 \times uf$	4	30

Table 3: Floating-Point Functions. Value `f` is the floating-point number having the same bit representation as the unsigned integer `uf`.

Functions `float_abs`, `float_f2i` and `float_half` must handle the full range of possible argument values, including not-a-number (NaN) and infinity. The IEEE standard does not specify precisely how to handle NaN's, and the IA32 behavior is a bit obscure. We will follow a convention that for any function returning a NaN value, it will return the one with bit representation `0x7FC00000`.

The included program `fshow` helps you understand the structure of floating point numbers. To compile `fshow`, switch to the handout directory and type:

```
unix> make
```

You can use `fshow` to see what an arbitrary pattern represents as a floating-point number:

```
unix> ./fshow 2080374784
```

```
Floating point value 2.658455992e+36
```

```
Bit Representation 0x7c000000, sign = 0, exponent = f8, fraction = 000000
Normalized. 1.0000000000 X 2^(121)
```

You can also give `fshow` hexadecimal and floating point values, and it will decipher their bit structure.

5 Evaluation

Your score will be computed out of a maximum of 71 points based on the following distribution:

41 Correctness points.

30 Performance points.

Correctness points. The 15 puzzles you must solve have been given a difficulty rating between 1 and 4, such that their weighted sum totals to 41. We will evaluate your functions using the `btest` program, which is described in the next section. You will get full credit for a puzzle if it passes all of the tests performed by `btest`, and no credit otherwise.

Performance points. Our main concern at this point in the course is that you can get the right answer. However, we want to instill in you a sense of keeping things as short and simple as you can. Furthermore, some of the puzzles can be solved by brute force, but we want you to be more clever. Thus, for each function we've established a maximum number of operators that you are allowed to use for each function. This limit is very generous and is designed only to catch egregiously inefficient solutions. You will receive two points for each correct function that satisfies the operator limit.

Autograding your work

We have included some autograding tools in the handout directory — `btest`, `dlc`, and `driver.pl` — to help you check the correctness of your work.

- **btest**: This program checks the functional correctness of the functions in `bits.c`. To build and use it, type the following two commands:

```
unix> make
unix> ./btest
```

Notice that you must rebuild `btest` each time you modify your `bits.c` file.

You'll find it helpful to work through the functions one at a time, testing each one as you go. You can use the `-f` flag to instruct `btest` to test only a single function:

```
unix> ./btest -f bitXor
```

You can feed it specific function arguments using the option flags `-1`, `-2`, and `-3`:

```
unix> ./btest -f bitXor -1 7 -2 0xf
```

Check the file `README` for documentation on running the `btest` program.

- **dlc:** This is a modified version of an ANSI C compiler from the MIT CILK group that you can use to check for compliance with the coding rules for each puzzle. The typical usage is:

```
unix> ./dlc bits.c
```

The program runs silently unless it detects a problem, such as an illegal operator, too many operators, or non-straightline code in the integer puzzles. Running with the `-e` switch:

```
unix> ./dlc -e bits.c
```

causes `dlc` to print counts of the number of operators used by each function. Type `./dlc -help` for a list of command line options.

- **driver.pl:** This is a driver program that uses `btest` and `dlc` to compute the correctness and performance points for your solution. It takes no arguments:

```
unix> ./driver.pl
```

Your instructors will use `driver.pl` to evaluate your solution.

6 Handin Instructions

Once you have finished your implementation and your test cases have passed, you can submit your code. Its similar to what you have done in Lab 2. Make sure that you add the `bits.c` file, and commit your changes. You can do so with the following commands

```
unix> git add bits.c
unix> git commit -m "Your commit message"
```

First command adds `bits.c` to your commit. Then, you can commit it by typing commit command. Execute following command to make sure that you do not have any uncommitted changes to the (`bits.c`) file.

```
unix> git status
```

To hand in your lab, execute the following command

```
unix> make handin
```

This step will push your local commits onto your GitLab remote repository. Make sure that your remote repository is your forked version of the Lab 2. Your remote URL should be something like the following.

```
ssh://git@cs230.kaist.ac.kr:10022/[Your_user_name]/lab2.git
```

You can check your remote URL using the following command:

```
unix> git remote -v
```

Check the tags section in the GitLab Web interface to see if your latest code has been pushed onto the server. The URL to check your tags is the following.

```
https://cs230.kaist.ac.kr:10080/[Your_user_name]/lab2/tags
```

Same as previous lab, if you can see the tag on GitLab, your submission is successfully uploaded.

7 Advice

- Don't include the `<stdio.h>` header file in your `bits.c` file, as it confuses `dlc` and results in some non-intuitive error messages. You will still be able to use `printf` in your `bits.c` file for debugging without including the `<stdio.h>` header, although `gcc` will print a warning that you can ignore.
- The `dlc` program enforces a stricter form of C declarations than is the case for C++ or that is enforced by `gcc`. In particular, any declaration must appear in a block (what you enclose in curly braces) before any statement that is not a declaration. For example, it will complain about the following code:

```
int foo(int x)
{
    int a = x;
    a *= 3;      /* Statement that is not a declaration */
    int b = a;   /* ERROR: Declaration not allowed here */
}
```

8 The “Beat the Prof” Contest

For fun, we're offering an optional “Beat the Prof” contest that allows you to compete with other students and the instructor to develop the most efficient puzzles. The goal is to solve each Data Lab puzzle using the fewest number of operators. Students who match or beat the instructor's operator count for each puzzle are winners!

To submit your entry to the contest, type:

```
unix> ./driver.pl -u ``Your Nickname``
```

Nicknames are limited to 35 characters and can contain alphanumerics, apostrophes, commas, periods, dashes, underscores, and ampersands. You can submit as often as you like. Your most recent submission will appear on a real-time scoreboard, identified only by your nickname. You can view the scoreboard by pointing your browser at

`http://143.248.139.117:8080`