



DO-IT-YOURSELF: PROJECT



Fig. 5: Wheels attached to motor shafts

all components as per the circuit diagram (Fig. 2). Mount the Arduino Uno, HC-05 Bluetooth module, and motor driver onto the robot chassis.

In this device, a wooden plank serves as the chassis.

Attach the DC motors to the chassis and fix the wheels onto the motor shafts. Fig. 4 shows assembly of motor driver and Arduino mounted on the chassis while Fig. 5 shows wheels attached to motor shafts.

To power the robot, use the battery holder fitted with 18650 Li-ion cells. Once powered, the HC-05 Bluetooth module's LED should blink or stay steady, indicating that it is ON.

Open the Serial Bluetooth Terminal application on a mobile device. Turn on Bluetooth and search for available devices. Select HC-05 to connect. If prompted, enter the default password (usually 0000 or 1234).

Once the mobile device is successfully connected to the HC-05 module, use the following character

TO DOWNLOAD SOURCE CODE AND RESOURCES



Scan this QR code or go to <https://sourcecode.electronicsforu.com> to access and download source code and other resources for this project

commands to control the trolley:

- f – move forward
- b – move backward
- r – turn right
- l – turn left
- s – stop

These commands enable full directional control of the smart trolley robot via Bluetooth. **EFY**



Navpreet Singh Tung is In-charge at the Artificial Intelligence and Robotics Lab, Sandeepani Gurukul, Pathankot, Punjab, India.

ELECTRONICS equals OPPORTUNITIES

Can You Afford To Miss?

Subscribe Now.

Get Free Delivery. Every Month

VISIT:
<https://bit.ly/subefy>

OR SCAN

